

User manual for device - GSM

Once the device is received, open the sim card slot, enter a micro sim card and turn on the toggle switch on.

The status LED can be one of the 3 colors red, green or blue. It should take approximately around **30 seconds** to turn green, but if it gets stuck in between, the conditions are mentioned below.

Red: It means the device is not connected to the GPRS network or the area where the device is being used has no network coverage.

Blue: It means the device is connected to the internet via 2G network.

Green: It means that the device is connected to the server and its ready for being used.

Fixing method: Use double-sided tape to make the product stick to the table to achieve a fixed effect.

1. MQTT server details

- 1. Host name:** hub.swittons.com
- 2. Username:** swittonsdevice
- 3. Password:** swittonsprescriber360

2. Topic details for edge device

- 1. Publisher:** swittons/
- 2. Subscriber:** swittons/DEVICE_ID (where IMEI number for GSM)

3. Edge device behaviour for topics vs messages

The edge device should execute certain actions if a specific message is received on the topic mentioned in point **(2.2)**.

Message: ERR

Action: Light up RED LED in a blinking pattern for 2 times. (on-off, on-off) with a delay of 200 ms between on and offs

Message: OK

Action: Light up GREEN LED in a blinking pattern for 3 times. (on-off, on-off) with a delay of 200 ms between on and offs

4. Edge device message description for orders

The edge device should send a message to the following topic when connected to the MQTT broker

Topic: swittons/device

Message: {"device_id":" DEVICE_ID","button":"01"}

Description: 01 can be 01,02,03 or 04 depending on the button pressed. DEVICE_ID is mac address for WiFi, IMEI number for GSM

The edge device should send a message along with button press information to the following topic

Topic: swittons/order

Message: {"device_id":" DEVICE_ID","button":"01"}

Description: 01 can be 01,02,03 or 04 depending on the button pressed. DEVICE_ID is IMEI number for GSM

Note: The client ID for the edge device should be unique and in no way similar to one another. The message format as mentioned in point 4 should always be a valid JSON STRING.

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.