

# MPE REPORT

FCC ID: 2AUJS-L1

Date of issue: July 15, 2020

Report number:	MTi20061213-11E3
Sample description:	Poooli Smart Pocket Printer
Model(s):	L1, Poooli L1
Applicant:	Xiao Hao(Shenzhen)Technology Co., Ltd.
Address:	2#2407, C District, Nanshan Zhiyuan, Nanshan District, Shenzhen, China
Date of test:	July 01, 2020 to July 15, 2020

Shenzhen Microtest Co., Ltd.

<http://www.mtitest.com>

This test report is valid for the tested samples only. It cannot be reproduced except in full without prior written consent of Shenzhen Microtest Co., Ltd.



### TEST RESULT CERTIFICATION

Applicant's name:	Xiao Hao(Shenzhen)Technology Co., Ltd.
Address:	2#2407, C District, Nanshan Zhiyuan, Nanshan District, Shenzhen, China
Manufacture's name:	Xiao Hao(Shenzhen)Technology Co., Ltd.
Address:	2#2407, C District, Nanshan Zhiyuan, Nanshan District, Shenzhen, China
Product name:	Poooli Smart Pocket Printer
Trademark:	poooli
Model and/or type reference:	L1
Serial model:	Poooli L1
RF exposure procedures:	KDB 447498 D01 v06

This device described above has been tested by Shenzhen Microtest Co., Ltd and the test results show that the equipment under test (EUT) is in compliance with the FCC requirements. And it is applicable only to the tested sample identified in the report.

Tested by:

Danny Xu

July 15, 2020

Reviewed by:

Leo Su

July 15, 2020

Approved by:

Tom Xue

July 15, 2020



## RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm <sup>2</sup> )	Averaging time (minutes)
<b>(A) Limits for Occupational/Controlled Exposure</b>				
0.3-3.0	614	1.63	*100	6
3.0-30	1842/f	4.89/f	*900/f <sup>2</sup>	6
30-300	61.4	0.163	1.0	6
300-1,500			f/300	6
1,500-100,000			5	6
<b>(B) Limits for General Population/Uncontrolled Exposure</b>				
0.3-1.34	614	1.63	*100	30
1.34-30	824/f	2.19/f	*180/f <sup>2</sup>	30
30-300	27.5	0.073	0.2	30
300-1,500			f/1500	30
1,500-100,000			1.0	30

f = frequency in MHz \* = Plane-wave equivalent power density

### MPE Calculation Method

Friis transmission formula:  $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot R^2)$

Where

$P_d$  = Power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

$G$  = Numeric gain of the antenna relative to isotropic antenna

$\pi$  = 3.1415926

$R$  = distance between observation point and center of the radiator in cm(20cm)

$P_d$  the limit of MPE, 1mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

## Measurement Result

Operation Frequency: BT/BLE: 2402-2480MHz

Power density limited: 1mW/ cm<sup>2</sup>

Antenna Type: PCB Antenna;

WIFI antenna gain: 1dBi

R=20cm

$mW=10^{(dBm/10)}$

antenna gain Numeric= $10^{(dBi/10)}=10^{(1/10)}=1.26$

Channel Freq. (MHz)	modulation	conducted power	Tune-up power (dBm)	Max		Antenna		Evaluation result	Power density Limits
		(dBm)		tune-up power		Gain		(mW/cm2 )	(mW/cm2)
				(dBm)	(mW)	(dBi)	Numeric		
2402	GFSK	4.439	5±1	6	3.981	1.00	1.26	0.0010	1
2441		4.897	5±1	6	3.981	1.00	1.26	0.0010	1
2480		5.528	5±1	6	3.981	1.00	1.26	0.0010	1
2402	π/4-DQPSK	3.313	4±1	5	3.162	1.00	1.26	0.0008	1
2441		4.077	4±1	5	3.162	1.00	1.26	0.0008	1
2480		4.659	4±1	5	3.162	1.00	1.26	0.0008	1
2402	8DPSK	3.049	4±1	5	3.162	1.00	1.26	0.0008	1
2441		4.332	4±1	5	3.162	1.00	1.26	0.0008	1
2480		4.922	4±1	5	3.162	1.00	1.26	0.0008	1

Channel Freq. (MHz)	modulation	conducted power	Tune-up power (dBm)	Max		Antenna		Evaluation result	Power density Limits
		(dBm)		tune-up power		Gain		(mW/cm2 )	(mW/cm2)
				(dBm)	(mW)	(dBi)	Numeric		
2402	GFSK	4.232	5±1	6	3.981	1.00	1.26	0.0010	1
2440		4.979	5±1	6	3.981	1.00	1.26	0.0010	1
2480		5.648	5±1	6	3.981	1.00	1.26	0.0010	1

### Conclusion:

For the max result: 0.0010≤ 1.0 for 1g SAR, No SAR is required.

----END OF REPORT----