

Mini Wireless Keyboard Touchpad IR Combo Installation & User Manual

New Product With
MULTI TOUCH


CE FCC RoHS
Made in China
VER: 1.0
M/C: 06251004001

IN LINE WITH THE POLICY OF CONTINUED DEVELOPMENT THE MANUFACTURER RESERVES THE RIGHT TO AMEND THE SPECIFICATIONS WITHOUT PRIOR NOTIFICATION, THE PICTURES AND DATE IN THE STECHBOOK ARE CONSULT ONLY, IF THERE IS INSTRUCTION, ACCORDING TO THE REAL OBJECT PLEASE.

Overview

Thank you for purchasing this Wireless Mini QWERTY Keyboard & Touchpad & IR Combo. You can use it for emails, chat, remote control, message input and games. It is compatible with PC, Laptop, Raspberry Pi 2, Mac OS, Linux, HTPC, IPTV, Google Android smart TV Box, XBMC, Windows 2000 XP Vista 7 8 10. Use it with, infrared remote control is suitable for TV and Android boxes. It can't control air-conditioning your Android box or smart tv on your sofa or browse the internet in the most comfortable fashion.

Quick Start



Quick Guide

1 Receiver Chamber




USB Receiver inside

2 Connect




Plug the USB Receiver into the USB port

3 Switch



4 Touchpad



FCC notice

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FAQ

Q1: Keyboard and touch pad do not respond, and the indicators can not be illuminated.

A: Check whether the switch is in the "ON" position.

Q2: How long is required to charge the battery?

A: The red indicator will be lighted during charging and off when it is fully charged. It requires about 3 hours to charge the battery fully.

Q3: The USB cable supplied can be used for data transmission?

A: No. It is only used to charge the battery.

Q4: The keyboard works but the touch pad does not respond.

A: Press FN+ [Touchpad]

Q5: These 8 orange buttons on the keyboard do not control the device.

A: These 8 orange buttons are Infrared learning buttons. You need to use the original remote control of the device before learning to use these 8 buttons before you can use them.

System Requirements

- HID compatible device
- Terminal with USB port
- Window 2000 • Window XP
- Windows Vista, Windows CE, Windows 7, Window 8
- Linux(Debian-3, 1, Redhat-9.0, Ubuntu-8.10, Fedora-7.0 tested)
- Android OS (With standard USB interface)

Please note

1. It can work on Amazon Fire TV with an App-app2 fire on android. You can't install any App to fire TV.

Note that it only works on side loaded applications.

For example Google chrome, Firefox, show box, Kodi is a native app on fire.

2. Not suitable for all smart TV. Some smart TV does not support external input device. Before you place the order, please use a wired keyboard to check if it can work.

Specifications

Receiver (dongle): Nano style
Connection port: With USB2.0 or above
Transmission mode: GFSK 2.4GHz wireless, up to 10 meters
Transmission Power: Less than +4db
Power supply: Rechargeable polymer Lithium-Ion battery
Charging voltage: 4.4V - 5.25V Charging current: 300mA
Sleeping current class1: <48uA Operation voltage: 3.7V
Operating current: <35mA Product weight: 125g
Product size: 153.5*95.2*19mm

Installation

1. Take off the USB receiver from back cover of the keyboard
2. Plug the USB Receiver into your device's USB port
3. Turn on the keyboard.

A Blue LED will stay on. That means the keyboard has paired with your device.

Note: The blue light will flash when the battery voltage is low or the keyboard is not connected wirelessly. The solution is as follows:

A. If the keyboard works normally, please charge the keyboard.
B. If the keyboard does not work properly, first charge the keyboard, then re-pair the keyboard and receiver. As for how to pair, please try the following methods.

Step1: Take the receiver out of the USB port of the computer or Android box.

Step2: Keep your PC or Android power on. When the keyboard is turned off, press and hold the Esc key, and then turn on keyboard switch, the Blue light will flash quickly. At this time, insert the receiver into the computer or Android box. Keep the keyboard as close to the receiver as possible when inserting the receiver into the USB port of the computer or Android box. If the blue light stays on, the pairing is successful.

4. Meaning of the three LEDs (Blue + Red, yellow and Red)




Blue + Red - When the blue light is on, the blue light will flash. When the touch panel is touched, the blue light will flash. When the battery is low, the blue light will flash rapidly. When the orange infrared button is pressed, the red light will flash, but what you see is the purple light flashing. Because blue + red is purple, this is normal.

Yellow - Capslock indicator.

Red - means charging status. When start to charge, it will be on. When it is full, it will be off automatically.

5. Shortcut Keys:




6. Auto Sleep Mode

This keyboard has auto sleep / wake up function. when there is no any operation in 3 minutes, it will into sleep automatically. Press any button to wake it up. Make sure it is on enough power.

Using the Touch pad

The touch pad is activated together with the keyboard. When the keyboard is on, the keyboard is ready for you to use. FN + [Touchpad] can turn on/off touch pad. You will enjoy more convenience and control on-screen menu easier.

Infrared learning method



1. Pull the switch to turn on the keyboard power. When the connection is normal, the blue light will be on.

2. The 8 orange buttons on the keyboard are infrared learning keys. Press and hold one of the orange buttons until the keyboard purple light is on. At this time, the orange button is the learning receiving state.

3. Hold the remote control that is being studied. Align the front of the infrared emission area with the silkscreen mark on the top of the keyboard. The distance is about 3-5mm. Press the button you are learning to not release until the purple light flashes quickly 3 times and then go out, indicating learning success.

4. Repeat steps 2-3 to sequentially complete the 8 infrared learning keys. Use the infrared keys on the keyboard to control your device. If there are buttons that cannot be controlled normally, repeat steps 2-3.

Switching off the keyboard after use

After use, push the switch to the "OFF" position. The USB receiver does not need to be pulled out from the terminal. You can use it next time directly.

Charging the battery

The device uses built-in lithium-ion battery. Please use only approved USB cables and chargers.

Note: Fully charge the unit before initial operation. This device can be used when charging. But charging time will be extended. When the battery is low, the blue light will blink to warn the user. The unit will be automatically turned off if the battery has been depleted.

Multi-finger Functions Touchpad

This touchpad supports multi-finger functions.

1. Single-finger click functions as mouse left click.
2. Two-finger click functions as mouse right click.
3. Two-finger dragging functions as mouse Scrolling.
4. Single-finger functions as sliding pointer.

Turn on/off the Backlit LED (Only for Backlight versions)

Two Modes: Software Control and Manual Control

After the keyboard is turned on, you can press the [Backlight] button to manually switch the backlight to save power.

Backlit (Only for backlight versions)

When the keyboard is turned on, there is no button or touch. The backlight will turn off after 15 seconds. Press the button or touch again, the backlight will automatically light up.

Warning

- When charging finishes, pull out the charging cable.
- Never try to open or repair this product yourself.
- Keep this device away from fluids, such as water.

Maintenance

- Do not attempt to disassemble the device or replace the rechargeable battery yourself.

- The battery will discharge when it is stored for a long time without operation.
- Use the specified charger. Disconnect the device when the battery is fully charged.
- Overcharging will shorten the battery life.

Disposal

Always dispose the used appliance at a recycling center. Do not dispose the used appliance together with the household waste.

Note: Due to 2.4G wave technology adoption, the connection can be subject to interference from obstacles, like walls, metals, or other electronic devices. Please keep the space between the keyboard and USB receiver free of obstacle.

In line with the policy of continued development, the manufacturer reserves the right to amend the specifications without prior notification. The illustrations in the user manual are for reference only. Please operate according to the real design.

项目名称	RT 851	备注	
物料名称	RT 851说明书	版本	V1.0
物料编号	RG.06251004001	制作	James
物料尺寸	100*90mm	日期	2019-9-18