

RF EXPOSURE EVALUATION

EUT Specification

EUT	Portable Bluetooth Boombox
Frequency band (Operating)	<input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input type="checkbox"/> WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz <input type="checkbox"/> WLAN: 5.745GHz ~ 5.825GHz <input checked="" type="checkbox"/> Others(Bluetooth: 2.402GHz ~ 2.480GHz)
Device category	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others ____
Antenna diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Max. output power	1.575 (1.44mW) for BDR+EDR
Antenna gain	-0.58dBi
Evaluation applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure (MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)
300-1500	--	--	F/1500
1500-100000	--	--	1

Friis transmission formula: $Pd=(Pout \cdot G) / (4 \cdot \pi \cdot R^2)$

Where

Pd = Power density in mW/cm^2

$Pout$ =output power to antenna in mW

G = gain of antenna in linear scale

π =3.1416

R = distance between observation point and center of the radiator in cm

Pd the limit of MPE, $1mW/cm^2$. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

Channel	Channel Frequency (MHz)	Max Output power (dBm)	Max Output power (mW)	Power density at 20cm (mW/cm^2)	Power density Limits (mW/cm^2)
2.4G BT GFSK					
High	2480	1.575	1.44	0.000251	1

According to KDB447498 D01 V06, Compliance with RF Exposure requirement.