



KSIGN (Guangdong) Testing Co., Ltd.

West Side of 1/F., Building C, Zone A, Fuyuan New Factory, Jiujiu Industrial Park,
Minzhu, Shatou, Shajing, Bao'an District, Shenzhen, Guangdong, People's Republic of China
Tel.: + (86)755-29852678 Fax: + (86)755-29852397 E-mail: info@gdksign.cn Website: www.gdksign.com

Maximum Permissible Exposure Evaluation

FCC ID: 2AWOV-SW-BLE03

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b)

EUT Specification

EUT	SW-BLE03
Frequency band (Operating)	<input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz/2.422GHz~2.452 GHz <input type="checkbox"/> WCDMA Band II, Band IV, Band V <input type="checkbox"/> LTE FDD Band 2, Band 4, Band 5, Band 12 <input checked="" type="checkbox"/> Others
Device category	<input type="checkbox"/> Portable (<20cm separation) <input type="checkbox"/> Mobile (>20cm separation) <input checked="" type="checkbox"/> Fixed (>20cm separation) <input type="checkbox"/> Others ____
Exposure classification	<input type="checkbox"/> Occupational/Controlled exposure (S=5mW/cm2) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm2)
Antenna diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Max. output power	-7.51 dBm
Antenna gain (Max)	0dBi
Evaluation applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation



Limits for Maximum Permissible Exposure (MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot R^2)$

Where

P_d = Power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm


P_d the limit of MPE 1mW/cm². If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

Operating Mode	Channel Frequency (MHz)	Max. Measured Power (dBm)	Tune up tolerance (dBm)	Max. Tune up Power (dBm)	Antenna Gain (dBi)	Power density at 20cm (mW/cm ²)	Power density Limits (mW/cm ²)
CH00	2402	-7.51	-7.51±1	-6.51	0	4.436 x 10 ⁻⁵	1
CH19	2440	-8.63	-8.63±1	-7.63	0	3.442 x 10 ⁻⁵	1
CH39	2480	-9.83	-9.83±1	-8.83	0	2.606 x 10 ⁻⁵	1

Note

For a more detailed features description, please refer to the RF Test Report.



*****THE END*****