



RADIO TEST REPORT

Report No.: SHATBL2208018W01

Applicant:
Suzhou EICCOMM Technology CO., Ltd.

Address:
Room 304, Building 4, Zhuyuan Road 209, GAOXIN District, Suzhou,
Jiangsu Province, China

Product Name : LED tube

Brand Name : RAB

Model Name : LCBT8-18-48P-8TW-SD-BYP-SS

Series Model : N/A

Test Standard : FCC Part15.247

FCC ID : 2AXD8-BLET8WT

"Shanghai ATBL Technology Co., Ltd." hereby certifies that according to actual testing conditions. The test results or observations are provided in accordance with measured value, without taking risks caused by uncertainty into account. Without explicit stipulation in special agreements, standards or regulations, ATBL shall not assume any responsibility. The test results or observations are applicable only to tested sample. Client shall be responsible for representativeness of the sample and authenticity of the material. This report will be void without authorized signature or special seal for testing report. Do not copied without authorization.

Tel:+86(0)21-51298625

Web:www.atbl-lab.com

Email:atbl@atbl-lab.com

GENERAL DESCRIPTION

Applicant's Name..... : Suzhou EICCOMM Technology CO., Ltd.
Address..... : Room 304, Building 4, Zhuyuan Road 209, GAOXIN District, Suzhou, Jiangsu Province, China
Manufacture's Name..... : RAB lighting INC
Address..... : No. 9, Jiaozhou Road, Jingan District, Shanghai, China

Product Description

Product Name..... : LED tube
Brand Name..... : RAB
Model Name..... : LCBT8-18-48P-8TW-SD-BYP-SS
SeriesModel..... : N/A

Test Standards..... : FCC Part15.247
Test Procedure..... : ANSI C63.10-2013

This device described above has been tested by ATBL, the test results show that the equipment under test (EUT) is in compliance with the FCC requirements. And it is applicable only to the tested sample identified in the report.

This report shall not be reproduced except in full, without the written approval of ATBL, this document may be altered or revised by ATBL, personal only, and shall be noted in the revision of the document.

Date of receipt of test item..... : 16 Aug. 2022
Date (s) of performance of tests..... : 16 Aug. 2022 ~ 20 Aug. 2022
Date of Issue..... : 20 Aug. 2022
Test Result..... : **Pass**

Report Prepared by :

Roean Wei

(Roean Wei)

Report Approved by :

Ghost Li.

(Ghost Li)

Authorized Signatory :

Terry Yang

(Terry Yang)



Table of Contents

1. SUMMARY OF TEST RESULTS	6
2. GENERAL INFORMATION	7
2.1 GENERAL DESCRIPTION OF THE EUT	7
2.2 DESCRIPTION OF THE TEST MODES	9
2.3 TEST SOFTWARE AND POWER LEVEL	9
2.4 BLOCK DIGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED	10
2.5 DESCRIPTION OF NECESSARY ACCESSORIES AND SUPPORT UNITS	11
2.6 LABORATORY INFORMATION	11
2.7 MEASUREMENT UNCERTAINTY	12
2.8 EQUIPMENTS LIST	13
3. EMC EMISSION TEST	15
3.1 CONDUCTED EMISSION MEASUREMENT	15
3.2 TEST PROCEDURE	15
3.3 TEST SETUP	16
3.4 EUT OPERATING CONDITIONS	16
3.5TEST RESULTS	16
4. RADIATED EMISSION MEASUREMENT	18
4.1 RADIATED EMISSION LIMITS	18
4.2 TEST PROCEDURE	20
4.3 TEST SETUP	21
4.4 EUT OPERATING CONDITIONS	21
4.5 FIELD STRENGTH CALCULATION	22
4.6 TEST RESULTS	23
5. CONDUCTED SPURIOUS & BAND EDGE EMISSION	36
5.1 LIMIT	36
5.2 TEST PROCEDURE	36
5.3 TEST SETUP	36
5.4 EUT OPERATION CONDITIONS	36
5.5 TEST RESULTS	37
6. POWER SPECTRAL DENSITY TEST	40
6.1 LIMIT	40
6.2 TEST PROCEDURE	40
6.3 TEST SETUP	40

Table of Contents

6.4 EUT OPERATION CONDITIONS	40
6.5 TEST RESULTS	41
7. BANDWIDTH TEST	43
7.1 LIMIT	43
7.2 TEST PROCEDURE	43
7.3 TEST SETUP	43
7.4 EUT OPERATION CONDITIONS	43
7.5 TEST RESULTS	44
8. PEAK OUTPUT POWER TEST	46
8.1 LIMIT	46
8.2 TEST PROCEDURE	46
8.3 TEST SETUP	46
8.4 EUT OPERATION CONDITIONS	46
8.5 TEST RESULTS	46
9. ANTENNA REQUIREMENT	49
9.1 STANDARD REQUIREMENT	49
9.2 EUT ANTENNA	49
APPENDIX-PHOTOS OF TEST SETUP	50

Revision History

Rev.	Issue Date	Report NO.	Effect Page	Contents
00	20 Aug. 2022	SHATBL2208018W01	ALL	Initial Issue

1. SUMMARY OF TEST RESULTS

Test procedures according to the technical standards:
KDB 558074 D01 15.247 Meas Guidance v05r02.

FCC Part15.247,Subpart C			
Standard Section	Test Item	Judgment	Remark
15.207	Conducted Emission	PASS	--
15.247 (a)(2)	6dB&99% Bandwidth	PASS	--
15.247 (b)(3)	Output Power	PASS	--
15.247(d) & 15.209 & 15.205	Radiated Spurious Emission	PASS	--
15.247(d) & 15.205	Conducted Spurious & Band Edge Emission	PASS	--
15.247 (e)	Power Spectral Density	PASS	--
15.205	Restricted bands of operation	PASS	--
15.203	Antenna Requirement	PASS	--

NOTE:

- (1) 'N/A' denotes test is not applicable in this Test Report.
- (2) All tests are according to ANSI C63.10-2013.

2. GENERAL INFORMATION

2.1 GENERAL DESCRIPTION OF THE EUT

Product Name	LED tube	
Trade Name	RAB	
Model Name	LCBT8-18-48P-8TW-SD-BYP-SS	
Series Model	T8-12-48G-8xx-SD-BYP-DIM/LCB	
Model Difference	The color temperature is different	
Product Description	The EUT is a LED tube	
	Operation Frequency:	2402~2480 MHz
	Modulation Type:	GFSK
	Radio Technology:	BLE
	Bluetooth Version:	5.0
	Bluetooth Configuration:	LE(Support 1M PHY)
	Number Of Channel:	40
	Antenna Designation:	Please refer to the Note 3.
	AntennaGain (dBi)	-1.8 dBi
Channel List	Please refer to the Note 2.	
Power Rating	18W	
Battery	N/A	
Hardware version number	V2.0	
Software versionnumber	V1.0.1	
Connecting I/O Port(s)	Please refer to the Note 1.	

Note:

1. For a more detailed features description, please refer to the manufacturer's specifications or the User Manual.

2.

Channel List							
Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
00	2402	10	2422	20	2442	30	2462
01	2404	11	2424	21	2444	31	2464
02	2406	12	2426	22	2446	32	2466
03	2408	13	2428	23	2448	33	2468
04	2410	14	2430	24	2450	34	2470
05	2412	15	2432	25	2452	35	2472
06	2414	16	2434	26	2454	36	2474
07	2416	17	2436	27	2456	37	2476
08	2418	18	2438	28	2458	38	2478
09	2420	19	2440	29	2460	39	2480

3.

Table for Filed Antenna

Ant.	Brand	Model Name	Antenna Type	Connector	Gain (dBi)	NOTE
1	RAB	LCBT8-18-48P-8TW-SD-BYP-S S	Single-stage	N/A	-1.8 dBi	BLE ANT

2.2 DESCRIPTION OF THE TEST MODES

For conducted test items and radiated spurious emissions

Each of these EUT operation mode(s) or test configuration mode(s) mentioned below was evaluated respectively.

Worst Mode	Description	Data/Modulation
Mode 1	TX CH00(2402MHz)	1 Mbps/GFSK
Mode 2	TX CH19(2440MHz)	1 Mbps/GFSK
Mode 3	TX CH39(2480MHz)	1 Mbps/GFSK

Note:

(1) The measurements are performed at all Bit Rate of Transmitter, the worst data was reported.

For Conducted Emission

Test Case	
Conducted Emission	Mode 4 : Keeping BT TX


2.3 TEST SOFTWARE AND POWER LEVEL

During testing channel & power controlling software provided by the customer was used to control the operating channel as well as the output power level.


RF Function	Type	Mode Or Modulation type	Ant Gain(dBi)	Power Class	Software For Testing
BLE	BLE	GFSK	-1.8	default	EMI_Test_Tool

2.4 BLOCK DIGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED

Radiated Spurious Emission Test



Conduction Emission Test



2.5 DESCRIPTION OF NECESSARY ACCESSORIES AND SUPPORT UNITS

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

Necessary accessories

Item	Equipment	Mfr/Brand	Model/Type No.	Length	Note
N/A	N/A	N/A	N/A	N/A	N/A

Support units

Item	Equipment	Mfr/Brand	Model	Type No.	Note
E-2	Notebook	Lenovo	DESKTOP-USDEO09	00326-10000-00000-AA636	N/A
C-1	USB Cable	N/A	100cm	N/A	N/A

Note:

- (1) The support equipment was authorized by Declaration of Confirmation.
- (2) For detachable type I/O cable should be specified the length in cm in 『Length』 column.

2.6 LABORATORY INFORMATION

Company Name:	Shanghai ATBL Technology Co., Ltd.
Address:	Building 8, No. 160, Basheng Road, Waigaoqiao Free Trade Zone, Pudong New Area, Shanghai
Telephone:	+86(0)21-51298625
The FCC Registration Number (FRN):	0031025281
A2LA Number:	6184.01
CNAS Number:	CNAS L14531

2.7 MEASUREMENT UNCERTAINTY

The reported uncertainty of measurement $y \pm U$, where expanded uncertainty U is based on a standard uncertainty multiplied by a coverage factor of $k=2$, providing a level of confidence of approximately 95 %.

No.	Item	Uncertainty
1	RF output power, conducted	$\pm 0.962\text{dB}$
2	Conducted spurious emissions	$\pm 2.986\text{dB}$
3	All emissions, radiated 30MHz-1GHz	$\pm 2.49\text{dB}$
4	All emissions, radiated 1GHz-18GHz	$\pm 3.50\text{dB}$
5	Occupied bandwidth	$\pm 23.36\text{dB}$
6	Power spectral density	$\pm 0.866\text{dB}$

2.8 EQUIPMENTS LIST

2.8.1 Radiation Test equipment

Kind of Equipment	Manufacturer	Type No.	Serial No.	Management number	Calibrated until
Test Receiver	R&S	ESCI	100469	SHATBL-E003	2023.05.20
Spectrum Analyzer	Agilent	N9020A	MY50200811	SHATBL-E017	2023.05.20
Bilog Antenna	SCHWARZBECK	VLUB 9168	01174	SHATBL-E008	2023.05.20
Horn Antenna	SCHWARZBECK	BBHA 9120D	02014	SHATBL-E009	2023.05.20
Pre-Amplifier (0.1M-3GHz)	JPT	JPA-10M1G35	21010100035001	SHATBL-E005	2023.05.20
Pre-Amplifier (1G-18GHz)	JPT	JPA0118-55-303A	1910001800055000	SHATBL-E006	2023.05.20
Temperature & Humidity	DeLi	DeLi	N/A	SHATBL-E016	2023.05.20
Antenna/Turntable Controller	Brilliant	N/A	N/A	SHATBL-E007	N/A
Test SW	FALA	EMC-RI(Ver.4A2)		SHATBL-E046	N/A

2.8.2 Conduction Test equipment

Kind of Equipment	Manufacturer	Type No.	Serial No.	Management number	Calibration date
Test Receiver	R&S	ESPI	101679	SHATBL-E012	2023.05.20
LISN	R&S	ENV216	101300	SHATBL-E013	2023.05.20
LISN	R&S	ENV216	100333	SHATBL-E041	2023.05.20
Temperature & Humidity	DeLi	DeLi	N/A	SHATBL-E015	2023.05.20
Test SW	FALA	EZ-EMC(Ver.EMC-CON3A1.1)		SHATBL-E044	N/A

2.8.3 RF Connected Test

Kind of Equipment	Manufacturer	Type No.	Serial No.	equipment number	Calibrated until
Power meter (with pulse power sensor)	Anritsu	ML2496A	1935001	SHATBL-W030	2022.10.26
Pulse power sensor (with power meter)	Anritsu	MA2411B	1911006	SHATBL-W031	2022.10.26
Signal Analyzer	Agilent	N9020A	MY57300196	SHATBL-W004	2022.10.07
Signal Generator	Agilent	N5182B	MY46240556	SHATBL-W005	2022.10.07
Wireless Communications Test Set	R&S	CMW500	101331	SHATBL-W007	2022.10.07
Temperature & Humidity	Deli	deli	N/A	SHATBL-W011	2022.10.07
Attenuator	Agilent	8494B	DC-18G	SHATBL-W009	2022.10.07
Attenuator	Agilent	8496B	DC-18G	SHATBL-W010	2022.10.07
power splitter	MNK	MPD-DC/6-2 S	62315 G51	SHATBL-W015	2022.10.07
			62315 G52	SHATBL-W016	2022.10.07
Filter	Chengdu kangmaiwei	ZBSF-C2400 -2483.5-T3	N/A	SHATBL-W021	N/A
Constant temperature and humidity box	KSON	THS-B6C-150	6159K	SHATBL-W019	2023.01.17
Test SW	FALA	LZ-RF(Ver.LzRF-03A3.1)		SHATBL-W020	N/A

3. EMC EMISSION TEST

3.1 CONDUCTED EMISSION MEASUREMENT

3.1.1 POWER LINE CONDUCTED EMISSION LIMITS

Operating frequency band. In case the emission fall within the restricted band specified on Part 207(a)limit in the table below has to be followed.

FREQUENCY (MHz)	Conducted Emissionlimit (dBUV)	
	Quasi-peak	Average
0.15 -0.5	66 - 56 *	56 - 46 *
0.50 -5.0	56.00	46.00
5.0 -30.0	60.00	50.00

Note:

- (1) The tighter limit applies at the band edges.
- (2) The limit of “ * ” marked band means the limitation decreases linearly with the logarithm of the frequency in the range.


The following table is the setting of the receiver

Receiver Parameters	Setting
Attenuation	10 dB
Start Frequency	0.15 MHz
Stop Frequency	30 MHz
IF Bandwidth	9 kHz

3.2 TEST PROCEDURE

- a. The EUT is 0.8 m from the horizontal ground plane and 0.4 m from the vertical ground plane with EUT being connected to the power mains through a line impedance stabilization network (LISN). All other support equipments are powered from additional LISN(s). The LISN provides 50 Ohm/ 50uH of coupling impedance for the measuring instrument.
- b. Interconnecting cables that hang closer than 40 cm to the ground plane shall be folded back and forth in the center forming a bundle 30 to 40 cm long.
- c. I/O cables that are not connected to a peripheral shall be bundled in the center. The end of the cable may be terminated, if required, using the correct terminating impedance. The overall length shall not exceed 1 m.
- d. LISN is at least 80 cm from the nearest part of EUT chassis.
- e. For the actual test configuration, please refer to the related Item –EUT Test Photos.

3.3 TEST SETUP




3.4 EUT OPERATING CONDITIONS


The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.

3.5 TEST RESULTS

L1



No.	Frequency (MHz)	Reading (dBuV)	Correct (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Remark
1	0.1780	47.86	9.76	57.62	79.00	-21.38	QP
2	0.1780	35.95	9.76	45.71	66.00	-20.29	AVG
3	0.4550	34.38	9.75	44.13	79.00	-34.87	QP
4	0.4550	16.34	9.75	26.09	66.00	-39.91	AVG
5	2.1140	31.60	9.79	41.39	73.00	-31.61	QP
6	2.1140	13.80	9.79	23.59	60.00	-36.41	AVG
7	3.3450	31.74	9.82	41.56	73.00	-31.44	QP
8	3.3450	14.08	9.82	23.90	60.00	-36.10	AVG
9	9.5150	32.30	9.96	42.26	73.00	-30.74	QP
10	9.5150	11.69	9.96	21.65	60.00	-38.35	AVG
11	27.1260	33.30	10.37	43.67	73.00	-29.33	QP
12	27.1260	24.84	10.37	35.21	60.00	-24.79	AVG



No.	Frequency (MHz)	Reading (dBuV)	Correct (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Remark
1	0.1790	48.18	9.73	57.91	79.00	-21.09	QP
2	0.1790	36.01	9.73	45.74	66.00	-20.26	AVG
3	0.3350	40.43	9.72	50.15	79.00	-28.85	QP
4	0.3350	12.94	9.72	22.66	66.00	-43.34	AVG
5	1.0070	38.66	9.73	48.39	73.00	-24.61	QP
6	1.0070	18.75	9.73	28.48	60.00	-31.52	AVG
7	1.5950	37.43	9.75	47.18	73.00	-25.82	QP
8	1.5950	18.89	9.75	28.64	60.00	-31.36	AVG
9	4.8560	30.78	9.84	40.62	73.00	-32.38	QP
10	4.8560	14.48	9.84	24.32	60.00	-35.68	AVG
11	27.0370	34.36	10.45	44.81	73.00	-28.19	QP
12	27.0370	26.02	10.45	36.47	60.00	-23.53	AVG

4. RADIATED EMISSION MEASUREMENT

4.1 RADIATED EMISSION LIMITS

In any 100 kHz bandwidth outside the operating frequency band. In case the emission fall within the Restricted band specified on Part15.205(a)&209(a) limit in the table and according to ANSI C63.10-2013below has to be followed.

LIMITS OF RADIATED EMISSION MEASUREMENT (Frequency Range 9kHz-1000MHz)

Frequencies (MHz)	Field Strength (micorvolts/meter)	Measurement Distance (meters)
0.009~0.490	2400/F(KHz)	300
0.490~1.705	24000/F(KHz)	30
1.705~30.0	30	30
30~88	100	3
88~216	150	3
216~960	200	3
Above 960	500	3

LIMITS OF RADIATED EMISSION MEASUREMENT (Above 1000MHz)

FREQUENCY (MHz)	(dBuV/m) (at 3M)	
	PEAK	AVERAGE
Above 1000	74	54

Notes:

- (1) The limit for radiated test was performed according to FCC PART 15C.
- (2) The tighter limit applies at the band edges.
- (3) Emission level (dBuV/m)=20log Emission level (uV/m).

LIMITS OF RESTRICTED FREQUENCY BANDS

FCC:

FREQUENCY (MHz)	FREQUENCY (MHz)	FREQUENCY (MHz)	FREQUENCY (GHz)
0.090-0.110	16.42-16.423	399.9-410	4.5-5.15
0.495-0.505	16.69475-16.69525	608-614	5.35-5.46
2.1735-2.1905	16.80425-16.80475	960-1240	7.25-7.75
4.125-4.128	25.5-25.67	1300-1427	8.025-8.5
4.17725-4.17775	37.5-38.25	1435-1626.5	9.0-9.2
4.20725-4.20775	73-74.6	1645.5-1646.5	9.3-9.5
6.215-6.218	74.8-75.2	1660-1710	10.6-12.7
6.26775-6.26825	108-121.94	1718.8-1722.2	13.25-13.4
6.31175-6.31225	123-138	2200-2300	14.47-14.5
8.291-8.294	149.9-150.05	2310-2390	15.35-16.2
8.362-8.366	156.52475-156.52525	2483.5-2500	17.7-21.4
8.37625-8.38675	156.7-156.9	2690-2900	22.01-23.12
8.41425-8.41475	162.0125-167.17	3260-3267	23.6-24.0
12.29-12.293	167.72-173.2	3332-3339	31.2-31.8
12.51975-12.52025	240-285	3345.8-3358	36.43-36.5
12.57675-12.57725	322-335.4	3600-4400	Above 38.6
13.36-13.41			

For Radiated Emission

Spectrum Parameter	Setting
Attenuation	Auto
Detector	Peak/QP/AV
Start Frequency	9 KHz/150KHz(Peak/QP/AV)
Stop Frequency	150KHz/30MHz(Peak/QP/AV)
RB / VB (emission in restricted band)	200Hz (From 9kHz to 0.15MHz)/ 9KHz (From 0.15MHz to 30MHz); 200Hz (From 9kHz to 0.15MHz)/ 9KHz (From 0.15MHz to 30MHz)

Spectrum Parameter	Setting
Attenuation	Auto
Detector	Peak/QP
Start Frequency	30 MHz(Peak/QP)
Stop Frequency	1000 MHz (Peak/QP)
RB / VB (emission in restricted band)	120 KHz / 300 KHz

Spectrum Parameter	Setting
Attenuation	Auto
Detector	Peak/AV
Start Frequency	1000 MHz(Peak/AV)
Stop Frequency	10th carrier hamonic(Peak/AV)
RB / VB (emission in restricted band)	1MHz / 3MHz(Peak) 1 MHz/1/T MHz(AVG)

For Restricted band

Spectrum Parameter	Setting
Detector	Peak/AV
Start/Stop Frequency	Lower Band Edge: 2310 to 2410 MHz Upper Band Edge: 2475to 2500 MHz
RB / VB	1 MHz / 3 MHz(Peak) 1 MHz/1/T MHz(AVG)

Receiver Parameter	Setting
Start ~ Stop Frequency	9kHz~90kHz / RB 200Hz for PK & AV
Start ~ Stop Frequency	90kHz~110kHz / RB 200Hz for QP
Start ~ Stop Frequency	110kHz~490kHz / RB 200Hz for PK & AV
Start ~ Stop Frequency	490kHz~30MHz / RB 9kHz for QP
Start ~ Stop Frequency	30MHz~1000MHz / RB 120kHz for QP

4.2 TEST PROCEDURE


- The measuring distance of at 3 m shall be used for measurements at frequency 0.009MHz up to 1GHz, and above 1GHz.
- The EUT was placed on the top of a rotating table 0.8 meters (above 1GHz is 1.5 m) above the ground at a 3 meter anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.
- The height of the equipment shall be 0.8 m (above 1GHz is 1.5 m); the height of the test antenna shall vary between 1 m to 4 m. Horizontal and vertical polarizations of the antenna are set to make the measurement.
- The initial step in collecting conducted emission data is a spectrum analyzer peak detector mode pre-scanning the measurement frequency range. Significant peaks are then marked and then Quasi Peak detector mode re-measured.
- If the Peak Mode measured value compliance with and lower than Quasi Peak Mode Limit, the EUT shall be deemed to meet QP Limits and then no additional QP Mode measurement performed.
- For the actual test configuration, please refer to the related Item –EUT Test Photos.

Note:


Both horizontal and vertical antenna polarities were tested and performed pretest to three orthogonal axis. The worst case emissions were reported.

4.3 TEST SETUP


(A) Radiated Emission Test-Up Frequency Below 30MHz



(B) Radiated Emission Test-Up Frequency 30MHz~1GHz



(C) Radiated Emission Test-Up Frequency Above 1GHz



4.4 EUT OPERATING CONDITIONS

The EUT tested system was configured as the statements of 2.3 Unless otherwise a special operating condition is specified in the follows during the testing.

4.5 FIELD STRENGTH CALCULATION

The field strength is calculated by adding the Antenna Factor and Cable Factor and subtracting the Amplifier Gain and Duty Cycle Correction Factor (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CL - AG$$

Where

FS = Field Strength

CL = Cable Attenuation Factor (Cable Loss)

RA = Reading Amplitude

AG = Amplifier Gain

AF = Antenna Factor

For example

Frequency	FS	RA	AF	CL	AG	Factor
(MHz)	(dBμV/m)	(dBμV/m)	(dB)	(dB)	(dB)	(dB)
300	40	58.1	12.2	1.6	31.9	-18.1

$$\text{Factor} = \text{AF} + \text{CL} - \text{AG}$$

4.6 TEST RESULTS

Temperature:	23.0℃	Relative Humidity:	59%RH
Test Voltage:	DC 3V	Polarization:	--
Test Mode:	TX Mode1/3		

Note:

The amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has no need to be reported.

Distance extrapolation factor = $40 \log (\text{specific distance/test distance})$ (dB);

Limit line = specific limits(dBuv) + distance extrapolation factor.

(9KHz-30MHz)

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Horizontal / Vertical
Test Mode:	TX Mode 1		

Remark:

1. 9KHz-30MHz Emission detected are more than 20dB below the limit.

(30MHz -1000MHz)


Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Horizontal
Test Mode:	TX Mode 1		

Remark:

1. Margin = Result (Result =Reading + Factor)–Limit

2. Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 1 Horizontal



Mk.	Freq.(MHz)	Level(d BuV/m)	Limit(dB uV/m)	Margin(dB)	Ant.F/G.(d B/m)	Amp.G.(d B)	Cbl.L. (dB)	Pol.
1	42.080322	10.9	40.0	29.1	14.0	32.4	0.8	H
2	75.977347	3.3	40.0	36.7	9.9	32.9	0.9	H
3	155.092197	11.0	43.5	32.5	14.1	32.9	1.4	H
4	243.804269	10.0	46.0	36.0	11.5	32.8	2.5	H
5	334.858889	13.0	46.0	33.0	13.2	32.6	2.7	H
6	603.539169	16.4	46.0	29.6	16.0	32.3	3.4	H


Temperature:	23.0℃	Relative Humidity:	59%RH
Test Voltage:	DC 3V	Phase:	Vertical
Test Mode:	TX Mode 1		

Remark:

1. Margin = Result (Result = Reading + Factor)—Limit

2. Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 1 Vertical



Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dBuV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
1	44.508721	10.2	40.0	29.8	13.8	32.5	0.8	V
2	134.559188	10.3	43.5	33.2	13.1	32.9	1.4	V
3	244.660683	10.2	46.0	35.8	11.5	32.8	2.5	V
4	417.641063	13.1	46.0	32.9	15.2	32.3	2.7	V
5	605.659229	19.3	46.0	26.7	18.4	32.3	3.4	V
6	895.425214	24.6	46.0	21.4	21.6	31.6	3.6	V


(30MHz -1000MHz)

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Horizontal
Test Mode:	TX Mode 3		

Remark:

1. Margin = Result (Result = Reading + Factor)–Limit
2. Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 3 Horizontal




Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dB uV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
1	43.505724	10.6	40.0	29.4	13.9	32.5	0.8	H
2	137.179492	9.9	43.5	33.6	13.3	32.9	1.4	H
3	245.950949	10.4	46.0	35.6	11.5	32.8	2.5	H
4	425.773890	14.1	46.0	31.9	14.1	32.4	2.7	H
5	604.598270	16.1	46.0	29.9	16.0	32.3	3.4	H
6	892.290853	23.2	46.0	22.8	19.6	31.7	3.6	H

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Vertical
Test Mode:	TX Mode 3		

Remark:

1. Margin = Result (Result = Reading + Factor)–Limit
2. Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 3 Vertical



Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dBuV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
1	42.599954	10.7	40.0	29.3	13.9	32.4	0.8	V
2	66.266167	5.8	40.0	34.2	11.5	32.8	0.8	V
3	159.784415	10.7	43.5	32.8	14.1	32.9	1.5	V
4	333.686743	13.5	46.0	32.5	13.5	32.6	2.7	V
5	605.659229	18.6	46.0	27.4	18.4	32.3	3.4	V
6	890.727788	25.1	46.0	20.9	21.5	31.7	3.6	V


(1000MHz -18000MHz)

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Horizontal
Test Mode:	TX Mode 1		

Remark:

- Margin = Result (Result =Reading + Factor)–Limit
- Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 1 Horizontal




Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dBuV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
Peak								
1	1434.400000	33.1	74.0	40.9	20.8	57.3	2.4	H
2	2240.900000	42.7	74.0	31.3	22.5	50.1	2.8	H
3	3490.500000	40.9	74.0	33.1	24.2	50.5	3.1	H
4	5471.250000	45.9	74.0	28.1	24.9	49.1	4.0	H
5	7913.250000	48.7	74.0	25.3	26.0	48.6	4.8	H
6	16385.250000	59.0	74.0	15.0	30.8	48.0	6.7	H
Avg								
1	1434.400000	24.5	54.0	29.5	20.8	57.3	2.4	H
2	2240.900000	33.1	54.0	20.9	22.5	50.1	2.8	H
3	3490.500000	31.6	54.0	22.4	24.2	50.5	3.1	H
4	5471.250000	36.7	54.0	17.3	24.9	49.1	4.0	H
5	7913.250000	38.7	54.0	15.3	26.0	48.6	4.8	H
6	16385.250000	50.8	54.0	3.2	30.8	48.0	6.7	H

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Vertical
Test Mode:	TX Mode 1		

Remark:

1. Margin = Result (Result = Reading + Factor) - Limit
2. Factor = Antenna factor + Cable attenuation factor (cable loss) - Amplifier gain

Mode 1 Vertical



Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dBuV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
Peak								
1	1548.900000	34.1	74.0	39.9	21.1	56.6	2.5	V
2	2458.400000	42.6	74.0	31.4	23.3	50.2	2.8	V
3	3909.000000	42.6	74.0	31.4	24.7	50.2	3.2	V
4	6153.750000	48.2	74.0	25.8	25.7	48.9	4.2	V
5	10444.500000	54.4	74.0	19.6	28.8	48.6	5.5	V
6	16768.500000	60.1	74.0	13.9	31.4	47.5	6.8	V
Avg								
1	1548.900000	25.8	54.0	28.2	21.1	56.6	2.5	V
2	2458.400000	32.6	54.0	21.4	23.3	50.2	2.8	V
3	3909.000000	34.5	54.0	19.5	24.7	50.2	3.2	V
4	6153.750000	38.3	54.0	15.7	25.7	48.9	4.2	V
5	10444.500000	45.4	54.0	8.6	28.8	48.6	5.5	V
6	16768.500000	51.5	54.0	2.5	31.4	47.5	6.8	V


(1000MHz -18000MHz)

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Horizontal
Test Mode:	TX Mode 3		

Remark:

1. Margin = Result (Result =Reading + Factor)–Limit
2. Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 3 Horizontal




Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dBuV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
Peak								
1	1344.600000	32.8	74.0	41.2	20.8	57.3	2.3	H
2	2112.600000	42.2	74.0	31.8	22.2	50.1	2.7	H
3	3517.500000	41.8	74.0	32.2	24.2	50.5	3.1	H
4	5568.750000	45.7	74.0	28.3	25.0	49.1	4.0	H
5	9681.750000	52.1	74.0	21.9	27.4	48.5	5.4	H
6	16750.500000	59.3	74.0	14.7	30.9	47.5	6.8	H
Avg								
1	1344.600000	24.1	54.0	29.9	20.8	57.3	2.3	H
2	2112.600000	31.3	54.0	22.7	22.2	50.1	2.7	H
3	3517.500000	32.7	54.0	21.3	24.2	50.5	3.1	H
4	5568.750000	36.9	54.0	17.1	25.0	49.1	4.0	H
5	9681.750000	42.5	54.0	11.5	27.4	48.5	5.4	H
6	16750.500000	51.8	54.0	2.2	30.9	47.5	6.8	H

Temperature:	23.3℃	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Phase:	Vertical
Test Mode:	TX Mode 3		

Remark:

1. Margin = Result (Result = Reading + Factor)–Limit
2. Factor= Antenna factor+Cable attenuation factor(cable loss)-Amplifier gain

Mode 3 Vertical




Mk.	Freq.(MHz)	Level(dBuV/m)	Limit(dBuV/m)	Margin(dB)	Ant.F/G.(dB/m)	Amp.G.(dB)	Cbl.L.(dB)	Pol.
Peak								
1	1445.100000	33.0	74.0	41.0	20.9	57.3	2.4	V
2	2426.700000	45.1	74.0	28.9	23.2	50.2	2.8	V
3	3708.750000	42.5	74.0	31.5	24.7	50.3	3.2	V
4	5948.250000	47.0	74.0	27.0	25.5	48.9	4.1	V
5	10488.750000	54.4	74.0	19.6	28.9	48.6	5.5	V
6	16750.500000	60.3	74.0	13.7	31.4	47.5	6.8	V
Avg								
1	1445.100000	23.9	54.0	30.1	20.9	57.3	2.4	V
2	2426.700000	39.0	54.0	15.0	23.2	50.2	2.8	V
3	3708.750000	34.3	54.0	19.7	24.7	50.3	3.2	V
4	5948.250000	37.9	54.0	16.1	25.5	48.9	4.1	V
5	10488.750000	44.8	54.0	9.2	28.9	48.6	5.5	V
6	16750.500000	51.5	54.0	2.5	31.4	47.5	6.8	V

Note:

- 1.All TX Mode, the worst case is mode1&3, only show the worst case.
- 2.Other 18G-25G Emission detected are more than 20dB below the limit.


4.6 TEST RESULTS (Restricted Bands Requirements)

GFSK-Low Horizontal




Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
PK								
1	2382.052625	43.0	74.0	31.0	22.7	50.2	2.8	H
2	2390.000000	41.2	74.0	32.8	22.8	50.2	2.8	H

Vertical




Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
PK								
1	2377.362179	43.1	74.0	30.9	23.1	50.2	2.8	V
2	2390.000000	42.2	74.0	31.8	23.1	50.2	2.8	V

GFSK-Low Horizontal




Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
AVG								
1	2378.013077	30.2	54.0	23.8	22.7	50.2	2.8	H
2	2390.000000	30.0	54.0	24.0	22.8	50.2	2.8	H

Vertical




Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
AVG								
1	2354.048124	30.6	54.0	23.4	23.0	50.2	2.8	V
2	2390.000000	30.2	54.0	23.8	23.1	50.2	2.8	V

GFSK-High Horizontal




Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
PK								
1	2483.500000	42.6	74.0	31.4	22.9	50.2	2.8	H
2	2487.943551	42.8	74.0	31.2	22.9	50.2	2.8	H

Vertical




Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
PK								
1	2483.500000	43.6	74.0	30.4	23.3	50.2	2.8	V
2	2488.487560	43.9	74.0	30.1	23.3	50.2	2.8	V

GFSK- High Horizontal



Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
AVG								
1	2483.500000	30.4	54.0	23.6	22.9	50.2	2.8	H
2	2485.949868	30.2	54.0	23.8	22.9	50.2	2.8	H

Vertical



Mk.	Frequency (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Ant.F/G. (dB/m)	Amp.G. (dB)	Cbl.L. (dB)	Pol.
AVG								
1	2483.500000	30.7	54.0	23.3	23.3	50.2	2.8	V
2	2486.191442	30.7	54.0	23.3	23.3	50.2	2.8	V

5. CONDUCTED SPURIOUS & BAND EDGE EMISSION

5.1 LIMIT

According to FCC section 15.247(d), in any 100kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20dB below that in the 100kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement.


5.2 TEST PROCEDURE

Spectrum Parameter	Setting
Detector	Peak
Start/Stop Frequency	30 MHz to 10th carrier harmonic
RB / VB (emission in restricted band)	100 KHz/300 KHz
Trace-Mode:	Max hold

For Band edge

Spectrum Parameter	Setting
Detector	Peak
Start/Stop Frequency	Lower Band Edge: 2300 – 2407 MHz Upper Band Edge: 2475 – 2500 MHz
RB / VB (emission in restricted band)	100 KHz/300 KHz
Trace-Mode:	Max hold

5.3 TEST SETUP



The EUT which is powered by the Battery, is connected to the Spectrum Analyzer; the RF load attached to the EUT antenna terminal is 50 Ohm; the path loss as the factor is calibrated to correct the reading. Make the measurement with the spectrum analyzer's resolution bandwidth(RBW) = 100 kHz. In order to make an accurate measurement, set the span greater than RBW.


5.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 2.3 Unless otherwise a special operating condition is specified in the follows during the testing.


5.5 TEST RESULTS

Temperature:	25°C	Relative Humidity:	50%RH
Test Voltage:	DC 3V	Test Mode:	TX Mode 1/2/3


Mode1 CH00



Mode2 CH19




Mode3 CH39




For Band edge(it's also the reference level for conducted spurious emission)

Mode1 CH00



Mode3 CH39



6. POWER SPECTRAL DENSITY TEST

6.1 LIMIT

FCC Part15.247,Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(e)	Power Spectral Density	≤ 8 dBm (RBW ≥ 3 KHz)	2400-2483.5	PASS

6.2 TEST PROCEDURE

1. Set analyzer center frequency to DTS channel center frequency.
2. Set the span to 1.5 times the DTS channel bandwidth.
3. Set the RBW to: $100\text{ kHz} \geq \text{RBW} \geq 3\text{ kHz}$.
4. Set the VBW $\geq 3 \times \text{RBW}$.
5. Detector = peak.
6. Sweep time = auto couple.
7. Trace mode = max hold.
8. Allow trace to fully stabilize.
9. Use the peak marker function to determine the maximum amplitude level.
10. If measured value exceeds limit, reduce RBW (no less than 3 kHz) and repeat.

6.3 TEST SETUP



6.4 EUT OPERATION CONDITIONS


The EUT tested system was configured as the statements of 2.3 Unless otherwise a special operating condition is specified in the follows during the testing.

6.5 TEST RESULTS


Temperature:	25 °C	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Test Mode:	TX Mode1/2/3

Frequency	Power Density	Limit (3KHz/dBm)	Result
	(dBm/3kHz)		
2402 MHz	3.146	≤8	PASS
2440 MHz	0.677	≤8	PASS
2480 MHz	0.000	≤8	PASS


Mode1 CH00



Mode2 CH19



Mode3 CH39



7. BANDWIDTH TEST

7.1 LIMIT

FCC Part15.247,Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(a)(2)	Bandwidth	$\geq 500\text{KHz}$ (6dB bandwidth)	2400-2483.5	PASS


7.2 TEST PROCEDURE

Connect the UUT to the spectrum analyser and use the following settings:

Center Frequency	The centre frequency of the channel under test
Detector	Peak
RBW	For 6 dB Bandwidth :100KHz For 99% Bandwidth :1% to 5% of the occupied bandwidth
VBW	For 6dB Bandwidth : $\geq 3 \times \text{RBW}$ For 99% Bandwidth : approximately $3 \times \text{RBW}$
Trace	Max hold
Sweep	Auto

Allow the trace to stabilize and measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB and 99% relative to the maximum level measured in the fundamental emission.

7.3 TEST SETUP



7.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 2.3 Unless otherwise a special operating condition is specified in the follows during the testing.


7.5 TEST RESULTS

Temperature:	25 °C	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Test Mode:	TX Mode1/2/3


Frequency	6dB Bandwidth (KHz)	99% Bandwidth (KHz)	6dB Bandwidth Limit(KHz)	Result
2402 MHz	671.4	1030.8	≥500KHz	PASS
2440 MHz	676.6	1033.0	≥500KHz	PASS
2480 MHz	668.5	1035.7	≥500KHz	PASS

6dB Bandwidth &99% Bandwidth


Mode1 CH00



Mode2 CH19



Mode3 CH39



8. PEAK OUTPUT POWER TEST

8.1 LIMIT

FCC Part15.247,Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(b)(3)	Output Power	1 watt or 30dBm	2400-2483.5	PASS

8.2 TEST PROCEDURE

PKPM1 Peak power meter method:

The maximum peak conducted output power may be measured using a broadband peak RF power meter. The power meter shall have a video bandwidth that is greater than or equal to the DTS bandwidth and shall use a fast-responding diode detector.

8.3 TEST SETUP



8.4 EUT OPERATION CONDITIONS

The EUT tested system was configured as the statements of 2.3 Unless otherwise a special operating condition is specified in the follows during the testing.

8.5 TEST RESULTS

Temperature:	25 °C	Relative Humidity:	60%RH
Test Voltage:	DC 3V	Test Mode:	TX Mode1/2/3


Test Channel	Frequency	Peak Conducted Output Power	Average Conducted Output Power	LIMIT
	(MHz)	(dBm)	(dBm)	dBm
CH00	2402	9.14	9.07	30
CH19	2440	9.53	9.48	30
CH39	2480	9.76	9.71	30

EIRP Power

Test Channel	Frequency	Peak Conducted Output Power	Antenna Gain	EIRP Power	LIMIT
	(MHz)	(dBm)	(dBi)	(dBm)	dBm
CH0	2402	9.14	-1.8	7.34	36
CH19	2440	9.53	-1.8	7.73	36
CH39	2480	9.76	-1.8	7.96	36

Note: Our power sensor test AVG power has no duty cycle display. The power sensor measures AVG power is Burst power. The software has considered the factor of the duty cycle factor, so it is unnecessary to add it again.

Duty cycle



Ton	Tp	Duty cycle(%)
/	/	100

9. ANTENNA REQUIREMENT

9.1 STANDARD REQUIREMENT


15.203 requirement: For intentional device, according to 15.203: an intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device.

9.2 EUT ANTENNA

The EUT antenna is Single-stageAntenna. It comply with the standard requirement.

APPENDIX-PHOTOS OF TEST SETUP


Radiation emission
30MHz-1GHz




Conduction emission




Conducted



RSE 30MHz-1000MHz



RSE 1GHz-18GHz



※※※※END OF THE REPORT※※※※