

ConnectSense® Router Rebooter

with EZ Setup/Use Technology



Router



Automatic monitoring and reboot

Just plug your router into the Rebooter!

The Rebooter is constantly looking at your internet connection and determining if it is good or bad. If the connection is good the Rebooter does nothing. If the Rebooter determines that the internet connection is bad then the Rebooter resets the router/modem by powering OFF the router/modem, waiting and then powering ON the router/modem.

Features

- Automatic monitoring of Internet connection
- Auto reboot when Internet is not available
- Manual reboot button that can be used anytime
- Remote reboot with iOS & Android Apps
- Daily or weekly reboot at specific time of day
- Voice commands from Amazon Alexa and Google Home to perform reboot

FAQ

- Question:** Why do I need a REBOOTER?
Answer: If your internet connection stops working or gets painfully slow, then rebooting fixes the problem.
-
- Question:** How does the REBOOTER know when to reboot?
Answer: The REBOOTER pings several different internet sites and expects a reply from each one. If these internet sites fail to provide a reply/ping then your internet router cannot communicate with the internet and requires to be rebooted.
-
- Question:** Can I use the REBOOTER for other things than a router?
Answer: Yes, you can turn off the automatic Rebooter function and use the REBOOTER as a scheduled ON/OFF cyclor or remote ON/OFF controller.

ConnectSense® Router Rebooter

with EZ Setup/Use Technology

Specifications

| | |
|-------------------------|---|
| Wi-Fi | IEEE 802.11 b/g/n Wi-Fi 2.4Ghz |
| Input power | 90-135VAC |
| Output power | 120VAC, 15A Max |
| Inrush current | 30A |
| Standby Power | <1Watt |
| Frequency | 60Hz |
| Over Current Protection | 30A |
| Operating Temperature | -10 to +40 degC |
| Storage Temperature | -20 to +60 degC |
| Relative Humidly | 8 to 80% non-condensing |
| Certifications | ETL certified to UL standard FCC certified |
| Color | White |
| Size | 500mm(L) x 65mm(W) x 27mm(H) |
| Part Number | CS-MINI-CORD-REBOOTER |

FCC Notice

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum distance between 20cm the radiator your body: Use only the supplied antenna.

FCC ID: 2AXIE-SW02WU



630-245-1445 CONNECTSENSE.COM