



RF EXPOSURE Test Report

Report No.: MTi221130014-02E3
Date of issue: 2023-03-09
Applicant: JIANGSU SHUSHI TECHNOLOGY CO.LTD
Product: Smart Night Light-T
Model(s): 3RSNL02042TM
FCC ID: 2BAGQ-3RSNL02042TM

Shenzhen Microtest Co., Ltd.

<http://www.mtitest.com>

Instructions

1. The report shall not be partially reproduced without the written consent of the laboratory;
2. The test results of this report are only responsible for the samples submitted;
3. This report is invalid without the seal and signature of the laboratory;
4. This report is invalid if transferred, altered or tampered with in any form without authorization;
5. Any objection to this report shall be submitted to the laboratory within 15 days from the date of receipt of the report.



| Test Result Certification | |
|----------------------------------|--|
| Applicant: | JIANGSU SHUSHI TECHNOLOGY CO.LTD |
| Address: | NO.9 NANXU ROAD RUNZHOU DISTRICT ZHENJIANG, JIANGSU, China |
| Manufacturer: | Shushi (Zhenjiang) Intelligent Technology Co., Ltd. |
| Address: | NO.9 NANXU ROAD RUNZHOU DISTRICT ZHENJIANG JIANGSU CHINA |
| Product description | |
| Product name: | Smart Night Light-T |
| Trademark: | N/A |
| Model name: | 3RSNL02042TM |
| Serial Model: | N/A |
| Standards: | N/A |
| Test procedure: | KDB 447498 D01 v06 |
| Date of Test | |
| Date of test: | 2022-12-26~2023-01-13 |
| Test result: | Pass |

Test Engineer :

Yanice Xie

(Yanice Xie)

Reviewed By: :

Leon Chen

(Leon Chen)

Approved By: :

Tom Xue

(Tom Xue)

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

| Frequency range (MHz) | Electric field strength (V/m) | Magnetic field strength (A/m) | Power density (mW/cm ²) | Averaging time (minutes) |
|--|-------------------------------|-------------------------------|-------------------------------------|--------------------------|
| (A) Limits for Occupational/Controlled Exposure | | | | |
| 0.3-3.0 | 614 | 1.63 | *100 | 6 |
| 3.0-30 | 1842/f | 4.89/f | *900/f ² | 6 |
| 30-300 | 61.4 | 0.163 | 1.0 | 6 |
| 300-1,500 | | | f/300 | 6 |
| 1,500-100,000 | | | 5 | 6 |
| (B) Limits for General Population/Uncontrolled Exposure | | | | |
| 0.3-1.34 | 614 | 1.63 | *100 | 30 |
| 1.34-30 | 824/f | 2.19/f | *180/f ² | 30 |
| 30-300 | 27.5 | 0.073 | 0.2 | 30 |
| 300-1,500 | | | f/1500 | 30 |
| 1,500-100,000 | | | 1.0 | 30 |

f = frequency in MHz * = Plane-wave equivalent power density

MPE Calculation Method

Friis transmission formula: $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot R^2)$

Where

P_d = Power density in mW/cm²

P_{out} = output power to antenna in mW

G = Numeric gain of the antenna relative to isotropic antenna

π = 3.1415926

R = distance between observation point and center of the radiator in cm (20cm)

P_d the limit of MPE, 1mW/cm². If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

BLE:

Operation Frequency: 2402-2480MHz,

Antenna gain:2.1dBi

Zigbee:

Operation Frequency: 2405-2480MHz

Antenna Type: PCB Antenna;

Antenna gain: 2.1dBi

R=20cm

$mW=10^{(dBm/10)}$

antenna gain Numeric= $10^{(dBi/10)}= 10^{(-1.08/10)}= 1.62$

BLE:

| Channel Freq. (MHz) | modulation | conducted power (dBm) | Tune-up power (dBm) | Max | | Antenna | | Evaluation result (mW/cm ²) | Power density Limits (mW/cm ²) |
|---------------------|------------|-----------------------|---------------------|---------------|--------|---------|---------|---|--|
| | | | | tune-up power | | Gain | | | |
| | | | | (dBm) | (mW) | (dBi) | Numeric | | |
| 2402 | BLE-1M | 13.84 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2440 | | 13.71 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2480 | | 13.80 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2402 | BLE-2M | 13.88 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2440 | | 13.78 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2480 | | 13.84 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |

Zigbee:

| Channel Freq. (MHz) | modulation | conducted power (dBm) | Tune-up power (dBm) | Max | | Antenna | | Evaluation result (mW/cm ²) | Power density Limits (mW/cm ²) |
|---------------------|------------|-----------------------|---------------------|---------------|--------|---------|---------|---|--|
| | | | | tune-up power | | Gain | | | |
| | | | | (dBm) | (mW) | (dBi) | Numeric | | |
| 2405 | Zigbee | 14.05 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2440 | | 13.76 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |
| 2480 | | 13.81 | 14±1 | 15 | 31.623 | 2.1 | 1.62 | 0.0102 | 1 |

Conclusion:

For the max result: $0.0102 \leq 1.0$ SAR, No SAR is required.

----END OF REPORT----