## TF-G03说明书 成品尺寸: 73X93mm 128克铜版纸 覆哑膜 双面印刷 钢琴折





# 音频线 说明书与保修卡

## 蓝牙版本: V5.4 传输距离: ≥10m

喇叭类型: Φ40mm 阻抗: 16Ω±15% 灵敏度: 116dB±3dB 频率响应: 20Hz-20KHz 电池容量: 4.2V1200mAh 额定输入: 5V===500mA 充电时间:≈3小时

## 播放音乐时间:≈100小时

- 1. 除说明书有特殊标示的操作方式以外,请勿尝试拆卸或更换产品内的任何零件。
- 2. 请勿将产品放入水或其他任何液体中, 此产品非防水设计。
- 3. 如果有任何液体不小心进入产品内时、请立即断开连接并移开此产品。
- 4. 为避免触电,请在安装或卸载产品时,确保手上没有沾水。 5. 请勿将此产品放置于热源附近或直接暴露在火源附近。
- 6.请勿将此产品放置在有强大电磁力的环境中 否则会导致产品故障。

## ② 麦克风键 ③ EQ键 ④ M键 ⑤ 音量转轮 ⑥ 麦克风 ⑦ 指示灯 ® Type-C充电线接口 / 音频线接口

- 开机:耳机关机状态下,长按3秒开关键,蓝灯长亮1秒,语音提示音"Power on"响起。 关机: 耳机开机状态下, 长按5秒开关键, 红灯长亮1秒, 语音提示音"Power off"响起, 低电量报警及自动关机功能:当电池电压低于3.3V时,耳机会发出语音提示音"Battery low",此时应该及时给耳机充电。当电池电压低于3.1V时,耳机将会自动关机。
- 耳机开机后,开启设备蓝牙,搜索"TF-G03"并点击连接。配对成功后,语音提示音 "Connected"响起。耳机无连接或断开连接超过5分钟,耳机将会自动关机。 注意:首次使用耳机时,耳机开机后自动进入配对模式。本产品有蓝牙记忆功能,再次 使用时,开启耳机和设备蓝牙,蓝牙会自动回连。
- 按下麦克风,麦克风弹出后即可拉出使用。不用时,将麦克风推入并再次按压收回。 开启麦克风:通话状态下,双击麦克风键,语音提示音"mic on"响起。 关闭表克风:诵话状态下,双击麦克风键,语音提示音"mic off"响起。 接听/挂断电话: 单击麦克风键。
- 拒听电话·长按2秒麦克风键。

游戏 / 音乐模式(开机默认): 单击EQ键。

- 播放 / 暂停音乐: 单击M键。下一曲: 双击M键。上一曲: 三击M键。
- 6. 语音助手 唤醒Siri: 长按2秒M键,
- 调低音量:转轮向左减小音量,最小音量时有提示音。
- 调高音量:转轮向右增大音量,最大音量时有提示音。
- 耳机插入Type-C充电线或音频线时, 耳机将会自动关机。
- 首先,耳机开机与第一台设备连接。其次,关闭第一台设备蓝牙,耳机重新开机,并与 第二台设备连接。最后,打开第一台设备蓝牙,耳机自动与第一台设备连接。耳机能在

## 重置配对设备列表

耳机开机状态下,六击开关键,红蓝灯交替闪,语音提示音"Pairing"响起,重新进入搜索配对状态。

模式	灯显	语音提示音	
开机	蓝灯长亮1秒	"Power on"	
关机	红灯长亮1秒 "Power off		
配对/清除配对	红蓝灯交替闪烁	"Pairing"	
连接成功	灯光熄灭	"Connected"	
断开连接	红蓝灯交替闪烁	"Disconnected"	
接听电话	蓝灯长亮		
充电状态	红灯长亮	_	
充电完成	蓝灯长亮		
低电报警状态	红灯每5秒闪烁一次	"Battery low"	

## 产品中有害物质的名称及含量

100 like day 2 lin	有害物质					
部件名称	铅 Pb	汞 Hg	镉 Cd	六价铬 Cr(VI)	多溴联苯 PBB	多溴二苯醚 PBDE
印刷电路板组件	0	0	0	0	0	0
外壳等小结构件	0	0	0	0	0	0

## 本表格依据SJ/T 11364的规定编制。

- :表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572规定的限量要求以下。 :表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572规定的限量要求。
- É: 1. 表中标记"×"的部件, 皆因全球技术发展水平限制而无法实现有害物质的替代;
- 2. 印刷电路板组件:包括印刷电路板及其零部件、电子元器件等; 3. 根据产品型号不同、您所购买的产品可能不会含有以上所有部件。



在中华人民共和国境内销售的电子电气产品必须标识此标志,标志内的 数字代表在正常的使用状态下的产品的环保使用期限。

## 以上保证是我们就产品做出的全部保证 目仅在中国大陆地区境内适用。本文件的任何内 服务监督热线: 400-885-8808 FC Z CE O CE CE

## TRANSFORMERS



销售商信息	
名 称	
地 址	
联系电话	邮政编码
销售日期	发票号码
备 注	

	合格证
产品型号: 生产日期: 检验员:	



Warranty card

Product barcode / Serial number /


Contact number Postal code Sales date Invoice number

Certificate Of Approval

## TRANSFORMERS



TF-G03 BT dual-mode headsets Instruction manual







Speaker type: Ф40mm

Sensitivity: 116dB±3dB Frequency response: 20Hz-20KHz Battery capacity: 4 2V1200mAh


## Charging time: ≈3 hours Play music time: ≈100 hours

- 1. Except for the operation methods specifically marked in the manual, do not try to disassemble or replace any parts in the product.
- 2. Do not put the product in the water or any others liquid, the product is not 3. If any liquid accidentally enters the product, please disconnect and remove the
- 4. To avoid electric shock, please make sure that there is no water on your hands when installing or uninstalling the product.
- 5. Do not put the product near a heat source or directly expose it to a fire source 6. Do not put the product in an environment with strong electromagnetic force, otherwise it will cause product malfunction.

## ② Microphone key 3 EQ key

⑤ Volume wheel Microphone ⑦ Pilot lamp





- Power on: When the headsets are power off, press and hold the switch key for 3 seconds, the blue light will be on for 1 second, and the voice prompt "Power on" will sound. Power off: When the headsets are power on, press and hold the switch key for 5 seconds, the red light will be on for 1 second, and the voice prompt "Power off" will sound.

  Low power alarm and automatic shutdown function: When the battery voltage is lower than 3.3V, the headsets will emit a voice prompt "Battery low", and the headsets should be charged in time. When the battery voltage is lower than 3.1V, the headsets will automatically power off.
- After the headsets are power on, turn on the device BT, search for "TF-G03" and click connect. After successful pairing, the voice prompt "Connected" will sound. If the headsets are not again, turn on the headset and device BT, and BT will automatically reconnect.
- 3. Phone call

  Press the microphone, and after the microphone ejects, it can be pulled out for use. When not in use, push the microphone in and press it again to take it back. Turn on the microphone: In the call state, double-click the microphone key, and the voice urn off the microphone: In the call state, double-click the microphone key, and the voice
- prompt "mic off" will sound.

  Answer / end Call: Click the microphone key.

  Reject Call: Press and hold the microphone key for 2 seconds. Game / music mode (power-on default): Click the EO key

- Previous song: Triple-click the M key.
- Turn down the volume: Turn the wheel to the left to reduces the volume, and there is a prompt
- tone at the maximum volume. When the headsets are plugged into the Type-C charging cable or audio cable, the headsets will automatically power off.
- One drag two function First of all, the headsets are turned on and connected to the first device. Secondly, turn off the the BT of the first device, and the headsets will automatically connect to the first device.

## Headsets can switch between devices. Reset paired device list

When the headsets are power on, six clicks the switch key, the red and blue lights flash alternately, the voice prompt "Pairing" will sound, and then re-enter the search pairing

Mode	Lamp display	Voice prompt tone
Power on	The blue light is on for 1 second	"Power on"
Power off	The red light is on for 1 second	"Power off"
Pairing / Clear Pairing	The red and blue lights flash alternately	"Pairing"
Connected	The light goes out	"Connected"
Disconnected	The red and blue lights flash alternately	"Disconnected"
Answer	The blue light is steady on	
Charging state	The red light is steady on	_
Charging completed	The blue light is steady on	
Low power alarm state	The red light flashes every 5 seconds	"Battery low"

## The name and content of harmful substances in the product

本使用手册没有任何形式的担保、立场表达或其他暗示。本使用手册所提到的产品、规格

就本文件附随的产品做如下保证: 如产品在您购买日起十二 (12) 个月 ("保修期") 内,

在正常使用情况下因质量瑕疵发生损坏,能修理的,免费修理;经厂家确认无法修理的,

免费事施·修理或事换后的产品 在剩余保修期(最短不小干30干)内继续享有保修 购

买日以销售发票日期为准,如无法确定购买日,则保修期自产品生产日期起按十三(13)

个月计算。如申请保修,请先致电产品服务热线,并按我们指示的方式执行。申请保修

产品及随附物料的齐备和外观完好不属于保证范围。您应在接收产品时当场检验并对任何

3 因误用 滥用或不适当的运输 使用 维护或保管而导致的故障或损坏:

4 因不可抗力(如地震、战争、火灾等)或意外导致的故障或损坏:

10. 产品正常使用过程中发生的老化、脱色、磨损、破裂和其他损耗;

11. 如产品原有标识标签被更改或损毁,本保证将失效。

及信息仅供参考,内容亦会随时更新于网页,恕不另行通知。

时,您需要提供准确、完整和清晰填写的有效销售发票。

2. 涂改保修卡, 产品编码与产品本体不符;

以上保证不适用于下列情况。

5. 拉链、塔扣因受力过大而损坏

6. 因承载过重造成的脱线或撕裂

7 任何因少纷物体造成的损坏:

8. 有烧损或水浸迹象的产品:

9. 因擅自拆改导致的损坏

1. 超过三包有效期的;

Destruction	Harmful substances					
Part name	Pb	Hg	Cd	Cr(VI)	PBB	PBDE
ted circuit board components	0	0	0	0	0	0
II structural parts such as shell	0	0	0	0	0	0

- This form is compiled in accordance with the provisions of SJ/T 11364. : Indicates that the content of the hazardous substance in all homogeneous
- materials of the part is below the limit requirements specified in GB/T 26572. : Indicates that the content of the hazardous substance in at least one homoger material of the part exceeds the limit requirements specified in GB/T 26572.
- lote: 1. The parts marked with "×" on the table are unable to achieve the replacemen of harmful substances due to limitations in global technological development; 2. Printed circuit board components: including printed circuit boards and their parts electronic components etc.
- 3. Depending on the product model, the product you purchased may not contain



Electronic and electrical products sold in the People's Republic of China must mark this logo, the number in the logo represents the product under normal use environmental protection use period.



and the content will also be updated on the web at any time without additional separate notice

- The above guarantee does not apply to the following situations:

  1. Exceeding the validity period of three guarantees;

  2. Altering the warranty card, the product code does not match the product body;

  3. Failure or damage caused by misuse, abuse or improper transportation, use, maintenance or
- storage.

  4. Fallure or damage caused by force majeure (such as earthquake, war, fire, etc.) or accidents.

  5. Zipper and tower buckle are damaged due to excessive force;

  6. Disconnection or tearing caused by excessive load;

  7. Any damage caused by sharp objects;

  8. Products with signs of burning or flooding;

  9. Damage caused by unauthorized disassembly;
- 0. Aging, discoloration, abrasion, rupture and other losses that occur during the normal use of the product;

  11. If the original identification label of the product is changed or damaged, this guarantee will become invalid.

scope of the guarantee. You should inspect the product on the spot when you receive it and raise objections to any discrepancies.

The above guarantees are all guarantees we make regarding the products, and are only applicable in Chinese Mainland. Nothing in this document affects consumer rights that cannot be



























## FCC Warnning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection againstharmful interference in a residential installation. This equipment generates, uses and can radiateradio frequency energy and, if not installed and used in accordance with the instructions, maycause harmful interference to radio communications. However, there is no guarantee thatinterference will not occur in a particular installation. If this equipment does cause harmfulinterference to radio or television reception, which can be determined by turning the equipmentoff and on, the user is encouraged to try to correct the interference by one or more of thefollowing measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1)This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.