

TF-G06说明书 成品尺寸: 70X100mm 128铜版纸 覆哑膜 钢琴折

正面

TRANSFORMERS




TF-G06蓝牙双模头戴耳机
使用说明书

包装清单

耳机 *1	Type-C充电线 *1
3.5mm音频线 *1	说明书与保修卡 *1

产品示意图

- 音量加按键,下一曲目
- 音量减按键,上一曲目
- 多功能按键 (MFB)
- 3.5mm音频线接口
- 蓝牙指示灯/电源指示灯
- 充电Type-C接口
- 麦克风



电池使用注意

- 如果电池更换不当, 则存在爆炸危险。
- 电池只能用相同类型或同等类型的电池更换。
- 不建议未经许可更换电池。
- 可以退回制造商进行更换电池。
- 电池【电池组或电池组合】不得暴露在照明, 烘烤或类似过热的环境中。

产品参数

蓝牙版本: V5.4
传输距离: ≥10m
喇叭直径: Φ40mm
喇叭阻抗: 32Ω±15%
灵敏度: 116dB±3dB @1kHz
频响范围: 20Hz-20KHz
充电时间: 约2.5小时
播放时间: 约8小时
电池容量: 250mAh 3.7V
额定输入: 5V \equiv 200mA

产品操作说明

- 1. 电源开关**
耳机关机状态: 长按**多功能按键 (MFB)**, 蓝灯长亮1秒, 并听到"Power on"语音提示, 耳机开机。
耳机开机状态: 方法1. 长按**多功能按键**, 红灯长亮1秒, 并听到"Power off"语音提示, 耳机关机。方法2. 无连接状态5分钟后自动关机。
- 2. 配对**
长按**多功能按键**, 开启智能设备蓝牙并搜索"TF-G06"耳机进行配对, 点击连接, 当配对成功, 你会听到"Connected"语音提示。
注意: 首次使用并开机时, 耳机将自动进入配对模式。本产品有蓝牙记忆功能, 再次使用只需开启耳机和设备, 自动回连。
- 3. 音量控制**
调低音量: 短按音量 "-" 键, 最小音量时有提示音。
调高音量: 短按音量 "+" 键, 最高音量时有提示音。
- 4. 通话**
接听/结束通话: 短按MFB;
拒绝来电: 长按MFB约2秒;
未导重拨: 双击MFB, 会重拨最后一个通话号码。



- 5. 音乐**
播放/暂停: 短按MFB;
上一曲: 长按音量 "-" 键2秒;
下一曲: 长按音量 "+" 键2秒。
- 6. 语音助手控制功能**
唤醒 Siri: 三击MFB。
- 7. 音频线操作**
使用 3.5mm 音频线连接耳机到设备时, 耳机进入自动关机。
拔掉音频线后, 需按照配对步骤重新连接蓝牙功能。
- 8. 一拖二功能**
步骤1: 耳机开机与第一台设备连接;
步骤2: 关闭第一台设备蓝牙, 并与第二台设备连接;
步骤3: 打开第一台设备蓝牙, 耳机自动与第一台设备连接; 能在设备之间切换。

LED指示灯状态

模式	灯显	声音提示
开机	蓝灯长亮1秒	"Power On"
关机	红灯长亮1秒	"Power Off"
配对状态	红蓝灯交替闪烁	"Pairing"
连接成功	灭灯	"Connected"
充电状态	红灯常亮	—
充电完成	灭灯	—
低电报警状态	红灯每5秒闪烁一次	"battery low"
插入音频线	红灯亮1秒后熄灭	"power off"
清除配对	红蓝交替慢闪	"paring"

重置配对设备

开机状态下, 同时长按 "+" 和 "-" 键 5 秒清除配对记录, 进入配对听到声音提示 "Pairing".

产品中有害物质名称及含量

部件名称	有害物质					
	铅(Pb)	汞(Hg)	镉(Cd)	六价铬(Cr(VI))	多溴联苯(PBB)	多溴二苯醚(PBDE)
印刷电路组件	○	○	○	○	○	○
外壳等小结构件	○	○	○	○	○	○

本表格依据SJ/T11364的规定编制
O:表示该有害物质在该部件所有均质材料中的含量均在GB/T26572规定限量要求以下。
X:表示该有害物质至少在该部件的某一均质材料中的含量超出GB26572规定的限量要求。
表格标记"X"的部件,皆因全球技术发展水平限制而无法实现有害物质的替代。

本表格依据SJ/T11364的规定编制
印刷电路板组件* 包括印刷电路板及其零部件,电子元器件等。
根据产品型号不同,您所购买的产品可能不会含有以上所有部件

指不含有6种有毒有害物质或含量小于限量值。
字母"e"代表英文字母电子(electronic); 电子(electrical)和环境(environment)的首字母; 环境的曲线箭头表示可回收利用。



保修声明

免责声明
本产品附带的产品保修卡, 请仔细阅读。本使用手册所提到的产品、规格及信息仅供参考, 内容除会随时更新外, 恕不另行通知。

保修声明
如申请保修, 请先致电产品服务热线, 并按我们指示的方式执行。申请保修时, 您需提供准确、完整和清晰填写的有效销售发票。以上保证不适用于下列情况:
1. 超过三包有效期的;
2. 涂改保修卡、产品编码与产品本体不符;
3. 因误用、滥用或不当的运输、使用、维护或保管而导致的故障或损坏;
4. 因不可抗力(如地震、战争、火灾等)或意外导致的故障或损坏;
5. 刮蹭、磕碰和因受力过大而损坏;
6. 因承载过重造成的断线或断裂;
7. 任何因不可抗力造成的损坏;
8. 有烧损或水浸迹象的产品;
9. 因擅自拆卸导致的损坏;
10. 产品在维修过程中发生的老化、变色、磨损、破裂和其他损耗。
11. 如产品原有标识被更改或损毁, 本保证将失效。
产品及附件物料的准备和外壳完好不属于保证范围, 您在接收产品时当场检验并对任何不符提出异议。

以上保证是我们就产品做出的全部保证, 且仅在中国大陆地区境内适用。本文件的任何内容均不影响根据法律规定不能排除或限制的消费者权利。

服务热线: 400-885-8808

虚线做
易撕线

保修卡

尊敬的用户, 本保修卡是您将来申请保修的凭证, 请您配合销售商填写并妥善保管!

用户信息	
用户姓名	电子邮箱
联系电话	邮政编码
通讯地址	
产品信息	
产品名称	产品型号
产品条码/编号/批号	

销售商信息

名称	
地址	
联系电话	邮政编码
销售日期	发票号码
备注	

合格证

产品编号: _____
生产日期: _____
检验员: _____

反面

Warranty Service

Dear user, this warranty card is the proof of your future warranty application, please cooperate with the seller to fill it out and keep it for future use!

User info	
User name	Email
Contact number	Postal code
Mailing address	
Product information	
Product name	Product number
Product barcode / Serial number / Batch number	

Vendor information

Name	
Address	
Contact number	Postal code
Sales date	Invoice number
Remark	

Certificate of Approval

Product No.: _____
Production Time: _____
QC: _____

TRANSFORMERS




TF-G06 BT dual-mode headphones
Instruction manual

Packing list

Headphones *1	Type-C Charging cable *1
3.5mm audio cable * 1	Instructions and Warranty card *1

Product diagram

- Volume and buttons. Next track
- Volume down button. Previous track
- Multi Function Button (MFB)
- 3.5mm Audio Port
- Microphone
- Type-C Charging Port
- BT Indicator/power indicator



Caution On Battery

- Risk of explosion if battery is not replaced properly
- Replace with same type of batteries only
- Self replacement of battery is prohibited
- Return to manufacturer for service
- Keep batteries away from direct sunlight, high temperature and humidity

Headset specifications

BT version: V5.4
Transmission distance: ≥10m
Horn diameter: Φ40mm
Horn impedance: 32Ω±15%
sensitivity: 116dB±3dB @1kHz
Frequency response: 20Hz-20KHz
Charging time: About 2.5 hours
Music time: About 8 hours
Battery capacity: 250mAh 3.7V
Rated input: 5V \equiv 200mA

Product operation instructions

- 1. Power On/Off**
Earphone Off state: Press and hold **multi-function button (MFB)**, the blue light will keep on for 1 second, and you will hear "Power on" voice hint, earphones on.
When the headset is powered on: Method 1. Press and hold the **multi-function button**. When the red light turns on for one second and you hear Power off, the headset is powered off. Method 2. The device automatically shuts down after 5 minutes of no connection.
- 2. Pairing**
Long press **multi-function key**, open the smart devices BT and search for the "TF-G06" headset match, click the connection, when the pairing is successful, you will hear "Connected".
Note: When first used and turned on, the headset will automatically enter pairing mode. This product has memory function. When you use it again, you only need to turn on the headset and the device and automatically connect back).
- 3. Volume Control**
To lower the volume, press the "-" key. An announcement tone is played at the minimum volume.
Up the volume: Press the "+" key for the volume. At the highest volume, an announcement is played.



4. Phone Call

- Answer/End Call: short press the MFB
Reject Call: long press the MFB about 2 seconds
Redial: quick double press the MFB to call the last dialed number.
- 5. Music**
Play/Pause: press MFB;
Previous: Long press the volume "-" key for 2 seconds;
Next: Long press the volume "+" key for 2 seconds.
- 6. Voice assistant control function**
Wake up Siri: Three hits MFB.
- 7. Audio Cable Operation**
When the headset is connected to the device using a 3.5mm audio cable, the headset enters the automatic shutdown. After unplugging the audio cable, follow the pairing steps to reconnect the BT function.
- 8. One drag two function**
Step 1: Turn on the headset and connect to the first device;
Step 2: Turn off the Bluetooth of the first device and connect to the second device;
Step 3: Turn on the BT of the first device, and the headset automatically connects with the first device; Ability to switch between devices.

LED indicator status

Mode	Lamp display	Voice Prompt
Power On	Keep the blue light on for 1 second	"Power On"
Power Off	Keep the red light on for 1 second	"Power Off"
Pairing state	The red and blue lights flash alternately	"Pairing"
Connected	Light off	"Connected"
Charging state	The red light is steady on.	—
Charging completed	Light off	—
Low power alarm state	The red light flashes every five seconds	"battery low"
Insert audio cable	The red light is on for one second and then off	"power off"
Clear pairing	Red and blue alternating slow flashes	"paring"

Reset Paired Device List

When the device is powered on, hold down the "+" and "-" keys for 5 seconds to clear the Pairing record. When pairing is entered, the audio prompt "pairing" is heard.

The name and content of harmful substances in the earbuds

Part Names	Harmful Substances					
	Pb	Hg	Cd	Cr(VI)	PBB	PBDE
Printed circuit assembly	○	○	○	○	○	○
Small structural parts such as shell	○	○	○	○	○	○

This form is compiled in accordance with SJ/T 11364.
O: Indicates that the content of the hazardous substance in all homogeneous materials of the part is in below the limit required by GB/T 26572.
X: Indicates that the hazardous substance at least in a certain homogeneous material of the part exceeds the limit requirements specified in GB/T 26572.
The parts marked with "X" on the form are all harmful due to the limitations of global technological development. Substitution of substances.

Printed circuit board components:
Including printed circuit boards and their parts, electronic components, etc. and depending on the product model, the earbuds you purchased may not contain all of the above components.

Does not contain 6 kinds of toxic and harmful substances or contains but is less than the limit value, the letter "e" stands for the English letter electronic; The initials of electrical and environment; The curved arrows around it indicate recyclability.



Warranty statement

Disclaimer
This user manual does not have any form of guarantee, position expression or other implication. The mentioned products specifications and information are for reference only, and the content will also be updated on the web at any time without additional separate notice.

Warranty statement:
The product attached to this document is guaranteed as follows: If the product is twelve (12) months from the date of purchase ("Warranty Period") under normal conditions of use due to quality defects, damaged, can be repaired. Free repair/Free replacement if the manufacturer confirms that it cannot be repaired; repaired or replaced product. Continue to enjoy the warranty during the remaining warranty period (the shortest not less than 30 days). Purchased by sale the ticket date shall prevail if the purchase date cannot be determined, the warranty period shall be 15 (15) months.
If you apply for a warranty, please call the product service hotline first and execute it in the manner instructed by us. When applying for warranty, you need to provide an accurate, complete and clearly filled out valid sales invoice.

The above guarantee does not apply to the following situations:
1. Exceeding the validity period of the three packs;
2. Altering the warranty card and product code does not match the product body;
3. Causes caused by misuse, abuse or improper transportation, use, maintenance or storage obstacles or damage;
4. Failure or damage caused by force majeure (such as earthquake, war, disaster, etc.) or accident loss;
5. The zipper and tower buckle are damaged due to excessive force;
6. Disconnection or tearing caused by excessive load;
7. Any damage caused by sharp objects;
8. Products with signs of burning or flooding;
9. Damage caused by unauthorized disassembly;
10. Aging, discoloration, abrasion, rupture and other losses that occur during the normal use of the product.
11. If the original identification label of the product is changed or damaged, this guarantee will become invalid.

The completeness and appearance of the product and accompanying materials are not within the scope of the guarantee. You should check on the spot and raise objections to any discrepancies.

The above guarantees are all guarantees we make regarding the products, and are only applicable in mainland China. Nothing in this document affects consumer rights that cannot be excluded or restricted under the law profit.

Service supervision hotline: 400-885-8808

虚线做
易撕线

TRANSFORMERS

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.