

1. RF Exposure Requirements

1.1 General Information

Client Information

Applicant: Shelly Europe Ltd.
Address of applicant: 103 Cherni Vrah Blvd., 1407 Sofia, Bulgaria

Manufacturer: Shelly Europe Ltd.
Address of manufacturer: 103 Cherni Vrah Blvd., 1407 Sofia, Bulgaria

General Description of EUT:

Product Name: Z-Wave smart switch with power measurement

Trade Name: 

Model No.: Wave Pro 2PM
Adding Model: Wave Pro 1PM, Wave Pro Shutter
Rated Voltage: 110-240 VAC, 50/60Hz
Battery capacity: /
Power Adaptor: /
FCC ID: 2BDC6-WAVEPRO2PM
Equipment Type: Mobile device

Technical Characteristics of EUT:

Frequency Range: 908.42MHz
Max. Field Strength: 90.90dBuV/m
Modulation: FSK
Antenna Type: Integral Antenna
Antenna Gain: 0dBi

1.2 RF Exposure Exemption

According to §1.1307(b)(3) and KDB 447498 D04 Interim General RF Exposure Guidance v01, system operating under the provisions of this section shall be operating in a manner that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure.

Option A: FCC Rule Part 1.1307 (b)(3)(i)(A): The available maximum time-averaged power is no more than 1mW, regardless of separation distance.

Option B: FCC Rule Part 1.1307 (b)(3)(i)(B): The available maximum time-averaged power or effective radiated power (ERP), whichever is greater, is less than or equal to the threshold P_{th} (mW) described in the following formula. P_{th} is given by:

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases}$$

Where

$$x = -\log_{10} \left(\frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right) \text{ and } f \text{ is in GHz};$$

and

$$ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases}$$

d = the separation distance (cm);

Option C: FCC Rule Part 1.1307 (b)(3)(i)(C): The minimum separation distance (R in meters) from the body of a nearby person for the frequency (f in MHz) at which the source operates, the ERP (watts) is no more than the calculated value prescribed for that frequency. R must be at least $\lambda/2\pi$, where λ is the free-space operating wavelength in meters.

Single RF Sources Subject to Routine Environmental Evaluation	
RF Source frequency (MHz)	Threshold ERP (watts)
0.3-1.34	$1,920 R^2$
1.34-30	$3,450 R^2/f^2$
30-300	$3.83 R^2$
300-1,500	$0.0128 R^2f$
1,500-100,000	$19.2R^2$

For Multiple RF sources: FCC Rule Part 1.1307(b)(3)(ii):

- (A) The available maximum time-averaged power of each source is no more than 1 mW and there is a separation distance of two centimeters between any portion of a radiating structure operating and the nearest portion of any other radiating structure in the same device, except if the sum of multiple sources is less than 1 mW during the time-averaging period, in which case they may be treated as a single source (separation is not required).
- (B) In the case of fixed RF sources operating in the same time-averaging period, or of multiple mobile or portable RF sources within a device operating in the same time averaging period, if the sum of the fractional contributions to the applicable thresholds is less than or equal to 1 as indicated in the following equation.

$$\sum_{i=1}^a \frac{P_i}{P_{th,i}} + \sum_{j=1}^b \frac{ERP_j}{ERP_{th,j}} + \sum_{k=1}^c \frac{Evaluated_k}{Exposure\ Limit_k} \leq 1$$

1.3 Calculated Result

Radio Access Technology	Prediction Frequency (MHz)	Max. Field Strength (dBuV/m)	Antenna Gain (dBi)	Output Power (dBm)	Tune-Up Power (dBm)	ERP (dBm)
SRD	908.42	90.90	0	-4.36	-4.00	-6.15

Frequency (MHz)	Option	Min. Distance (cm)	Max. Power (dBm) (mW)		Exposure Limit (mW)	Ratio	Result (Pass/Fail)
908.42	B	0.5	-4.00	0.40	8.22	0.05	Pass

Note: 1. $EIRP = E - 104.8 + 20 \log D$; $Output\ Power = EIRP - Antenna\ Gain$;
 $ERP = EIRP - 2.15\ dB$

2. Option A, B and C refers as clause 1.2.

3. For option B, Max (time-averaged power, effective radiated power (ERP)) converts to Max. Power.

For option C, ERP converts to Max. Power;

4. For option B, P_{th} (mW) converts to Exposure Limit (mW); For option C, ERP (W) converts to Exposure Limit (mW).

5. $Ratio = \text{Tune-Up ERP (mW)} / \text{Exposure Limit (mW)}$

Mode for Simultaneous Multi-band Transmission:

Radio Access Technology	Ratio 1	Ratio 2	Ratio 3	Simultaneous Ratio	Limit	Result (Pass/Fail)
/	/	/	/	/	/	/

Result: Pass