



CTC Laboratories, Inc.

1-2/F., Building 2, Jiaquan Building, Guanlan High-Tech Park, Shenzhen, Guangdong, China
Tel: +86-755-27521059 Fax: +86-755-27521011 <http://www.sz-ctc.com.cn>

RF Exposure Evaluation

FCC ID: 2BFST-SANAGS3S

According to KDB447498 D01 General RF Exposure Guidance v06, Clause 4.3.1(a)

EUT Specification

EUT	OWS BLUETOOTH HEADSET
Trade Mark:	/
Model/Type reference:	sanag S3S
Listed Model(s):	sanag S3S AI
Frequency band (Operating)	BT: 2.402GHz ~ 2.480GHz
Device category	<input checked="" type="checkbox"/> Portable (<5mm separation) <input type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Fixed (>20cm separation) <input type="checkbox"/> Others _____
Antenna diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Antenna gain (Max)	2.71dBi

Limit

For 100 MHz to 6 GHz and test separation distances ≤ 50 mm, the 1-g and 10-g SAR test exclusion thresholds are determined by the following:

$$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f_{(\text{GHz})}}] \leq 3.0 \text{ for 1-g SAR, and } \leq 7.5 \text{ for 10-g extremity SAR}$$

Where

- $f_{(\text{GHz})}$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation
- The result is rounded to one decimal place for comparison
- The values 3.0 and 7.5 are referred to as numeric thresholds in step b) below

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm, and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm according to 4.1 f) is applied to determine SAR test exclusion.



Measurement Result

Mode	Channel Frequency (MHz)	Max. Measured Power (dBm)	Max. Tune up Power (dBm)	Result	Limit
GFSK (BLE 2M)	2480	-3.844	-3	0.281	3.0
GFSK ($\pi/4$ -DQPSK)	2480	-3.480	-3	0.281	3.0

Note:

1. Calculate by Worst-case mode.
2. Max. Tune Up Power by Manufacturer's Declaration, and Max. Tune Up Power is used to calculate.
3. For a more detailed features description, please refer to the RF Test Report.

*****THE END*****