

Safety

Before you install, service, or remove the outlet, ensure you read and adhere to all safety measures, which include the following precautions:

-CAUTION- Electric Shock Risk:

To de-energize the equipment before servicing, more than one disconnect switch may be necessary. A circuit breaker disconnecting the Line and Neutral conductor simultaneously is recommended. Make sure the power is switched off at the circuit breaker before installing or removing any outlet. Utilize a non-contact voltage tester to confirm the power is off.

-Compliance with Codes:

The Smart Outlet must be installed and operated in line with the National Electric Code (NEC) or your local electrical code. If you are not yet familiar with these codes or feel uncomfortable with the installation process, seek advice from a qualified electrician.

-Safety Precautions:

Avoid installing the Smart Outlet with wet hands or while standing on wet or damp surfaces.

-Installation Requirements:

Install the Smart Outlet exclusively in a suitable UL Listed outlet box with dimensions meeting the following criteria: H > 2.95 in/75 mm, W > 1.81 in/46 mm, D > 3.15 in/80mm.


-Terminal Screw Tightening:

Ensure terminal screws are tightened to 13 lbs-in.

Wiring instructions


1. Remove the Old Outlet

Turn off power at the circuit breaker, remove your old wallplate, and gently pull the outlet out.




2. Disconnect the Wires

Disconnect the wires from your old outlet.




3. Connect the New Wires

Connect wires to the terminals of the new outlet and tighten the screws holding the wires onto the terminals.




4. Secure the New Outlet

Secure the new outlet and wallplate with the screws provided.



5. Make sure the outlet is installed in the correct position

For a proper installation, ensure the Deco LED is positioned at the bottom.



FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Information

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.