

RF Exposure Evaluation Report

Report Reference No......: **MTEB24070186-H**

FCC ID.....: **2BHAO-6143**

Compiled by

(position+printed name+signature)...: File administrators Alisa Luo

Supervised by

(position+printed name+signature)...: Test Engineer Sunny Deng

Approved by

(position+printed name+signature)...: Manager Yvette Zhou

Date of issue.....: **July 17,2024**

Representative Laboratory Name.: **Shenzhen Most Technology Service Co., Ltd.**

Address: No.5, 2nd Langshan Road, North District, Hi-tech Industrial Park,
Nanshan, Shenzhen, Guangdong, China.

Applicant's name.....: **NINGBO LONGMARCH IMPORT&EXPORT CO.,LTD**

Address: ROOM 1505, 15TH FLOOR, BUILDING 3, YUNHUI CENTER,
NO. 299 TONGJI ROAD, JIANGBEI DISTRICT, NINGBO, CHINA

Test specification/ Standard: **47 CFR Part 1.1307;47 CFR Part 1.1310**
KDB447498D01 General RF Exposure Guidance v06

TRF Originator.....: Shenzhen Most Technology Service Co., Ltd.

Shenzhen Most Technology Service Co., Ltd. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen Most Technology Service Co., Ltd. is acknowledged as copyright owner and source of the material. Shenzhen Most Technology Service Co., Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test item description: **SPEAKER LIGHT BULB**

Trade Mark: **BELL+HOWELL**

Model/Type reference.....: **6143**

Listed Models: **N/A**

Modulation Type: **GFSK, $\pi/4$ DQPSK**

Operation Frequency.....: **From 2402MHz to 2480MHz**

Hardware Version.....: **DC375-V1.0**

Software Version: **20210622**

Rating: **AC 120V/60Hz**

Result.....: **PASS**

TEST REPORT

Equipment under Test : SPEAKER LIGHT BULB

Model /Type : 6143

Listed Models : N/A

Remark : N/A

Applicant : NINGBO LONGMARCH IMPORT&EXPORT CO.,LTD

Address : ROOM 1505, 15TH FLOOR, BUILDING 3, YUNHUI CENTER,
NO. 299 TONGJI ROAD, JIANGBEI DISTRICT, NINGBO, CHINA

Manufacturer : NINGBO LI SENSOR ELETRONICS CO.,LTD

Address : NO. 5 JINSHAN 7TH ROAD, NINGHAI COUNTRY, NINGBO,
CHINA

Test Result:	PASS
--------------	------

The test report merely corresponds to the test sample.
It is not permitted to copy extracts of these test result without the written permission of the test laboratory.

1. Revision History

Revision	Issue Date	Revisions	Revised By
00	2024.07.17	Initial Issue	Alisa Luo

2. SAR Evaluation

2.1 RF Exposure Compliance Requirement

2.1.1 Standard Requirement

According to KDB447498D01 General RF Exposure Guidance v06

4.3.1. Standalone SAR test exclusion considerations

Unless specifically required by the published RF exposure KDB procedures, standalone 1-g head or body and 10-g extremity SAR evaluation for general population exposure conditions, by measurement or numerical simulation, is not required when the corresponding SAR Exclusion Threshold condition, listed below, is satisfied.

2.1.2 Limits

According to FCC Part1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in part1.1307(b)

TABLE 1—LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A) Limits for Occupational/Controlled Exposures				
0.3–3.0	614	1.63	*(100)	6
3.0–30	1842/f	4.89/f	*(900/f ²)	6
30–300	61.4	0.163	1.0	6
300–1500	f/300	6
1500–100,000	5	6
(B) Limits for General Population/Uncontrolled Exposure				
0.3–1.34	614	1.63	*(100)	30
1.34–30	824/f	2.19/f	*(180/f ²)	30
30–300	27.5	0.073	0.2	30
300–1500	f/1500	30
1500–100,000	1.0	30

F= Frequency in MHz

Friis Formula

Friis transmission formula: $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot R^2)$ Where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

P_d is the limit of MPE, 1 mW/cm². If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

2.1.3 EUT RF Exposure

BT classic

GFSK			
Test channel	Peak Output Power (dBm)	Tune up tolerance (dBm)	Maximum tune-up Power
			(dBm)
Lowest(2402MHz)	-0.856	-0.856 ± 1	0.144
Middle(2441MHz)	-0.496	-0.496 ± 1	0.504
Highest(2480MHz)	-1.025	-1.025 ± 1	-0.025

$\pi/4$ DQPSK			
Test channel	Peak Output Power (dBm)	Tune up tolerance (dBm)	Maximum tune-up Power
			(dBm)
Lowest(2402MHz)	0.018	0.018 ± 1	1.018
Middle(2441MHz)	0.409	0.409 ± 1	1.409
Highest(2480MHz)	-0.181	-0.181 ± 1	0.819

Worst case: $\pi/4$ DQPSK						
Channel	Maximum tune-up Power (dBm)	Maximum tune-up Power (MW)	Antenna Gain (dBi)	Power Density at R = 20 cm (mW/cm ²)	Limit	Result
Middle(2441MHz)	1.409	1.38	-0.68	0.00024	1.0	Pass

Note: 1) Refer to report MTEB24070186-R for EUT test Max Conducted average Output Power value.

Note: 2) $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot R^2) = (1.38 \cdot 0.86) / (4 \cdot 3.1416 \cdot 20^2) = 0.00024$

Note: 3) EUT's Bluetooth module is more than 20cm away from the human body.

BLE

GFSK			
Test channel	Peak Output Power (dBm)	Tune up tolerance (dBm)	Maximum tune-up Power
			(dBm)
Lowest(2402 MHz)	1.181	1.181 ± 1	2.181
Middle(2440MHz)	1.010	1.010 ± 1	2.01
Highest(2480MHz)	1.766	1.766 ± 1	2.766

BLE

Worst case: GFSK						
Channel	Maximum tune-up Power (dBm)	Maximum tune-up Power (MW)	Antenna Gain (dBi)	Power Density at R = 20 cm (mW/cm ²)	Limit	Result
Highest(2480MHz)	2.766	1.89	-0.68	0.00032	1.0	Pass

Note: 1) Refer to report MTEB24070186-R1 for EUT test Max Conducted average Output Power value.

Note: 2) $P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot R^2) = (1.89 \cdot 0.86) / (4 \cdot 3.1416 \cdot 20^2) = 0.00032$

.....**THE END OF REPORT**.....