

RF EXPOSURE REPORT

FCC ID: 2BCE7-ESTCXX

Report Reference No. : 23EFSB07004

Date of issue : 2023-09-09

Applicant's name : ES Intelligent Manufacturing (Dongguan) Technology Co., Ltd.

Address : Room 3026, No. 37, Liaobu Panlong Road, Liaobu
Town, Dongguan City, Guangdong Province

Manufacturer : ES Intelligent Manufacturing (Dongguan) Technology Co., Ltd.

Equipment : Wireless dog training collar

Trade Mark : /

Model : ES-TC01, ES-TC02

Ratings : Input: DC 5V Charged
DC 3.7V Li-ion Battery

Testing Laboratory : DongGuan ShuoXin Electronic Technology Co., Ltd.

Address : Zone A, 1F, No. 6, XinGang Road YuanGang Street,
XinAn District, ChangAn Town, DongGuan City,
GuangDong, China

According : KDB 447498 D04 Interim General RF Exposure Guidance v01

Test Engineer:




Blue Qiu

Responsible Engineer :



Smile Wang

Authorized Signatory:



King Wang

MPE CALCULATION METHOD:

$$P_{th} \text{ (mW)} = ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left(\frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right)$$

and f is in GHz, d is the separation distance (cm), and $ERP_{20 \text{ cm}}$ is per Formula (B.1). The example values shown in Table B.2 are for illustration only.

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

$$e_{irp} = p_t \times g_t = (E \cdot d)^2 / 30$$

where:

p_t = transmitter output power in watts,

g_t = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, --- $10^{((\text{dB}\mu\text{V}/\text{m})/20)}/10^6$

d = measurement distance in meters (m)---3m

$$\text{So } p_t = (E \cdot d)^2 / 30 \times g_t$$

$$\text{Ant gain} = 1.5 \text{ dBi} [-2.15 + 1.5 \text{ dBd}(0.8609)]$$

$$\text{Field strength} = 75.78 \text{ dB}\mu\text{V}/\text{m} @ 3\text{m} @ 434.0649 \text{ MHz}$$

$$\text{So } P_t = \{ [10^{(75.78/20)}/10^6 \times 3]^2 / 30 \} \times 1000 \text{ mW} = 0.0114 \text{ mW} < 20 \text{ mW}$$

$$\text{So } ERP = 0.0114 \times 0.8609 = 0.0098 < 20 \text{ mW}$$

Then SAR evaluation is not required

END