



## Appendix C

### RF Test Data for 2.4GWIFI (Conducted Measurement)

Product Name: InvisOutlet

Test Model: IVO1

#### Environmental Conditions

Temperature:	23.8 ° C
Relative Humidity:	52.1%
ATM Pressure:	100.0 kPa
Test Engineer:	Paddi Chen
Supervised by:	Nick Peng





### C.1 -6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	b	2412	Ant1	8.534	>=0.5	Pass
NVNT	b	2437	Ant1	8.09	>=0.5	Pass
NVNT	b	2462	Ant1	8.04	>=0.5	Pass
NVNT	g	2412	Ant1	16.09	>=0.5	Pass
NVNT	g	2437	Ant1	16.288	>=0.5	Pass
NVNT	g	2462	Ant1	16.307	>=0.5	Pass
NVNT	n20	2412	Ant1	16.819	>=0.5	Pass
NVNT	n20	2437	Ant1	17.113	>=0.5	Pass
NVNT	n20	2462	Ant1	17.124	>=0.5	Pass
NVNT	n40	2422	Ant1	34.476	>=0.5	Pass
NVNT	n40	2437	Ant1	35.59	>=0.5	Pass
NVNT	n40	2452	Ant1	35.158	>=0.5	Pass





Test Graphs

-6dB Bandwidth NVNT b 2412MHz Ant1



-6dB Bandwidth NVNT b 2437MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



-6dB Bandwidth NVNT b 2462MHz Ant1




-6dB Bandwidth NVNT g 2412MHz Ant1






-6dB Bandwidth NVNT g 2437MHz Ant1




-6dB Bandwidth NVNT g 2462MHz Ant1






-6dB Bandwidth NVNT n20 2412MHz Ant1




-6dB Bandwidth NVNT n20 2437MHz Ant1






-6dB Bandwidth NVNT n20 2462MHz Ant1




-6dB Bandwidth NVNT n40 2422MHz Ant1






-6dB Bandwidth NVNT n40 2437MHz Ant1



-6dB Bandwidth NVNT n40 2452MHz Ant1







## C.2 Maximum Peak Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	b	2412	Ant1	15.14	30	Pass
NVNT	b	2437	Ant1	15.67	30	Pass
NVNT	b	2462	Ant1	15.46	30	Pass
NVNT	g	2412	Ant1	14.88	30	Pass
NVNT	g	2437	Ant1	14.7	30	Pass
NVNT	g	2462	Ant1	14.79	30	Pass
NVNT	n20	2412	Ant1	13.85	30	Pass
NVNT	n20	2437	Ant1	13.8	30	Pass
NVNT	n20	2462	Ant1	13.75	30	Pass
NVNT	n40	2422	Ant1	12.9	30	Pass
NVNT	n40	2437	Ant1	12.62	30	Pass
NVNT	n40	2452	Ant1	12.62	30	Pass





### C.3 Maximum Power Spectral Density Level


Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	b	2412	Ant1	-8.07	8	Pass
NVNT	b	2437	Ant1	-5.49	8	Pass
NVNT	b	2462	Ant1	-8.66	8	Pass
NVNT	g	2412	Ant1	-15.95	8	Pass
NVNT	g	2437	Ant1	-15.54	8	Pass
NVNT	g	2462	Ant1	-15.67	8	Pass
NVNT	n20	2412	Ant1	-16.14	8	Pass
NVNT	n20	2437	Ant1	-15.48	8	Pass
NVNT	n20	2462	Ant1	-17.17	8	Pass
NVNT	n40	2422	Ant1	-20.63	8	Pass
NVNT	n40	2437	Ant1	-21.04	8	Pass
NVNT	n40	2452	Ant1	-20.14	8	Pass






Test Graphs

PSD NVNT b 2412MHz Ant1




PSD NVNT b 2437MHz Ant1






PSD NVNT b 2462MHz Ant1




PSD NVNT g 2412MHz Ant1










PSD NVNT g 2437MHz Ant1





PSD NVNT g 2462MHz Ant1













### C.4 Band Edge


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	b	2412	Ant1	-44.23	-20	Pass
NVNT	b	2462	Ant1	-59.6	-20	Pass
NVNT	g	2412	Ant1	-30.32	-20	Pass
NVNT	g	2462	Ant1	-40.06	-20	Pass
NVNT	n20	2412	Ant1	-29.8	-20	Pass
NVNT	n20	2462	Ant1	-40.73	-20	Pass
NVNT	n40	2422	Ant1	-37.6	-20	Pass
NVNT	n40	2452	Ant1	-38.09	-20	Pass






Test Graphs

Band Edge NVNT b 2412MHz Ant1 Ref




Band Edge NVNT b 2412MHz Ant1 Emission






Band Edge NVNT b 2462MHz Ant1 Ref




Band Edge NVNT b 2462MHz Ant1 Emission






Band Edge NVNT g 2412MHz Ant1 Ref




Band Edge NVNT g 2412MHz Ant1 Emission






Band Edge NVNT g 2462MHz Ant1 Ref




Band Edge NVNT g 2462MHz Ant1 Emission






Band Edge NVNT n20 2412MHz Ant1 Ref



Band Edge NVNT n20 2412MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Band Edge NVNT n20 2462MHz Ant1 Ref




Band Edge NVNT n20 2462MHz Ant1 Emission






Band Edge NVNT n40 2422MHz Ant1 Ref




Band Edge NVNT n40 2422MHz Ant1 Emission








Band Edge NVNT n40 2452MHz Ant1 Ref



Band Edge NVNT n40 2452MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



### C.5 Conducted RF Spurious Emission


Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	b	2412	Ant1	-51.42	-20	Pass
NVNT	b	2437	Ant1	-52.09	-20	Pass
NVNT	b	2462	Ant1	-51.81	-20	Pass
NVNT	g	2412	Ant1	-46.13	-20	Pass
NVNT	g	2437	Ant1	-45.26	-20	Pass
NVNT	g	2462	Ant1	-45.54	-20	Pass
NVNT	n20	2412	Ant1	-44.08	-20	Pass
NVNT	n20	2437	Ant1	-43.55	-20	Pass
NVNT	n20	2462	Ant1	-43.78	-20	Pass
NVNT	n40	2422	Ant1	-40.18	-20	Pass
NVNT	n40	2437	Ant1	-39.92	-20	Pass
NVNT	n40	2452	Ant1	-39.6	-20	Pass






Test Graphs

Tx. Spurious NVNT b 2412MHz Ant1 Ref



Tx. Spurious NVNT b 2412MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT b 2437MHz Ant1 Ref



Tx. Spurious NVNT b 2437MHz Ant1 Emission






Tx. Spurious NVNT b 2462MHz Ant1 Ref



Tx. Spurious NVNT b 2462MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT g 2412MHz Ant1 Ref



Tx. Spurious NVNT g 2412MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT g 2437MHz Ant1 Ref



Tx. Spurious NVNT g 2437MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT g 2462MHz Ant1 Ref




Tx. Spurious NVNT g 2462MHz Ant1 Emission








Tx. Spurious NVNT n20 2412MHz Ant1 Ref



Tx. Spurious NVNT n20 2412MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT n20 2437MHz Ant1 Ref



Tx. Spurious NVNT n20 2437MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT n20 2462MHz Ant1 Ref




Tx. Spurious NVNT n20 2462MHz Ant1 Emission






Tx. Spurious NVNT n40 2422MHz Ant1 Ref



Tx. Spurious NVNT n40 2422MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT n40 2437MHz Ant1 Ref



Tx. Spurious NVNT n40 2437MHz Ant1 Emission



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Tx. Spurious NVNT n40 2452MHz Ant1 Ref



Tx. Spurious NVNT n40 2452MHz Ant1 Emission





### C.6 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	b	2412	Ant1	99.13	0	0.01
NVNT	b	2437	Ant1	99.16	0	0.01
NVNT	b	2462	Ant1	99.13	0	0.01
NVNT	g	2412	Ant1	97.75	0.1	0.37
NVNT	g	2437	Ant1	97.68	0.1	0.37
NVNT	g	2462	Ant1	97.75	0.1	0.37
NVNT	n20	2412	Ant1	97.25	0.12	0.44
NVNT	n20	2437	Ant1	97.25	0.12	0.44
NVNT	n20	2462	Ant1	97.25	0.12	0.44
NVNT	n40	2422	Ant1	97.23	0.12	0.46
NVNT	n40	2437	Ant1	97.14	0.13	0.46
NVNT	n40	2452	Ant1	97.23	0.12	0.46






Test Graphs

Duty Cycle NVNT b 2412MHz Ant1



Duty Cycle NVNT b 2437MHz Ant1



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China


Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity






Duty Cycle NVNT b 2462MHz Ant1




Duty Cycle NVNT g 2412MHz Ant1








Duty Cycle NVNT g 2437MHz Ant1




Duty Cycle NVNT g 2462MHz Ant1








Duty Cycle NVNT n20 2462MHz Ant1




Duty Cycle NVNT n40 2422MHz Ant1






Duty Cycle NVNT n40 2437MHz Ant1



Duty Cycle NVNT n40 2452MHz Ant1





## C.7 Restrict Band

Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	Duty Factor (dB)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	b	2412	Ant1	2310	-50.64	4.16	-	48.78	Peak	74	Pass
NVNT	b	2412	Ant1	2310	-58.43	4.16	0	40.99	Average	54	Pass
NVNT	b	2412	Ant1	2389.911	-46.22	4.16	-	53.2	Peak	74	Pass
NVNT	b	2412	Ant1	2389.677	-56.12	4.16	0	43.3	Average	54	Pass
NVNT	b	2412	Ant1	2390	-45.94	4.16	-	53.48	Peak	74	Pass
NVNT	b	2412	Ant1	2390	-56.76	4.16	0	42.66	Average	54	Pass
NVNT	b	2462	Ant1	2483.5	-46.6	4.16	-	52.82	Peak	74	Pass
NVNT	b	2462	Ant1	2483.5	-56.07	4.16	0	43.35	Average	54	Pass
NVNT	b	2462	Ant1	2487.598	-44.83	4.16	-	54.59	Peak	74	Pass
NVNT	b	2462	Ant1	2485.266	-54.99	4.16	0	44.43	Average	54	Pass
NVNT	b	2462	Ant1	2500	-50.32	4.16	-	49.1	Peak	74	Pass
NVNT	b	2462	Ant1	2500	-57.93	4.16	0	41.49	Average	54	Pass
NVNT	g	2412	Ant1	2310	-50.29	4.16	-	49.13	Peak	74	Pass
NVNT	g	2412	Ant1	2310	-58.41	4.16	0.1	41.11	Average	54	Pass
NVNT	g	2412	Ant1	2388.858	-36.87	4.16	-	62.55	Peak	74	Pass
NVNT	g	2412	Ant1	2389.794	-52.15	4.16	0.1	47.37	Average	54	Pass
NVNT	g	2412	Ant1	2390	-37.19	4.16	-	62.23	Peak	74	Pass
NVNT	g	2412	Ant1	2390	-52.04	4.16	0.1	47.48	Average	54	Pass
NVNT	g	2462	Ant1	2483.5	-34.68	4.16	-	64.74	Peak	74	Pass
NVNT	g	2462	Ant1	2483.5	-53.5	4.16	0.1	46.02	Average	54	Pass
NVNT	g	2462	Ant1	2483.517	-34.68	4.16	-	64.74	Peak	74	Pass
NVNT	g	2462	Ant1	2483.517	-53.5	4.16	0.1	46.02	Average	54	Pass
NVNT	g	2462	Ant1	2500	-50.12	4.16	-	49.3	Peak	74	Pass
NVNT	g	2462	Ant1	2500	-58.03	4.16	0.1	41.49	Average	54	Pass
NVNT	n20	2412	Ant1	2310	-50.24	4.16	-	49.18	Peak	74	Pass
NVNT	n20	2412	Ant1	2310	-58.65	4.16	0.12	40.89	Average	54	Pass
NVNT	n20	2412	Ant1	2389.794	-31.26	4.16	-	68.16	Peak	74	Pass
NVNT	n20	2412	Ant1	2389.092	-51.2	4.16	0.12	48.34	Average	54	Pass
NVNT	n20	2412	Ant1	2390	-37	4.16	-	62.42	Peak	74	Pass
NVNT	n20	2412	Ant1	2390	-50.38	4.16	0.12	49.16	Average	54	Pass
NVNT	n20	2462	Ant1	2483.5	-38.41	4.16	-	61.01	Peak	74	Pass
NVNT	n20	2462	Ant1	2483.5	-54.17	4.16	0.12	45.37	Average	54	Pass
NVNT	n20	2462	Ant1	2483.941	-34.82	4.16	-	64.6	Peak	74	Pass
NVNT	n20	2462	Ant1	2483.676	-52.27	4.16	0.12	47.27	Average	54	Pass
NVNT	n20	2462	Ant1	2500	-51.93	4.16	-	47.49	Peak	74	Pass
NVNT	n20	2462	Ant1	2500	-58.04	4.16	0.12	41.5	Average	54	Pass
NVNT	n40	2422	Ant1	2310	-51.63	4.16	-	47.79	Peak	74	Pass



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



NVNT	n40	2422	Ant1	2310	-58.71	4.16	0.12	40.83	Average	54	Pass
NVNT	n40	2422	Ant1	2387.816	-36.46	4.16	-	60.96	Peak	74	Pass
NVNT	n40	2422	Ant1	2389.52	-52.87	4.16	0.12	46.67	Average	54	Pass
NVNT	n40	2422	Ant1	2390	-44.35	4.16	-	55.07	Peak	74	Pass
NVNT	n40	2422	Ant1	2390	-53.26	4.16	0.12	46.28	Average	54	Pass
NVNT	n40	2452	Ant1	2483.5	-39.83	4.16	-	59.59	Peak	74	Pass
NVNT	n40	2452	Ant1	2483.5	-52.22	4.16	0.12	47.32	Average	54	Pass
NVNT	n40	2452	Ant1	2483.62	-35.84	4.16	-	63.58	Peak	74	Pass
NVNT	n40	2452	Ant1	2484.244	-52.51	4.16	0.12	47.03	Average	54	Pass
NVNT	n40	2452	Ant1	2500	-48.92	4.16	-	50.5	Peak	74	Pass
NVNT	n40	2452	Ant1	2500	-58.32	4.16	0.12	41.22	Average	54	Pass









Test Graphs

Restrict Band NVNT b 2412MHz Ant1 Peak



Restrict Band NVNT b 2412MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China


Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity






Restrict Band NVNT b 2462MHz Ant1 Peak



Restrict Band NVNT b 2462MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity





Restrict Band NVNT g 2412MHz Ant1 Peak




Restrict Band NVNT g 2412MHz Ant1 Average








Restrict Band NVNT n20 2412MHz Ant1 Peak




Restrict Band NVNT n20 2412MHz Ant1 Average






Restrict Band NVNT n20 2462MHz Ant1 Peak



Restrict Band NVNT n20 2462MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.


Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com


Scan code to check authenticity



Restrict Band NVNT n40 2422MHz Ant1 Peak




Restrict Band NVNT n40 2422MHz Ant1 Average






Restrict Band NVNT n40 2452MHz Ant1 Peak



Restrict Band NVNT n40 2452MHz Ant1 Average



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity