



# ELEMENT WASHINGTON DC LLC

7185 Oakland Mills Road, Columbia, MD 21046 USA  
Tel. 410.290.6652 / Fax 410.290.6654  
<http://www.element.com>

## TEST REPORT CBSD-SAS Interoperability

**Applicant Name:**  
Samsung Electronics Co., Ltd.  
129, Samsung-ro,  
Yeongtong-gu, Suwon-si  
Gyeonggi-do, 16677, Korea

**Date of Testing:**  
6/22/2022 – 7/22/2022  
**Test Site/Location:**  
Element Lab. Columbia, MD, USA  
**Test Report Serial No.:**  
1M2205100060-01.A3L

<b>FCC ID:</b>	<b>A3LRT2203-48A</b>
<b>APPLICANT:</b>	<b>Samsung Electronics Co., Ltd.</b>

**Application Type:** Certification  
**Model:** RT2203-48A  
**EUT Type:** Cat. B LTE/NR Access Point  
**Frequency Range:** 3550 – 3700 MHz  
**FCC Classification:** Citizens Band Category A and B Devices (CBD)  
**FCC Rule Part(s):** Part 96  
**Test Procedure(s):** KDB 940660 D01 v03, KDB 940660 D02 v01, WINNF-TS-0122-V1.0.2, CBRSA-TS-9001 V.1.0.0

This equipment has been shown to be capable of compliance with the applicable technical standards as indicated in the measurement report and was tested in accordance with the measurement procedures specified in the test procedures listed above. Test results reported herein relate only to the item(s) tested.

I attest to the accuracy of data. All measurements reported herein were performed by me or were made under my supervision and are correct to the best of my knowledge and belief. I assume full responsibility for the completeness of these measurements and vouch for the qualifications of all persons taking them.

**RJ Ortanez**  
Executive Vice President



<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 1 of 72

# TABLE OF CONTENTS

1.0	INTRODUCTION.....	3
1.1	Scope.....	3
1.2	Element Test Location .....	3
1.3	Test Facility / Accreditations .....	3
2.0	PRODUCT INFORMATION .....	4
2.1	Equipment Description.....	4
2.2	Device Capabilities .....	4
2.3	Test Configuration .....	4
2.4	Modifications.....	4
3.0	TEST EQUIPMENT CALIBRATION DATA.....	5
4.0	ENVIRONMENTAL CONDITIONS .....	6
5.0	EVALUATION PROCEDURE .....	7
6.0	TEST Summary.....	8
6.1	Summary .....	8
7.0	CONCLUSION .....	10
APPENDIX A – TEST RESULT AND DATA .....		11
A1	[WINNF.FT.C.REG.1] MULTI-STEP REGISTRATION .....	11
A2	[WINNF.FT.C.REG.8] MISSING REQUIRED PARAMETERS (RESPONSECODE 102) .....	13
A3	[WINNF.FT.C.REG.10] PENDING REGISTRATION (RESPONSECODE 200) .....	15
A4	[WINNF.FT.C.REG.12] INVALID PARAMETER (RESPONSECODE 103) .....	17
A5	[WINNF.FT.C.REG.14] BLACKLISTED CBSD (RESPONSECODE 101) .....	19
A6	[WINNF.FT.C.REG.16] UNSUPPORTED SAS PROTOCOL VERSION (RESPONSECODE 100) .....	21
A7	[WINNF.FT.C.REG.18] GROUP ERROR (RESPONSECODE 201) .....	23
A8	[WINNF.FT.C.GRA.1] UNSUCCESSFUL GRANT RESPONSECODE=400 (INTERFERENCE) .....	25
A9	[WINNF.FT.C.GRA.2] UNSUCCESSFUL GRANT RESPONSECODE=401 (GRANT_CONFLICT) .....	27
A10	[WINNF.FT.C.HBT.1] HEARTBEAT SUCCESS CASE (FIRST HEARTBEAT RESPONSE).....	29
A11	[WINNF.FT.C.HBT.3] HEARTBEAT RESPONSECODE=105 (DEREGISTER) .....	33
A12	[WINNF.FT.C.HBT.4] HEARTBEAT RESPONSECODE=500 (TERMINATED_GRANT) .....	35
A13	[WINNF.FT.C.HBT.5] HEARTBEAT RESPONSECODE=501 (SUSPENDED_GRANT) IN FIRST HEARTBEAT RESPONSE .....	37
A14	[WINNF.FT.C.HBT.6] HEARTBEAT RESPONSECODE=501 (SUSPENDED_GRANT) IN SUBSEQUENT HEARTBEAT RESPONSE.....	39
A15	[WINNF.FT.C.HBT.7] HEARTBEAT RESPONSECODE=502 (UNSYNC_OP_PARAM).....	41
A16	[WINNF.FT.C.HBT.9] HEARTBEAT RESPONSE ABSENT (FIRST HEARTBEAT).....	43
A17	[WINNF.FT.C.HBT.10] HEARTBEAT RESPONSE ABSENT (SUBSEQUENT HEARTBEAT) .....	45
A18	[WINNF.FT.C.MES.1] REGISTRATION RESPONSE CONTAINS MEASREPORTCONFIG .....	47
A19	[WINNF.FT.C.RLQ.1] SUCCESSFUL RELINQUISHMENT .....	48
A20	[WINNF.FT.C.DRG.1] SUCCESSFUL DEREGISTRATION.....	50
A21	[WINNF.FT.C.SCS.1] SUCCESSFUL TLS CONNECTION BETWEEN UUT AND SAS TEST HARNESS.....	52
A22	[WINNF.FT.C.SCS.2] TLS FAILURE DUE TO REVOKED CERTIFICATE .....	55
A23	[WINNF.FT.C.SCS.3] TLS FAILURE DUE TO EXPIRED SERVER CERTIFICATE.....	57
A24	[WINNF.FT.C.SCS.4] TLS FAILURE WHEN SAS TEST HARNESS CERTIFICATE IS ISSUED BY AN UNKNOWN CA.....	59
A25	[WINNF.FT.C.SCS.5] TLS FAILURE WHEN CERTIFICATE AT THE SAS TEST HARNESS IS CORRUPTED .....	61
A26	[WINNF.PT.C.HBT.1] UUT RF TRANSMIT POWER MEASUREMENT.....	63
APPENDIX B – TEST LOGS .....		71

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 2 of 72

## 1.0 INTRODUCTION

### 1.1 Scope

Measurement and determination of compliance with the technical rules and regulations of the Federal Communications Commission.

### 1.2 Element Test Location

These measurement tests were conducted at the Element laboratory located at 7185 Oakland Mills Road, Columbia, MD 21046.

### 1.3 Test Facility / Accreditations

**Measurements were performed at Element lab located in Columbia, MD 21046, U.S.A.**

- Element is a CBRS Alliance (OnGo) Approved Test Lab
- Element is a WInnForum Approved Test Lab
- Element is an ISO 17025-2017 accredited test facility under the American Association for Laboratory Accreditation (A2LA) with Certificate number 2041.01 for CBRS Alliance Certification Test Plan and WInnForum Conformance and Performance Test Technical Standard.
- Element is an ISO 17025-2017 accredited test facility under the American Association for Laboratory Accreditation (A2LA) with Certificate number 2041.01 for Specific Absorption Rate (SAR), Hearing Aid Compatibility (HAC) testing, where applicable, and Electromagnetic Compatibility (EMC) testing for FCC and Innovation, Science, and Economic Development Canada rules.
- Element TCB is a Telecommunication Certification Body (TCB) accredited to ISO/IEC 17065-2012 by A2LA (Certificate number 2041.03) in all scopes of FCC Rules and ISED Standards (RSS).
- Element facility is a registered (2451B) test laboratory with the site description on file with ISED.

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 3 of 72

## 2.0 PRODUCT INFORMATION

### 2.1 Equipment Description

The Equipment Under Test (EUT) is the **Samsung Electronics Co., Ltd., Cat B LTE/NR Access Point FCC ID: A3LRT2203-48A**. The test data contained in this report pertains only to CBSD-SAS interoperability. The EUT is a CBSD.

**Test Device Serial Number(s):** 72300121600061

**Test Device Hardware Version:** PCS00

**Test Device Software Version:** 22A

### 2.2 Device Capabilities

This device contains the following capabilities:

LTE Band 48, NR n48

This device supports the following conditional features:

	Conditional Test Case Definitions	Supported
<b>C1</b>	Mandatory for UUT which supports multi-step registration message	<input checked="" type="checkbox"/>
<b>C2</b>	Mandatory for UUT which supports single-step registration with no CPI-signed data in the registration message. By definition, this is a subset of Category A devices which determine all registration information, including location, without CPI intervention.	<input type="checkbox"/>
<b>C3</b>	Mandatory for UUT which supports single-step registration containing CPI-signed data in the registration message.	<input type="checkbox"/>
<b>C4</b>	Mandatory for UUT which supports RECEIVED_POWER_WITHOUT_GRANT measurement report type.	<input checked="" type="checkbox"/>
<b>C5</b>	Mandatory for UUT which supports RECEIVED_POWER_WITH_GRANT measurement report type.	<input type="checkbox"/>
<b>C6</b>	Mandatory for UUT which supports parameter change being made at the UUT and prior to sending a deregistration	<input type="checkbox"/>

**Table 2-1. Conditional Features**

### 2.3 Test Configuration

The EUT was connected to the SAS Test Harness developed by WINNF WG4-CBSD. The latest version of the SAS Test Harness (V1.0.0.2) provided by CBRS Alliance was used. The SAS Test Harness is synchronized to UTC time.

### 2.4 Modifications

No modifications were made to EUT during testing.

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 4 of 72

### 3.0 TEST EQUIPMENT CALIBRATION DATA

Test Equipment Calibration is traceable to the National Institute of Standards and Technology (NIST).

Manufacturer	Model	Description	Cal Date	Cal Interval	Cal Due	Serial Number
Agilent	N9020A	MXA Signal Analyzer	3/4/2022	Annual	3/4/2023	US46470561
Dell	Latitude 5580	Test Harness Laptop	N/A	N/A	N/A	N/A

**Table 3-1 Annual Test Equipment Calibration Schedule**

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 5 of 72

## 4.0 ENVIRONMENTAL CONDITIONS

The temperature is controlled within range of 15°C to 35°C. The relative humidity is controlled within range of 10% to 75%. The atmospheric pressure is monitored within the range 86-106kPa (860-1060mbar).

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 6 of 72

## 5.0 EVALUATION PROCEDURE

The measurement procedure described in KDB940660 D01 V03 and WINNF-TS-0122V1.0.2 were used in the measurement of the EUT.

**Deviation from measurement procedure.....None**

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 7 of 72

## 6.0 TEST SUMMARY

### 6.1 Summary

Company Name: Samsung Electronics Co., Ltd.

FCC ID: A3LRT2203-48A

**Table 6-1. Summary of Test Results**

FCC Part Section(s)	KDB940660 D01 Section 3.3 a)	Test Case Description	WinnForum Test Case	Test Result
96.39 (c)	1	Confirm that the device will only transmit after it receives authorization from a SAS	WINNF.FT.C.REG.1 WINNF.FT.C.REG.8 WINNF.FT.C.REG.10 WINNF.FT.C.REG.12 WINNF.FT.C.REG.14 WINNF.FT.C.REG.16 WINNF.FT.C.REG.18 WINNF.FT.C.GRA.1 WINNF.FT.C.GRA.2 WINNF.FT.C.HBT.5	Pass
96.39 (c)	2	Check the device registration and authorization with the SAS – determine if the device behaves appropriately for successful and unsuccessful registrations. The device should not be transmitting without authorization from the SAS.	WINNF.FT.C.REG.1 WINNF.FT.C.REG.8 WINNF.FT.C.REG.10 WINNF.FT.C.REG.12 WINNF.FT.C.REG.14 WINNF.FT.C.REG.16 WINNF.FT.C.REG.18	Pass
96.39(c)(1)	3	Confirm that the device changes its operating power and/or channel in response to a command from the SAS.	WINNF.FT.C.HBT.1	Pass
96.39	4	Confirm that the device correctly configures based on the different license classes	N/A	Pass
96.39(c)(1)	5	Confirm that the device transmits at a power level less than or equal to the maximum power level approved by the SAS.	WINNF.PT.C.HBT	Pass
96.39(b)(c)	6	Confirm that the device transmits with a bandwidth less than or equal to the SAS specified bandwidth.	WINNF.FT.C.HBT.1	Pass
96.39(c)(2)	7	Confirm that the device transmits on the SAS specified frequency.	WINNF.FT.C.HBT.1	Pass
96.39(c)(2)	8	Confirm that the device stops transmission in response to a command from the SAS, within a period as required by Part 96.	WINNF.FT.C.HBT.3 WINNF.FT.C.HBT.4 WINNF.FT.C.HBT.6 WINNF.FT.D.HBT.7 WINNF.FT.C.HBT.10 WINNF.FT.C.RLQ.1 WINNF.FT.C.DRG.1	Pass

**Table 6-2. Summary of Test Results (continued)**

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 8 of 72

V1.0

96.39 (c)	9	Confirm that the device sends measurements data in response to the command from the SAS.	WINNF.FT.C.MES.1	Pass
96.39(a)	10	For devices with geo-location, confirm that it notifies the SAS of a new location when it is beyond the required distance parameter ( $\pm 50$ m) within the required time frame.	N/A	N/A
96.39 (c)	11	Confirm that the device is capable of reporting the signal level (measurement data) and frequency to SAS.	WINNF.FT.C.MES.1	Pass
	12	For a device that operates as a Category A CBSD and then desires to operate as a Category B CBSD (or vice versa), confirm that it re-registers with the SAS for the updated authorization status.	N/A	Pass
96 E	13	When CBSDs communicate through a management system, confirm compliance with all requirements.	N/A	Pass
96.39	14	When communication between the CBSD and SAS is lost: i) Describe how the CBSD would react if the communications between the device and the SAS is lost. Confirm that the CBSD stops transmission once it loses the link to the SAS. ii) Describe the process for re-establishment of the communications and confirm that the CBSD acts accordingly. iii) Confirm power-on restart process for registration (re-registration) occurs as expected. iv) Confirm the process for de-registration occurs as expected.	WINNF.FT.C.HBT.9 WINNF.FT.C.HBT.10	Pass
96.39(f)	KDB940660 D01 Section 4	SAS and Device Security Requirements	WINNF.FT.C.SCS.1 WINNF.FT.C.SCS.2 WINNF.FT.C.SCS.3 WINNF.FT.C.SCS.4 WINNF.FT.C.SCS.5	Pass

**Notes:**

- Test cases denoted as “N/A” in the table above are not applicable to the EUT and are either Optional or Conditional per Section 6 of WINNF-TS-0122.
- Please see Appendices for test data.

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 9 of 72

## 7.0 CONCLUSION

The data collected relate only to the item(s) tested and show that the **Samsung Electronics Co., Ltd., Cat B LTE/NR Router FCC ID: A3LRT2203-48A** has been tested to show compliance with Part 96 and WinnForum TS-0122.

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 10 of 72

V1.0


## APPENDIX A – TEST RESULT AND DATA

### A1 [WINNF.FT.C.REG.1] Multi-Step registration


	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with the SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul> CBSD sends correct Registration request information, as specified in [n.5], to the SAS Test Harness:	--	--
2	<ul style="list-style-type: none"> <li>• The required userId, fcId and cbsdSerialNumber registration parameters shall be sent from the CBSD and conform to proper format and acceptable ranges.</li> <li>• Any REG-conditional or optional registration parameters that may be included in the message shall be verified that they conform to proper format and are within acceptable ranges.</li> </ul> Note: It is outside the scope of this document to test the Registration information that is supplied via another means.	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	<ul style="list-style-type: none"> <li>• SAS Test Harness sends a CBSD Registration Response as follows:               <ul style="list-style-type: none"> <li>- cbsdId = Ci</li> <li>- measReportConfig shall not be included</li> <li>- responseCode = 0</li> </ul> </li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 11 of 72

**Test Plots:**



**Plot 1. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.1) - LTE**




**Plot 2. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.1) - NR**

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 12 of 72

## A2 [WINNF.FT.C.REG.8] Missing Required parameters (responseCode 102)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul>	--	--
2	CBSD sends a Registration request to SAS Test Harness.	--	--
3	SAS Test Harness rejects the request by sending a CBSD Registration Response as follows: <ul style="list-style-type: none"> <li>- SAS response does not include cbsdId</li> <li>- responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



**Plot 3. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.8) – LTE**


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 13 of 72



### A3 [WINNF.FT.C.REG.10] Pending registration (responseCode 200)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul>	--	--
2	CBSD sends a Registration request to SAS Test Harness.	--	--
3	SAS Test Harness rejects the request by sending a CBSD Registration Response as follows: <ul style="list-style-type: none"> <li>- SAS response does not include cbsdId</li> <li>- responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



**Plot 5. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.10) – LTE**


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 15 of 72



## A4 [WINNF.FT.C.REG.12] Invalid parameter (responseCode 103)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul>	--	--
2	CBSD sends a Registration request to SAS Test Harness.	--	--
3	SAS Test Harness rejects the request by sending a CBSD Registration Response as follows: <ul style="list-style-type: none"> <li>- SAS response does not include cbsdId</li> <li>- responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



Plot 7. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.12) – LTE


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 17 of 72



## A5 [WINNF.FT.C.REG.14] Blacklisted CBSD (responseCode 101)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul>	--	--
2	CBSD sends a Registration request to SAS Test Harness.	--	--
3	SAS Test Harness rejects the request by sending a CBSD Registration Response as follows: <ul style="list-style-type: none"> <li>- SAS response does not include cbsdId</li> <li>- responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



**Plot 9. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.14) – LTE**


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 19 of 72



## A6 [WINNF.FT.C.REG.16] Unsupported SAS protocol version (responseCode 100)

Test Execution Steps		PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul>	--	--
2	CBSD sends a Registration request to SAS Test Harness.	--	--
3	SAS Test Harness rejects the request by sending a CBSD Registration Response as follows: <ul style="list-style-type: none"> <li>- SAS response does not include cbsdId</li> <li>- responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



**Plot 11. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.16) – LTE**


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 21 of 72



## A7 [WINNF.FT.C.REG.18] Group Error (responseCode 201)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT is in the Unregistered state</li> </ul>	--	--
2	CBSD sends a Registration request to SAS Test Harness.	--	--
3	SAS Test Harness rejects the request by sending a CBSD Registration Response as follows: <ul style="list-style-type: none"> <li>- SAS response does not include cbsdId</li> <li>- responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



**Plot 13. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.REG.18) – LTE**


FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 23 of 72



## A8 [WINNF.FT.C.GRA.1] Unsuccessful Grant responseCode=400 (INTERFERENCE)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness, with cbsdId = C</li> </ul>	--	--
2	UUT sends valid Grant Request.	--	--
3	SAS Test Harness sends a Grant Response message, including <ul style="list-style-type: none"> <li>• cbsdId=C</li> <li>• responseCode = R</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



**Plot 15. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.GRA.1) – LTE**


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 25 of 72	



### A9 [WINNF.FT.C.GRA.2] Unsuccessful Grant responseCode=401 (GRANT\_CONFLICT)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: • UUT has registered successfully with SAS Test Harness, with cbsdId = C	--	--
2	UUT sends valid Grant Request.	--	--
3	SAS Test Harness sends a Grant Response message, including • cbsdId=C • responseCode = R	--	--
4	After completion of step 3, SAS Test Harness will not provide any positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: • UUT shall not transmit RF	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



Plot 17. Conducted Measurement – No RF transmission in entire band for 60s of elapsed time (WINNF.FT.C.GRA.2) – LTE

FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 27 of 72	




## A10 [WINNF.FT.C.HBT.1] Heartbeat Success Case (first Heartbeat Response)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: • UUT has registered successfully with SAS Test Harness, with cbsdId = C	--	--
2	UUT sends a message: • If message is type Spectrum Inquiry Request, go to step 3, or • If message is type Grant Request, go to step 5	--	--
3	UUT sends Spectrum Inquiry Request. Validate: • cbsdId = C • List of frequencyRange objects sent by UUT are within the CBRS frequency range	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	SAS Test Harness sends a Spectrum Inquiry Response message, including the following parameters: • cbsdId = C • availableChannel is an array of availableChannel objects • responseCode = 0	--	--
5	UUT sends Grant Request message. Validate: • cbsdId = C • maxEIRP is at or below the limit appropriate for CBSD category as defined by Part 96 • operationFrequencyRange, F, sent by UUT is a valid range within the CBRS band	<input checked="" type="checkbox"/>	<input type="checkbox"/>
6	SAS Test Harness sends a Grant Response message, including the parameters: • cbsdId = C • grantId = G = a valid grant ID • grantExpireTime = UTC time greater than duration of the test • responseCode = 0	--	--
7	UUT sends a first Heartbeat Request message. Verify Heartbeat Request message is formatted correctly, including: • cbsdId = C • grantId = G • operationState = "GRANTED"	<input checked="" type="checkbox"/>	<input type="checkbox"/>
8	SAS Test Harness sends a Heartbeat Response message, with the following parameters: • cbsdId = C • grantId = G • transmitExpireTime = current UTC time + 200 seconds • responseCode = 0	--	--
9	For further Heartbeat Request messages sent from UUT after completion of step 8, validate message is sent within latest specified heartbeatInterval, and: • cbsdId = C • grantId = G • operationState = "AUTHORIZED" and SAS Test Harness responds with a Heartbeat Response message including the following parameters: • cbsdId = C • grantId = G • transmitExpireTime = current UTC time + 200 seconds • responseCode = 0	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 29 of 72


10	Monitor the RF output of the UUT from start of test until UUT transmission commences. Verify: <ul style="list-style-type: none"> <li>• UUT does not transmit at any time prior to completion of the first heartbeat response</li> <li>• UUT transmits after step 8 is complete, and its transmission is limited to within the bandwidth range F</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
----	--	-------------------------------------	--------------------------

### Test Plots:




**Plot 19. Conducted Measurement - RF transmission after SAS heartbeat response (WINNF.FT.C.HBT.1) – LTE**

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 30 of 72




Plot 20. Conducted Measurement - RF transmission after SAS heartbeat response (WINNF.FT.C.HBT.1) – NR



Plot 21. Conducted Measurement Occupied Bandwidth for 20MHz (WINNF.FT.C.HBT.1) – LTE

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 31 of 72



Plot 22. Conducted Measurement Occupied Bandwidth for 20MHz (WINNF.FT.C.HBT.1) – NR


FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 32 of 72

### A11 [WINNF.FT.C.HBT.3] Heartbeat responseCode=105 (DEREGISTER)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows:               <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in AUTHORIZED state and is transmitting within the grant bandwidth F on RF interface</li> </ul>	--	--
2	UUT sends a Heartbeat Request message. Ensure Heartbeat Request message is sent within Heartbeat Interval specified in the latest Heartbeat Response, and formatted correctly, including: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "AUTHORIZED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness sends a Heartbeat Response message, including the following parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• transmitExpireTime = T = Current UTC time</li> <li>• responseCode = 105 (DEREGISTER)</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness shall not allow any further grants to the UUT.	--	--
5	Monitor the RF output of the UUT. Verify: <ul style="list-style-type: none"> <li>• UUT shall stop transmission within (T + 60 seconds) of completion of step 3</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A		<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 33 of 72

Test Plots:



Plot 23. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (WINNF.FT.C.HBT.3) – LTE



Plot 24. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (WINNF.FT.C.HBT.3) – NR


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 34 of 72

## A12 [WINNF.FT.C.HBT.4] Heartbeat responseCode=500 (TERMINATED\_GRANT)


	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows:               <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in AUTHORIZED state and is transmitting within the grant bandwidth F on RF interface</li> </ul>	--	--
2	UUT sends a Heartbeat Request message. Ensure Heartbeat Request message is sent within Heartbeat Interval specified in the latest Heartbeat Response, and formatted correctly, including: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "AUTHORIZED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness sends a Heartbeat Response message, including the following parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• transmitExpireTime = T = Current UTC time</li> <li>• responseCode = 500 (TERMINATED_GRANT)</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness shall not allow any further grants to the UUT.	--	--
5	Monitor the RF output of the UUT. Verify: <ul style="list-style-type: none"> <li>• UUT shall stop transmission within (T + 60 seconds) of completion of step 3</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 35 of 72

**Test Plots:**



**Plot 25. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (X) (WINNF.FT.C.HBT.4) – LTE**



**Plot 26. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (X) (WINNF.FT.C.HBT.4) – NR**


FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 36 of 72

### A13 [WINNF.FT.C.HBT.5] Heartbeat responseCode=501 (SUSPENDED\_GRANT) in First Heartbeat Response


	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows:               <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in AUTHORIZED state and is transmitting within the grant bandwidth F on RF interface</li> </ul>	--	--
2	UUT sends a Heartbeat Request message. Ensure Heartbeat Request message is sent within Heartbeat Interval specified in the latest Heartbeat Response, and formatted correctly, including: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "GRANTED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness sends a Heartbeat Response message, including the following parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• transmitExpireTime = T = Current UTC time</li> <li>• responseCode = 501 (SUSPENDED_GRANT)</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness shall not allow any further grants to the UUT.	--	--
5	Monitor the SAS-CBSD interface. Verify either A OR B occurs: <p>A. UUT sends a Heartbeat Request message. Ensure message is sent within latest specified heartbeatInterval, and is correctly formatted with parameters:</p> <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "GRANTED"</li> </ul> <p>B. UUT sends a Relinquishment request message. Ensure message is correctly formatted with parameters:</p> <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> </ul> Monitor the RF output of the UUT. Verify: <ul style="list-style-type: none"> <li>• UUT does not transmit at any time</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 37 of 72

**Test Plots:**



**Plot 27. Conducted Measurement – No RF transmission in entire band (WINNF.FT.C.HBT.5) – LTE**



**Plot 28. Conducted Measurement – No RF transmission in entire band (WINNF.FT.C.HBT.5) – NR**


FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 38 of 72

## A14 [WINNF.FT.C.HBT.6] Heartbeat responseCode=501 (SUSPENDED\_GRANT) in Subsequent Heartbeat Response

	Test Execution Steps	PASS	FAIL
1	<p>Ensure the following conditions are met for test entry:</p> <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows: <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in AUTHORIZED state and is transmitting within the grant bandwidth F on RF interface</li> </ul>	--	--
2	<p>UUT sends a Heartbeat Request message.</p> <p>Ensure Heartbeat Request message is sent within Heartbeat Interval specified in the latest Heartbeat Response, and formatted correctly, including:</p> <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "AUTHORIZED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	<p>SAS Test Harness sends a Heartbeat Response message, including the following parameters:</p> <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• transmitExpireTime = T = Current UTC time</li> <li>• responseCode = 501 (SUSPENDED_GRANT)</li> </ul>	--	--
4	<p>After completion of step 3, SAS Test Harness shall not allow any further grants to the UUT.</p>	--	--
5	<p>Monitor the SAS-CBSD interface. Verify either A OR B occurs:</p> <p>A. UUT sends a Heartbeat Request message. Ensure message is sent within latest specified heartbeatInterval, and is correctly formatted with parameters:</p> <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "GRANTED"</li> </ul> <p>B. UUT sends a Relinquishment request message. Ensure message is correctly formatted with parameters:</p> <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> </ul> <p>Monitor the RF output of the UUT. Verify:</p> <ul style="list-style-type: none"> <li>• UUT shall stop transmission within (T + 60 seconds) of completion of step 3</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 39 of 72

**Test Plots:**



**Plot 29. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (X) (WINNF.FT.C.HBT.6) – LTE**



**Plot 30. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (X) (WINNF.FT.C.HBT.6) – NR**


FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 40 of 72

## A15 [WINNF.FT.C.HBT.7] Heartbeat responseCode=502 (UNSYNC\_OP\_PARAM)

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows:               <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in AUTHORIZED state and is transmitting within the grant bandwidth F on RF interface</li> </ul>	--	--
2	UUT sends a Heartbeat Request message. Ensure Heartbeat Request message is sent within Heartbeat Interval specified in the latest Heartbeat Response, and formatted correctly, including: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "AUTHORIZED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness sends a Heartbeat Response message, including the following parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• transmitExpireTime = T = Current UTC time</li> <li>• responseCode = 502 (UNSYNC_OP_PARAM)</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness shall not allow any further grants to the UUT.	--	--
5	Monitor the SAS-CBSID interface. Verify: <ul style="list-style-type: none"> <li>• UUT sends a Grant Relinquishment Request message. Verify message is correctly formatted with parameters:               <ul style="list-style-type: none"> <li>o cbsdId = C</li> <li>o grantId = G</li> </ul> </li> </ul> Monitor the RF output of the UUT. Verify: <ul style="list-style-type: none"> <li>• UUT shall stop transmission within (T+60) seconds of completion of step 3.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 41 of 72

### Test Plots:



Plot 31. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (X) (WINNF.FT.C.HBT.7) – LTE



Plot 32. Conducted Measurement - RF transmission stops within 60s of SAS message indicated by Marker 1 (X) (WINNF.FT.C.HBT.7) – NR


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 42 of 72

## A16 [WINNF.FT.C.HBT.9] Heartbeat Response Absent (First Heartbeat)


	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows:               <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in GRANTED, but not AUTHORIZED state (i.e. has not performed its first Heartbeat Request)</li> </ul>	--	--
2	UUT sends a Heartbeat Request message. Ensure Heartbeat Request message is sent within latest specified heartbeatInterval, and is formatted correctly, including: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "GRANTED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	After completion of Step 2, SAS Test Harness does not respond to any further messages from UUT to simulate loss of network connection	--	--
4	Monitor the RF output of the UUT from start of test to 60 seconds after step 3. Verify: <ul style="list-style-type: none"> <li>• At any time during the test, UUT shall not transmit on RF interface</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 43 of 72

**Test Plots:**



**Plot 33. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.HBT.9) – LTE**



**Plot 34. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.HBT.9) – NR**


FCC ID: A3LRT2203-48A		<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 44 of 72

## A17 [WINNF.FT.C.HBT.10] Heartbeat Response Absent (Subsequent Heartbeat)


	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has registered successfully with SAS Test Harness</li> <li>• UUT has a valid single grant as follows:               <ul style="list-style-type: none"> <li>o valid cbsdId = C</li> <li>o valid grantId = G</li> <li>o grant is for frequency range F, power P</li> <li>o grantExpireTime = UTC time greater than duration of the test</li> </ul> </li> <li>• UUT is in AUTHORIZED state and is transmitting within the grant bandwidth F on RF interface</li> </ul>	--	--
2	UUT sends a Heartbeat Request message. Verify Heartbeat Request message is sent within the latest specified heartbeatInterval, and is formatted correctly, including: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• operationState = "AUTHORIZED"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness sends a Heartbeat Response message, including the following parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• transmitExpireTime = current UTC time + 200 seconds</li> <li>• responseCode = 0</li> </ul>	--	--
4	After completion of Step 3, SAS Test Harness does not respond to any further messages from UUT	--	--
5	Monitor the RF output of the UUT. Verify: <ul style="list-style-type: none"> <li>• UUT shall stop all transmission on RF interface within (transmitExpireTime + 60 seconds), using the transmitExpireTime sent in Step 3.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 45 of 72

Test Plots:



Plot 35. Conducted Measurement - RF transmission stops within transmitExpireTime + 60s. The last SAS heartbeat message is indicated by Marker 1 (X) (WINNF.FT.C.HBT.10) – LTE



Plot 36. Conducted Measurement - RF transmission stops within transmitExpireTime + 60s. The last SAS heartbeat message is indicated by Marker 1 (X) (WINNF.FT.C.HBT.10) – NR

MEASUREMENT REPORT (CERTIFICATION)			Approved by: Technical Manager
FCC ID: A3LRT2203-48A	Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point
			Page 46 of 72

## A18 [WINNF.FT.C.MES.1] Registration Response contains measReportConfig

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> </ul>	--	--
2	UUT sends a Registration Request message. Validate the Registration Request message is formatted correctly, including: <ul style="list-style-type: none"> <li>userId is present and correct</li> <li>fccId is present and correct</li> <li>cbsdSerialNumber is present and correct</li> <li>measCapability = "RECEIVED_POWER_WITHOUT_GRANT"</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness sends a Registration Response message, with the following parameters: <ul style="list-style-type: none"> <li>cbsdId = C = valid cbsdId for this UUT</li> <li>measReportConfig= "RECEIVED_POWER_WITHOUT_GRANT"</li> <li>responseCode = 0</li> </ul>	--	--
4	UUT sends a message: <ul style="list-style-type: none"> <li>If message is type Spectrum Inquiry Request, go to step 5, or</li> <li>If message is type Grant Request, go to step 7</li> </ul>	--	--
5	UUT sends message type Spectrum Inquiry Request. Verify message contains all required parameters properly formatted, and specifically: <ul style="list-style-type: none"> <li>cbsdId = C</li> <li>measReport is present, and is a properly formatted rcvdPowerMeasReport.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
6	SAS Test Harness sends a Spectrum Inquiry Response, with the following parameters: <ul style="list-style-type: none"> <li>cbsdId = C</li> <li>availableChannel is an array of availableChannel objects</li> <li>responseCode = 0</li> </ul>	--	--
7	UUT sends message type Grant Request message. Verify message contains all required parameters properly formatted, and specifically: <ul style="list-style-type: none"> <li>cbsdId = C</li> <li>measReport is present, and is a properly formatted rcvdPowerMeasReport.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>


<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 47 of 72

## A19 [WINNF.FT.C.RLQ.1] Successful Relinquishment


	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT has successfully registered with SAS Test Harness, with cbsdId=C</li> <li>• UUT has received a valid grant with grantId = G</li> <li>• UUT is in Grant State AUTHORIZED and is actively transmitting within the bounds of its grant.</li> </ul> Invoke trigger to relinquish UUT Grant from the SAS Test Harness	--	--
2	UUT sends a Relinquishment Request message. Verify message contains all required parameters properly formatted, and specifically: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	SAS Test Harness shall approve the request with a Relinquishment Response message with parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• grantId = G</li> <li>• responseCode = 0</li> </ul>	--	--
4	After completion of step 3, SAS Test Harness will not provide any additional positive response (responseCode=0) to further request messages from the UUT.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall stop RF transmission at any time between triggering the relinquishment and UUT sending the relinquishment request</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 48 of 72

### Test Plots:



Plot 37. Conducted Measurement - RF transmission stops (WINNF.FT.C.RLQ.1) – LTE



Plot 38. Conducted Measurement - RF transmission stops (WINNF.FT.C.RLQ.1) – NR


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 49 of 72

## A20 [WINNF.FT.C.DRG.1] Successful Deregistration

	Test Execution Steps	PASS	FAIL
1	Ensure the following conditions are met for test entry: <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with SAS Test Harness</li> <li>• UUT has successfully registered with SAS Test Harness, with cbsdId=C</li> <li>• UUT has received a valid grant with grantId = G</li> <li>• UUT is in Grant State AUTHORIZED and is actively transmitting within the bounds of its grant.</li> </ul> Invoke trigger to deregister UUT from the SAS Test Harness	--	--
2	UUT sends a Relinquishment request and receives Relinquishment response with responseCode=0	--	--
3	UUT sends Deregistration Request to SAS Test Harness with cbsdId = C.	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	SAS Test Harness shall approve the request with a Deregistration Response message with parameters: <ul style="list-style-type: none"> <li>• cbsdId = C</li> <li>• responseCode = 0</li> </ul>	--	--
5	After completion of step 3, SAS Test Harness will not provide any additional positive response (responseCode=0) to further request messages from the UUT	--	--
6	Monitor the RF output of the UUT from start of test until 60 seconds after Step 4 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT stopped RF transmission at any time between triggering the deregistration and either A OR B occurs:               <ul style="list-style-type: none"> <li>A. UUT sending a Registration Request message, as this is not mandatory</li> <li>B. UUT sending a Deregistration Request message</li> </ul> </li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 50 of 72

**Test Plots:**



**Plot 39. Conducted Measurement - RF transmission stops within 60s. The SAS message is indicated by Marker 1 (X) (WINNF.FT.C.DRG.1) – LTE**



**Plot 40. Conducted Measurement - RF transmission stops within 60s. The SAS message is indicated by Marker 1 (X) (WINNF.FT.C.DRG.1) – NR**


FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point		Page 51 of 72

**A21 [WINNF.FT.C.SCS.1] Successful TLS connection between UUT and SAS Test Harness**


	Test Execution Steps	PASS	FAIL
1	<ul style="list-style-type: none"> <li>• UUT shall start CBSD-SAS communication with the security procedure</li> <li>• The UUT shall establish a TLS handshake with the SAS Test Harness using configured certificate.</li> <li>• Configure the SAS Test Harness to accept the security procedure and establish the connection</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
2	<ul style="list-style-type: none"> <li>• Make sure that Mutual authentication happens between UUT and the SAS Test Harness.</li> <li>• Make sure that UUT uses TLS v1.2</li> <li>• Make sure that cipher suites from one of the following is selected,</li> <li>• TLS_RSA_WITH_AES_128_GCM_SHA256</li> <li>• TLS_RSA_WITH_AES_256_GCM_SHA384</li> <li>• TLS_ECDHE_ECDSA_WITH_AES_128_GCM_SHA256</li> <li>• TLS_ECDHE_ECDSA_WITH_AES_256_GCM_SHA384</li> <li>• TLS_ECDHE_RSA_WITH_AES_128_GCM_SHA256</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	<p>A successful registration is accomplished using one of the test cases described in section 6.1.4.1, depending on CBSD capability.</p> <ul style="list-style-type: none"> <li>• UUT sends a registration request to the SAS Test Harness and the SAS Test Harness sends a Registration Response with responseCode = 0 and cbsdId.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	<p>Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify:</p> <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 52 of 72

**Test Plots:**



**Plot 41. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.1) – LTE**



**Plot 42. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.1) – NR**

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 53 of 72



No.	Time	Source	Destination	Protocol	Length	Info
76	2022-06-23 19:28:58.831021	173.59.230.213	4.71.13.195	TLV1.2	3101	Server Hello, Certificate, Certificate Request, Server Hello Done
77	2022-06-23 19:28:58.881146	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=314 Ack=1441 Win=17144 Len=0
78	2022-06-23 19:28:58.881147	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
79	2022-06-23 19:28:58.881184	4.71.13.195	173.59.230.213	TLV1.2	1494	5224 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
80	2022-06-23 19:28:58.881185	4.71.13.195	173.59.230.213	TLV1.2	1470	Certificate
81	2022-06-23 19:28:58.881186	4.71.13.195	173.59.230.213	TLV1.2	321	Client Key Exchange
82	2022-06-23 19:28:58.881192	4.71.13.195	173.59.230.213	TLV1.2	323	Certificate Verify
83	2022-06-23 19:28:58.881193	4.71.13.195	173.59.230.213	TLV1.2	60	Change Cipher Spec
84	2022-06-23 19:28:58.881194	4.71.13.195	173.59.230.213	TLV1.2	99	Encrypted Handshake Message
85	2022-06-23 19:28:58.881197	173.59.230.213	4.71.13.195	TCP	54	443 → 5224 [ACK] Seq=3048 Ack=3757 Win=263424 Len=0
86	2022-06-23 19:28:58.905885	173.59.230.213	4.71.13.195	TLV1.2	105	Change Cipher Spec, Encrypted Handshake Message
87	2022-06-23 19:28:58.947587	4.71.13.195	173.59.230.213	TCP	1494	5224 → 443 [ACK] Seq=3757 Ack=3099 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
88	2022-06-23 19:28:58.947588	4.71.13.195	173.59.230.213	TLV1.2	1096	Application Data
89	2022-06-23 19:28:58.947589	173.59.230.213	4.71.13.195	TCP	54	443 → 5224 [ACK] Seq=3099 Ack=6239 Win=263424 Len=0
90	2022-06-23 19:28:58.989971	173.59.230.213	4.71.13.195	TLV1.2	100	Application Data
91	2022-06-23 19:28:58.973464	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=6239 Ack=3145 Win=35072 Len=0
92	2022-06-23 19:28:58.073519	173.59.230.213	4.71.13.195	TLV1.2	546	Application Data, Application Data
93	2022-06-23 19:28:58.114762	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=6239 Ack=3637 Win=37888 Len=0
98	2022-06-23 19:29:01.692192	4.71.13.195	173.59.230.213	TCP	74	5364 → 443 [SYN] Seq=0 Win=28800 Len=0 MSS=1440 SACK_PERM=1 TSval=2396696831 TSecr=0 WS=256
99	2022-06-23 19:29:01.692228	173.59.230.213	4.71.13.195	TCP	66	443 → 5364 [SYN, ACK] Seq=0 Ack=1 Win=5535 Len=0 MSS=1460 WS=256 SACK_PERM=1
100	2022-06-23 19:29:01.733358	4.71.13.195	173.59.230.213	TCP	60	5364 → 443 [ACK] Seq=1 Ack=1 Win=28928 Len=0
101	2022-06-23 19:29:01.735660	4.71.13.195	173.59.230.213	TLV1.2	367	Client Hello
102	2022-06-23 19:29:01.735666	173.59.230.213	4.71.13.195	TLV1.2	3101	Server Hello, Certificate, Certificate Request, Server Hello Done
103	2022-06-23 19:29:01.782798	4.71.13.195	173.59.230.213	TCP	60	5364 → 443 [ACK] Seq=314 Ack=2881 Win=34560 Len=0
104	2022-06-23 19:29:01.782798	4.71.13.195	173.59.230.213	TCP	60	5364 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
105	2022-06-23 19:29:01.783491	4.71.13.195	173.59.230.213	TCP	1494	5364 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
106	2022-06-23 19:29:01.783493	4.71.13.195	173.59.230.213	TLV1.2	1470	Certificate
107	2022-06-23 19:29:01.783494	4.71.13.195	173.59.230.213	TLV1.2	321	Client Key Exchange
108	2022-06-23 19:29:01.783592	173.59.230.213	4.71.13.195	TCP	54	443 → 5364 [ACK] Seq=3048 Ack=3457 Win=263424 Len=0
109	2022-06-23 19:29:01.783595	4.71.13.195	173.59.230.213	TLV1.2	323	Certificate Verify
110	2022-06-23 19:29:01.785286	4.71.13.195	173.59.230.213	TLV1.2	60	Change Cipher Spec
111	2022-06-23 19:29:01.785282	173.59.230.213	4.71.13.195	TCP	54	443 → 5364 [ACK] Seq=3048 Ack=3712 Win=263168 Len=0
112	2022-06-23 19:29:01.785460	4.71.13.195	173.59.230.213	TLV1.2	99	Encrypted Handshake Message
113	2022-06-23 19:29:01.785462	173.59.230.213	4.71.13.195	TCP	54	443 → 5364 [ACK] Seq=3048 Ack=3757 Win=263168 Len=0
114	2022-06-23 19:29:01.804111	173.59.230.213	4.71.13.195	TLV1.2	105	Change Cipher Spec, Encrypted Handshake Message
115	2022-06-23 19:29:01.852408	4.71.13.195	173.59.230.213	TCP	1494	5364 → 443 [ACK] Seq=3757 Ack=3099 Win=37632 Len=1440 [TCP segment of a reassembled PDU]
116	2022-06-23 19:29:01.852499	4.71.13.195	173.59.230.213	TCP	1494	5364 → 443 [ACK] Seq=5197 Ack=3099 Win=37632 Len=1440 [TCP segment of a reassembled PDU]
117	2022-06-23 19:29:01.852590	4.71.13.195	173.59.230.213	TCP	1494	5364 → 443 [ACK] Seq=6637 Ack=3099 Win=37632 Len=1440 [TCP segment of a reassembled PDU]
118	2022-06-23 19:29:01.852595	4.71.13.195	173.59.230.213	TLV1.2	60	Application Data
119	2022-06-23 19:29:01.852596	173.59.230.213	4.71.13.195	TCP	54	443 → 5364 [ACK] Seq=3099 Ack=8888 Win=263424 Len=0
120	2022-06-23 19:29:01.856370	173.59.230.213	4.71.13.195	TLV1.2	100	Application Data
121	2022-06-23 19:29:01.939955	4.71.13.195	173.59.230.213	TCP	60	5364 → 443 [ACK] Seq=8888 Ack=3145 Win=37632 Len=0
122	2022-06-23 19:29:01.940001	173.59.230.213	4.71.13.195	TLV1.2	804	Application Data, Application Data
123	2022-06-23 19:29:01.989117	4.71.13.195	173.59.230.213	TCP	60	5364 → 443 [ACK] Seq=8888 Ack=3895 Win=40448 Len=0

### Plot 43. WireShark Screenshot – Successful Handshake (WINNF.FT.C.SCS.1) – LTE

No.	Time	Source	Destination	Protocol	Length	Info
543	2022-06-22 20:11:15.990488	4.71.13.195	173.59.230.213	TCP	74	8791 → 443 [SYN] Seq=0 Win=28800 Len=0 MSS=1440 SACK_PERM=1 TSval=2312832858 TSecr=0 WS=256
544	2022-06-22 20:11:15.990726	173.59.230.213	4.71.13.195	TCP	66	443 → 8791 [SYN, ACK] Seq=0 Ack=1 Win=5535 Len=0 MSS=1460 WS=256 SACK_PERM=1
545	2022-06-22 20:11:16.039682	4.71.13.195	173.59.230.213	TCP	60	8791 → 443 [ACK] Seq=1 Ack=1 Win=28928 Len=0
546	2022-06-22 20:11:16.042418	4.71.13.195	173.59.230.213	TLV1.2	367	Client Hello
547	2022-06-22 20:11:16.042822	173.59.230.213	4.71.13.195	TLV1.2	3101	Server Hello, Certificate, Certificate Request, Server Hello Done
548	2022-06-22 20:11:16.089122	4.71.13.195	173.59.230.213	TCP	60	8791 → 443 [ACK] Seq=314 Ack=1441 Win=31744 Len=0
549	2022-06-22 20:11:16.089123	4.71.13.195	173.59.230.213	TCP	60	8791 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
550	2022-06-22 20:11:16.090398	4.71.13.195	173.59.230.213	TCP	1494	8791 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
551	2022-06-22 20:11:16.090399	4.71.13.195	173.59.230.213	TLV1.2	1470	Certificate
552	2022-06-22 20:11:16.090401	4.71.13.195	173.59.230.213	TLV1.2	321	Client Key Exchange
553	2022-06-22 20:11:16.090486	173.59.230.213	4.71.13.195	TCP	54	443 → 8791 [ACK] Seq=3048 Ack=3437 Win=263424 Len=0
554	2022-06-22 20:11:16.092975	4.71.13.195	173.59.230.213	TLV1.2	323	Certificate Verify
555	2022-06-22 20:11:16.093048	173.59.230.213	4.71.13.195	TCP	54	443 → 8791 [ACK] Seq=3048 Ack=3786 Win=263168 Len=0
556	2022-06-22 20:11:16.093114	4.71.13.195	173.59.230.213	TLV1.2	60	Change Cipher Spec
557	2022-06-22 20:11:16.093115	4.71.13.195	173.59.230.213	TLV1.2	99	Encrypted Handshake Message
558	2022-06-22 20:11:16.093156	173.59.230.213	4.71.13.195	TCP	54	443 → 8791 [ACK] Seq=3048 Ack=3757 Win=263168 Len=0
559	2022-06-22 20:11:16.124083	173.59.230.213	4.71.13.195	TLV1.2	105	Change Cipher Spec, Encrypted Handshake Message
560	2022-06-22 20:11:16.169707	4.71.13.195	173.59.230.213	TCP	1494	8791 → 443 [ACK] Seq=3757 Ack=3099 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
561	2022-06-22 20:11:16.169708	4.71.13.195	173.59.230.213	TLV1.2	1092	Application Data
562	2022-06-22 20:11:16.169752	173.59.230.213	4.71.13.195	TCP	54	443 → 8791 [ACK] Seq=3099 Ack=6235 Win=263424 Len=0
563	2022-06-22 20:11:16.198686	173.59.230.213	4.71.13.195	TLV1.2	100	Application Data
564	2022-06-22 20:11:16.482239	4.71.13.195	173.59.230.213	TCP	60	8791 → 443 [ACK] Seq=6235 Ack=3145 Win=35072 Len=0
565	2022-06-22 20:11:16.482281	173.59.230.213	4.71.13.195	TLV1.2	546	Application Data, Application Data
566	2022-06-22 20:11:16.522029	4.71.13.195	173.59.230.213	TCP	60	8791 → 443 [ACK] Seq=6235 Ack=3637 Win=37888 Len=0
570	2022-06-22 20:11:19.096576	4.71.13.195	173.59.230.213	TCP	74	8753 → 443 [SYN] Seq=0 Win=28800 Len=0 MSS=1440 SACK_PERM=1 TSval=2312835962 TSecr=0 WS=256
571	2022-06-22 20:11:19.096756	173.59.230.213	4.71.13.195	TCP	66	443 → 8753 [SYN, ACK] Seq=0 Ack=1 Win=5535 Len=0 MSS=1460 WS=256 SACK_PERM=1
572	2022-06-22 20:11:19.143275	4.71.13.195	173.59.230.213	TCP	60	8753 → 443 [ACK] Seq=1 Ack=1 Win=28928 Len=0
573	2022-06-22 20:11:19.146187	4.71.13.195	173.59.230.213	TLV1.2	367	Client Hello
574	2022-06-22 20:11:19.146439	173.59.230.213	4.71.13.195	TLV1.2	3101	Server Hello, Certificate, Certificate Request, Server Hello Done
575	2022-06-22 20:11:19.193082	4.71.13.195	173.59.230.213	TCP	60	8753 → 443 [ACK] Seq=314 Ack=1441 Win=31744 Len=0
576	2022-06-22 20:11:19.193084	4.71.13.195	173.59.230.213	TCP	60	8753 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
577	2022-06-22 20:11:19.193939	4.71.13.195	173.59.230.213	TCP	1494	8753 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
578	2022-06-22 20:11:19.193944	4.71.13.195	173.59.230.213	TLV1.2	1470	Certificate
579	2022-06-22 20:11:19.193945	4.71.13.195	173.59.230.213	TLV1.2	321	Client Key Exchange
580	2022-06-22 20:11:19.194026	173.59.230.213	4.71.13.195	TCP	54	443 → 8753 [ACK] Seq=3048 Ack=3437 Win=263424 Len=0
581	2022-06-22 20:11:19.195942	4.71.13.195	173.59.230.213	TLV1.2	323	Certificate Verify
582	2022-06-22 20:11:19.195996	173.59.230.213	4.71.13.195	TCP	54	443 → 8753 [ACK] Seq=3048 Ack=3786 Win=263168 Len=0
583	2022-06-22 20:11:19.196034	4.71.13.195	173.59.230.213	TLV1.2	60	Change Cipher Spec
584	2022-06-22 20:11:19.196394	4.71.13.195	173.59.230.213	TLV1.2	99	Encrypted Handshake Message
585	2022-06-22 20:11:19.196400	173.59.230.213	4.71.13.195	TCP	54	443 → 8753 [ACK] Seq=3048 Ack=3757 Win=263168 Len=0
586	2022-06-22 20:11:19.202774	173.59.230.213	4.71.13.195	TLV1.2	105	Change Cipher Spec, Encrypted Handshake Message
588	2022-06-22 20:11:19.254331	4.71.13.195	173.59.230.213	TCP	1494	8753 → 443 [ACK] Seq=3757 Ack=3099 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
589	2022-06-22 20:11:19.254332	4.71.13.195	173.59.230.213	TCP	1494	8753 → 443 [ACK] Seq=5197 Ack=3099 Win=35072 Len=1440 [TCP segment of a reassembled PDU]
590	2022-06-22 20:11:19.254333	4.71.13.195	173.59.230.213	TCP	1494	8753 → 443 [ACK] Seq=6637 Ack=3099 Win=35072 Len=1440 [TCP segment of a reassembled PDU]


### Plot 44. WireShark Screenshot – Successful Handshake (WINNF.FT.C.SCS.1) – NR

FCC ID: A3LR2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by:
			Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 54 of 72

## A22 [WINNF.FT.C.SCS.2] TLS failure due to revoked certificate


	Test Execution Steps	PASS	FAIL
1	<ul style="list-style-type: none"> <li>UUT shall start CBSD-SAS communication with the security procedure</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
2	<ul style="list-style-type: none"> <li>Make sure that UUT uses TLS v1.2 for security establishment.</li> <li>Make sure UUT selects the correct cipher suite.</li> <li>UUT shall use CRL or OCSP to verify the validity of the server certificate.</li> <li>Make sure that Mutual authentication does not happen between UUT and the SAS Test Harness</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	UUT may retry for the security procedure which shall fail	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	SAS Test-Harness shall not receive any Registration request or any application data.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



Plot 45. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.2) – LTE

FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 55 of 72	



**Plot 46. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.2) – NR**

No.	Time	Source	Destination	Protocol	Length	Info
44	2022-06-23 19:31:44.695761	4.71.13.195	173.59.230.213	TCP	74	5224 → 443 [SYN] Seq=0 Win=2880 Len=0 MSS=1448 SACK_PERM=1 TSval=239659743 TSecr=0 WS=256
45	2022-06-23 19:31:44.696812	173.59.230.213	4.71.13.195	TCP	66	443 → 5224 [SYN, ACK] Seq=0 Ack=1 Min=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
46	2022-06-23 19:31:44.657282	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=1 Ack=1 Min=28928 Len=0
47	2022-06-23 19:31:44.657621	4.71.13.195	173.59.230.213	TLSv1.2	367	Client Hello
48	2022-06-23 19:31:44.658598	173.59.230.213	4.71.13.195	TLSv1.2	329	Server Hello, Certificate, Certificate Request, Server Hello Done
49	2022-06-23 19:31:44.704838	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=314 Ack=1441 Min=31744 Len=0
50	2022-06-23 19:31:44.704839	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [ACK] Seq=314 Ack=3176 Min=35328 Len=0
51	2022-06-23 19:31:44.718361	4.71.13.195	173.59.230.213	TLSv1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
52	2022-06-23 19:31:44.718362	4.71.13.195	173.59.230.213	TCP	60	5224 → 443 [RST, ACK] Seq=321 Ack=3176 Min=35328 Len=0

**Plot 47. WireShark Screenshot - Failed Handshake (WINNF.FT.C.SCS.2) – LTE**

No.	Time	Source	Destination	Protocol	Length	Info
9	2022-06-22 20:16:16.209838	4.71.13.195	173.59.230.213	TCP	74	8934 → 443 [SYN] Seq=0 Win=2880 Len=0 MSS=1448 SACK_PERM=1 TSval=23133858 TSecr=0 WS=256
10	2022-06-22 20:16:16.204846	173.59.230.213	4.71.13.195	TCP	66	443 → 8934 [SYN, ACK] Seq=0 Ack=1 Min=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
11	2022-06-22 20:16:16.244181	4.71.13.195	173.59.230.213	TCP	60	8934 → 443 [ACK] Seq=1 Ack=1 Min=28928 Len=0
12	2022-06-22 20:16:16.247256	4.71.13.195	173.59.230.213	TLSv1.2	367	Client Hello
13	2022-06-22 20:16:16.247623	173.59.230.213	4.71.13.195	TLSv1.2	329	Server Hello, Certificate, Certificate Request, Server Hello Done
14	2022-06-22 20:16:16.294386	4.71.13.195	173.59.230.213	TCP	60	8934 → 443 [ACK] Seq=314 Ack=1441 Min=31744 Len=0
15	2022-06-22 20:16:16.294387	4.71.13.195	173.59.230.213	TCP	60	8934 → 443 [ACK] Seq=314 Ack=3176 Min=35328 Len=0
16	2022-06-22 20:16:16.309344	4.71.13.195	173.59.230.213	TLSv1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
17	2022-06-22 20:16:16.309345	4.71.13.195	173.59.230.213	TCP	60	8934 → 443 [RST, ACK] Seq=321 Ack=3176 Min=35328 Len=0


**Plot 48. WireShark Screenshot - Failed Handshake (WINNF.FT.C.SCS.2) – NR**

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 56 of 72

### A23 [WINNF.FT.C.SCS.3] TLS failure due to expired server certificate


	Test Execution Steps	PASS	FAIL
1	• UUT shall start CBSD-SAS communication with the security procedure	<input checked="" type="checkbox"/>	<input type="checkbox"/>
2	<ul style="list-style-type: none"> <li>• Make sure that UUT uses TLS v1.2 for security establishment.</li> <li>• Make sure UUT selects the correct cipher suite.</li> <li>• UUT shall use CRL or OCSP to verify the validity of the server certificate.</li> <li>• Make sure that Mutual authentication does not happen between UUT and the SAS Test Harness.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	UUT may retry for the security procedure which shall fail	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	SAS Test-Harness shall not receive any Registration request or any application data.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



Plot 49. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.3) – LTE

FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 57 of 72	



**Plot 50. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.3) – NR**

No.	Time	Source	Destination	Protocol	Length	Info
31	2022-06-23 19:33:30.356406	4.71.13.195	173.59.230.213	TCP	74	5400 → 443 [SYN] Seq=0 Win=2896 Len=0 MSS=1440 SACK_PERM=1 TSval=239695408 TSecr=0 WS=256
32	2022-06-23 19:33:30.356636	173.59.230.213	4.71.13.195	TCP	66	443 → 5400 [SYN, ACK] Seq=0 Ack=1 Win=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
33	2022-06-23 19:33:30.397895	4.71.13.195	173.59.230.213	TCP	60	5400 → 443 [ACK] Seq=1 Ack=1 Min=28928 Len=0
34	2022-06-23 19:33:30.408393	4.71.13.195	173.59.230.213	TLSv1.2	367	Client Hello
35	2022-06-23 19:33:30.408784	173.59.230.213	4.71.13.195	TLSv1.2	3119	Server Hello, Certificate, Certificate Request, Server Hello Done
36	2022-06-23 19:33:30.457591	4.71.13.195	173.59.230.213	TCP	60	5400 → 443 [ACK] Seq=314 Ack=1441 Win=31744 Len=0
37	2022-06-23 19:33:30.457592	4.71.13.195	173.59.230.213	TCP	60	5400 → 443 [ACK] Seq=314 Ack=3066 Win=35872 Len=0
38	2022-06-23 19:33:30.458636	4.71.13.195	173.59.230.213	TLSv1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
39	2022-06-23 19:33:30.458637	4.71.13.195	173.59.230.213	TCP	60	5400 → 443 [RST, ACK] Seq=321 Ack=3066 Win=35872 Len=0

**Plot 51. WireShark Screenshot - Failed Handshake (WINNF.FT.C.SCS.3) – LTE**

No.	Time	Source	Destination	Protocol	Length	Info
139	2022-06-22 20:18:47.079276	4.71.13.195	173.59.230.213	TCP	74	8834 → 443 [SYN] Seq=0 Win=2896 Len=0 MSS=1440 SACK_PERM=1 TSval=231328936 TSecr=0 WS=256
140	2022-06-22 20:18:47.079584	173.59.230.213	4.71.13.195	TCP	66	443 → 8834 [SYN, ACK] Seq=0 Ack=1 Win=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
141	2022-06-22 20:18:47.124367	4.71.13.195	173.59.230.213	TCP	60	8834 → 443 [ACK] Seq=1 Ack=1 Min=28928 Len=0
142	2022-06-22 20:18:47.134225	4.71.13.195	173.59.230.213	TLSv1.2	367	Client Hello
143	2022-06-22 20:18:47.134668	173.59.230.213	4.71.13.195	TLSv1.2	3119	Server Hello, Certificate, Certificate Request, Server Hello Done
144	2022-06-22 20:18:47.184329	4.71.13.195	173.59.230.213	TCP	60	8834 → 443 [ACK] Seq=314 Ack=2081 Win=34560 Len=0
145	2022-06-22 20:18:47.184330	4.71.13.195	173.59.230.213	TCP	60	8834 → 443 [ACK] Seq=314 Ack=3066 Win=37632 Len=0
146	2022-06-22 20:18:47.185767	4.71.13.195	173.59.230.213	TLSv1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
147	2022-06-22 20:18:47.185768	4.71.13.195	173.59.230.213	TCP	60	8834 → 443 [RST, ACK] Seq=321 Ack=3066 Win=37632 Len=0


**Plot 52. WireShark Screenshot - Failed Handshake (WINNF.FT.C.SCS.3) – NR**

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 58 of 72

## A24 [WINNF.FT.C.SCS.4] TLS failure when SAS Test Harness certificate is issued by an unknown CA


	Test Execution Steps	PASS	FAIL
1	• UUT shall start CBSD-SAS communication with the security procedure	<input checked="" type="checkbox"/>	<input type="checkbox"/>
2	<ul style="list-style-type: none"> <li>• Make sure that UUT uses TLS v1.2 for security establishment.</li> <li>• Make sure UUT selects the correct cipher suite.</li> <li>• UUT shall use CRL or OCSP to verify the validity of the server certificate.</li> <li>• Make sure that Mutual authentication does not happen between UUT and the SAS Test Harness.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	UUT may retry for the security procedure which shall fail	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	SAS Test-Harness shall not receive any Registration request or any application data.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



Plot 53. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.4) – LTE

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 59 of 72



**Plot 54. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.4) – NR**

No.	Time	Source	Destination	Protocol	Length	Info
61	2022-06-23 19:35:11.883999	4.71.13.195	173.59.230.213	TCP	74	5227 → 443 [SYN] Seq=0 Win=28800 Len=0 MSS=1440 SACK_PERM=1 TSval=2397667014 TSecr=0 WS=256
62	2022-06-23 19:35:11.884056	173.59.230.213	4.71.13.195	TCP	60	443 → 5227 [SYN, ACK] Seq=0 Ack=1 Min=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
63	2022-06-23 19:35:11.920796	4.71.13.195	173.59.230.213	TCP	60	5227 → 443 [ACK] Seq=1 Ack=1 Min=28928 Len=0
64	2022-06-23 19:35:11.931584	4.71.13.195	173.59.230.213	TLV1.2	367	Client Hello
65	2022-06-23 19:35:11.931941	173.59.230.213	4.71.13.195	TLV1.2	3119	Server Hello, Certificate, Certificate Request, Server Hello Done
66	2022-06-23 19:35:11.978047	4.71.13.195	173.59.230.213	TCP	60	5227 → 443 [ACK] Seq=314 Ack=1441 Min=31744 Len=0
67	2022-06-23 19:35:11.978048	4.71.13.195	173.59.230.213	TCP	60	5227 → 443 [ACK] Seq=314 Ack=3066 Min=35072 Len=0
68	2022-06-23 19:35:11.978387	4.71.13.195	173.59.230.213	TLV1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
69	2022-06-23 19:35:11.978388	4.71.13.195	173.59.230.213	TCP	60	5227 → 443 [RST, ACK] Seq=321 Ack=3066 Min=35072 Len=0

**Plot 55. WireShark Screenshot – Failed Handshake (WINNF.FT.C.SCS.4) – LTE**

No.	Time	Source	Destination	Protocol	Length	Info
21	2022-06-22 20:20:22.796313	4.71.13.195	173.59.230.213	TCP	74	6929 → 443 [SYN] Seq=0 Win=28800 Len=0 MSS=1440 SACK_PERM=1 TSval=233379657 TSecr=0 WS=256
22	2022-06-22 20:20:22.796569	173.59.230.213	4.71.13.195	TCP	66	443 → 6929 [SYN, ACK] Seq=0 Ack=1 Min=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
23	2022-06-22 20:20:22.843595	4.71.13.195	173.59.230.213	TCP	60	6929 → 443 [ACK] Seq=1 Ack=1 Min=28928 Len=0
24	2022-06-22 20:20:22.846365	4.71.13.195	173.59.230.213	TLV1.2	367	Client Hello
25	2022-06-22 20:20:22.846782	173.59.230.213	4.71.13.195	TLV1.2	3121	Server Hello, Certificate, Certificate Request, Server Hello Done
27	2022-06-22 20:20:22.893502	4.71.13.195	173.59.230.213	TCP	60	6929 → 443 [ACK] Seq=314 Ack=1441 Min=31744 Len=0
28	2022-06-22 20:20:22.893503	4.71.13.195	173.59.230.213	TCP	60	6929 → 443 [ACK] Seq=314 Ack=3068 Min=35072 Len=0
29	2022-06-22 20:20:22.893720	4.71.13.195	173.59.230.213	TLV1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
30	2022-06-22 20:20:22.893722	4.71.13.195	173.59.230.213	TCP	60	6929 → 443 [RST, ACK] Seq=321 Ack=3068 Min=35072 Len=0


**Plot 56. WireShark Screenshot – Failed Handshake (WINNF.FT.C.SCS.4) – NR**

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 60 of 72

## A25 [WINNF.FT.C.SCS.5] TLS failure when certificate at the SAS Test Harness is corrupted


	Test Execution Steps	PASS	FAIL
1	• UUT shall start CBSD-SAS communication with the security procedure	<input checked="" type="checkbox"/>	<input type="checkbox"/>
2	<ul style="list-style-type: none"> <li>• Make sure that UUT uses TLS v1.2 for security establishment.</li> <li>• Make sure UUT selects the correct cipher suite.</li> <li>• UUT shall use CRL or OCSP to verify the validity of the server certificate.</li> <li>• Make sure that Mutual authentication does not happen between UUT and the SAS Test Harness.</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
3	UUT may retry for the security procedure which shall fail	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4	SAS Test-Harness shall not receive any Registration request or any application data.	--	--
5	Monitor the RF output of the UUT from start of test until 60 seconds after Step 3 is complete. This is the end of the test. Verify: <ul style="list-style-type: none"> <li>• UUT shall not transmit RF</li> </ul>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

### Test Plots:



Plot 57. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.5) – LTE

FCC ID: A3LRT2203-48A		MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 61 of 72	



**Plot 58. Conducted Measurement – No RF transmission in entire band at anytime (WINNF.FT.C.SCS.5) – NR**

40	2022-06-23 19:36:57.216741	4.71.13.195	173.59.230.213	TCP	74	5383 → 443 [SYN] Seq=0 Win=28960 Len=0 MSS=1440 SACK_PERM=1 TSval=2297122341 TSecr=0 WS=256
41	2022-06-23 19:36:57.216836	173.59.230.213	4.71.13.195	TCP	66	443 → 5383 [SYN, ACK] Seq=0 Ack=1 Win=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
42	2022-06-23 19:36:57.263192	4.71.13.195	173.59.230.213	TCP	60	5383 → 443 [ACK] Seq=1 Ack=1 Win=28928 Len=0
43	2022-06-23 19:36:57.266828	4.71.13.195	173.59.230.213	TLSv1.2	367	Client Hello
44	2022-06-23 19:36:57.266186	173.59.230.213	4.71.13.195	TLSv1.2	3121	Server Hello, Certificate, Certificate Request, Server Hello Done
45	2022-06-23 19:36:57.313871	4.71.13.195	173.59.230.213	TCP	60	5383 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
46	2022-06-23 19:36:57.314337	4.71.13.195	173.59.230.213	TLSv1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
47	2022-06-23 19:36:57.314337	4.71.13.195	173.59.230.213	TCP	60	5383 → 443 [RST, ACK] Seq=321 Ack=3068 Win=35072 Len=0

**Plot 59. WireShark Screenshot - Failed Handshake (WINNF.FT.C.SCS.5) – LTE**

No.	Time	Source	Destination	Protocol	Length	Info
14	2022-06-22 20:25:04.855616	4.71.13.195	173.59.230.213	TCP	74	6986 → 443 [SYN] Seq=0 Win=28960 Len=0 MSS=1440 SACK_PERM=1 TSval=2313661717 TSecr=0 WS=256
15	2022-06-22 20:25:04.855873	173.59.230.213	4.71.13.195	TCP	66	443 → 6986 [SYN, ACK] Seq=0 Ack=1 Win=65535 Len=0 MSS=1460 WS=256 SACK_PERM=1
16	2022-06-22 20:25:04.899310	4.71.13.195	173.59.230.213	TCP	60	6986 → 443 [ACK] Seq=1 Ack=1 Win=28928 Len=0
17	2022-06-22 20:25:04.899385	4.71.13.195	173.59.230.213	TLSv1.2	367	Client Hello
18	2022-06-22 20:25:04.899861	173.59.230.213	4.71.13.195	TLSv1.2	3181	Server Hello, Certificate, Certificate Request, Server Hello Done
19	2022-06-22 20:25:04.946495	4.71.13.195	173.59.230.213	TCP	60	6986 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
20	2022-06-22 20:25:04.946495	4.71.13.195	173.59.230.213	TCP	60	6986 → 443 [ACK] Seq=314 Ack=3048 Win=35072 Len=0
21	2022-06-22 20:25:04.948780	4.71.13.195	173.59.230.213	TLSv1.2	61	Alert (Level: Fatal, Description: Certificate Unknown)
22	2022-06-22 20:25:04.948781	4.71.13.195	173.59.230.213	TCP	60	6986 → 443 [RST, ACK] Seq=321 Ack=3048 Win=35072 Len=0

**Plot 60. WireShark Screenshot - Failed Handshake (WINNF.FT.C.SCS.5) – NR**

FCC ID: A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 62 of 72

## A26 [WINNF.PT.C.HBT] UUT RF Transmit Power Measurement

	Test Execution Steps	PASS	FAIL
1	<p>Ensure the following conditions are met for test entry:</p> <ul style="list-style-type: none"> <li>• UUT has successfully completed SAS Discovery and Authentication with the SAS Test Harness</li> <li>• UUT has registered with the SAS, with CBSID ID = C</li> <li>• UUT has a single valid grant G with parameters {lowFrequency = FL, highFrequency = FH, maxEirp = Pi}, with grant in AUTHORIZED state, and grantExpireTime set to a value far past the duration of this test case</li> </ul> <p><i>Note: in order for the UUT to request a grant with the parameters {lowFrequency, highFrequency, maxEirp}, the SAS Test Harness may need to provide appropriate guidance in the availableChannel object of the spectrumInquiry response message, and the operationParam object of the grant response message. Alternately, the UUT vendor may provide the ability to set those parameters on the UUT so that the UUT will request a grant with those parameters.</i></p>	--	--
2	<p>UUT and SAS Test Harness perform a series of Heartbeat Request/Response cycles, which continues until the other test steps are complete. Messaging for each cycle is as follows:</p> <ul style="list-style-type: none"> <li>• UUT sends Heartbeat Request, including: <ul style="list-style-type: none"> <li>o cbsdId = C</li> <li>o grantId = G</li> </ul> </li> <li>• SAS Test Harness responds with Heartbeat Response, including: <ul style="list-style-type: none"> <li>o cbsdId = C</li> <li>o grantId = G</li> <li>o transmitExpireTime = current UTC time + 200 seconds</li> <li>o responseCode = 0</li> </ul> </li> </ul>	--	--
3	<p>Tester performs power measurement on RF interface(s) of UUT, and verifies it complies with the maxEirp setting, Pi. The RF measurement method is out of scope of this document, but may include additional configuration of the UUT, as required, to fulfil the requirements of the power measurement method.</p> <p><i>Note: it may be required for the vendor to provide a method or configuration to bring the UUT to a mode which is required by the measurement methodology. Any such mode is vendor-specific and depends upon UUT behavior and the measurement methodology.</i></p>	<input checked="" type="checkbox"/>	<input type="checkbox"/>

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 63 of 72



## RF Power Measurements:

Testing is performed per KDB 971168 D01 and across the transmit dynamic range of 20dBm/MHz to 3dBm/MHz for 20MHz Bandwidth. Per the manufacturer, Tx1 and Tx2 produce correlated signals per KDB 662911 D01. The PSD of each transmitter was measured and summed in linear terms and then the directional antenna gain was added to yield the max EIRP.

Freq [MHz]	SAS Granted maxEIRP [dBm/MHz]	Tx1 Conducted PSD [dBm/MHz]	Tx2 Conducted PSD [dBm/MHz]	Summed Conducted PSD [dBm/MHz]	Dir.Ant Gain [dBi]	maxEIRP [dBm/MHz]	Margin [dB]
3560	20	8.10	7.69	10.91	8.5	19.41	-0.59
3560	10	-1.74	-1.51	1.38	8.5	9.88	-0.12
3560	3	-8.14	-9.04	-5.56	8.5	2.94	-0.06

Table 7-1 RF Output Power Measurements (WINNF.PT.C.HBT.1 – LTE)

Freq [MHz]	SAS Granted maxEIRP [dBm/MHz]	Tx1 Conducted PSD [dBm/MHz]	Tx2 Conducted PSD [dBm/MHz]	Summed Conducted PSD [dBm/MHz]	Dir.Ant Gain [dBi]	maxEIRP [dBm/MHz]	Margin [dB]
3560	20	8.31	7.95	11.14	8.5	19.64	-0.36
3560	10	-1.81	-1.86	1.18	8.5	9.68	-0.32
3560	3	-8.55	-9.04	-5.78	8.5	2.72	-0.28

Table 7-1 RF Output Power Measurements (WINNF.PT.C.HBT.1 – NR)

Directional Gain Calculation:

Ant1 gain = Ant2 gain = 5.5dBi


Correlated Directional Gain =  $10 \cdot \log(((\text{Ant1} + \text{Ant2})^n)/n) = 10 \cdot \log(((5.5+5.5)^2)/2) = 8.5 \text{ dBi}$

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 64 of 72


V1.0

Unless otherwise specified, no part of this report may be reproduced or utilized in any part, form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from Element. If you have any questions about this or have an enquiry about obtaining additional rights to this report or assembly of contents thereof, please contact [ct.info@element.com](mailto:ct.info@element.com).

**Test Plots:**




**Plot 61. Conducted PSD, 3.56GHz, 20MHz BW – ANT1, SAS Granted maxEIRP 20dBm/MHz (LTE)**




**Plot 62. Conducted PSD, 3.56GHz, 20MHz BW – ANT2, SAS Granted maxEIRP 20dBm/MHz (LTE)**

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 65 of 72




Plot 63. Conducted PSD, 3.56GHz, 20MHz BW – ANT1, SAS Granted maxEIRP 10dBm/MHz (LTE)




Plot 64. Conducted PSD, 3.56GHz, 20MHz BW – ANT2, SAS Granted maxEIRP 10dBm/MHz (LTE)

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 66 of 72




Plot 65. Conducted PSD, 3.56GHz, 20MHz BW – ANT1, SAS Granted maxEIRP 3dBm/MHz (LTE)




Plot 66. Conducted PSD, 3.56GHz, 20MHz BW – ANT2, SAS Granted maxEIRP 3dBm/MHz (LTE)

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 67 of 72




Plot 67. Conducted PSD, 3.56GHz, 20MHz BW – ANT1, SAS Granted maxEIRP 20dBm/MHz (NR)




Plot 68. Conducted PSD, 3.56GHz, 20MHz BW – ANT2, SAS Granted maxEIRP 20dBm/MHz (NR)

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 68 of 72




Plot 69. Conducted PSD, 3.56GHz, 20MHz BW – ANT1, SAS Granted maxEIRP 10dBm/MHz (NR)




Plot 70. Conducted PSD, 3.56GHz, 20MHz BW – ANT2, SAS Granted maxEIRP 10dBm/MHz (NR)

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 69 of 72



Plot 71. Conducted PSD, 3.56GHz, 20MHz BW – ANT1, SAS Granted maxEIRP 3dBm/MHz (NR)



Plot 72. Conducted PSD, 3.56GHz, 20MHz BW – ANT2, SAS Granted maxEIRP 3dBm/MHz (NR)

FCC ID: A3LRT2203-48A	MEASUREMENT REPORT (CERTIFICATION)		Approved by: Technical Manager
Test Report S/N: 1M2205100060-01.A3L	Test Dates: 6/22/2022 – 7/22/2022	EUT Type: Cat. B LTE/NR Access Point	Page 70 of 72


## APPENDIX B – TEST LOGS

Logs are available upon request

-  PowerMeasTest\_2022-07-07T02.05.06Z
-  PowerMeasTest\_2022-07-07T02.33.01Z
-  PowerMeasTest\_2022-07-07T02.44.47Z
-  WINNF.FT.C.DRG.1\_2022-07-07T01.48.34Z
-  WINNF.FT.C.GRA.1\_2022-07-06T00.42.50Z
-  WINNF.FT.C.GRA.2\_2022-07-06T00.44.48Z
-  WINNF.FT.C.HBT.1\_2022-07-07T00.58.37Z
-  WINNF.FT.C.HBT.3\_2022-07-07T01.04.43Z
-  WINNF.FT.C.HBT.4\_2022-07-15T04.52.38Z
-  WINNF.FT.C.HBT.5\_2022-07-07T01.10.24Z
-  WINNF.FT.C.HBT.6\_2022-07-07T01.13.02Z
-  WINNF.FT.C.HBT.7\_2022-07-07T01.19.33Z
-  WINNF.FT.C.HBT.9\_2022-07-07T01.25.09Z
-  WINNF.FT.C.HBT.10\_2022-07-07T01.30.48Z
-  WINNF.FT.C.MES.1\_2022-07-07T01.39.01Z
-  WINNF.FT.C.REG.1\_2022-06-23T19.27.55Z
-  WINNF.FT.C.REG.8\_2022-06-23T19.51.12Z
-  WINNF.FT.C.REG.10\_2022-06-23T19.52.21Z
-  WINNF.FT.C.REG.12\_2022-06-23T19.53.06Z
-  WINNF.FT.C.REG.14\_2022-06-23T19.53.50Z
-  WINNF.FT.C.REG.16\_2022-06-23T19.54.26Z
-  WINNF.FT.C.REG.18\_2022-06-23T19.55.13Z
-  WINNF.FT.C.RLQ.1\_2022-07-07T01.40.46Z
-  PowerMeasTest\_2022-07-07T03.24.10Z
-  PowerMeasTest\_2022-07-07T03.30.58Z
-  PowerMeasTest\_2022-07-07T03.34.43Z
-  WINNF.FT.C.DRG.1\_2022-06-23T03.04.24Z
-  WINNF.FT.C.GRA.1\_2022-06-22T20.40.00Z
-  WINNF.FT.C.GRA.2\_2022-06-22T20.51.23Z
-  WINNF.FT.C.HBT.1\_2022-06-22T22.44.25Z
-  WINNF.FT.C.HBT.3\_2022-06-22T23.34.40Z
-  WINNF.FT.C.HBT.4\_2022-06-22T23.42.15Z
-  WINNF.FT.C.HBT.5\_2022-06-22T23.52.23Z
-  WINNF.FT.C.HBT.6\_2022-06-23T00.09.19Z
-  WINNF.FT.C.HBT.7\_2022-07-22T20.05.22Z
-  WINNF.FT.C.HBT.9\_2022-06-23T02.02.24Z
-  WINNF.FT.C.HBT.10\_2022-06-23T02.16.35Z
-  WINNF.FT.C.MES.1\_2022-06-23T02.48.05Z
-  WINNF.FT.C.REG.1\_2022-06-22T20.10.54Z
-  WINNF.FT.C.REG.8\_2022-06-22T20.26.34Z
-  WINNF.FT.C.REG.10\_2022-06-22T20.28.29Z
-  WINNF.FT.C.REG.12\_2022-06-22T20.29.23Z
-  WINNF.FT.C.REG.14\_2022-06-22T20.30.21Z
-  WINNF.FT.C.REG.16\_2022-06-22T20.34.19Z
-  WINNF.FT.C.REG.18\_2022-06-22T20.35.54Z
-  WINNF.FT.C.RLQ.1\_2022-06-23T02.55.28Z

<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 71 of 72

## APPENDIX C – TEST SETUP



<b>FCC ID:</b> A3LRT2203-48A	<b>MEASUREMENT REPORT (CERTIFICATION)</b>		<b>Approved by:</b> Technical Manager
<b>Test Report S/N:</b> 1M2205100060-01.A3L	<b>Test Dates:</b> 6/22/2022 – 7/22/2022	<b>EUT Type:</b> Cat. B LTE/NR Access Point	Page 72 of 72