



## PART 0 SAR CHAR REPORT

**Applicant Name:**

Samsung Electronics Co., Ltd.  
129, Samsung-ro, Maetan dong,  
Yeongtong-gu, Suwon-si  
Gyeonggi-do, 16677, Korea

**Date of Testing:**

06/07/23 - 07/27/23

**Test Site/Location:**

Element, Columbia, MD, USA

**Document Serial No.:**

1M2304260060-02.A3L (Rev1)

**FCC ID:**

**A3LSMS711U**

**APPLICANT:**

**SAMSUNG ELECTRONICS CO., LTD**

**Report Type:**

Part 0 SAR Characterization

**DUT Type:**

Portable Handset

**Model(s):**

SM-S711U, SM-S711U1

Note: This revised Test Report (S/N: 1M2304260060-02.A3L (Rev1)) supersedes and replaces the previously issued test report on the same subject device for the same type of testing as indicated. Please discard or destroy the previously issued test report(s) and dispose of it accordingly.

I attest to the accuracy of data. All measurements reported herein were performed by me or were made under my supervision and are correct to the best of my knowledge and belief. I assume full responsibility for the completeness of these measurements and vouch for the qualifications of all persons taking them.

Test results reported herein relate only to the item(s) tested.



RJ Ortanez  
Executive Vice President



<b>FCC ID:</b> A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	<b>Approved by:</b> Technical Manager
<b>Document S/N:</b> 1M2304260060-02.A3L (Rev1)	<b>DUT Type:</b> Portable Handset	Page 1 of 11

## TABLE OF CONTENTS

1	DEVICE UNDER TEST	3
1.1	Device Overview	3
1.2	Time-Averaging for SAR and Power Density	4
1.3	Nomenclature for Part 0 Report	4
1.4	Bibliography	4
2	SAR AND POWER DENSITY MEASUREMENTS	5
2.1	SAR Definition	5
2.2	SAR Measurement Procedure	5
3	SAR CHARACTERIZATION	7
3.1	DSI and SAR Determination	7
3.2	SAR Design Target	7
3.3	SAR Char	8
4	EQUIPMENT LIST	10
5	MEASUREMENT UNCERTAINTIES	11
	APPENDIX A: SAR TEST RESULTS FOR $P_{Limit}$ CALCULATIONS	1

<b>FCC ID:</b> A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	<b>Approved by:</b> Technical Manager
<b>Document S/N:</b> 1M2304260060-02.A3L (Rev1)	<b>DUT Type:</b> Portable Handset	Page 2 of 11

# 1 DEVICE UNDER TEST

## 1.1 Device Overview

This device uses the Qualcomm® Gen2 Smart Transmit feature to control and manage transmitting power in real time and to ensure the time-averaged RF exposure is in compliance with the FCC requirement at all times for 2G/3G/4G/5G WWAN operations. Additionally, this device supports WLAN/BT/NFC/UWB technologies, but the output power of these modems is not controlled by the Smart Transmit algorithm.

Band & Mode	Operating Modes	Tx Frequency
GSM/GPRS/EDGE 850	Voice/Data	824.20 - 848.80 MHz
GSM/GPRS/EDGE 1900	Voice/Data	1850.20 - 1909.80 MHz
UMTS 850	Voice/Data	826.40 - 846.60 MHz
UMTS 1750	Voice/Data	1712.4 - 1752.6 MHz
UMTS 1900	Voice/Data	1852.4 - 1907.6 MHz
LTE Band 71	Voice/Data	665.5 - 695.5 MHz
LTE Band 12	Voice/Data	699.7 - 715.3 MHz
LTE Band 17	Voice/Data	706.5 - 713.5 MHz
LTE Band 13	Voice/Data	779.5 - 784.5 MHz
LTE Band 14	Voice/Data	790.5 - 795.5 MHz
LTE Band 26 (Cell)	Voice/Data	814.7 - 848.3 MHz
LTE Band 5 (Cell)	Voice/Data	824.7 - 848.3 MHz
LTE Band 66 (AWS)	Voice/Data	1710.7 - 1779.3 MHz
LTE Band 4 (AWS)	Voice/Data	1710.7 - 1754.3 MHz
LTE Band 25 (PCS)	Voice/Data	1850.7 - 1914.3 MHz
LTE Band 2 (PCS)	Voice/Data	1850.7 - 1909.3 MHz
LTE Band 30	Voice/Data	2307.5 - 2312.5 MHz
LTE Band 7	Voice/Data	2502.5 - 2567.5 MHz
LTE Band 41	Voice/Data	2498.5 - 2687.5 MHz
LTE Band 38	Voice/Data	2572.5 - 2617.5 MHz
LTE Band 48	Voice/Data	3552.5 - 3697.5 MHz
NR Band n71	Voice/Data	665.5 - 695.5 MHz
NR Band n12	Voice/Data	701.5 - 713.5 MHz
NR Band n26	Voice/Data	816.5 - 846.5 MHz
NR Band n66	Voice/Data	1712.5 - 1777.5 MHz
NR Band n25	Voice/Data	1852.5 - 1912.5 MHz
NR Band n30	Voice/Data	2307.5 - 2312.5 MHz
NR Band n41	Voice/Data	2506.02 - 2679.99 MHz
NR Band n38	Voice/Data	2575 - 2615 MHz
NR Band n48	Voice/Data	3555 - 3694.98 MHz
NR Band n77	Voice/Data	3455.01 - 3544.98 MHz 3705 - 3975 MHz
2.4 WLAN	Voice/Data	2412 - 2462 MHz
U-NII-1	Voice/Data	5180 - 5240 MHz
U-NII-2A	Voice/Data	5260 - 5320 MHz
U-NII-2C	Voice/Data	5500 - 5720 MHz
U-NII-3	Voice/Data	5745 - 5825 MHz
U-NII-4	Voice/Data	5845 - 5885 MHz
U-NII-5	Voice/Data	5935 - 6415 MHz
U-NII-6	Voice/Data	6435 - 6515 MHz
U-NII-7	Voice/Data	6535 - 6875 MHz
U-NII-8	Voice/Data	6895 - 7115 MHz
Bluetooth	Data	2402 - 2480 MHz
NFC	Data	13.56 MHz
NR Band n258	Data	24250 - 24450 MHz; 24750 - 25250 MHz
NR Band n260	Data	37000 - 40000 MHz
NR Band n261	Data	27500 - 28350 MHz

FCC ID: A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	<b>Approved by:</b> Technical Manager
<b>Document S/N:</b> 1M2304260060-02.A3L (Rev1)	<b>DUT Type:</b> Portable Handset	Page 3 of 11

## 1.2 Time-Averaging for SAR and Power Density

This device is enabled with Qualcomm® Gen2 Smart Transmit algorithm to control and manage transmitting power in real time and to ensure that the time-averaged RF exposure from 2G/3G/4G/5G Sub-6 NR WWAN is in compliance with FCC requirements. This Part 0 report shows SAR characterization of WWAN radios for 2G/3G/4G/5G Sub-6 NR. Characterization is achieved by determining  $P_{Limit}$  for 2G/3G/4G/5G Sub-6 NR that corresponds to the exposure design targets after accounting for all device design related uncertainties, i.e., SAR\_design\_target (< FCC SAR limit) for sub-6 radio. The SAR characterization is denoted as SAR Char in this report. Section 1.3 includes a nomenclature of the specific terms used in this report.

The compliance test under the static transmission scenario and simultaneous transmission analysis are reported in Part 1 report. The validation of the time-averaging algorithm and compliance under the dynamic (time-varying) transmission scenario for WWAN technologies are reported in Part 2 report (report SN could be found in Section 1.4 – Bibliography).

## 1.3 Nomenclature for Part 0 Report

Technology	Term	Description
2G/3G/4G/5G Sub-6 NR	$P_{limit}$	Power level that corresponds to the exposure design target ( <i>SAR_design_target</i> ) after accounting for all device design related uncertainties
	$P_{max}$	Maximum tune up output power
	<i>SAR_design_target</i>	Target SAR level < FCC SAR limit after accounting for all device design related uncertainties
	<i>SAR Char</i>	Table containing $P_{limit}$ for all technologies and bands

## 1.4 Bibliography

Report Type	Report Serial Number
Near Field PD Report (Part 1)	1M2304260060-27.A3L
Near Field PD Part 0 Report	
RF Exposure Part 2 Test Report	1M2304260060-25.A3L
RF Exposure Compliance Summary Report	1M2304260060-28.A3L
RF Exposure Part 1 Test Report	1M2304260060-01.A3L
WIFI 6GHz RF exposure	1M2304260060-26.A3L

FCC ID: A3LSMS711U	PART 0 SAR CHAR REPORT	Approved by: Technical Manager
Document S/N: 1M2304260060-02.A3L (Rev1)	DUT Type: Portable Handset	Page 4 of 11

## 2 SAR AND POWER DENSITY MEASUREMENTS

### 2.1 SAR Definition

Specific Absorption Rate is defined as the time derivative (rate) of the incremental energy (dU) absorbed by (dissipated in) an incremental mass (dm) contained in a volume element (dV) of a given density (ρ). It is also defined as the rate of RF energy absorption per unit mass at a point in an absorbing body (see Equation 2-1).

**Equation 2-1**  
**SAR Mathematical Equation**

$$SAR = \frac{d}{dt} \left( \frac{dU}{dm} \right) = \frac{d}{dt} \left( \frac{dU}{\rho dv} \right)$$

SAR is expressed in units of Watts per Kilogram (W/kg).

$$SAR = \frac{\sigma \cdot E^2}{\rho}$$

where:


σ	=	conductivity of the tissue-simulating material (S/m)
ρ	=	mass density of the tissue-simulating material (kg/m <sup>3</sup> )
E	=	Total RMS electric field strength (V/m)

NOTE: The primary factors that control rate of energy absorption were found to be the wavelength of the incident field in relation to the dimensions and geometry of the irradiated organism, the orientation of the organism in relation to the polarity of field vectors, the presence of reflecting surfaces, and whether conductive contact is made by the organism with a ground plane.[6]

### 2.2 SAR Measurement Procedure

The evaluation was performed using the following procedure compliant to FCC KDB Publication 865664 D01v01r04 and IEEE 1528-2013:

1. The SAR distribution at the exposed side of the head or body was measured at a distance no greater than 5.0 mm from the inner surface of the shell. The area covered the entire dimension of the device-head and body interface and the horizontal grid resolution was determined per FCC KDB Publication 865664 D01v01r04 (See Table 2-1) and IEEE 1528-2013.
2. The point SAR measurement was taken at the maximum SAR region determined from Step 1 to enable the monitoring of SAR fluctuations/drifts during the 1g/10g cube evaluation. SAR at this fixed point was measured and used as a reference value.
3. Based on the area scan data, the peak of the region with maximum SAR was determined by spline interpolation. Around this point, a volume was assessed according to the measurement resolution and volume size requirements of FCC KDB Publication 865664 D01v01r04 (See Table 2-1) and IEEE 1528-2013. On the



**Figure 2-1**  
**Sample SAR Area Scan**

FCC ID: A3LSMS711U	PART 0 SAR CHAR REPORT	Approved by: Technical Manager
Document S/N: 1M2304260060-02.A3L (Rev1)	DUT Type: Portable Handset	Page 5 of 11

REV 1.1  
04/08/2022

basis of this data set, the spatial peak SAR value was evaluated with the following procedure (see references or the DASY manual online for more details):

- a. SAR values at the inner surface of the phantom are extrapolated from the measured values along the line away from the surface with spacing no greater than that in Table 2-1. The extrapolation was based on a least-squares algorithm. A polynomial of the fourth order was calculated through the points in the z-axis (normal to the phantom shell).
  - b. After the maximum interpolated values were calculated between the points in the cube, the SAR was averaged over the spatial volume (1g or 10g) using a 3D-Spline interpolation algorithm. The 3D-spline is composed of three one-dimensional splines with the “Not a knot” condition (in x, y, and z directions). The volume was then integrated with the trapezoidal algorithm. One thousand points (10 x 10 x 10) were obtained through interpolation, in order to calculate the averaged SAR.
  - c. All neighboring volumes were evaluated until no neighboring volume with a higher average value was found.
4. The SAR reference value, at the same location as step 2, was re-measured after the zoom scan was complete to calculate the SAR drift. If the drift deviated by more than 5%, the SAR test and drift measurements were repeated.

**Table 2-1  
Area and Zoom Scan Resolutions per FCC KDB Publication 865664 D01v01r04\***

Frequency	Maximum Area Scan Resolution (mm) ( $\Delta x_{\text{area}}, \Delta y_{\text{area}}$ )	Maximum Zoom Scan Resolution (mm) ( $\Delta x_{\text{zoom}}, \Delta y_{\text{zoom}}$ )	Maximum Zoom Scan Spatial Resolution (mm)			Minimum Zoom Scan Volume (mm) (x,y,z)
			Uniform Grid	Graded Grid		
			$\Delta z_{\text{zoom}}(n)$	$\Delta z_{\text{zoom}}(1)^*$	$\Delta z_{\text{zoom}}(n>1)^*$	
≤ 2 GHz	≤ 15	≤ 8	≤ 5	≤ 4	≤ 1.5* $\Delta z_{\text{zoom}}(n-1)$	≥ 30
2-3 GHz	≤ 12	≤ 5	≤ 5	≤ 4	≤ 1.5* $\Delta z_{\text{zoom}}(n-1)$	≥ 30
3-4 GHz	≤ 12	≤ 5	≤ 4	≤ 3	≤ 1.5* $\Delta z_{\text{zoom}}(n-1)$	≥ 28
4-5 GHz	≤ 10	≤ 4	≤ 3	≤ 2.5	≤ 1.5* $\Delta z_{\text{zoom}}(n-1)$	≥ 25
5-6 GHz	≤ 10	≤ 4	≤ 2	≤ 2	≤ 1.5* $\Delta z_{\text{zoom}}(n-1)$	≥ 22

\*Also compliant to IEEE 1528-2013 Table 6

FCC ID: A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	<b>Approved by:</b> Technical Manager
<b>Document S/N:</b> 1M2304260060-02.A3L (Rev1)	<b>DUT Type:</b> Portable Handset	Page 6 of 11

### 3 SAR CHARACTERIZATION

#### 3.1 DSI and SAR Determination

This device uses different Device State Index (DSI) to configure different time averaged power levels based on certain exposure scenarios. Depending on the detection scheme implemented in the smartphone, the worst-case SAR was determined by measurements for the relevant exposure conditions for that DSI. Detailed descriptions of the detection mechanisms are included in the operational description.

When 1g SAR and 10g SAR exposure comparison is needed, the worst-case was determined from SAR normalized to 1g or 10g SAR limit.

The device state index (DSI) conditions used in Table 3-1 represent different exposure scenarios.

**Table 3-1  
DSI and Corresponding Exposure Scenarios**

Scenario	Description	SAR Test Cases
Head (DSI = 1)	<ul style="list-style-type: none"> <li>Device positioned next to head</li> <li>Receiver Active</li> </ul>	Head SAR per KDB Publication 648474 D04
Hotspot mode (DSI = 2)	<ul style="list-style-type: none"> <li>Device transmits in hotspot mode near body</li> <li>Hotspot Mode Active</li> </ul>	Hotspot SAR per KDB Publication 941225 D06
Phablet (DSI = 0)	<ul style="list-style-type: none"> <li>Device is held with hand</li> </ul>	Phablet SAR per KDB Publication 648474 D04 & KDB Publication 616217 D04
Body-worn (DSI = 0)	<ul style="list-style-type: none"> <li>Device being used with a body-worn accessory</li> </ul>	Body-worn SAR per KDB Publication 648474 D04

#### 3.2 SAR Design Target

*SAR\_design\_target* is determined by ensuring that it is less than FCC SAR limit after accounting for total device designed related uncertainties specified by the manufacturer (see Table 3-2).

**Table 3-2  
SAR\_design\_target Calculations**

<b>SAR_design_target</b>			
$SAR\_design\_target < SAR\_regulatory\_limit \times 10^{\frac{-Total\ Uncertainty}{10}}$			
1g SAR (W/kg)		10g SAR (W/kg)	
<i>Total Uncertainty</i>	1.0 dB	<i>Total Uncertainty</i>	1.0 dB
<i>SAR_regulatory_limit</i>	1.6 W/kg	<i>SAR_regulatory_limit</i>	4.0 W/kg
<i>SAR_design_target</i>	1.0 W/kg	<i>SAR_design_target</i>	2.5 W/kg

FCC ID: A3LSMS711U	PART 0 SAR CHAR REPORT	Approved by: Technical Manager
Document S/N: 1M2304260060-02.A3L (Rev1)	DUT Type: Portable Handset	Page 7 of 11

### 3.3 SAR Char

SAR test results corresponding to  $P_{max}$  for each antenna/technology/band/DSI can be found in Appendix A.

$P_{limit}$  is calculated by linearly scaling with the measured SAR at the  $P_{part0}$  to correspond to the  $SAR_{design\_target}$ . When  $P_{limit} < P_{max}$ ,  $P_{part0}$  was used as  $P_{limit}$  in the Smart Transmit EFS. When  $P_{limit} > P_{max}$  and  $P_{part0}=P_{max}$ , calculated  $P_{limit}$  was used in the Smart Transmit EFS. All reported SAR obtained from the  $P_{part0}$  SAR tests was less than  $SAR_{Design\_target} + 1$  dB Uncertainty. The final  $P_{limit}$  determination for each exposure scenario corresponding to  $SAR_{design\_target}$  are shown in Table 3-3.

**Table 3-3  
 $P_{Limit}$  Determination**

Device State Index (DSI)	$P_{Limit}$ Determination Scenarios
0	The worst-case SAR exposure is determined as maximum SAR normalized to the limit (i.e. lowest $P_{limit}$ ) among: 1. Body Worn SAR 2. Extremity SAR measured at 0 mm spacing
1	$P_{limit}$ is calculated based on 1g Head SAR
2	$P_{limit}$ is calculated based on 1g Hotspot SAR at 10 mm

FCC ID: A3LSMS711U	PART 0 SAR CHAR REPORT	Approved by: Technical Manager
Document S/N: 1M2304260060-02.A3L (Rev1)	DUT Type: Portable Handset	Page 8 of 11



**Table 3-4  
SAR Characterizations**

Exposure Scenario			Maximum Tune-Up Output Power*	Body-Worn	Phablet	Head	Hotspot
Averaging Volume				1g	10g	1g	1g
Spacing			Pmax	10 mm	0 mm	0 mm	10 mm
DSI				0	0	1	2
Technology/Band	Antenna	Antenna Group					
GSM 850	A	AG0	25.3	28.2		30.4	28.0
GSM 1900	A	AG0	22.1	20.0		30.6	20.0
UMTS 850	A	AG0	24.0	27.0		30.4	27.0
UMTS 1750	A	AG0	23.0	19.0		31.5	19.0
UMTS 1900	A	AG0	23.0	19.0		30.4	19.0
LTE Band 71	A	AG0	24.5	28.6		31.9	28.6
LTE Band 12	A	AG0	24.5	27.4		31.4	27.4
LTE Band 13	A	AG0	24.5	26.7		30.0	26.7
LTE Band 14	A	AG0	24.5	26.5		29.7	26.5
LTE Band 26 (Cell)	A	AG0	24.5	26.6		31.0	26.6
LTE Band 5 (Cell)	A	AG0	24.5	26.3		31.3	26.3
LTE Band 66/4 (AWS)	A	AG0	23.5	20.0		29.0	20.0
LTE Band 66/4 (AWS)	F	AG1	22.5	20.0		16.0	20.0
LTE Band 25/2 (PCS)	A	AG0	23.5	19.0		29.8	19.0
LTE Band 25/2 (PCS)	F	AG1	22.5	19.5		17.0	19.5
LTE Band 30	A	AG0	22.0	17.0		34.8	17.0
LTE Band 30	F	AG1	21.5	20.0		15.5	20.0
LTE Band 7	B	AG0	23.0	19.0		32.7	19.0
LTE Band 7	F	AG1	21.0	18.5		14.0	18.5
LTE Band 41/38 (PC3)	B	AG0	22.0	19.0		33.5	19.0
LTE Band 41 (PC2)	B	AG0	22.0	19.0		33.5	19.0
LTE Band 41/38 (PC3)	F	AG1	20.0	19.0		14.5	19.0
LTE Band 41 (PC2)	F	AG1	19.0	19.0		14.5	19.0
LTE Band 48	F	AG1	20.3	18.0		16.0	18.0
NR Band n71	A	AG0	24.5	28.8		32.6	28.8
NR Band n12	A	AG0	24.5	28.4		31.9	28.4
NR Band n26/n5	A	AG0	24.5	27.1		32.4	27.1
NR Band n66	A	AG0	23.5	20.0		30.0	20.0
NR Band n66	F	AG1	22.5	20.0		17.0	20.0
NR Band n25/n2 (PCS)	A	AG0	23.5	19.0		29.7	19.0
NR Band n25/n2 (PCS)	F	AG1	22.5	19.5		16.0	19.5
NR Band n30	A	AG0	22.5	17.0		34.5	17.0
NR Band n30	F	AG1	21.5	20.0		15.5	20.0
NR Band n41 (PC2)	B	AG0	26.0	19.0		19.0	19.0
NR Band n41 (PC2)	F	AG1	22.0	15.5		15.5	15.5
NR Band n41 (PC2)	E	AG1	19.5	16.5		16.5	16.5
NR Band n41 (PC2)	D	AG0	19.0	17.5		17.5	17.5
NR Band n48	F	AG1	22.3	18.0		16.0	18.0
NR Band n77 (PC2)	F	AG1	26.0	18.0		14.5	18.0
NR Band n77 (PC2)	C	AG0	22.0	14.5		13.5	14.5
NR Band n77 (PC2)	I	AG1	24.0	17.5		16.5	17.5
NR Band n77 (PC2)	D	AG0	21.5	13.0		12.0	13.0

**Notes:**

- For all modes/bands, when Hotspot Mode (DSI=2) and free space (DSI=0) are triggered at the same time, DSI=2 takes priority, thus the  $P_{limit}$  for DSI=2 is set to be less or equal to  $P_{limit}$  for DSI=0.
- When  $P_{max} < P_{limit}$ , the DUT will operate at a power level up to  $P_{max}$ .
- For all bands on AG1 when RCV is active, DSI=2 takes priority over all levels.

FCC ID: A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	Approved by: Technical Manager
Document S/N: 1M2304260060-02.A3L (Rev1)	DUT Type: Portable Handset	Page 9 of 11

# 4 EQUIPMENT LIST

## For SAR measurements

Manufacturer	Model	Description	Cal Date	Cal Interval	Cal Due	Serial Number
Agilent	E4404B	Spectrum Analyzer	N/A	N/A	N/A	MM4511242
Agilent	E4488C	ESG Vector Signal Generator	1/18/2023	Annual	1/18/2024	MM4722000
Agilent	E4488C	ESG Vector Signal Generator	4/25/2023	Annual	4/25/2024	US41460739
Agilent	N5182A	MWV Vector Signal Generator	11/26/2022	Annual	11/26/2023	MM4742663
Agilent	N5182A	MWV Vector Signal Generator	4/1/2023	Annual	4/1/2024	MM4742637
Agilent	N5182A	MWV Vector Signal Generator	7/4/2022	Annual	7/4/2023	MM4818066
Agilent	8733ES	S-Parameter Vector Network Analyzer	1/12/2023	Annual	1/12/2024	MM40001472
Agilent	8733ES	S-Parameter Vector Network Analyzer	6/14/2022	Annual	6/14/2023	US39170118
Agilent	E5355C	Wireless Communications Test Set	1/12/2023	Annual	1/12/2024	MM5026139
Agilent	N4010A	Wireless Connectivity Test Set	N/A	N/A	N/A	GB46170464
Amplifier Research	1551G6	Amplifier	CBT	N/A	CBT	433972
Amplifier Research	1551G6	Amplifier	CBT	N/A	CBT	343972
Amplifier Research	1551G6	Amplifier	CBT	N/A	CBT	433971
Amplifier Research	150A100C	Amplifier	CBT	N/A	CBT	350132
Anritsu	ML2496A	Power Meter	8/16/2022	Annual	8/16/2023	1351001
Anritsu	ML2496A	Power Meter	6/15/2023	Annual	6/15/2024	1138001
Anritsu	MA2411B	Pulse Power Sensor	2/18/2023	Annual	2/18/2024	1335051
Anritsu	MA2411B	Pulse Power Sensor	10/21/2022	Annual	10/21/2023	1207364
Anritsu	MT8821C	Radio Communication Analyzer MT8821C	1/16/2023	Annual	1/16/2024	620152467
Anritsu	MT8821C	Radio Communication Analyzer MT8821C	3/31/2023	Annual	3/31/2024	6201381794
Anritsu	MT8821C	Radio Communication Analyzer MT8821C	11/28/2022	Annual	11/28/2023	626126047
Anritsu	MT8821C	Radio Communication Analyzer MT8821C	6/27/2022	Annual	6/27/2023	626185213
Anritsu	MT8000A	Radio Communication Test Station	3/1/2023	Annual	3/1/2024	6272337419
Anritsu	MT8000A	Radio Communication Test Station	6/15/2023	Annual	6/15/2024	6261914237
Anritsu	MT8000A	Radio Communication Test Station	2/19/2023	Annual	2/19/2024	6272317408
Anritsu	MA24106A	USB Power Sensor	2/19/2023	Annual	2/19/2024	1329205
Anritsu	MA24106A	USB Power Sensor	4/21/2023	Annual	4/21/2024	1344515
Anritsu	MA24106A	USB Power Sensor	1/13/2023	Annual	1/13/2024	1344557
Mini-Circuits	PWR-404HS	USB Power Sensor	9/12/2022	Annual	11/12/2023	1171002062
Control Company	4352	Long Stem Thermometer	9/10/2021	Biennial	9/10/2023	21074678
Control Company	4352	Long Stem Thermometer	9/10/2021	Biennial	9/10/2023	21074685
Control Company	4352	Long Stem Thermometer	9/10/2021	Biennial	9/10/2023	21074675
Control Company	4040	Therm / Clock / Humidity Monitor	1/17/2023	Annual	1/17/2024	16079448
Traceable	9040 9080-9D	Therm / Clock / Humidity Monitor	5/11/2022	Biennial	5/11/2024	221514074
Traceable	9040 9080-9D	Therm / Clock / Humidity Monitor	5/11/2022	Biennial	5/11/2024	221514925
Mitutoyo	506-196-30	CD-67ASX 6inch Digital Caliper	2/16/2022	Triennial	2/16/2025	A20038413
Keyight Technologies	N6708	DC Power Analyzer	5/2/2021	Triennial	5/2/2024	MM53004059
Keyight Technologies	N9202A	MMA Signal Analyzer	3/15/2023	Annual	3/15/2024	US46479561
Keyight Technologies	N9202A	MMA Signal Analyzer	4/6/2023	Annual	4/6/2024	MM48020133
MCL	BW-NGW5+	6dB Attenuator	CBT	N/A	CBT	1139
Mini-Circuits	VLF-6000+	Low Pass Filter DC to 6000 MHz	CBT	N/A	CBT	11634
Mini-Circuits	VLF-6000+	Low Pass Filter DC to 6000 MHz	CBT	N/A	CBT	N/A
Mini-Circuits	BW-N200V4	DC to 18 GHz Precision Fixed 20 dB Attenuator	CBT	N/A	CBT	N/A
Mini-Circuits	NLP-1200+	Low Pass Filter DC to 1000 MHz	CBT	N/A	CBT	N/A
Mini-Circuits	NLP-2500+	Low Pass Filter DC to 2700 MHz	CBT	N/A	CBT	N/A
Mini-Circuits	BW-N200V5	Power Attenuator	CBT	N/A	CBT	1226
Mini-Circuits	ZUDC10-83-5+	Directional Coupler	CBT	N/A	CBT	2656
Mini-Circuits	ZUDC10-83-5+	Directional Coupler	CBT	N/A	CBT	2111
Narda	4772-3	Attenuator (3dB)	CBT	N/A	CBT	9406
Narda	BW-53V2	Attenuator (3dB)	CBT	N/A	CBT	120
Pfeiffer	PK501-1	Temp. Wrench	12/21/2021	Biennial	12/21/2023	104715
Rohde & Schwarz	CMW500	Wideband Radio Communication Tester	3/8/2023	Annual	3/8/2024	128635
Rohde & Schwarz	CMW500	Wideband Radio Communication Tester	4/5/2023	Annual	4/5/2024	167284
Rohde & Schwarz	CMW500	Wideband Radio Communication Tester	1/12/2023	Annual	1/12/2024	150117
Rohde & Schwarz	CMW500	Wideband Radio Communication Tester	2/12/2023	Annual	2/12/2024	164988
SFEAG	DAK-3.5	Portable Dielectric Assessment Kit	12/15/2022	Annual	12/15/2023	1078
SFEAG	DAKS-3.5	Portable Dielectric Assessment Kit	8/15/2022	Annual	8/15/2023	1041
SFEAG	DAKS-3.5	Portable Dielectric Assessment Kit	7/4/2023	Annual	7/4/2024	1039
SFEAG	DAE-32	Dielectric Assessment Kit (4MHz-3GHz)	3/13/2023	Annual	3/13/2024	1105
SFEAG	MA1A	Modulation and Audio Interference Analyzer	N/A	N/A	N/A	1237
SFEAG	MA1A	Modulation and Audio Interference Analyzer	N/A	N/A	N/A	1243
SFEAG	MA1A	Modulation and Audio Interference Analyzer	N/A	N/A	N/A	1237
SFEAG	D307E3	Confined Loop Antenna	9/15/2022	Annual	9/15/2023	1002
SFEAG	D750V1	750 MHz SAR Dipole	2/15/2023	Annual	2/15/2024	1046
SFEAG	D750V3	750 MHz SAR Dipole	5/11/2023	Annual	5/11/2024	1003
SFEAG	D830V2	835 MHz SAR Dipole	1/21/2021	Triennial	1/21/2024	46132
SFEAG	D830V2	835 MHz SAR Dipole	4/12/2023	Annual	4/12/2024	46119
SFEAG	D1750V1	1750 MHz SAR Dipole	1/18/2022	Annual	1/18/2023	1148
SFEAG	D1750V2	1750 MHz SAR Dipole	4/19/2023	Annual	4/19/2024	1051
SFEAG	D1750V2	1750 MHz SAR Dipole	5/17/2023	Annual	5/17/2024	1050
SFEAG	D1900V2	1900 MHz SAR Dipole	9/21/2021	Biennial	9/21/2023	56149
SFEAG	D1900V2	1900 MHz SAR Dipole	8/8/2022	Annual	8/8/2023	45080
SFEAG	D1900V2	1900 MHz SAR Dipole	4/18/2023	Annual	4/18/2024	56141
SFEAG	D2300V2	2300 MHz SAR Dipole	8/25/2022	Annual	8/25/2023	1073
SFEAG	D2450V2	2450 MHz SAR Dipole	11/25/2021	Biennial	11/25/2023	981
SFEAG	D2450V2	2450 MHz SAR Dipole	5/11/2023	Annual	5/11/2024	945
SFEAG	D2600V2	2600 MHz SAR Dipole	11/15/2022	Annual	11/15/2023	1071
SFEAG	D2600V2	2600 MHz SAR Dipole	6/13/2022	Biennial	6/13/2024	1009
SFEAG	D2600V2	2600 MHz SAR Dipole	9/9/2020	Triennial	9/9/2023	1069
SFEAG	D3800V2	3800 MHz SAR Dipole	1/19/2023	Annual	1/19/2024	1097
SFEAG	D3900V2	3900 MHz SAR Dipole	8/12/2022	Annual	8/12/2023	1065
SFEAG	D3700V2	3700 MHz SAR Dipole	1/19/2021	Triennial	1/19/2024	1018
SFEAG	D3700V2	3700 MHz SAR Dipole	10/21/2022	Annual	10/21/2023	1002
SFEAG	D3900V2	3900 MHz SAR Dipole	11/13/2020	Triennial	11/13/2023	1062
SFEAG	D3900V2	3900 MHz SAR Dipole	1/18/2023	Annual	1/18/2024	1191
SFEAG	DAE4	5 GHz SAR Dipole	7/18/2022	Annual	7/18/2023	1583
SFEAG	DAE4	5 GHz SAR Dipole	1/17/2023	Annual	1/17/2024	1558
SFEAG	DAE4	5 GHz SAR Dipole	7/18/2022	Annual	7/18/2023	1677
SFEAG	DAE4	5 GHz SAR Dipole	2/18/2023	Annual	2/18/2024	1538
SFEAG	DAE4	5 GHz SAR Dipole	11/10/2022	Annual	11/10/2023	1323
SFEAG	DAE4	5 GHz SAR Dipole	6/15/2023	Annual	6/15/2024	1334
SFEAG	DAE4	5 GHz SAR Dipole	2/15/2023	Annual	2/15/2024	665
SFEAG	DAE4	5 GHz SAR Dipole	2/16/2023	Annual	2/16/2024	646
SFEAG	DAE4	5 GHz SAR Dipole	1/20/2023	Annual	1/20/2024	1466
SFEAG	DAE4	5 GHz SAR Dipole	10/17/2022	Annual	10/17/2023	1322
SFEAG	DAE4	5 GHz SAR Dipole	3/16/2023	Annual	3/16/2024	1652
SFEAG	DAE4	5 GHz SAR Dipole	2/13/2023	Annual	2/13/2024	1408
SFEAG	DAE4	5 GHz SAR Dipole	11/21/2022	Annual	11/21/2023	791
SFEAG	EK30V4	SAR Probe	7/19/2022	Annual	7/19/2023	7410
SFEAG	EK30V4	SAR Probe	1/11/2023	Annual	1/11/2024	7570
SFEAG	EK30V4	SAR Probe	7/18/2022	Annual	7/18/2023	7406
SFEAG	EK30V4	SAR Probe	2/11/2023	Annual	2/11/2024	7721
SFEAG	EK30V4	SAR Probe	11/11/2022	Annual	11/11/2023	7551
SFEAG	EK30V4	SAR Probe	6/15/2023	Annual	6/15/2024	7409
SFEAG	EK30V4	SAR Probe	2/8/2023	Annual	2/8/2024	7417
SFEAG	EK30V4	SAR Probe	2/18/2023	Annual	2/18/2024	7640
SFEAG	EK30V4	SAR Probe	1/12/2023	Annual	1/12/2024	7565
SFEAG	EK30V4	SAR Probe	10/18/2022	Annual	10/18/2023	7547
SFEAG	EK30V4	SAR Probe	3/16/2023	Annual	3/16/2024	7637
SFEAG	EK30V4	SAR Probe	3/16/2023	Annual	3/16/2024	7638
SFEAG	EK30V4	SAR Probe	11/21/2022	Annual	11/21/2023	8817

Note:

1. CBT (Calibrated Before Testing). Prior to testing, the measurement paths containing a cable, amplifier, attenuator, coupler or filter were connected to a calibrated source (i.e. a signal generator) to determine the losses of the measurement path. The power meter offset was then adjusted to compensate for the measurement system losses. This level offset is stored within the power meter before measurements are made. This calibration verification procedure applies to the system verification and output power measurements. The calibrated reading is then taken directly from the power meter after compensation of the losses for all final power measurements.
2. Each equipment item was used solely within its respective calibration period.

FCC ID: A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	<b>Approved by:</b> Technical Manager
Document S/N: 1M2304260060-02.A3L (Rev1)	DUT Type: Portable Handset	Page 10 of 11

## 5 MEASUREMENT UNCERTAINTIES

### For SAR Measurements

a	b	c	d	e = f(d,k)	f	g	h = c x f/e	i = c x g/e	k
Uncertainty Component	IEEE 1528 Sec.	ToL (± %)	Prob. Dist.	Div.	c <sub>f</sub> 1 gm	c <sub>g</sub> 10 gm	1 gm u <sub>f</sub> (± %)	10 gm u <sub>g</sub> (± %)	v <sub>i</sub>
<b>Measurement System</b>									
Probe Calibration	E.2.1	7	N	1	1	1	7.0	7.0	∞
Axial Isotropy	E.2.2	0.25	N	1	0.7	0.7	0.2	0.2	∞
Hemishperical Isotropy	E.2.2	1.3	N	1	0.7	0.7	0.9	0.9	∞
Boundary Effect	E.2.3	2	R	1.732	1	1	1.2	1.2	∞
Linearity	E.2.4	0.3	N	1	1	1	0.3	0.3	∞
System Detection Limits	E.2.4	0.25	R	1.732	1	1	0.1	0.1	∞
Modulation Response	E.2.5	4.8	R	1.732	1	1	2.8	2.8	∞
Readout Electronics	E.2.6	0.3	N	1	1	1	0.3	0.3	∞
Response Time	E.2.7	0.8	R	1.732	1	1	0.5	0.5	∞
Integration Time	E.2.8	2.6	R	1.732	1	1	1.5	1.5	∞
RF Ambient Conditions - Noise	E.6.1	3	R	1.732	1	1	1.7	1.7	∞
RF Ambient Conditions - Reflections	E.6.1	3	R	1.732	1	1	1.7	1.7	∞
Probe Positioner Mechanical Tolerance	E.6.2	0.8	R	1.732	1	1	0.5	0.5	∞
Probe Positioning w/ respect to Phantom	E.6.3	6.7	R	1.732	1	1	3.9	3.9	∞
Extrapolation, Interpolation & Integration algorithms for Max. SAR Evaluation	E.5	4	R	1.732	1	1	2.3	2.3	∞
<b>Test Sample Related</b>									
Test Sample Positioning	E.4.2	3.12	N	1	1	1	3.1	3.1	35
Device Holder Uncertainty	E.4.1	1.67	N	1	1	1	1.7	1.7	5
Output Power Variation - SAR drift measurement	E.2.9	5	R	1.732	1	1	2.9	2.9	∞
SAR Scaling	E.6.5	0	R	1.732	1	1	0.0	0.0	∞
<b>Phantom &amp; Tissue Parameters</b>									
Phantom Uncertainty (Shape & Thickness tolerances)	E.3.1	7.6	R	1.73	1.0	1.0	4.4	4.4	∞
Liquid Conductivity - measurement uncertainty	E.3.3	4.3	N	1	0.78	0.71	3.3	3.0	76
Liquid Permittivity - measurement uncertainty	E.3.3	4.2	N	1	0.23	0.26	1.0	1.1	75
Liquid Conductivity - Temperature Uncertainty	E.3.4	3.4	R	1.732	0.78	0.71	1.5	1.4	∞
Liquid Permittivity - Temperature Uncertainty	E.3.4	0.6	R	1.732	0.23	0.26	0.1	0.1	∞
Liquid Conductivity - deviation from target values	E.3.2	5.0	R	1.73	0.64	0.43	1.8	1.2	∞
Liquid Permittivity - deviation from target values	E.3.2	5.0	R	1.73	0.60	0.49	1.7	1.4	∞
<b>Combined Standard Uncertainty (k=1)</b>	RSS						12.2	12.0	191
<b>Expanded Uncertainty</b> (95% CONFIDENCE LEVEL)	k=2						24.4	24.0	

The above measurement uncertainties are according to IEEE Std. 1528-2013

FCC ID: A3LSMS711U	<b>PART 0 SAR CHAR REPORT</b>	<b>Approved by:</b> Technical Manager
<b>Document S/N:</b> 1M2304260060-02.A3L (Rev1)	<b>DUT Type:</b> Portable Handset	Page 11 of 11