

August 27, 2024

Federal Communications Commission  
7435 Oakland Mills Road  
Columbia, MD 21046 USA

RE: FCC ID: A3LSMS928U C2PC RF Exposure Evaluation

To Whom It May Concern:

This permissive change is to enable the following features via SW only:  
- Additional DLCA added

As there is no change in HW, Tx path, or power for any of the above DL operations, conducted power measurements were taken for the new combinations. Please see the included LTE CA document for measurement results. The LTE test data in the original filing additionally demonstrates RF Exposure compliance for these added capabilities.

Best Regards,

RJ Ortanez  
Executive Vice President  
rj.ortanez@element.com


## RF EXPOSURE EVALUATION

SAR test exclusion for LTE downlink Carrier Aggregation is determined by power measurements according to the number of component carriers (CCs) supported by the product implementation. Per April 2018 TCBC Workshop Notes, the following test reduction methodology was applied to determine the combinations required for conducted power measurements.

**LTE DLCA Test Reduction Methodology:**


- The supported combinations were arranged by the number of component carriers in columns.
- Any limitations on the PCC or SCC for each combination were identified alongside the combination (e.g. CA\_2A-2A-4A-12A, but B12 can only be configured as a SCC).
- Power measurements were performed for "supersets" (LTE CA combinations with multiple components carriers) and any "subsets" (LTE CA combinations with fewer component carriers) that were not completely covered by the supersets.
- Only subsets that have the exact same components as a superset were excluded for measurement.
- When there were certain restrictions on component carriers that existed in the superset that were not applied for the subset, the subset configuration was additionally evaluated.
- Both inter-band and intra-band downlink carrier aggregation scenarios were considered.
- Downlink CA combinations for SISO and 4x4 Downlink MIMO operations were measured independently, per May 2017 TCBC Workshop notes.

**Table A-1 – Example of Exclusion Table for SISO Configurations**



FCC ID: A3LSMS928U	<b>SAR EVALUATION REPORT</b>	Approved by: Technical Manager
DUT Type: Portable Handset		Page 1 of 6

**Table A-2 – Example of Exclusion Table for 4x4 Downlink MIMO Configurations**



Note: [CC] indicates component carrier with 4x4 DL MIMO antenna configuration

### A.1 LTE Downlink Only Carrier Aggregation Test Selection and Setup

SAR test exclusion for LTE downlink Carrier Aggregation is determined by power measurements according to the number component carriers (CCs) supported by the product implementation. For those configurations required by April 2018 TCBC Workshop Notes, conducted power measurements with LTE Carrier Aggregation (CA) (downlink only) active are made in accordance to KDB Publication 941225 D05Av01r02. The RRC connection is only handled by one cell, the primary component carrier (PCC) for downlink and uplink communications. After making a data connection to the PCC, the UE device adds secondary component carrier(s) (SCC) on the downlink only. All uplink communications and acknowledgements remain identical to specifications when downlink carrier aggregation is inactive on the PCC. Additional conducted output powers are measured with the downlink carrier aggregation active for the configuration with highest measured maximum conducted power with downlink carrier


FCC ID: A3LSMS928U	<b>SAR EVALUATION REPORT</b>	<b>Approved by:</b> Technical Manager
DUT Type: Portable Handset		Page 2 of 6

aggregation inactive measured among the channel bandwidth, modulation, and RB combinations in each frequency band.


Per FCC KDB Publication 941225 D05Av01r02, no SAR measurements are required for carrier aggregation configurations when the maximum average output power with downlink only carrier aggregation active is not more than 0.25 dB higher than the average output power with downlink only carrier aggregation inactive. All bands required for SAR testing per FCC KDB procedures were considered. Based on the measured maximum powers below, no additional SAR tests were required for DLCA SAR configurations.

General PCC and SCC configuration selection procedure

- PCC uplink channel, channel bandwidth, modulation and RB configurations were selected based on section C)3)b)ii) of KDB 941225 D05 V01r02. All LTE bandwidth conducted powers needed for PCC uplink configuration selection can be found in the RF Conducted Powers Section and LTE/NR Lower Bandwidth RF Conducted Power Appendix. The downlink PCC channel was paired with the selected PCC uplink channel according to normal configurations without carrier aggregation.
- To maximize aggregated bandwidth, highest channel bandwidth available for that CA combination was selected for SCC. For inter-band CA, the SCC downlink channels were selected near the middle of their transmission bands. For contiguous intra-band CA, the downlink channel spacing between the component carriers was set to multiple of 300 kHz less than the nominal channel spacing defined in section 5.4.1A of 3GPP TS 36.521. For non-contiguous intra-band CA, the downlink channel spacing between the component carriers was set to be larger than the nominal channel spacing and provided maximum separation between the component carriers.
- All selected PCC and SCC(s) remained fully within the uplink/downlink transmission band of the respective component carrier.



**Figure A-1**  
**DL CA Power Measurement Setup**



**Figure A-2**  
**DL CA with DL 4x4 MIMO Power Measurement Setup**

FCC ID: A3LSMS928U	SAR EVALUATION REPORT	Approved by: Technical Manager
DUT Type: Portable Handset		Page 3 of 6





