

APPENDIX 4 : Test configuration for HSPA device

1. Explanation of the WCDMA HSDPA/HSPA Power measurement mode

3GPP TS 34.121 defines test requirements and procedures for testing all variations of WCDMA. 3GPP TS 34.121 defines 4 HSDPA test configurations and 5 HSUPA test configurations ("Subtests") for various RF Conformance tests. And also FCC KDB941225 D01 is referencing 3GPP Subtest configurations for FCC Type Approval Testing. The Following table shows Release 6 HSPA Subtest Configurations per 3GPP TS 34.121.

[HSDPA]

Table C.10.1.4: β values for transmitter characteristics tests with HS-DPCCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1, Note 2)	CM (dB) (Note 3)	MPR (dB) (Note 3)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15	15/15	64	12/15	24/15	1.0	0.0
	(Note 4)	(Note 4)		(Note 4)			
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5
Note 1: Δ_{ACK}, Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$. Note 2: For the HS-DPCCH power mask requirement test in clause 5.2C, 5.7A, and the Error Vector Magnitude (EVM) with HS-DPCCH test in clause 5.13.1A, and HSDPA EVM with phase discontinuity in clause 5.13.1AA, Δ_{ACK} and $\Delta_{NACK} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$, and $\Delta_{CQI} = 24/15$ with $\beta_{HS} = 24/15 * \beta_c$. Note 3: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{HS}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH and HS-DPCCH the MPR is based on the relative CM difference. This is applicable for only UEs that support HSDPA in release 6 and later releases. Note 4: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.							

[HSUPA]

Table C.11.1.3: β values for transmitter characteristics tests with HS-DPCCH and E-DCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1)	β_{oc}	β_{ed} (Note 5) (Note 6)	β_d (SF)	β_{ed} (Codes)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 6)	E- TFCI
1	11/15 (Note 3)	15/15 (Note 3)	64	11/15 (Note 3)	22/15	209/225	1309/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1}: 47/15$ $\beta_{ed2}: 47/15$	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 (Note 4)	15/15 (Note 4)	64	15/15 (Note 4)	30/15	24/15	134/15	4	1	1.0	0.0	21	81
Note 1: Δ_{ACK}, Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$. Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{HS}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference. Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$. Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$. Note 5: In case of testing by UE using E-DPDCH Physical Layer category 1, Sub-test 3 is omitted according to TS25.306 Table 5.1g. Note 6: β_{ed} can not be set directly, it is set by Absolute Grant Value.													

2. Maximum Output Power Verification

[HSDPA]

Maximum output power was verified on High, Middle and Low channels according to the Release 6 procedures described in section 5.2 of 3GPP TS 34.121, using an FRC with H-set 1 and 12.2kbps RMC with TPC (transmit power control) set to all "1's". Output power was measured according requirements for HS-DPCCH Sub-test 1-4.

[HSUPA]

Maximum output power was verified on the High, Middle and Low channels according to Release 6 procedures in section 5.2 of 3GPP TS 34.121, using the appropriate RMC, FRC and E-DCH configurations. When E-DCH was active, inner loop power control with power control algorithm 2 was used to maintain E-TFCI requirements. Output power for the applicable HSPA modes was measured for E-DCH Sub-test 1-5.

3. SAR Measurements for Head

Condition that 12.2 kbps AMR Mode measurement is necessary

SAR for head exposure configurations in voice mode is measure using a 12.2 kbps RMC with TPC bits configured to all "1's". SAR in AMR configurations is not required when the maximum average output of each RF channel for 12.2 kbps AMR is less than ¼ dB higher than that measured in 12.2 kbps RMC.

Measurement configurations for 12.2 kbps AMR

SAR is measured on the maximum output channel in 12.2 kbps AMR with a 3.4 kbps SRB (signaling radio bearer) using the exposure configuration that results in the highest SAR in 12.2 kbps RMC for that RF channel.

4. SAR Measurements for Body

Condition that Body SAR measurement is necessary

[HSDPA]

Body SAR is required for HSDPA when the maximum average output of each RF channel with HSDPA active is at least ¼ dB higher than that measured without HSDPA using 12.2 kbps RMC or the maximum SAR for 12.2 kbps RMC was above 75% of the SAR limit.

[HSPA]

Body SAR is required for HSPA when the maximum average output of each RF channel with HSPA active is at least ¼ dB higher than that measured without HSPA using 12.2 kbps RMC or the maximum SAR for 12.2 kbps RMC is above 75% of the SAR limit.

Measurement configurations for Body SAR

[HSDPA]

Body SAR for HSDPA is measured using FRC with H-Set 1 in Sub-test 1 and 12.2 kbps RMC configured in Test Loop Mode 1, using the highest body SAR configuration in 12.2 kbps RMC without HSDPA. SAR for body exposure configurations in data modes is measured using a 12.2 kbps RMC with TPC bits configured to all "1's".

[HSUPA]

Body SAR for HSUPA is measured with E-DCH Sub-test 5, using H-Set 1 and QPSK for FRC and a 12.2 kbps RMC configured in Test Loop Mode 1 with power control algorithm 2, according to the highest body SAR configuration in 12.2 kbps RMC without HSPA. Inner loop power control with power control algorithm 2 is required to maintain E-TFCI requirements.

5. Test Equipment Setting Summary Table

The following table is the key parameters that was configured in test equipment.

Subtest	Mode	Loopback Mode	Rel99 RMC	HSDPA FRC	HSUPA Test	Common Setting		$\beta c/\beta d$	MPR	Power Class 3 limit
						βc	βd			
	Rel99	Test Mode 1	12.2kbps RMC	-	-			8/15		24(+1.7/-3.7dB)
1	Rel6 HSDPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	-	2/15	15/15	2/15	0	24(+1.7/-3.7dB)
2	Rel6 HSDPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	-	12/15	15/15	12/15	0	24(+1.7/-3.7dB)
3	Rel6 HSDPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	-	15/15	8/15	15/8	0.5	23.5(+2.2/-3.7dB)
4	Rel6 HSDPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	-	15/15	4/15	15/4	0.5	23.5(+2.2/-3.7dB)
1	Rel6 HSUPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	HSUPA Loopback	11/15	15/15	11/15	0	24(+1.7/-3.7dB)
2	Rel6 HSUPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	HSUPA Loopback	6/15	15/15	6/15	2	22(+3.7/-3.7dB)
3	Rel6 HSUPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	HSUPA Loopback	15/15	9/15	15/9	1	23(+2.7/-3.7dB)
4	Rel6 HSUPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	HSUPA Loopback	2/15	15/15	2/15	2	22(+3.7/-3.7dB)
5	Rel6 HSUPA	Test Mode 1	12.2kbps RMC	H-Set 1 (QPSK)	HSUPA Loopback	15/15	15/15	15/15	0	24(+1.7/-3.7dB)

Subtest	HSDPA Specific Settings						
	$\Delta A C K$	$\Delta NACK$	ΔCQI	Ack-Nack repetition factor	CQI Feedback	CQI Repetition Factor	Ahs= $\beta h s/\beta c$
Rel 6 HSDPA							
1	8	8	8	3	4ms	2	30/15
2	8	8	8	3	4ms	2	30/15
3	8	8	8	3	4ms	2	30/15
4	8	8	8	3	4ms	2	30/15

Subtest	HSDPA Specific Settings							HSUPA Specific Settings			HSUPA Additional Info	
	$\Delta A C K$	$\Delta NACK$	ΔCQI	Ack-Nack repetition factor	CQI Feedback	CQI Repetition Factor	Ahs= $\beta h s/\beta c$	$\Delta E-D P C C H$	$\Delta H A R Q$	AG Index	ETFCI(form TS34.121 Table C.11.1.3)	Associated Max UL Data Rate kbps
Rel 6 HSUPA												
1	8	8	8	3	4ms	2	30/15	6	0	20	75	242.1
2	8	8	8	3	4ms	2	30/15	8	0	12	67	174.9
3	8	8	8	3	4ms	2	30/15	8	0	15	92	482.8
4	8	8	8	3	4ms	2	30/15	5	0	17	71	205.8
5	8	8	8	3	4ms	2	30/15	7	0	21	81	308.9

UL Japan, Inc.

Head Office EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone: +81 596 24 8116

Facsimile: +81 596 24 8124

HSUPA Reference E-TFCI Parameters

[Subtest 1,2,4,5]

Information Element	Value/Remark
E-DCH info	Uplink DPCH info
- E-DPDCH info	
- Reference E-TFCIs	5 E-TFCIs
- Reference E-TFCI	11
- Reference E-TFCI PO	4
- Reference E-TFCI	67
- Reference E-TFCI PO	18
- Reference E-TFCI	71
- Reference E-TFCI PO	23
- Reference E-TFCI	75
- Reference E-TFCI PO	26
- Reference E-TFCI	81
- Reference E-TFCI PO	27

[Subtest 3]gyuz

Information Element	Value/Remark
E-DCH info	Uplink DPCH info
- E-DPDCH info	
- Reference E-TFCIs	2 E-TFCIs
- Reference E-TFCI	11
- Reference E-TFCI PO	4
- Reference E-TFCI	92
- Reference E-TFCI PO	18