



C-MAC Engineering
21 Richardson Side rd
Kanata ON K2K 2C1 · Canada
Tel 613 763 7847
Fax 613 763 8091

www.cmac.com

Denis Lalonde
Radio Compatibility Eng.

June 9, 2000

Federal Communications Commission
Authorization and Evaluation Division
Equipment Authorization Branch
7435 Oakland Mills Road
Columbia, Maryland, 21046

Re: AB6CTR2808M

Dear Sir or Madam:

This document describes the method used for determining the minimum separation distance between the CTR and the general public in order to prevent RF exposure as per paragraph 1.1310.

The minimum separation distance was determined with calculations. They were done using FCC OST/OET Bulletin 65 ("Evaluating Compliance with FCC Specified Guidelines for Human Exposure to Radiofrequency Radiation"). The aperture antenna equations for predicting RF fields from that document were used. They yielded the following results.

The power density of the 28-08M CTR:

- at the surface of the antenna is 0.84 mW/cm^2 (OST/OET Bulletin 65 equation 11)
- in the near field ($R < 2.8 \text{ m}$) is less than 0.62 mW/cm^2 (equation 12, 13, 14)
- in the transition region ($2.8 \text{ m} < R < 6.7 \text{ m}$) is less than 0.62 mW/cm^2 (equation 16, 17)
- in the far field ($R > 6.7 \text{ m}$) is less than 0.27 mW/cm^2 (equation 18)

Power = 23.0 dBm = 1 dB compression point of the CTR

Antenna diameter = 13.7 inches

Frequency = 27925 MHz

Antenna gain = 38.8 dBi

The FCC General Population limit is 1 mW/cm^2 , hence the use of 0 cm as the minimum separation limit.

A drawing of the radiation warning label and a picture of its location as been submitted. The exhibit type of those files is "ID Label/Location Info". Their file name are;

- CTR_RF_Label.pdf
- Exposure_Label_Position.pdf

The size of the label is 2.5 inches by 3.5 inches. A label is installed on both sides of the CTR.

Regards,

Denis Lalonde
Product Integrity
email: dlalonde@kan.cmac.com
C-MAC Engineering

