

## Description of Instrumentation and calculation

## (1) Measurement equipment

a. Field Strength Meter : Electro-Metrics Model EMC-50

Bandwidth Setting : 1 MHz

Detector Function : Linear Average Detection

b. Receiving Antenna : Electro-Metrics Model RGA-180

Frequency Range : 1 - 18 GHz

c. Microwave Survey Meter : Narda Model 8110B

## (2) Test Condition

a. Antenna Height Variation : 1.0 - 1.5 m

b. Distance of Antenna to Test unit : 3.0 m

c. Test Unit Height : 1.0 m

## (3) Calculation Formula

Field Strength at 3 m (dBuV/m)

$$= \text{Receiver Reading (dBuV)} + \text{Antenna Factor (dB/m)} + \text{Cable Loss (dB)}$$

Field Strength at 300m (uV/m)

$$= K * 10^{\frac{\text{Field Strength at 3 m (dBuV/m)}}{20}}$$

K : Conversion Factor for 3 m to 300 m

Frequency (MHz)	Antenna Factor (dB/m)	Cable Loss (dB)	Conv. Factor K
2400	29	0.7	0.0061
Fundamental	29.3	0.7	0.0062
2500	29.5	0.7	0.0063
4900	33.4	0.9	0.01
7350	36.5	1.2	0.01
9800	38.2	1.4	0.01

Example : 2nd Harmonics

Receiver Reading = 20 dB @ 3 m

$$\text{FIS @300 m} = 0.01 * 10^{\frac{20 + 33.4 + 0.9}{20}} = 5.19 \text{ (uV/m)}$$

## Exhibit 1 Test Equipment List

---

Name / Model No.	S / No.	Manufacturer	Last Calibrated
Field Strength Meter Model EMC - 50	175	Electro Metrics	07 / 02 / 04
Microwave Survey Meter 8110B	20915	Narda	07 / 08 / 03
Ridged Guide Antenna RGA - 180	2455	Electro Metrics	08 / 20 / 88
Network Analyzer 8410B	1647A00704	Hewlett Packard	06 / 17 / 88
Reflection Unit 8743A	1330A01358	Hewlett Packard	06 / 17 / 88
Sweep Oscillator 8620C	1645A00827	Hewlett Packard	06 / 17 / 88
Frequency Meter 536A	1441A00695	Hewlett Packard	09 / 17 / 88
Power Meter 436A	1629A1172	Hewlett Packard	08 / 05 / 89
Spectrum Analyzer 8555A	1642A06830	Hewlett Packard	08 / 21 / 88

---