

**TYPE OF EXHIBIT:** RF EXPOSURE EVALUATION

**FCC PART:** 1.1310

**IC PART:** RSS-119, Section 9, RSS-102

**MANUFACTURER:** RITRON, Inc.

**MODEL:** RPM-460

**TYPE OF UNIT:** UHF Mobile Transceiver

**FCC ID:** AIERIT24-460

**IC ID:** 1084A-RIT24460

**DATE:** March 15, 2006

**PROCEDURE:**

Because this product is used as a mobile device, an RF evaluation was done. The RF evaluation entailed testing the unit on RITRON'S 3-meter range to determine EIRP and then calculating the minimum safe distance from the antenna necessary to ensure compliance with the appropriate RF exposure limits.

1. The measurement for effective radiated power was taken at the RITRON, Inc. 3-meter test site, details of which are on file with the FCC and Industry Canada.
2. The DUT was aligned for transmitter operation on lower, middle and upper band edge frequencies at the 40.0 watt maximum output power rating of the RPM-460 per the tune-up procedure outlined in the Maintenance Manual. The unit was then terminated at the antenna port in a quarterwave magnetic mount antenna which is typical of what might be used with this product. (The user may connect other antennas, however.)
3. All field strength measurements were made with the Hewlett-Packard Model 8560E Spectrum Analyzer and an Electro-Metrics EM-6924 adjustable dipole antenna tuned to the carrier frequency.

**TYPE OF EXHIBIT:** RF EXPOSURE EVALUATION

**FCC PART:** 1.1310

**IC PART:** RSS-119, Section 9, RSS-102

**MANUFACTURER:** RITRON, Inc.

**MODEL:** RPM-460

**TYPE OF UNIT:** UHF Mobile Transceiver

**FCC ID:** AIERIT24-460

**IC ID:** 1084A-RIT24460

**DATE:** March 15, 2006

**PROCEDURE (CONT.):**

4. The quarterwave antenna was connected to the DUT via its cable and tested above a 0.5m x 0.5 m ground plane. The height of the field strength measurement antenna and the azimuth orientation of the antenna were varied to provide maximum field strength. The maximum levels were noted.
5. A substitution antenna, an Electro-Metrics EM-6924 adjustable dipole, was substituted for the quarterwave antenna at the RPM-460's previous location. An RF signal generator was set for the frequency of the DUT with the level at the substitution antenna noted.
6. The height of the receiving antenna was adjusted for maximum signal strength. The level at the receiving antenna was noted.

**TYPE OF EXHIBIT:** RF EXPOSURE EVALUATION  
**FCC PART:** 1.1310  
**IC PART:** RSS-119, Section 9, RSS-102  
**MANUFACTURER:** RITRON, Inc.  
**MODEL:** RPM-460  
**TYPE OF UNIT:** UHF Mobile Transceiver  
**FCC ID:** AIERIT24-460  
**IC ID:** 1084A-RIT24460  
**DATE:** March 15, 2006

**EQUATIONS FOR EIRP:**

The substitution antenna is specified from the manufacturer in terms of antenna factor rather than antenna gain. The conversion is:

$$Ga(dbd) = 20 \log f \text{ (MHz)} - AF(dB) - 31.9$$

The effective radiated power (ERP) is then:

$$ERP(dBm) = Pr(dBm) + Pgen(dBm) - Ps(dBm) - Ga(dBd)$$

Where:

Pr is the power level of the radio's emission at the receiving antenna output.

Pgen is the RF signal generator level at the substitution antenna input.

Ps is the power level of the substitution antenna emission at the receiving antenna output.

Ga is the gain of the substitution antenna.

The ERP is converted to watts from dBm by:

$$ERP(watts) = \text{antilog}_{10}((ERP(dBm) - 30)/10)$$

And finally, ERP is converted to EIRP (isotropic radiator) by:  $EIRP = 1.64 ERP$

**TYPE OF EXHIBIT:** RF EXPOSURE EVALUATION  
**FCC PART:** 1.1310  
**IC PART:** RSS-119, Section 9, RSS-102  
**MANUFACTURER:** RITRON, Inc.  
**MODEL:** RPM-460  
**TYPE OF UNIT:** UHF Mobile Transceiver  
**FCC ID:** AIERIT24-460  
**IC ID:** 1084A-RIT24460  
**DATE:** March 15, 2006

**RESULTS FOR EIRP:**

Frequency	Pr (dBm)	Pgen (dBm)	Ps (dBm)	Ga (dBd)	ERP (dBm)	EIRP (watts)
450.1 MHz	+16.0	0.0	-27.3	0.1	+43.2	33.5
460.1 MHz	+14.7	0.0	-27.5	0.1	+42.1	26.6
469.1 MHz	+14.5	0.0	-27.9	0.1	+42.3	27.9

**DETERMINING MPE DISTANCE:**

Power density is related to EIRP:

$S(W/m^2) = EIRP(W)/4\pi r^2$  where r is the distance from the source in meters.  
 Rearranging for distance:

$$r = \sqrt{(EIRP/4\pi S)}$$

The MPE (maximum permissible exposure) for a device operating in a Occupational/Controlled Exposure environment is  $f(\text{MHz})/300 \text{ mW/cm}^2$ .  
 Converting to  $W/m^2$ , the limit becomes  $f(\text{MHz})/30 \text{ W/m}^2$ . The MPE limit is substituted for S and EIRP is entered in the above equation.

**TYPE OF EXHIBIT:** RF EXPOSURE EVALUATION  
**FCC PART:** 1.1310  
**IC PART:** RSS-119, Section 9, RSS-102  
**MANUFACTURER:** RITRON, Inc.  
**MODEL:** RPM-460  
**TYPE OF UNIT:** UHF Mobile Transceiver  
**FCC ID:** AIERIT24-460  
**IC ID:** 1084A-RIT24460  
**DATE:** March 15, 2006

**RESULTS FOR MPE:**

Frequency	EIRP (watts)	Duty Cycle %	S limit W/m <sup>2</sup>	Distance cm	Distance in
450.1 MHz	33.5	50	15.0	30	12
460.1 MHz	26.6	50	15.3	26	10
469.1 MHz	27.9	50	15.6	27	11

**RF WARNING STATEMENT:**

The following statement appears in the Users Manual regarding RF safety:

The RPM-460 has been evaluated for compliance with the maximum exposure limits for RF energy at the maximum power rating of the unit with a common unity gain quarterwave magnetic mount mobile antenna. To ensure compliance with the Occupational/Controlled maximum exposure limits, please observe the following:

When the quarterwave remote magnetic mount antenna is used, mount the antenna in a location that will ensure that all persons will be at least 12 inches (30 cm) away from the antenna.

Antennas other than a quarterwave magnetic mount antenna must be tested with the RPM-460 for RF exposure compliance in the environment in which it is to be used per the FCC's OET Bulletin 65, Edition 97-01 or Industry Canada RSS-102.