

# FCC / ISED REPORT

**Class II Permissive Change** 

Applicant Name: Kenwood USA Corporation

#### Address:

1-16-2, Hakusan, Midori-ku, Yokohama-shi, Kanagawa, 226-8525 JAPAN

Date of Issue: July 19, 2018 Location: HCT CO., LTD., 74, Seoicheon-ro 578beon-gil, Majang-myeon, Icheon-si, Gyeonggi-do, 17383, Rep. of KOREA **Report No.:** HCT-RF-1807-FI006

#### ISED Registration Number: 5944A-6

FCC ID:	ALH442000
ISED: APPLICANT:	282D-442000 Kenwood USA Corporation
	NX-5400-K2 NX-5400-K3 NX-5400-E2 NX-5400-E3 TK-5430-E2 TK-5430-E3 VP5430-E2

FCC Model(s): NX-5400-K2, NX-5400-K3, NX-5400-F2, NX-5400-F3, TK-5430-F2, TK-5430-F3, VP5430-F2, VP5430-F2, VP5430-F3

ISED Model(s): NX-5400-K2, NX-5400-K3, TK-5430-F2, TK-5430-F3, VP5430-F2, VP5430-F3, VP6430-F2, VP6430-F3

EUT Type: 700/800MHZ DIGITAL TRANSCEIVER

Frequency Range: FCC : 769-775, 799-805, 806-824, 851-869 MHz

ISED : 768-776, 798 - 806, 806 – 824, 851-869 MHz

FCC Rule Part: Part 90

ISED Rule: RSS-Gen Issue 5(April 2018), RSS-119 Issue 12

Engineering Statement:

The measurements shown in this report were made in accordance with the procedures indicated, and the emissions from this

equipment were found to be within the limits applicable. I assume full responsibility for the accuracy and completeness of these measurements, and for the qualifications of all persons taking them.

HCT CO., LTD. Certifies that no party to this application has subject to a denial of Federal benefits that includes FCC benefits pursuant

to section 5301 of the Anti-Drug Abuse Act of 1998,21 U.S. C.853(a)

A

Report prepared by : Kwon Jeong Engineer of Telecommunication Testing Center

Report approved by : Jong Seok Lee Manager of Telecommunication Testing Center

This report only responds to the tested sample and may not be reproduced, except in full, without written approval of the HCT Co., Ltd.



# **Version**

TEST REPORT NO.	DATE	DESCRIPTION
HCT-RF-1807-FI006	July 19, 2018	- First Approval Report



# **Table of Contents**

1. GENERAL INFORMATION	ļ
2. EUT DESCRIPTION	,
3. TEST METHODOLOGY	)
3.1 EUT CONFIGURATION	j
3.2 EUT EXERCISE	j
3.3 GENERAL TEST PROCEDURES 6	j
3.4 DESCRIPTION OF TEST MODES 7	,
3.5 Type of Emission7	,
4. INSTRUMENT CALIBRATION	;
5. FACILITIES AND ACCREDITATIONS	;
5.1 FACILITIES	;
5.2 EQUIPMENT	
6. SUMMARY TEST OF RESULTS	)
7. TEST RESULT 1 0	)
7.1 Unwanted Emissions : Radiated Spurious Emission 1 0	1
7.2 Unwanted Emissions : Receiver Radiated Spurious Emission	1
8. LIST OF TEST EQUIPMENT 2 0	)
8.1 LIST OF TEST EQUIPMENT 2 0	)
9. APPENDIX A_ TEST SETUP PHOTO 2 1	

## **1. GENERAL INFORMATION**

Manufacturer:	Kenwood USA Corporation
Address:	3-12, Moriyacho, Kanagawa-ku, Yokohama-shi, Knagawa, 221-0022 JAPAN
FCC ID:	ALH442000
ISED:	282D-442000
EUT Type:	700/800MHZ DIGITAL TRANSCEIVER
FCC Model name(s):	NX-5400-K2, NX-5400-K3, NX-5400-F2, NX-5400-F3, TK-5430-F2, TK-5430-F3, VP5430-F2, VP5430-F3, VP6430-F2, VP6430-F3
ISED Model name(s):	NX-5400-K2, NX-5400-K3, TK-5430-F2, TK-5430-F3, VP5430-F2, VP5430-F3, VP6430-F2, VP6430-F3
Date(s) of Tests:	July 02, 2018 ~ July 11, 2018
Diago of Tooto	HCT Co., Ltd.
Place of Tests:	74, Seoicheon-ro 578beon-gil, Majang-myeon, Icheon-si, Gyeonggi-do, 17383, Korea



# 2. EUT DESCRIPTION

EUT Type	700/800MHZ DIGITAL TRANSCEIVER
FCC Model Name	NX-5400-K2, NX-5400-K3, NX-5400-F2, NX-5400-F3, TK-5430-F2, TK-5430-F3, VP5430-F2, VP5430-F3, VP6430-F2, VP6430-F3
ISED Model Name	NX-5400-K2, NX-5400-K3, TK-5430-F2, TK-5430-F3, VP5430-F2, VP5430-F3, VP6430-F2, VP6430-F3
Power Supply	DC 7.5 V
Output Power	3 W (Power output continuously variable to 1 W)
Battery type	Li-ion Battery
	(KNB-L1, KNB-L2, KNB-L3, KNB-LS7)
Channel Bandwidth	FCC/ ISED : 25kHz, 12.5 kHz, 6.25kHz
Operating	30 °C ~ +60 °C
Temperature	
Frequency Range	FCC : 769-775, 799-805, 806-824, 851-869 MHz
	ISED : 768-776, 798 - 806, 806 – 824, 851-869 MHz
Test Frequency	FCC : 769.05 MHz, 815.05 MHz, 868.95 MHz
	ISED : 768.05 MHz

# 3. TEST METHODOLOGY

TIA-603-E dated March, 2016 entitled "Land Mobile FM or PM Communications Equipment Measurement and Performance Standards" were used in the measurement.

## **3.1 EUT CONFIGURATION**

The EUT configuration for testing is installed on RF field strength measurement to meet the Commissions requirement and operating in a manner that intends to maximize its emission characteristics in a continuous normal application.

## 3.2 EUT EXERCISE

The EUT was operated in the engineering mode to fix the Tx frequency that was for the purpose of the measurements. According to its specifications, the EUT must comply with the requirements of the FCC Rules Part 2 and Part 90.

## 3.3 GENERAL TEST PROCEDURES

#### **Radiated Emissions**

Radiated emission measurements are performed in the Fully-anechoic chamber. The equipment under test is placed on a non-conductive table 3-meters away from the receive antenna in accordance with ANSI/TIA-603-E-2016 Clause 2.2.17. The turntable is rotated through 360 degrees, and the receiving antenna scans in order to determine the level of the maximized emission. The level and position of the maximized emission is recorded with the spectrum analyzer using a positive peak detector.

A half wave dipole is then substituted in place of the EUT. For emissions above 1GHz, a horn antenna is substituted in place of the EUT. The substitute antenna is driven by a signal generator and the previously recorded signal was duplicated.

The power is calculated by the following formula;

 $P_{d(dBm)} = Pg_{(dBm)} - cable loss_{(dB)} + antenna gain_{(dB)}$ 

Where:  $P_d$  is the dipole equivalent power and  $P_g$  is the generator output power into the substitution antenna.

The maximum EIRP is calculated by adding the forward power to the calibrated source plus its appropriate gain value. These steps are repeated with the receiving antenna in both vertical and horizontal polarization. the difference between the gain of the horn and an isotropic antenna are taken into consideration.



### 3.4 DESCRIPTION OF TEST MODES

The EUT has been tested under operating condition. Test program used to control the EUT for staying in continuous transmitting is programmed.

## 3.5 Type of Emission

16K0F3E	(Analogue)
14K0F3E	(Analogue)
11K0F3E	(Analogue)
8K10F1E, 8K10F1D	(P25 phase1)
8K10F1W	(P25 phase 2, TDMA)
8K30F1E, 8K30F1D, 8K30F7W	(NXDN)
7K60FXD, 7K60FXE	(DMR)
4K00F1E, 4K00F1D, 4K00F7W	(NXDN)
4K00F2D	(CWID)

# 4. INSTRUMENT CALIBRATION

The measuring equipment, which was utilized in performing the tests documented herein, has been calibrated in accordance with the manufacturer's recommendations for utilizing calibration equipments, which is traceable to recognized national standards.

# 5. FACILITIES AND ACCREDITATIONS

## 5.1 FACILITIES

The Fully-anechoic chamber and conducted measurement facility used to collect the radiated data are located at the **74**, **Seoicheon-ro 578beon-gil**, **Majang-myeon**, **Icheon-si**, **Gyeonggi-do**, **Korea**.

#### 5.2 EQUIPMENT

Radiated emissions are measured with one or more of the following types of Linearly polarized antennas: tuned dipole, bi-conical, log periodic, bi-log, and/or ridged waveguide, horn. Spectrum analyzers with pre-selectors and guasi-peak detectors are used to perform radiated measurements.

Conducted emissions are measured with Line Impedance Stabilization Networks and EMI Test

Receivers. Calibrated wideband preamplifiers, coaxial cables, and coaxial attenuators are also used for making measurements.

All receiving equipment conforms to CISPR Publication 16-1, "Radio Interference Measuring Apparatus and Measurement Methods."



# 6. SUMMARY TEST OF RESULTS

Test Description	ECC Port Section(a)	ISED Part	Teet Limit	Test
Test Description	FCC Part Section(S)	Section(s)		Result
	§2.1051,			
Field Strength of Spurious	§2.1053,	DSS110 (12/5 9)	Varies	PASS
Radiation	§2.1057,	K33119-112(5.6)		
	§90.210			
Receiver Spurious Emissions	-	RSS-Gen(7)	cf. Section 7.2	PASS



## 7. TEST RESULT

## 7.1 Unwanted Emissions : Radiated Spurious Emission

### Definition

Radiated spurious emissions are emissions from the equipment when transmitting into a

non-radiating load on a frequency or frequencies that are outside an occupied band sufficient to ensure transmission of information of required quality for the class of communications desired.

## **TEST CONFIGURATION**

#### **Below 1 GHz**



#### Above 1 GHz



#### **TEST PROCEDURE USED**

- a) Connect the equipment as illustrated.
- b) Adjust the spectrum analyzer for the following settings:
  - 1) Resolution Bandwidth = 10 kHz for spurious emissions below 1 GHz, and 1 MHz for spurious emissions above 1GHz.
  - 2) Video Bandwidth = 300 kHz for spurious emissions below 1 GHz, and 3 MHz for spurious emissions above 1 GHz.
  - 3) Sweep Speed slow enough to maintain measurement calibration.
  - 4) Detector Mode = Positive Peak.
- c) Place the transmitter to be tested on the turntable in the standard test site, or an FCC listed site compliant with ANSI C63.4-2001 clause 5.4. The transmitter is transmitting into a nonradiating load that is placed on the turntable. The RF cable to this load should be of minimum length. For transmitters with integral antennas, the tests are to be run with the unit operating into the integral antenna.
- d) For each spurious measurement the test antenna should be adjusted to the correct length for the frequency involved. This length may be determined from a calibration ruler supplied with the equipment. Measurements shall be made from the lowest radio frequency generated in the equipment to the tenth harmonic of the carrier, except for the region close to the carrier equal
  - to  $\pm$  the test bandwidth (see 1.3.4.4).
- e) Key the transmitter.
- f) For each spurious frequency, raise and lower the test antenna from 1 m to 4 m to obtain a maximum reading on the spectrum analyzer with the test antenna at horizontal polarity. Then the turntable should be rotated 360° to determine the maximum reading.

Repeat this procedure to obtain the highest possible reading. Record this maximum reading.

- g) Repeat step f) for each spurious frequency with the test antenna polarized vertically.
- h) Reconnect the equipment as illustrated.
- i) Keep the spectrum analyzer adjusted as in step b).
- j) Remove the transmitter and replace it with a substitution antenna (the antenna should be halfwavelength for each frequency involved). The center of the substitution antenna should be approximately at the same location as the center of the transmitter. At the lower frequencies, where the substitution antenna is very long, this will be impossible to achieve when the antenna is polarized vertically. In such case the lower end of the antenna should be 0.3 m above the ground.
- k) Feed the substitution antenna at the transmitter end with a signal generator connected to the antenna by means of a nonradiating cable. With the antennas at both ends horizontally polarized, and with the signal generator tuned to a particular spurious frequency, raise and lower the test antenna to obtain a maximum reading at the spectrum analyzer. Adjust the level of the signal generator output until the previously recorded maximum reading for this set of conditions is obtained. This should be done carefully repeating the adjustment of the test antenna and generator output.

I) Repeat step k) with both antennas vertically polarized for each spurious frequency.

 m) Calculate power in dBm into a reference ideal half-wave dipole antenna by reducing the readings obtained in steps k) and l) by the power loss in the cable between the generator and the antenna, and further corrected for the gain of the substitution antenna used relative to an ideal half-wave dipole antenna by the following formula:

Pd(dBm) = Pg(dBm) - cable loss (dB) + antenna gain (dB)

where:

*Pd* is the dipole equivalent power and

Pg is the generator output power into the substitution antenna.

n) The *Pd* levels record in step m) are the absolute levels of radiated spurious emissions in dBm. The radiated spurious emissions in dB can be calculated by the following:

Radiated spurious emissions (dB) =

10\*log<sub>10</sub>(TX power in watts/0.001)- *the levels in step m*)

#### Operating Mode

EUT Type	Modulation	Modulation	
(Worst case)	(Worst case)	Dallery	(MHz)
	16/0525		768.05 (ISED)
Stand along	10K0F3E		769.05 (FCC/ ISED)
Stand alone		KIND-LS7	815.05 (FCC/ ISED)
	4K00F1E, 4K00F1D, 4K00F7W		868.95 (FCC/ ISED)

#### <u>Note:</u>

All modes of operation were investigated and the worst case configuration results are reported.

#### TEST RESULTS

#### Type of Emission : 16K0F3E

Frequency : 768.05 Battery : KNB-LS7						
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)
1536.10	-32.83	-4.35	Z-H	-37.18	-13.00	24.18
2304.15	-35.69	1.21	Z-H	-34.48	-13.00	21.48
6912.45	-54.10	14.13	Z-H	-39.97	-13.00	26.97

Frequency : 769.05 Battery : KNB-LS7						
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)
1538.10	-32.94	-4.35	Z-H	-37.29	-13.00	24.29
2307.15	-38.52	1.21	Z-H	-37.31	-13.00	24.31
6921.45	-53.09	14.13	Z-H	-38.96	-13.00	25.96



Γ

Frequency : 815.05 Battery : KNB-LS7						
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)
1630.10	-32.52	-4.99	Z-H	-37.51	-13.00	24.51
2445.15	-37.55	0.24	Z-H	-37.31	-13.00	24.31
6520.40	-45.23	13.27	Z-H	-31.96	-13.00	18.96

Frequency : 868.95 Battery : KNB-LS7						
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)
1737.90	-30.05	-4.88	Z-H	-34.93	-13.00	21.93
2606.85	-50.48	0.55	Z-H	-49.93	-13.00	36.93
3475.80	-48.71	3.38	Z-H	-45.33	-13.00	32.33
5213.70	-55.26	10.22	Z-H	-45.04	-13.00	32.04
6082.65	-55.71	12.02	Z-H	-43.69	-13.00	30.69
6951.60	-53.32	14.23	Z-H	-39.09	-13.00	26.09

Г

#### FCC ID: ALH442000 / ISED : 282D-442000

#### Type of Emission : 11K0F3E

Frequency : 768.05 Battery : KNB-LS7							
Freq(MHz) Reading[dBm] Factor(dBm) Pol Result(dB) Limit(dB) Margin							
1536.10	-33.53	-4.35	Z-H	-37.88	-20.00	17.88	
2304.15	-39.42	1.21	Z-H	-38.21	-20.00	18.21	
6912.45	-54.19	14.13	Z-H	-40.06	-20.00	20.06	

Frequency : 769.05 Battery : KNB-LS7							
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)	
1538.10	-33.92	-4.35	Z-H	-38.27	-20.00	18.27	
2307.15	-37.23	1.21	Z-H	-36.02	-20.00	16.02	
6921.45	-53.97	14.13	Z-H	-39.84	-20.00	19.84	



Γ

Frequency : 815.05 Battery : KNB-LS7							
Freq(MHz) Reading[dBm] Factor(dBm) Pol Result(dB) Limit(dB) Margin/							
1630.10	1630.10 -32.82 -4.99 Z-H -37.81 -20.00 17.81						
2445.15	-36.99	0.24	Z-H	-36.75	-20.00	16.75	
6520.40	-43.21	13.27	Z-H	-29.94	-20.00	9.94	

Frequency : 868.95 Battery : KNB-LS7							
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)	
1737.90	-29.88	-4.88	Z-H	-34.76	-20.00	14.76	
2606.85	-49.81	0.55	Z-H	-49.26	-20.00	29.26	
3475.80	-48.51	3.38	Z-H	-45.13	-20.00	25.13	
6951.60	-53.65	14.23	Z-H	-39.42	-20.00	19.42	

Г

## Type of Emission : 4K00F1E, 4K00F1D, 4K00F7W

Frequency : 768.05 Battery : KNB-LS7						
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)
812.30	-82.19	32.662	Z-H	-49.53	-20.00	29.53
1536.10	-32.83	-4.35	Z-H	-37.18	-25.00	12.18
2304.15	-35.77	1.21	Z-H	-34.56	-25.00	9.56
6912.45	-54.38	14.13	Z-H	-40.25	-25.00	15.25

Frequency : 769.05 Battery : KNB-LS7							
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)	
1538.10	-33.31	-4.35	Z-H	-37.66	-25.00	12.66	
2307.15	-35.31	1.21	Z-H	-34.10	-25.00	9.10	
6921.45	-54.58	14.13	Z-H	-40.45	-25.00	15.45	

Frequency : 815.05 Battery : KNB-LS7							
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)	
1630.10	-32.16	-4.99	Z-H	-37.15	-25.00	12.15	
2445.15	-36.43	0.24	Z-H	-36.19	-25.00	11.19	
6520.40	-44.36	13.27	Z-H	-31.09	-25.00	6.09	

Frequency : 868.95 Battery : KNB-LS7							
Freq(MHz)	Reading[dBm]	Factor(dBm)	Pol	Result(dB)	Limit(dB)	Margin(dB)	
1737.90	-30.17	-4.88	Z-H	-35.05	-25.00	10.05	
2606.85	-49.95	0.55	Z-H	-49.40	-25.00	24.40	
3475.80	-50.33	3.38	Z-H	-46.95	-25.00	21.95	
6951.60	-53.77	14.23	Z-H	-39.54	-25.00	14.54	

#### 7.2 Unwanted Emissions : Receiver Radiated Spurious Emission

- ISED Rule(s) : RSS-GEN
- Test Requirements : Blow the table
- Method of testing : Radiated
- S/A. Settings:

Frequency < 1 GHz : RBW 120 kHz, VBW 300 kHz (Quasi Peak)

Frequency > 1 GHz : RBW 1 MHz, VBW 1 MHz (Peak)

- Mode of operation : Receive
- Limit :

Frequency	Field Strength
(MHz)	(microvolts/m at 3 meters)
30 – 88	100
88 - 216	150
216 – 960	200
Above 960	500

#### TEST RESULTS

Frequency Range : 30 MHz ~ 1 GHz

Frequency	Reading	Ant. factor	Cable loss	Ant. POL	Total	Limit	Margin
MHz	dBμN	dB /m	dB	(H/V)	dB $\mu \! N/m$	dBµN/m	dB
No Critical peaks found							

Above 1 GHz

Frequency	Reading	Ant. factor	Cable loss	Ant. POL	Total	Limit	Margin	
MHz	dBμN	dB /m	dB	(H/V)	dBµN/m	dBµN/m	dB	
	No Critical peaks found							



# 8. LIST OF TEST EQUIPMENT 8.1 LIST OF TEST EQUIPMENT

Manufacture	Model/ Equipment	Serial Number	Calibration Interval	Calibration Due
CERNEX	CBLU1183540B-01/ POWER AMP	26822	Annual	2019-06-14
Wainwright	WHKX 10-900-1000-15000-40SS/H.P.F	5	Annual	2018-07-21
Schwarzbeck	BBHA 9120D/ Horn Antenna	9120D-1298	Biennial	2018-10-14
REOHDE&SCHWARZ	FSV40-N/Signal Analyzer	101068-SZ	Annual	2018-09-27
Schwarzbeck	VULB9160/ Bilog Antenna	3368	Biennial	2018-10-14
Agilent	8498A / Attenuator(30 dB)	51162	Annual	2019-02-19
narda	termination	-	-	-

# 9. APPENDIX A\_ TEST SETUP PHOTO

Please refer to test setup photo file no. as follows;

No.	Description
1	HCT-RF-1807-FI006-P