

**MEASUREMENT OF MODULATION
CHARACTERISTICS**
SECTION 2.1047

MEASUREMENT 2

MEASUREMENT OF MODULATION CHARACTERISTICS

SECTION 2.1047

The modulation methods used in CDMA are completely different from those used in FM analog System. The methods used in evaluating the PCBR are described in the EIA/TAIS document IS-97 “recommended Minimum performance Standards for Base Stations Supporting Dual-Mode Wideband Spread Spectrum Cellular Mobile Stations”. The modulation quantify criteria are as follows:

1.0 Modulation Requirements – Section 10.3 of IS-97

Waveform specifications are tested by measuring the waveform quality of ρ , as defined in IS-97 Section 12.4.2.1, and code domain power as defined in 12.4.2.2.

Transmit waveform quality can be viewed as the output of a normalized matched filter. The range of values for the transmit waveform quality is from 1.0 for a perfect CDMA waveform to 0.0 for a non-CDMA signal. As an example, the base station with a 0.5 dB degradation in its transmit waveform would have a quality, ρ , of 0.89.

1.1 Required Results

Section 10.3.2.3 of IS-97 “The normal cross correlation coefficient, ρ , shall be greater than 0.912 (excess power <0.4 dB)”.

The test method and diagrams are taken from IS-97 Section 10.

1.2 Waveform Quality

- 1.2.1 Definition Waveform quality is measured by determining the normalized correlated power between the actual waveform and the identical waveform
- 1.2.2 Method of Measurement – Refer to Figure 2A. of this exhibit for functional block diagram of the test set-up.

1. Configure transmit channel as shown in Table 2.1.
2. Tune the PCBR to the test middle channel.
3. Apply a CDMA digital transmit signal from arbitrary waveform generator at the PCBR backplane that will product 15% modulation level (pilot only) of the appropriate level for full transmit power (TX_IQ_SIN_FULL) –8.24 dB.
4. Set the PCBR power level to 40 for Cellular.
5. Measure Rho. This measurement should be greater than TX_RHO limit.

Type	Number of Channels	Fraction of Power (Linear)	Fraction of Power (dB)	Comments
Pilot	1	0.2000	-7.0	Walsh 0
Sync	1	0.0471	-13.3	Walsh 32, always 1/8 rate
Paging	1	0.1882	-7.3	Walsh 1, full rate only
Traffic	6	0.09412 each	-10.3 each	Variable Walsh Assignments, full rate only

TABLE 2.1 Base Station Test Model, Nominal

1.3 Minimum Standard

The normalized cross correlation coefficient, ρ , shall be greater than 0.912 (excess power <0.4 dB).

1.4 Results

The test verified that the waveform quality factor, the normalized cross correlation coefficient, ρ , is ≥ 0.98 . It also verifies that the frequency assignment is less than (+0.05 PPM) of the frequency assignment.

Figure 2A. RHO TEST SETUP

