
INTERTEK TESTING SERVICES

Table 4(b): Channel 4

Frequency (MHz)	Effective Radiated Power (dBm)	Attenuation (dB)	Limit (dB)	Margin (dB)
925.274	-20.4	45.0	37.6	7.4
1387.900	-29.2	53.8	37.6	16.2
1850.504	-28.9	53.5	37.6	15.9
2313.184	-20.8	45.4	37.6	7.8
2775.840	-29.4	54.0	37.6	16.4
3238.476	-34.3	58.9	37.6	21.3
3701.112	-35.4	60.0	37.6	22.4

- Remark:
1. Transmission power is 24.6 dBm or -5.4 dB(W).
 2. According to Section 95.635(b7), the unwanted emission should be attenuated below TP by at least $43 + 10 \log_{10} (TP)$ dB or 37.6 dB.
 3. The test is performed according to ANSI/TIA/EIA-603-1992.

Test Engineer: Ben W. K. Ho

Date of Test: July 18, 2001

INTERTEK TESTING SERVICES

Table 4(b): Channel 11

Frequency (MHz)	Effective Radiated Power (dBm)	Attenuation (dB)	Limit (dB)	Margin (dB)
935.273	-22.4	47.0	37.6	9.4
1402.918	-27.7	52.3	37.6	14.7
1870.562	-29.2	53.8	37.6	16.2
2338.152	-20.4	45.0	37.6	7.4
2805.843	-29.0	53.6	37.6	16.0
3273.479	-32.5	57.1	37.6	19.5
3741.115	-35.0	59.6	37.6	22.0

- Remark:
1. Transmission power is 24.6 dBm or -5.4 dB(W).
 2. According to Section 95.635(b7), the unwanted emission should be attenuated below TP by at least $43 + 10 \log_{10} (TP)$ dB or 37.6 dB.
 3. The test is performed according to ANSI/TIA/EIA-603-1992.

Test Engineer: Ben W. K. Ho

Date of Test: July 18, 2001