

2003/10/17 09:31:44

DR1-74U.TXT
SYSTEM X10 BILL OF MATERIAL

PAGE 1

LEVEL	PART IDENTIFIER	DESCRIPTION	EFF DATE	QTY/ASSY	UOM	ECN	REFERENCE
0	DR1-74U	DIGITAINER PC REMOTE	20030924	1.0000	EA		
1	183010H22190	BATTERY DOOR	20030924	1.0000	EA		
1	183010H22200	FRONT LENS	20030924	1.0000	EA		
1	183010H22210	SCROLL WHEEL	20030924	1.0000	EA		
1	185000H22220	TOP CABINET	20030924	1.0000	EA		
1	185000H22230	BOTTOM CABINET	20030924	1.0000	EA		
1	275000H12280	RUBBER KEYPAD	20030924	1.0000	EA		
1	403011H10150A	SPRING (C)	20030924	1.0000	EA		
1	851001H11791	PCB ASSY, RF 433.92MHZ	20030925	1.0000	EA		
.2	038010H10513-2	433 MC LABEL	20030328	1.0000	EA		
.2	042010H11118B	PCB	20030626	1.0000	EA	016491	
.2	076-10000012	CAP-MCC 10P .25P NPO 0603	20030730	2.0000	EA	016630	c6,12
.2	076-10400014	CAP-MCC 100N 10% X7R 0603	20030328	1.0000	EA		c4,14
.2	076-10900012	CAP-MCC 1P .25P NPO 0603	20030328	2.0000	EA	016630	c21,18
.2	076-15000012	CAP-MCC 15P 5% NPO 0603	20030730	1.0000	EA	016630	c9
.2	076-15900012	CAP-MCC 1P5 .25P NPO 0603	20030526	1.0000	EA	016630	c5
.2	076-18900012	CAP-MCC 1P8 .25P NPO 0603	20030328	1.0000	EA	016382	c17
.2	076-22000012	CAP-MCC 22P 5% NPO 0603	20030328	1.0000	EA	016630	c15
.2	076-30900012	CAP-MCC 3P .25P NPO 0603	20030328	1.0000	EA		c13
.2	076-40900012	CAP-MCC 4P .25P NPO 0603	20030328	2.0000	EA	016630	c10,11
.2	076-50800012	CAP-MCC 0P5 .25P NPO 0603	20030328	1.0000	EA		c16

DR1-74U.TXT						
.2	076-56000012	CAP-MCC 56P 5% NPO 0603	20030328	1.0000	EA	C8
.2	076-60900012	CAP-MCC 6P .25P NPO 0603	20030903	1.0000	EA 016737	C3
.2	076-70900012	CAP-MCC 7P .25P NPO 0603	20030328	1.0000	EA	C19
.2	080-00000010	SAW RESONATOR 433.92MHZ	20030328	1.0000	EA 016641	SAW1
.2	160-33800001	INDUCTOR 330NH 10%	20030526	1.0000	EA 016382	L2
.2	160-47700012	INDUCTOR 47N 10% 0603 SMD	20030730	1.0000	EA 016692	L1
.2	209-00000003	TRS-NPN 2SC3356 SMD	20030328	2.0000	EA	Q1,2
.2	241-00000003	RES-TFC 0R 5% 1/10W 0603	20030610	1.0000	EA 016441	R4
.2	241-10100003	RES-TFC 100R 5% 1/10W0603	20030328	1.0000	EA 016382	R6
.2	241-15100003	RES-TFC 150R 5% 1/10W0603	20030526	1.0000	EA 016382	R3
.2	241-68200003	RES-TFC 6K8 5% 1/10W 0603	20030328	3.0000	EA 016382	R1,2,5
.2	358-60821001	WIRE-JUMPER D=0.6MM	20030328	3.0000	EA	
1	851001H11944	PCB ASSY	20030925	1.0000	EA	
.2	042010H11196A	PCB	20030925	1.0000	EA	
.2	055-10250420	*CAP-C 1000P +/-10% 25V	20030925	1.0000	EA	C6
.2	057-10100019	CAP-E 100U 20% 10V	20030925	1.0000	EA	C7
.2	080001H10050	4MHZ RESONATOR W/2 CAP	20030925	1.0000	EA	Y1
.2	160-68100000	INDUCTOR 680UH 20%	20030925	1.0000	EA	L1
.2	209-00000001	TRS-NPN 2N3904 SMD	20030925	1.0000	EA	TR1
.2	211328H10145	IC PIC12C508 SMD	20031003	1.0000	EA	U2
.2	211328H10252	IC EM78P447S SMD	20030925	1.0000	EA	U1
.2	220-00000014	LED BLUE 3MM DIA	20030925	1.0000	EA	LED1
.2	240-10406011	RES-CF 100K +/-5% 1/8W	20030925	1.0000	EA	R6

			DR1-74U.TXT			
.2	240-10506011	RES-CF 1M +/-5% 1/8W	20030925	1.0000	EA	R4
.2	240-33906011	RES-CF 3R3 +/-5% 1/8W	20030925	1.0000	EA	R3
.2	240-68106011	RES-CF 680R +/-5% 1/8W	20030925	1.0000	EA	R5
.2	283-00000037	ENCODER SWITCH	20030925	1.0000	EA	SW1
.2	283011H10000	TAC-SW, 1P1T, 6X3.5X5	20030925	1.0000	EA	
.2	358-60821001	WIRE-JUMPER D=0.6MM	20030925	4.0000	EA	
.2	403011H10272	SPRING CONTACT (+VE)	20030925	1.0000	EA	
.2	403011H10307	SPRING CONTACT (-VE)	20030925	1.0000	EA	
.2	403011H10311	SPRING	20030925	1.0000	EA	

□