

英文名称	数量	位置号
Left headphone motherboard	1	
SMD. CAP 0201 10V 470nF ±10% X5R	5	C1, C13, C14, C4, C6
SMD CAP 0402 6.3V 4.7 μF ±20% X5R	2	C3, C5
SMD CAP 0201 6.3V 2.2 μF ±20% X5R	9	C12, C24, C25, C26, C27, C28, C7, C8, C9
SMD CAP 0201 10V 1 μF ±20% X5R	4	C10, C34, C37, C79
SMD CAP 0201 50V 1.5pF ±0.05pF HQC	1	C11
SMD. CAP 01005 25V 100pF ±5% NPO	2	C18, C19
SMD. CAP 01005 25V 15pF ±5% NPO	6	C35, C36, C38, C39, C45, C46
SMD. CAP 01005 25V 10pF ±5% NPO	1	C2
Chip capacitor 01005 6.3v 100nF ±10% X5R	5	C148, C149, C155, C16, C23
SMD LED 0603 RGB:180-360/450-900/72-140mc	1	D1
ESD73111CZ DWN0603-2L +/-5V 0.15pF TVS di	3	ESD1, ESD14, ESD2
Chip Bead 0201 1000 Ω ±25% 0.2A	2	FB1, FB2
带通滤波器 1608 2400-2500MHZ 2.1dB	1	FB3
Inductor 0603 4.7uH±20% 0.5A	2	L1, L2
MSM381A2718Z6ZM2 MEMS silicon microphone	2	MIC1, MIC2
Channel N MOSFET SSC8122GN1 DFN1006	3	Q1, Q2, Q4
P channel enhancement mode MOSFET CJBB313	1	Q3
SMD resistor 0 Ω 1/32W +/-5% 01005	2	R2, R59
Chip resistor 10K 1/32W +/-5% 01005	4	R13, R138, R3, R5
SMD RES 220K Ω 1/20W ±5% 0201	1	R8
Patch resistor 1M 1/32W ±5% 01005	1	R9
SMD RES 300K Ω 1/32W ±1% 01005	1	R10
Chip resistor 100K Ω 1/32W ±5% 01005	2	R11, R4
Chip resistor 1K 1/32W +/-5% 01005	3	R133, R22, R23
Chip resistor 100K 1/32W +/-1% 01005	1	R17
NTC thermistor 100K 1% 0201	1	R18
SMD Resistor 51 Ω 1/32W +/-5% 01005	1	R29
Tact switch 3.0*2.0*0.6 110gf±20gf	1	SW1
QCC3040 VFBGA-90 Bluetooth IC	1	U1
SGM41100A-445009 UTDFN-1.5×2-6L Battery	1	U104
CRYSTAL 32MHz ±10ppm 6pF 50 Ω SX-2016	1	Y1
Antenna Spring	2	P1, P2
MIC dust cloth	2	
PCB label	1	
SMD resistor 100 Ω 1/32W ±5% 01005	2	R14, R16

SMD. RES 6.8Ω 1/20W ±1% 0201	2	R20, R21
SMD RES 150Ω 1/20W ±5% 0201	1	R15
SMD Inductor 0201 15nH±5% 0.25A	2	L4, L5
SMD. CAP 0201 50V 1.2pF +/-0.05pF HQC	1	C15
SMD IND 0201 1.8±0.1nH 0.6A	1	R1
Right headphone motherboard	1	
SMD. CAP 0201 10V 470nF ±10% X5R	5	C101, C104, C106, C113, C114
SMD CAP 0402 6.3V 4.7μF ±20% X5R	2	C103, C105
SMD CAP 0201 6.3V 2.2μF ±20% X5R	9	C107, C108, C109, C112, C124, C125, C126, C127, C128
SMD CAP 0201 10V 1μF ±20% X5R	4	C110, C134, C137, C150
SMD CAP 0201 50V 1.5pF ±0.05pF HQC	1	C111
SMD. CAP 01005 25V 100pF ±5% NPO	2	C153, C154
SMD. CAP 01005 25V 15pF ±5% NPO	6	C135, C136, C138, C139, C145, C146
SMD. CAP 01005 25V 10pF ±5% NPO	1	C102
Chip capacitor 01005 6.3v 100nF ±10% X5R	5	C116, C123, C151, C152, C156
SMD LED 0603 RGB:180-360/450-900/72-140mc	1	D101
ESD73111CZ DWN0603-2L +/-5V 0.15pF TVS di	3	ESD101, ESD 102, ESD114
Chip Bead 0201 1000Ω ±25% 0.2A	2	FB101, FB10 2
带通滤波器 1608 2400-2500MHZ 2.1dB	1	FB103
Inductor 0603 4.7uH±20% 0.5A	2	L101, L102
MSM381A2718Z6ZM2 MEMS silicon microphone	2	MIC101, MIC 102
Channel N MOSFET SSC8122GN1 DFN1006	3	Q101, Q102, Q104
P channel enhancement mode MOSFET CJBB313	1	Q103
SMD resistor 0Ω 1/32W +/-5% 01005	2	R102, R134
Chip resistor 10K 1/32W +/-5% 01005	4	R103, R105, R113, R139
SMD RES 220KΩ 1/20W ±5% 0201	1	R108
Patch resistor 1M 1/32W ±5% 01005	1	R109
SMD RES 300KΩ 1/32W ±1% 01005	1	R110
Chip resistor 100KΩ 1/32W ±5% 01005	2	R104, R111
Chip resistor 1K 1/32W +/-5% 01005	3	R122, R123, R135
Chip resistor 100K 1/32W +/-1% 01005	1	R117

NTC thermistor 100K 1% 0201	1	R118
SMD Resistor 51Ω 1/32W +/-5% 01005	1	R129
Tact switch 3.0*2.0*0.6 110gf±20gf	1	SW101
QCC3040 VFBGA-90 Bluetooth IC	1	U101
SGM41100A-445009 UTDFN-1.5×2-6L Battery	1	U105
CRYSTAL 32MHz ±10ppm 6pF 50Ω SX-2016	1	Y101
Antenna Spring	2	P101, P102
MIC dust cloth	2	
PCB label	1	
SMD. RES 6.8Ω 1/20W ±1% 0201	2	R120, R121
SMD resistor 100Ω 1/32W ±5% 01005	2	R114, R116
SMD Inductor 0201 15nH±5% 0.25A	2	L104, L105
SMD. CAP 0201 50V 1.2pF +/-0.05pF HQC	1	C115
SMD IND 0201 1.8±0.1nH 0.6A	1	R101
SMD RES 150Ω 1/20W ±5% 0201	1	R115