




## G.1 LTE Downlink Only Carrier Aggregation Test Selection and Setup

SAR test exclusion for LTE downlink Carrier Aggregation is determined by power measurements according to the number component carriers (CCs) supported by the product implementation. For those configurations required by April 2018 TCBC Workshop Notes, conducted power measurements with LTE Carrier Aggregation (CA) (downlink only) active are made in accordance to KDB Publication 941225 D05Av01r02. The RRC connection is only handled by one cell, the primary component carrier (PCC) for downlink and uplink communications. After making a data connection to the PCC, the UE device adds secondary component carrier(s) (SCC) on the downlink only. All uplink communications and acknowledgements remain identical to specifications when downlink carrier aggregation is inactive on the PCC. Additional conducted output powers are measured with the downlink carrier aggregation active for the configuration with highest measured maximum conducted power with downlink carrier aggregation inactive measured among the channel bandwidth, modulation, and RB combinations in each frequency band.

Per FCC KDB Publication 941225 D05Av01r02, no SAR measurements are required for carrier aggregation configurations when the maximum average output power with downlink only carrier aggregation active is not more than 0.25 dB higher than the average output power with downlink only carrier aggregation inactive. All bands required for SAR testing per FCC KDB procedures were considered. Based on the measured maximum powers below, no additional SAR tests were required for DLCA SAR configurations.

General PCC and SCC configuration selection procedure

- PCC uplink channel, channel bandwidth, modulation and RB configurations were selected based on section C)3)b)ii) of KDB 941225 D05 V01r02. All LTE bandwidth conducted powers needed for PCC uplink configuration selection can be found in RF Conducted Powers Section and LTE/NR Lower Bandwidth RF Conducted Powers Appendix. The downlink PCC channel was paired with the selected PCC uplink channel according to normal configurations without carrier aggregation.
- To maximize aggregated bandwidth, highest channel bandwidth available for that CA combination was selected for SCC. For inter-band CA, the SCC downlink channels were selected near the middle of their transmission bands. For contiguous intra-band CA, the downlink channel spacing between the component carriers was set to multiple of 300 kHz less than the nominal channel spacing defined in section 5.4.1A of 3GPP TS 36.521. For non-contiguous intra-band CA, the downlink channel spacing between the component carriers was set to be larger than the nominal channel spacing and provided maximum separation between the component carriers.
- All selected PCC and SCC(s) remained fully within the uplink/downlink transmission band of the respective component carrier.



**Figure G-1**  
**DL CA Power Measurement Setup**

FCC ID: BCGA2899	SAR EVALUATION REPORT	Approved by: Technical Manager
DUT Type: Tablet Device		APPENDIX G: Page 2 of 13









### G.3 DL CA with DL 4x4 MIMO RF Conduction Powers

This device supports downlink 4x4 MIMO operations for some LTE bands. Uplink transmission is limited to a single output stream. When carrier aggregation was applicable, the general test selection and setup procedures described in Section G.1 were applied.

Per May 2017 TCB Workshop Notes, SAR for 4x4 DL MIMO was not needed since the maximum average output power in 4x4 DL MIMO mode was not more than 0.25 dB higher than the maximum output power with 4x4 DL MIMO inactive. Additionally, SAR for 4x4 MIMO Downlink Carrier Aggregation was not needed since the maximum average output power in 4x4 MIMO Downlink Carrier Aggregation mode was not more than 0.25 dB higher than the maximum output power with 4x4 MIMO Downlink and downlink carrier aggregation inactive.

#### G.3.1 LTE 4x4 MIMO DL Standalone Powers

**Table G-15**  
Maximum Output Powers - Antenna 1b

LTE Band	Bandwidth [MHz]	Channel	Frequency [MHz]	Modulation	RB Size	RB Offset	4x4 DL MIMO Tx. Power [dBm]	Single Antenna Tx. Power [dBm]	Target Power [dBm]
7	5	21425	2567.5	16QAM	1	12	12.00	11.79	11.4

**Table G-16**  
Maximum Output Powers - Antenna 2

LTE Band	Bandwidth [MHz]	Channel	Frequency [MHz]	Modulation	RB Size	RB Offset	4x4 DL MIMO Tx. Power [dBm]	Single Antenna Tx. Power [dBm]	Target Power [dBm]
25	5	26365	1882.5	256QAM	1	12	15.05	14.91	14.5

**Table G-17**  
Maximum Output Powers - Antenna 3b

LTE Band	Bandwidth [MHz]	Channel	Frequency [MHz]	Modulation	RB Size	RB Offset	4x4 DL MIMO Tx. Power [dBm]	Single Antenna Tx. Power [dBm]	Target Power [dBm]
41	20	40620	2593	QPSK	50	25	14.20	14.17	14.0

**Table G-18**  
Maximum Output Powers - Antenna 4

LTE Band	Bandwidth [MHz]	Channel	Frequency [MHz]	Modulation	RB Size	RB Offset	4x4 DL MIMO Tx. Power [dBm]	Single Antenna Tx. Power [dBm]	Target Power [dBm]
66	10	132022	1715	16QAM	1	49	14.96	14.78	14.6
30	10	27710	2310	QPSK	25	12	14.39	14.36	14.5
48	5	56715	3697.5	64QAM	1	12	12.60	12.56	11.9

FCC ID: BCGA2899	SAR EVALUATION REPORT	Approved by: Technical Manager
DUT Type: Tablet Device		APPENDIX G: Page 7 of 13













## G.4 Additional Downlink Carrier Aggregation with Uplink Carrier Aggregation Enabled

This device supports uplink carrier aggregation (ULCA) with additional Carrier Aggregation configurations active in the downlink. Power measurements were performed with ULCA active and additional CA configurations active in the downlink for the configuration per Fall 2017 TCB Workshop Notes.

Per FCC Guidance, additional SAR measurements for these configurations were not required since their maximum output power was not more than 0.25 dB higher than the maximum output power for with only CA\_7C, CA\_41C, or CA\_48C ULCA active.

### G.4.1 Additional DL Carrier Aggregation RF Conducted Powers with Uplink Carrier Aggregation Enabled

**Table G-31**  
Maximum Output Powers LTE Band 41

Combination	PCC										SCC1										SCC2										SCC3										SCC4										Power	
	PCC Band	PCC BW [MHz]	PCC [UL] Ch.	PCC [UL] Freq. [MHz]	Mod.	PCC UL# RB	PCC UL RB Offset	PCC [DL] Ch.	PCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	Mod.	SCC UL# RB	SCC UL RB Offset	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	Mod.	SCC UL# RB	SCC UL RB Offset	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	ULCA Tx Power with DL CA Enabled (dBm)	ULCA Tx Power (dBm)											
CA_41C41A	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	15.33	15.23										
CA_41C41B	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	15.33	15.23										
CA_41C41C	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	15.33	15.23										
CA_41E	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	15.33	15.23										
CA_41C41D	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	15.33	15.23										
CA_41C41E	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	QPSK	50	0	40020	2503	LTE B41	20	40020	2503	15.33	15.23										

**Table G-32**  
Maximum Output Powers LTE Band 48

Combination	PCC										SCC1										SCC2										SCC3										Power	
	PCC Band	PCC BW [MHz]	PCC [UL] Ch.	PCC [UL] Freq. [MHz]	Mod.	PCC UL# RB	PCC UL RB Offset	PCC [DL] Ch.	PCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [UL] Ch.	SCC [UL] Freq. [MHz]	Mod.	SCC UL# RB	SCC UL RB Offset	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	Mod.	SCC UL# RB	SCC UL RB Offset	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	ULCA Tx Power with DL CA Enabled (dBm)	ULCA Tx Power (dBm)					
CA_48D	LTE B48	20	56207	3646.7	QPSK	50	50	56207	3646.7	LTE B48	20	56405	3666.5	QPSK	50	0	56405	3666.5	LTE B48	20	56009	3626.9	QPSK	50	0	56009	3626.9	LTE B48	20	56009	3626.9	LTE B48	20	55811	3607.1	12.05	11.97					
CA_48E	LTE B48	20	56207	3646.7	QPSK	50	50	56207	3646.7	LTE B48	20	56405	3666.5	QPSK	50	0	56405	3666.5	LTE B48	20	56009	3626.9	QPSK	50	0	56009	3626.9	LTE B48	20	56009	3626.9	LTE B48	20	55811	3607.1	12.18	11.97					

### G.4.2 Additional 4x4 MIMO DL Carrier Aggregation RF Conducted Powers with Uplink Carrier Aggregation Enabled

Note: 4x4 DL MIMO is only operating in the downlink. Uplink transmission is limited to a single output stream for each component carrier of ULCA.

**Table G-33**  
Maximum Output Powers LTE Band 7

Combination	PCC										SCC1										Power	
	PCC Band	PCC BW [MHz]	PCC [UL] Ch.	PCC [UL] Freq. [MHz]	Mod.	PCC UL# RB	PCC UL RB Offset	PCC [DL] Ch.	PCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [UL] Ch.	SCC [UL] Freq. [MHz]	DL Ant. Config.	ULCA Tx Power with DL CA Enabled (dBm)	ULCA Tx Power (dBm)					
CA_7[C]	LTE B7	20	20850	2510	QPSK	1	99	2850	2630	4x4	LTE B7	20	21048	2529.8	QPSK	1	0	3048	2649.8	4x4	15.50	15.55

**Table G-34**  
Maximum Output Powers LTE Band 41

Combination	PCC										SCC1										SCC2										SCC3										SCC4										Power	
	PCC Band	PCC BW [MHz]	PCC [UL] Ch.	PCC [UL] Freq. [MHz]	Mod.	PCC UL# RB	PCC UL RB Offset	PCC [DL] Ch.	PCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [UL] Ch.	SCC [UL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	DL Ant. Config.	ULCA Tx Power with DL CA Enabled (dBm)	ULCA Tx Power (dBm)															
CA_41C41A	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	4x4	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	15.33	15.23											
CA_41C41B	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	4x4	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	15.33	15.23											
CA_41C41C	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	4x4	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	15.33	15.23											
CA_41E	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	4x4	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	15.33	15.23											
CA_41C41D	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	4x4	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	15.33	15.23											
CA_41C41E	LTE B41	20	38750	2506	QPSK	50	50	38750	2506	4x4	LTE B41	20	39948	2525.8	QPSK	50	0	39948	2525.8	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	4x4	LTE B41	20	40020	2503	15.33	15.23											



**Table G-35**  
**Maximum Output Powers LTE Band 48**

Combination	PCC										SCC1					SCC2					SCC3					Power						
	PCC Band	PCC BW [MHz]	PCC [U] Ch.	PCC [U] Freq. [MHz]	Mod.	PCC UL RB	PCC UL RB Offset	PCC [DL] Ch.	PCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [U] Ch.	SCC [U] Freq. [MHz]	Mod.	SCC UL RB	SCC UL RB Offset	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [U] Ch.	SCC [U] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [U] Ch.	SCC [U] Freq. [MHz]	DL Ant. Config.	ULCA Tx Power with DL CA Enabled (dBm)	ULCA Tx Power (dBm)
CA_148C	LTE B48	20	56207	3646.7	QPSK	50	50	56207	3646.7	4x4	LTE B48	20	56485	3666.5	QPSK	50	0	56485	3666.5	4x4	LTE B48	20	56207	3646.7	4x4	LTE B48	20	56207	3646.7	4x4	12.03	11.97
CA_148D	LTE B48	20	56207	3646.7	QPSK	50	50	56207	3646.7	4x4	LTE B48	20	56485	3666.5	QPSK	50	0	56485	3666.5	4x4	LTE B48	20	56207	3646.7	4x4	LTE B48	20	56207	3646.7	4x4	11.96	11.97
CA_148E	LTE B48	20	56207	3646.7	QPSK	50	50	56207	3646.7	4x4	LTE B48	20	56485	3666.5	QPSK	50	0	56485	3666.5	4x4	LTE B48	20	56207	3646.7	4x4	LTE B48	20	56207	3646.7	4x4	12.00	11.97

## G.5 Downlink Carrier Aggregation with Inter-band Uplink Carrier Aggregation enabled

This device supports inter-band uplink carrier aggregation (ULCA) with additional Carrier Aggregation configurations active in the downlink. Power measurements were performed with inter-band ULCA active and additional CA configurations active in the downlink for the configuration per Fall 2017 TCB Workshop Notes.

Per FCC Guidance, additional SAR measurements for these configurations were not required since their maximum output power was not more than 0.25 dB higher than the maximum output power for with only ULCA active.

### G.5.1 DL Carrier Aggregation RF Conducted Powers

**Table G-36**  
**Maximum Output Powers**

Combination	PCC										SCC1					SCC2					SCC3					SCC4					Power	
	PCC Band	PCC BW [MHz]	PCC [U] Ch.	PCC [U] Freq. [MHz]	Modulation	PCC UL RB	PCC UL RB Offset	PCC [DL] Ch.	PCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [U] Ch.	SCC [U] Freq. [MHz]	Modulation	SCC UL RB	SCC UL RB Offset	SCC [DL] Ch.	SCC [DL] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [U] Ch.	SCC [U] Freq. [MHz]	DL Ant. Config.	SCC Band	SCC BW [MHz]	SCC [U] Ch.	SCC [U] Freq. [MHz]	DL Ant. Config.	ULCA Tx Power with DL CA active (dBm)	ULCA Tx Power (dBm)
CA_148A-148A	CA_148A-148A	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148A	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148A	15	8121	1500	2x2	CA_148A-148A	15	8121	1500	2x2	12.00	11.97
CA_148A-148B	CA_148A-148B	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148B	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148B	15	8121	1500	2x2	CA_148A-148B	15	8121	1500	2x2	12.00	11.97
CA_148A-148C	CA_148A-148C	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148C	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148C	15	8121	1500	2x2	CA_148A-148C	15	8121	1500	2x2	12.00	11.97
CA_148A-148D	CA_148A-148D	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148D	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148D	15	8121	1500	2x2	CA_148A-148D	15	8121	1500	2x2	12.00	11.97
CA_148A-148E	CA_148A-148E	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148E	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148E	15	8121	1500	2x2	CA_148A-148E	15	8121	1500	2x2	12.00	11.97
CA_148A-148F	CA_148A-148F	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148F	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148F	15	8121	1500	2x2	CA_148A-148F	15	8121	1500	2x2	12.00	11.97
CA_148A-148G	CA_148A-148G	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148G	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148G	15	8121	1500	2x2	CA_148A-148G	15	8121	1500	2x2	12.00	11.97
CA_148A-148H	CA_148A-148H	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148H	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148H	15	8121	1500	2x2	CA_148A-148H	15	8121	1500	2x2	12.00	11.97
CA_148A-148I	CA_148A-148I	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148I	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148I	15	8121	1500	2x2	CA_148A-148I	15	8121	1500	2x2	12.00	11.97
CA_148A-148J	CA_148A-148J	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148J	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148J	15	8121	1500	2x2	CA_148A-148J	15	8121	1500	2x2	12.00	11.97
CA_148A-148K	CA_148A-148K	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148K	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148K	15	8121	1500	2x2	CA_148A-148K	15	8121	1500	2x2	12.00	11.97
CA_148A-148L	CA_148A-148L	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148L	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148L	15	8121	1500	2x2	CA_148A-148L	15	8121	1500	2x2	12.00	11.97
CA_148A-148M	CA_148A-148M	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148M	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148M	15	8121	1500	2x2	CA_148A-148M	15	8121	1500	2x2	12.00	11.97
CA_148A-148N	CA_148A-148N	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148N	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148N	15	8121	1500	2x2	CA_148A-148N	15	8121	1500	2x2	12.00	11.97
CA_148A-148O	CA_148A-148O	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148O	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148O	15	8121	1500	2x2	CA_148A-148O	15	8121	1500	2x2	12.00	11.97
CA_148A-148P	CA_148A-148P	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148P	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148P	15	8121	1500	2x2	CA_148A-148P	15	8121	1500	2x2	12.00	11.97
CA_148A-148Q	CA_148A-148Q	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148Q	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148Q	15	8121	1500	2x2	CA_148A-148Q	15	8121	1500	2x2	12.00	11.97
CA_148A-148R	CA_148A-148R	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148R	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148R	15	8121	1500	2x2	CA_148A-148R	15	8121	1500	2x2	12.00	11.97
CA_148A-148S	CA_148A-148S	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148S	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148S	15	8121	1500	2x2	CA_148A-148S	15	8121	1500	2x2	12.00	11.97
CA_148A-148T	CA_148A-148T	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148T	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148T	15	8121	1500	2x2	CA_148A-148T	15	8121	1500	2x2	12.00	11.97
CA_148A-148U	CA_148A-148U	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148U	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148U	15	8121	1500	2x2	CA_148A-148U	15	8121	1500	2x2	12.00	11.97
CA_148A-148V	CA_148A-148V	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148V	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148V	15	8121	1500	2x2	CA_148A-148V	15	8121	1500	2x2	12.00	11.97
CA_148A-148W	CA_148A-148W	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148W	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148W	15	8121	1500	2x2	CA_148A-148W	15	8121	1500	2x2	12.00	11.97
CA_148A-148X	CA_148A-148X	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148X	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148X	15	8121	1500	2x2	CA_148A-148X	15	8121	1500	2x2	12.00	11.97
CA_148A-148Y	CA_148A-148Y	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148Y	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148Y	15	8121	1500	2x2	CA_148A-148Y	15	8121	1500	2x2	12.00	11.97
CA_148A-148Z	CA_148A-148Z	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148Z	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148Z	15	8121	1500	2x2	CA_148A-148Z	15	8121	1500	2x2	12.00	11.97
CA_148A-148AA	CA_148A-148AA	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148AA	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148AA	15	8121	1500	2x2	CA_148A-148AA	15	8121	1500	2x2	12.00	11.97
CA_148A-148AB	CA_148A-148AB	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148AB	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148AB	15	8121	1500	2x2	CA_148A-148AB	15	8121	1500	2x2	12.00	11.97
CA_148A-148AC	CA_148A-148AC	15	8121	1500	QPSK	1	25	8121	1500	2x2	CA_148A-148AC</																					