

### MPE Calculation

RF feature(Worst Mode)	Frequency range (MHz)	Normal Target Power(dBm) <sup>Note1</sup>	Tolerance (dB)	ANT Gain (dBi) <sup>Note2</sup>	Maximum EIRP (dBm)	Maximum EIRP (mW)	Maximum power density (mW/cm <sup>2</sup> )	Requirement (mW/cm <sup>2</sup> )
NR Band n2(ANT1)	1850.00 ~ 1910.00	23.00	2.70	1.88	27.58	572.797	0.114 0	1.000 0
NR Band n5(ANT2)	824.00 ~ 849.00	23.00	2.70	-0.01	25.69	370.681	0.073 8	0.549 0
NR Band n12(ANT1)	699.00 ~ 716.00	23.00	2.70	-1.15	24.55	285.102	0.056 8	0.466 0
NR Band n66(ANT1)	1710.00 ~ 1780.00	23.00	2.70	0.18	25.88	387.258	0.077 1	1.000 0
NR Band n77(ANT2)	3450.00 ~ 3550.00	22.50	2.50	-1.13	23.87	243.782	0.048 5	1.000 0
NR Band n77(ANT2)	3700.00 ~ 3980.00	22.50	2.50	-2.36	22.64	183.654	0.036 6	1.000 0
Band14(ANT2)	788.00 ~ 798.00	23.00	2.70	-0.54	25.16	328.096	0.065 3	0.525 0
	~							
	~							
	~							
	~							
	~							

Note1: Please refer to the operation description for Max tune-up power.

Note2: including path loss between conducted test feeding point and antenna feeding point.

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user.

The MPE sample calculation for this exposure is shown below.

$$\begin{aligned}
 S &= \text{EIRP} / (4 R^2 \pi) \\
 &= 572.797 / (4 \times 20^2 \times \pi) \\
 &= 0.114 \text{ mW/cm}^2
 \end{aligned}$$

**- Note**

S= Maximum power density(mW/cm<sup>2</sup>)

EIRP= Equivalent Isotropic Radiated Power(mW)

R= Distance to the center of the radiation of the antenna(20cm)

**▪ Limits for Maximum Permissible Exposure (MPE)**

Frequency range (MHz)	Electric Field strength (V/m)	Magnetic field strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Averaging time (minutes)
0.3 ~ 1.34	614	1.63	*100	30
1.34 ~ 30	824/f	2.19 / f	*180 / f <sup>2</sup>	30
30 ~ 300	27.5	0.073	0.2	30
300 ~ 1,500			f / 1500	30
1,500 ~ 100,000			1.0	30

**Conclusion : The exposure condition of this device is compliant with FCC**