

- RF Exposure

1. EUT Information

Applicant	MOTREX CO., LTD.
Address of Applicant	1-1103 Ace High-Tech City B/D, 55-20, Mullae-dong3(sam)-ga, Yeongdeungpo-gu, Seoul, South Korea
Manufacturer	MOTREX CO., LTD.
Address of Manufacturer	1-1103 Ace High-Tech City B/D, 55-20, Mullae-dong3(sam)-ga, Yeongdeungpo-gu, Seoul, South Korea
Type of equipment	Smart display
Basic Model	MTXM100JA
FCC ID	BP9-MTXM100JA

1. Regulation

According to §15.247(i), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See § 1.1307(b)(1) of this Chapter.

Limits for Maximum Permissible Exposure: RF exposure is calculated.

Frequency Range	Electric Field Strength [V/m]	Magnetic Field Strength [A/m]	Power Density [mW/cm ²]	Averaging Time [minute]
Limits for General Population / Uncontrolled Exposure				
0.3 ~ 1.34	614	1.63	*(100)	30
1.34 ~ 30	824/f	2.19/f	*(180/f ²)	30
30 ~ 300	27.5	0.073	0.2	30
300 ~ 1 500	/	/	f/1 500	30
1 500 ~ 15 000	/	/	1.0	30

f=frequency in MHz, *= plane-wave equivalent power density

MPE (Maximum Permissible Exposure) Prediction

Predication of MPE limit at a given distance: Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2 \quad (\Rightarrow R = \sqrt{PG/4\pi S})$$

S = power density [mW/cm²]

P = Power input to antenna [mW]

G = Power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna [cm]

2. RF Exposure Compliance Issue

The information should be included in the user's manual:

This appliance and its antenna must not be co-located or operation in conjunction with any other antenna or transmitter. A minimum separation distance of 20 cm must be maintained between the antenna and the person for this appliance to satisfy the RF exposure requirements.

3. Calculation Result of RF Exposure

Mode	Target power [dBm]	Tune up tolerance [dB]	Max tune up power [dBm]	Max tune up power [mW]	Ant Gain [dBi]	Ant Gain [mW]	Power Density at 20 cm [mW/cm ²]	Limit [mW/cm ²]
Bluetooth_GFSK	5	±2.0	7	5.01	1.99	1.58	0.001 58	1.000 00
Total	-						0.001 58	1.000 00

4. Target power and tolerance, Max tuneup power

Mode	Target power [dBm]	Tolerance [dB]	Max tuneup power [dBm]	Average Power [dBm]
Bluetooth_GFSK Lowest	5	±2.0	7	5.82
Bluetooth_GFSK Middle	5	±2.0	7	5.44
Bluetooth_GFSK Highest	5	±2.0	7	5.13
Bluetooth_π/4QPSK Lowest	1	±2.0	3	2.22
Bluetooth_π/4QPSK Middle	1	±2.0	3	1.60
Bluetooth_π/4QPSK Highest	1	±2.0	3	1.22
Bluetooth_8DPSK Lowest	1	±2.0	3	2.02
Bluetooth_8DPSK Middle	1	±2.0	3	1.48
Bluetooth_8DPSK Highest	1	±2.0	3	1.19