

31LT Lavalier Microphone with body-pack transmitter:
31IT Instrument body-pack transmitter:

- (1) Open the battery compartment lid by sliding it down and raising it.
- (2) Insert one 9 volt battery into the compartment. Make sure battery polarity is correct.
- (3) Frequency Label
The Frequency label indicates what frequency in MHz the transmitter broadcasts on. The AZDEN receiver in use must also be on the same frequency.
- (4) 31IT 1/4-inch plug: Plugs into output on electric guitars and keyboards.
31LT lavalier mic: Clips onto a tie, lapel, etc.
The transmitter's cable doubles as an antenna. Extend the cable as much as possible for the best performance.
- (5) Audio Input Level Control
Turn clockwise to increase, or counterclockwise to decrease the input level. A small screwdriver is supplied to make adjustments. The level control is factory-preset in the center position.
- (6) 3 Position Switch
The left position: OFF
The middle position: STANDBY
The right position: ON
In the "STANDBY" position, the audio is muted.
- (7) LED Indicator
Turns red when the switch is in "STANDBY" position and green in "ON" position.

NOTES:

Remove the battery if the transmitter will not be used for a long period of time.

