

ALARM DEVICE MANUFACTURING COMPANY
165 EILEEN WAY
SYOSSET, NY 11791

CFS8DL5805

FCC ID# _____

DECEMBER, 14, 2001 GREG BARBATO KEN ADDY
 DATE:_____ TESTED BY:_____ APPROVED BY:_____

ADEMCO 5805 (TRANSMITTER)
 TEST SAMPLE (model): _____

TEST METHOD: ANSI C63.4-1992
 TEST SPECIFICATION: FCC PART 15, SUBPART C.

NOTES: 1) Fo= 345 MHZ
 2) DETECTOR = PEAK.
 3) FREQUENCY RANGE SCANNED TO 4 GHz.

$$4) \text{ CONVERTED READING} = 10 \left[\frac{(\text{METER READING} + \text{CABLE /AMP FACTOR} + \text{ANTENNA FACTOR})}{20} \right]$$

5) CORRECTED READING = CONVERTED READING X DUTY CYCLE

6) SIX HIGHEST EMISSIONS RECORDED.

Frequency (MHz)	Antenna Polarity (V-H)	Meter Reading (dB uV)	Cable/Amp Factor (dB)	Antenna Factor (dB/M)	Converted Reading (uV/M)	Duty Cycle (%)	Corrected Reading (uV/M)	Limit @ 3 Meter (uV/M)
30	H					14.3		729
345	V	50.33	2 . 3	16.66	2916.0	14.3	428.6	-----
690	V	33.87	3 . 2	21.56	854.7	14.3	125.6	729
1035	H	29.17	3 . 9	23.83	699.0	14.3	102.7	500
1380	H	29.17	4 . 6	24.91	859.5	14.3	126.3	500
1725	V	29.00	5 . 3	26.67	1118.1	14.3	164.3	729
2070	H	28.87	6 . 3	28.47	1521.9	14.3	223.7	729
2415	H	29.17	6 . 8	28.96	1764.2	14.3	259.3	729
2760	H	29.10	7 . 0	29.75	1962.4	14.3	228.5	729
3105	H	29.10	7 . 4	30.00	2252.6	14.3	331.1	729
3450	H	29.10	12 . 0	29.95	4007.2	14.3	589.0	729
4000	H					14.3		729