

MPE CALCULATIONS - FCC

1.0 APPLICANT:

DATE: 8/24/2017
NAME OF APPLICANT: HONEYWELL INTERNATIONAL INC.
FCC ID: CFS8DLCOMR6

2.0 FCC RULES CONCERNING MAXIMUM PERMISSIBLE RF EXPOSURE:

§ CFR 47 1.1310 Radiofrequency radiation exposure limits.

The criteria listed in table 1 shall be used to evaluate the environmental impact of human exposure to radiofrequency (RF) radiation as specified in § 1.1307(b), except in the case of portable devices which shall be evaluated according to the provisions of § 2.1093 of this chapter. Further information on evaluating compliance with these limits can be found in the FCC’s OST/OET Bulletin Number 65, “Evaluating Compliance with FCC-Specified Guidelines for Human Exposure to Radiofrequency Radiation.”

NOTE TO INTRODUCTORY PARAGRAPH:

These limits are generally based on recommended exposure guidelines published by the National Council on Radiation Protection and Measurements (NCRP) in “Biological Effects and Exposure Criteria for Radiofrequency Electromagnetic Fields,” NCRP Report No. 86, Sections 17.4.1, 17.4.1.1, 17.4.2 and 17.4.3. Copyright NCRP, 1986, Bethesda, Maryland 20814. In the frequency range from 100 MHz to 1500 MHz, exposure limits for field strength and power density are also generally based on guidelines recommended by the American National Standards Institute (ANSI) in Section 4.1 of “IEEE Standard for Safety Levels with Respect to Human Exposure to Radio Frequency Electromagnetic Fields, 3 kHz to 300 GHz,” ANSI/IEEE C95.1–1992, Copyright 1992 by the Institute of Electrical and Electronics Engineers.

3.0 UUT POWER OUTPUT AND ANTENNA GAIN

The maximum conducted output power from Exhibit 5-1 is measured as 17.36 dBm at 2405MHz.
The duty cycle from Exhibit 3-1 is 6.98%, or -23.1 dB.
There are two integrated inverted F type antennas, with gains of 3dBi and 5.8dBi. The maximum antenna gain of the two antennas is 5.8 dBi.

3.1 MPE CALCULATIONS:

FCC GENERAL POPULATION / UNCONTROLLED EXPOSURE LIMITS:

FOR 300 MHz to 1,500 MHz use $F / 1500 \text{ mW/cm}^2$;
FOR 1,500 to 100,000 MHz use 1 mW/cm^2

EQUATIONS:

MAX AVG EIRP (mW) = $10^{((\text{MAX COND PWR.} + \text{ANT GAIN} + \text{DUTY FACTOR})/10)}$

THE FRIIS TRANSMISSION EQUATION = $\text{EIRP} \times \text{DUTY CYCLE} / (4 \times \text{PI} \times 20 \text{ CM}^2)$

BANDS AND FCC IDs

BAND	FCC ID
2405	CFS8DLCOMR6

BAND:	CH No:	FREQ(Mhz)	TRP dbm	MAX COND. PWR (dBm)	ANTENNA GAIN(dbi):	DUTY FACTOR (dB)	MAX AVG EIRP (mW)	FRISS mW/CM ² :	EXP LIMIT mW/CM ² :	% OF LIMIT:
2405MHz	N/A	2405	N/A	17.36	5.8	23.10	1.014	0.0002017	1	0.0202

MAXIMUM MPE OF THE RF6 MODULE AS % OF LIMIT IS: 0.0202

4.0 RESULTS:

TEST RESULT: PASS

In the configuration tested the EUT complied with the standards specified above.

MPE CALCULATIONS - IC

1.0 APPLICANT:

DATE: 8/24/2017
NAME OF APPLICANT: HONEYWELL INTERNATIONAL INC.
IC NUMBER: 573F-COMR6

2.0 IC RULES CONCERNING MAXIMUM PERMISSIBLE RF EXPOSURE:

RSS-102 § 2.5.2 Exemption Limits for Routine Evaluation - RF Exposure Evaluation.

RF exposure evaluation is required if the separation distance between the user and/or bystander and the device’s radiating element is greater than 20 cm, except when the device operates as follows:

- at or above 300 MHz and below 6 GHz and the source-based, time-averaged maximum e.i.r.p. of the device is equal to or less than $1.31 \times 10^{-2} f^{0.6834} \text{ W}$ (adjusted for tune-up tolerance), where f is in MHz;

In these cases, the information contained in the RF exposure technical brief may be limited to information that demonstrates how the e.i.r.p. was derived.

3.0 UUT POWER OUTPUT AND ANTENNA GAIN

The maximum conducted output power from Exhibit 5-1 is measured as 17.36 dBm at 2405MHz.
The duty cycle from Exhibit 3-1 is 6.98%, or -23.1 dB.
There are two integrated inverted F type antennas, with gains of 3dBi and 5.8dBi. The maximum antenna gain of the two antennas is 5.8 dBi.
The max time-averaged EIRP per 2.0 above is $1.31 \times 10^{-2} \times 2405^{0.6834} \text{ (W)} = 2.679\text{W} = 2679 \text{ mW}$.
The power density exposure limit at 20cm corresponding to 2679 mW EIRP is $N/(4 \times \pi \times d^2)$ or $2679/(4 \times \pi \times 20^2) = 0.533 \text{ mW/CM}^2$

3.1 MPE CALCULATIONS:

IC GENERAL POPULATION / UNCONTROLLED EXPOSURE LIMITS:
FROM 300 MHz to 6 GHz use $(1.31 \times 10^{-2}) \times f^{0.6834}$ for max EIRP(W)

EQUATIONS:
MAX AVG EIRP (mW) = $10^{((\text{MAX COND PWR.} + \text{ANT GAIN} + \text{DUTY FACTOR})/10)}$
THE FRIIS TRANSMISSION EQUATION = $\text{EIRP} \times \text{DUTY CYCLE} / (4 \times \pi \times 20 \text{ CM}^2)$

BANDS AND IC NUMBERS

BAND	IC NUMBER:
2405	573F-COMR6

BAND:	CH No:	FREQ(Mhz)	TRP dbm	MAX COND. PWR (dBm)	ANTENNA GAIN(db):	DUTY FACTOR (dB)	MAX AVG EIRP (mW)	FRISS mW/CM ² :	EXP LIMIT mW/CM ² :	% OF LIMIT:
2405MHz	N/A	2405	N/A	17.36	5.8	23.10	1.014	0.0002017	0.533	0.0378

MAXIMUM MPE OF THE RF6 MODULE AS % OF LIMIT IS: 0.0378

4.0 RESULTS:

TEST RESULT: PASS

In the configuration tested the EUT complied with the standards specified above.