

Model D35

FCC ID: DKNW76XM

BT/BLE and Zigbee Antenna Gain Addendum

	Measured Max Field Strength (dBuV/m)	Converted EIRP (dBm/MHz)	EBW (MHz)	EBW Correction (dB)	Corrected Total EIRP (dBm)	Conducted Power Peak (dBm)	Effective Antenna Gain (measured EIRP – conducted power) (dBi)	Modelled Antenna Gain (dBi)
BT/BLE	108.62	13.42	1.11	0.45	13.87	8.81	5.06	4.2
Zigbee	108	12.8	1.58	2.0	14.8	11.82	2.98	4.1

Converted EIRP (dBm/MHz) = FS (dBuV/m) - 95.2

EBW Correction = $10\log(\text{EBW} / 1\text{MHz})$, used to correct for measured field strength in 1MHz BW for full emission BW

Corrected Total EIRP (dBm) = Converted EIRP (dBm/MHz) + EBW Correction

Effective Antenna Gain (dBi) = Corrected EIRP/MHz – Measured Conducted Power

Field strength values noted above specifically comes from 14160417-E1V1 (BLE, page 27), 14160419-E2V1 (BT, page 56) and 14441108-E1V1 (Zigbee, page 26).

Equipment lists, test methods for field strength values apply C63.10:2013 radiated bandedge procedures come from reports 14160419-E1V1, 14160419-E2V1 and 14441108-E1V1.