

FCC Part 24E Transmitter Certification

Test Report

FCC ID: DNY020MPAD

FCC Rule Part: CFR 47 Part 24 Subpart E

ACS Report Number: 07-0090-24E

Manufacturer: EMS Wireless Equipment Type: PCS Bi-Directional Repeater Tradename: MirrorCell[®] II

radename: MirrorCell® II Model: 020MPAD

RF Exposure

General Information:

Applicant: EMS Technologies, Inc.

ACS Project: 07-0090 FCC ID: DNY020MPAD

Device Category: Fixed

Exposure Conditions: Uncontrolled/General Population

Technical Information:

UPLINK:

Antenna Type: Yagi Antenna Gain Maximum: 15.1dBi Max Transmitter Output Power: 25.12dBm

Max System EIRP: 40.22dBm / 10.52W

Operating Configuration: Fixed

DOWNLINK:

Antenna Type: Panel
Antenna Gain Maximum: 7.5dBi
Max Transmitter Output Power: 43.5dBm
Max System EIRP: 51dBm / 125W

Operating Configuration: Fixed

NOTE: Multiple antennas are available for both the uplink and downlink applications. Listed above are antennas with the highest gain.

MPE Calculation

The Power Density (mW/cm²) is calculated as follows:

$$S = \frac{PG}{4\pi R^2}$$

Where:

S = power density (in appropriate units, e.g. mW/cm2)

P = power input to the antenna (in appropriate units, e.g., mW)

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna (appropriate units, e.g., cm)

Calculations were performed at the frequencies with the highest output power as determined during testing.

Maximum Permissible Exposure (MPE)								
General Population/Uncontrolled Exposure								
Transmit	Radio	Power	Radio	Antenna	Antenna	Distance (cm)	Power	
Frequency	Power	Density Limit	Power	Gain	Gain		Density	Configuaration
(MHz)	(dBm)	(mW/Cm2)	(mW)	(dBi)	(mW eq.)	(CIII)	(mW/cm^2)	
1860	25.12	1.00	325.09	15.1	32.359	29	0.995	Uplink
1948.75	43.5	1.00	22387.21	7.5	5.623	101	0.982	Downlink

Installation Guidelines

End-users and installers must be provided with antenna installation instructions and transmitter operating conditions for satisfying RF exposure compliance.