

ITEM NO.	LEVEL	COMP NO.	DESCRIPTION	UNIT	QTY.	PER DRAW NO.	LAST ECN. NO.	REMARK
*B-432/C			FRS-0168-HK 0168 CHASSIS 462.5625/467.7125MHz					
.1		CCM-0005007	C CAP 0.5pF +/-0.25pF 50V NPO PC SMD0603		1.0000			C65
.1		CCM-0022007	C CAP 2.2pF +/-0.25pF 50V NPO PC SMD0603		1.0000			C23
.1		CCM-0017-07	C CAP 1pF +/-0.25pF 50V PC SMD0603		3.0000	6211		C76,101,109
.1		CCM-0027-07	C CAP 2pF +/-0.25pF 50V PC SMD0603		3.0000	6211		C22,82,91
.1		CCM-0037-07	C CAP 3pF +/-0.25pF 50V PC SMD0603		2.0000	6211		C27,53
.1		CCM-0047-07	C CAP 4pF +/-0.25pF 50V PC SMD0603		3.0000	6211		C46,71,77
.1		CCM-0057-07	C CAP 5pF +/-0.25pF 50V PC SMD0603		4.0000	6211		C51,54,75,84
.1		CCM-0067-07	C CAP 6pF +/-0.25pF 50V PC SMD0603		2.0000	6211		C45,100
.1		CCM-0077-07	C CAP 7pF +/-0.25pF 50V PC SMD0603		1.0000	6211		C86
.1		CCM-0107-37	C CAP 10pF +/- 5% 50V SMD0603		2.0000	6211		C48,50
.1		CCM-0157-37	C CAP 15pF +/-5% 50V SMD0603		2.0000			C74,79
.1		CCM-0207-37	C CAP 20pF +/- 5% 50V SMD0603		1.0000	6211		C94
.1		CCM-0227-37	C CAP 22pF +/- 5% 50V SMD0603		1.0000	6211		C89
.1		CCM-0337-37	C CAP 33pF +/- 5% 50V SMD0603		2.0000	6211		C13,28
.1		CCM-0477-37	C CAP 47pF +/-5% 50V SMD0603		1.0000	6211		C15
.1		CCM-0567-37	C CAP 56pF +/- 5% 50V SMD0603		1.0000	6211		C16 ECN00-0411
.1		CCM-1187-37	C CAP 180pF +/-5% 50V		4.0000			C20,57,102,104
.1		CCM-1337-37	C CAP 330pF +/- 5% 50V SMD0603		3.0000	6211		C18,29,30
.1		CCM-2107-47	C CAP 1000pF +/-10% 50V SMD0603		17.0000	6211		C12,19,21,44,47,60,61,67,73,78, C80,81,95,97,98,99,103
.1		CCM-2477-47	C CAP 4700pF +/-10% 50V SMD0603		1.0000	6211		C10
.1		CCM-3107-47	C CAP 0.01uF +/-10% 50V SMD0603		3.0000	6211		C9,66,70 ECN00-0527
.1		CCM-3157-47	C CAP 0.015uF +/-10% 50V SMD0603		1.0000	6211		C34
.1		CCM-3227-45	C CAP 0.022uF +/-10% 25V SMD0603		2.0000			C4,36
.1		CCM-3337-44	C CAP 0.033uF +/-10% 16V SMD0603		2.0000	6211		C33,59

ITEM NO.	LEVEL	COMP NO.	DESCRIPTION	UNIT	QTY.	PER DRAW NO.	LAST ECN. NO.	REMARK
.1		CCM-4107-57	C CAP 0.1uF +/-20% 50V SMD0603	PC	21.0000			C3,5,6,9,11,17,42,55,56,58,62,68,83, C24-26,31,35,96,106,107 ECN00-0527
.1		CCM-4227-55	C CAP 0.22uF +/-20% 25V SMD0603	PC	2.0000			C7,52
.1		CTM-4474-56	C. TAN CAP. 0.47uF 20% 35V	PC	1.0000	6582		C14
.1		CTM-5104-52	C.TAN CAP. 1uF 20% 10V A-SIZE	PC	2.0000	6582		C32,37
.1		CTM-5224-52	C.TAN CAP. 2.2uF 20% 10V A SIZE	PC	1.0000	5677		C49
.1		CTM-6104-52	C TAN CAP. 10uF 20% 10V B SIZE	PC	2.0000	5677		C1,38
.1		CTM-6224-51	C.TAN CAP 22uF +/-20% 6.3V SIZE A	PC	2.0000	6582		C2,93
.1		CEC-6228-54	E CAP 22uF +/-20% 16V 5*5mm SUPER MINI	PC	1.0000	6210		C8
.1		CTM-6474-51	C.TAN CAP 47uF +/-20% 6.3V SIZE-C	PC	2.0000	6582		C64,105
.1		CEC-6476-54	E CAP 47uF +/-20% 16V5*7mm	PC	2.0000	2368		C40,43
.1		CEC-7106-52	E CAP 100uF +/-20% 10V 5*7	PC	1.0000			C39 ECN00-0411
.1		CEC-7226-54	E CAP 220uF +/-20% 16V DIA 6.3mm	PC	1.0000			C41
.1		CVM-0102600	C.TRIMMER CAP 10pF CVS310AK00	PC	1.0000	7034		VC1
.1		DSM-4148-00	DIODE IN4148 SMD TEMIC	PC	3.0000	5951		D1,2,5 ECN00-0527
.1		DSM-0782-00	SW DIODE BA782 GS	PC	3.0000	6192		D7,12,13
.1		DVC-0721-70	VC DIODE BB721 ITT	PC	2.0000	4474		DV1,2
.1		FCF-0027-BP	CER.FILTER LTWM450G C&Q 450KHz	PC	1.0000	7832		F3
.1		FCF-0022-BP	SAW FILTER 465MHz D465	PC	1.0000	7053		F1 ECN00-0411
.1		FCF-0028-BP	CRYSTAL FILTER 21.4MHz UM-5 AEI	PC	1.0000	7834		F2
.1		ICM-2304-QJ	OTP KS57P2304Q SAMSUNG	PC	1.0000	6241		U3
.1		ICM-0393-22	CHIP IC LM393M NS	PC	1.0000	6284		U5
.1		ICM-3361-1B	CHIP IC MC3361CD MOTOROLA SO-16	PC	1.0000	5657		U4
.1		ICM-0602-OM	CHIP IC KA8602BD SAMSUNG	PC	1.0000	5755		U6
.1		ICM-5E03-XB	CHIP IC MB15603PFV FUJITSU SSOP16	PC	1.0000	7835		U2
.1		ICO-3302-X1	IC XC62AP3302TH TOREX	PC	1.0000	6490		U1
.1		LCM-0012-37	C.INDUCTOR 12nH +/-5% 0603 ELJRE12NJF2 (PSI) 3K/REEL	PC	1.0000	7392		L6
.1		LCM-0018-37	C.INDUCTOR 18nH +/-5% 0603 ELJRE18NJF2 (PSI) 3K/REEL	PC	3.0000	7392		L3,5,16
.1		LCM-0022-37	C.INDUCTOR 22nH +/-5% 0603 ELJRE22NJF2 (PSI) 3K/REEL	PC	1.0000	7392		L2
.1		LCM-0033-37	C.INDUCTOR 33nH +/-5% 0603 ELJRE33NJF2 (PSI) 3K/REEL	PC	1.0000			L15
.1		LCM-0033-30	CHIP INDUCTOR NL252018T-3R3J TDK T/R	PC	1.0000			L14
.1		LTC-A030-50	AIR COIL A-0030-050	PC	4.0000	6964		L4,7,9,11 ECN00-0411
.1		LTC-A040-50	AIR COIL A-0040-050	PC	2.0000	6963		L1,8

ITEM NO.	LEVEL	COMP NO.	DESCRIPTION	UNIT	QTY.	PER DRAW NO.	LAST ECN, NO.	REMARK
.1		LTC-4070-40	IFT AS-814070 6mm	PC	1.0000			L17
.1		RCM-0003-39	C RES 0 OHM +/-5% 1/16W SMD0603	PC	2.0000			R36,71 ECN00-0527
.1		RCM-0101-38	C RES 10 OHM +/-5% 1/10W SMD0805	PC	1.0000			R13
.1		RCM-0103-39	C RES 10 OHM +/-5% 1/16W SMD0603	PC	2.0000			R53,86
.1		RCM-0333-39	C RES 33 OHM +/-5% 1/16W SMD0603	PC	1.0000			R21
.1		RCM-0473-39	C RES 47 OHM +/-5% 1/16W SMD0603	PC	3.0000			R31,58,84
.1		RCM-0683-39	C RES 68 OHM +/-5% 1/16W SMD0603	PC	2.0000			R30,60
.1		RCM-0823-39	C RES 82 OHM +/-5% 1/16W SMD0603	PC	1.0000			R8
.1		RCM-1103-39	C RES 100 OHM +/-5% 1/16W SMD0603	PC	1.0000			R39
.1		RCM-1203-39	C RES 200 OHM +/-5% 1/16W SMD0603	PC	1.0000			R1
.1		RCM-1223-39	C RES 220 OHM +/-5% 1/16W SMD0603	PC	3.0000			R35,54,77
.1		RCM-1273-39	C RES 270 OHM +/-5% 1/16W SMD0603	PC	1.0000			R4
.1		RCM-1333-39	C RES 330 OHM +/-5% 1/16W SMD0603	PC	3.0000			R57,70,128
.1		RCM-1683-39	C RES 680 OHM +/-5% 1/16W SMD0603	PC	2.0000			R67,76
.1		RCM-2103-39	C RES 1K OHM +/-5% 1/16W SMD0603	PC	5.0000			R12,69,72,78,89
.1		RCM-2123-39	C RES 1.2K OHM +/-5% 1/16W SMD0603	PC	1.0000			R41
.1		RCM-2153-39	C RES 1.5K OHM +/-5% 1/16W SMD0603	PC	2.0000			R3,37
.1		RCM-2183-39	C RES 1.8K OHM +/-5% 1/16W SMD0603	PC	1.0000			R2
.1		RCM-2223-39	C RES 2.2K OHM +/-5% 1/16W SMD0603	PC	1.0000			R87
.1		RCM-2333-39	C RES 3.3K OHM +/-5% 1/16W SMD0603	PC	2.0000			R28,43
.1		RCM-2473-39	C RES 4.7K OHM +/-5% 1/16W SMD0603	PC	2.0000			R7,80
.1		RCM-2563-39	C RES 5.6K OHM +/-5% 1/16W SMD0603	PC	5.0000			R14,27,32,49,92
.1		RCM-2683-39	C RES 6.8K OHM +/-5% 1/16W SMD0603	PC	3.0000			R6,29,55
.1		RCM-2823-39	C RES 8.2K OHM +/-5% 1/16W SMD0603	PC	1.0000			R38
.1		RCM-3103-39	C RES 10K OHM +/-5% 1/16W SMD0603	PC	12.0000			R17,23,25,40,45,50,51,61,62,68,79,83

ITEM NO.	LEVEL	COMP NO.	DESCRIPTION	UNIT	QTY.	PER DRAW NO.	LAST ECN. NO.	REMARK
.1		RCM-3123-39	C RES 12K OHM +/-5% 1/16W SMD0603	PC	1.0000			R33
.1		RCM-3183-39	C RES 18K OHM +/-5% 1/16W SMD0603	PC	3.0000			R11,75,85
.1		RCM-3223-39	C RES 22K OHM +/-5% 1/16W SMD0603	PC	2.0000			R48,82
.1		RCM-3273-39	C RES 27K OHM +/-5% 1/16W SMD0603	PC	1.0000			R44 ECN00-0411
.1		RCM-3333-39	C RES 33K OHM +/-5% 1/16W SMD0603	PC	2.0000			R42,59
.1		RCM-3363-39	C RES 36K OHM +/-5% 1/16W SMD0603	PC	2.0000			R10,26
.1		RCM-3393-39	C RES 39K OHM +/-5% 1/16W SMD0603	PC	1.0000			R20
.1		RCM-3473-39	C RES 47K OHM +/-5% 1/16W SMD0603	PC	1.0000			R34
.1		RCM-3513-39	C RES 51K OHM +/-5% 1/16W SMD0603	PC	1.0000			R65
.1		RCM-3623-39	C RES 62K OHM +/-5% 1/16W SMD0603	PC	1.0000			R15 ECN00-0527
.1		RCM-3683-39	C RES 68K OHM +/-5% 1/16W SMD0603	PC	2.0000			R19,47
.1		RCM-4103-39	C RES 100K OHM +/-5% 1/16W SMD0603	PC	4.0000			R9,16,56,66
.1		RCM-4153-39	C RES 150K OHM +/-5% 1/16W SMD0603	PC	1.0000			R5
.1		RCM-4183-39	C RES 180K OHM +/-5% 1/16W SMD0603	PC	1.0000			R24
.1		RCM-4223-39	C RES 220K OHM +/-5% 1/16W SMD0603	PC	1.0000			R64
.1		RCM-4393-39	C RES 390K OHM +/-5% 1/16W SMD0603	PC	2.0000			R22,52
.1		RCM-4473-39	C RES 470K OHM +/-5% 1/16W SMD0603	PC	2.0000			R46,63
.1		RTM-0003-5B	SEMI FIX B10K OHM CVR-32A	PC	2.0000			VR2,3
.1		TRM-3880-60	CHIP TRANSISTOR KTC38800	KEC PC	1.0000			Q13
.1		TRM-0812-C7	CHIP TRANSISTOR 2SA812-M7 SOT-23	NEC PC	4.0000			Q5,9,24,26
.1		TRM-1623-C6	CHIP TRANSISTOR 2SC1623-L6 SOT-23	NEC PC	6.0000			Q1-4,11,12
.1		TRM-5319-40	C.TRANSISTOR 2SC5319 TOSHIBA	PC	1.0000	7339		Q7
.1		TRM-R106-30	CHIP TRANSISTOR BFR106 PHILIPS	PC	1.0000			Q15
.1		TRM-R92A-3A	CHIP TRANSISTOR BFR92A PHILIPS	PC	4.0000			Q6,9,10,14
.1		TRM-179A-C0	MOSFET (SMD) NE5500179A	NEC PC	1.0000	7742		T1
.1		XTL-0227-LG	CRYSTAL 20.950MHZ AEI UM-1	PC	1.0000	7880		X3
.1		XTL-0123-JE	CRYSTAL 4MHZ HC-49S EMI	PC	1.0000	6581		X1
.1		M04-3621-110	PCB 0168/LCD D/S 1mm FR4-MTL	PC	1.0000	8123		
.1		M04-3631-110	PCB 0168/RF D/S 1mm FR4-MTL	PC	1.0000	8123		
.1		M04-3641-110	PCB 0168/MAIN D/S 1mm FR4-86	PC	1.0000	8123		