

Installation Instructions



Linear

USA & Canada (800) 421-1587 & (800) 392-0123
(760) 438-7000 - Toll Free FAX (800) 468-1340
www.linearcorp.com

Before system testing and operation, each transmitter must be programmed into its receiver. Refer to the receiver's or Console's instructions for details on programming transmitters into the system.

Diagram illustrating the components of the CX-65 Transmitter:

- CX-65 TRANSMITTER
- TRANSMIT INDICATOR
- OPTIONAL BLANK AQUA BUTTON
- MOUNTING PLATE
- ACTIVATION BUTTON
- TABLE-TOP FEET (4)
- MOUNTING SCREWS (2)

ATTACH WALL MOUNT BRACKET WITH TWO SCREWS

HOO K TOP OF TRANSMITTER ON TO THE BRACKET TABS

SWING TRANSMITTER ON TO BRACKET

TO REMOVE TRANSMITTER PRESS TAB ON BRACKET

FOR NON-WALL MOUNT APPLICATIONS, STICK THE FOUR ADHESIVE "FEET" ON TO THE MOUNTING BRACKET

1 PLACE THE CONSOLE OR RECEIVER INTO PROGRAMMING MODE

2 ACTIVATE THE TRANSMITTER TO PROGRAM IT INTO THE CONSOLE OR RECEIVER

Alert 1

ALARM STATUS

EMERGENCY

RESET

Alert 1 Console

NOTE: TO VERIFY THE RADIO RANGE, BE SURE TO TEST THE TRANSMITTER FROM THE INTENDED MOUNTED OR TABLE-TOP LOCATION

TEST SYSTEM WEEKLY!

1 PLACE THE CONSOLE OR RECEIVER INTO TEST MODE

2 ACTIVATE THE TRANSMITTER, VERIFY THAT THE SIGNAL WAS RECEIVED

Alert 1

EMERGENCY

ALERT 1 CONSOLE

- 1 TWIST A COIN OR SCREWDRIVER IN THE SLOT ON TOP OF TRANSMITTER TO OPEN THE CASE
- 2 REMOVE THE CASE TOP, BUTTON, SILICONE SEAL, AND LIFT OUT THE TRANSMITTER CIRCUIT BOARD
- 3 REPLACE THE BATTERY WITH ONE TYPE MAXELL CR2032 200mA HR OR DURACELL DL2032 COIN-CELL BATTERY PLUS SIDE AWAY FROM THE CIRCUIT BOARD
- 4 RE-ASSEMBLE THE UNIT BY REVERSING THE STEPS
- 5 TEST THE TRANSMITTER AFTER RE-ASSEMBLING

[illegible]

This Linear product is warranted against defects in material and workmanship for twelve (12) months. This warranty extends only to wholesale customers who buy direct from Linear or through Linear's normal distribution channels. Linear does not warrant this product to consumers. Consumers should inquire from their selling dealer as to the nature of the dealer's warranty, if any. There are no obligations or liabilities on the part of Linear LLC for consequential damages arising out of or in connection with use or performance of this product or other indirect damages with respect to loss of property, revenue, or profit, or cost of removal, installation, or reinstallation. All implied warranties, including implied warranties for merchantability and implied warranties for fitness, are voided only until the warranty expires. This Linear LLC Warranty is in lieu of all other warranties expressed or implied.

All products returned for warranty service require a Return Product Authorization Number (RPA#). Contact Linear Technical Services at 1-800-421-1587 for an RPA# and other important details.

IMPORTANT !!!

Linear radio controls provide a reliable communications link and fill an important need in portable wireless signaling. However, there are some limitations which must be observed.

- For U.S. installations only: The radios are required to comply with FCC Rules and Regulations as Part 15 devices. As such, they have limited transmitter power and therefore limited range.
- A receiver cannot respond to or more than one transmitter at a time and may be blocked by radio signals that occur on or near their operating frequencies, regardless of code settings.
- Changes or modifications to the device may void FCC compliance.

Frequently used radio links should be tested regularly to protect against undetected interference or fault.

General knowledge of radio operation should be obtained prior to acting as a wholesale distributor or dealer, and these radios should be commensurate to the ultimate user.

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes: (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.