

## **FCC 47 CFR MPE REPORT**

Guangzhou Panyu Juda Car Audio Equipment Co.,Ltd.

CD/USB MICRO COMPONENT SYSTEM

Model Number: TY-ASW91

FCC ID: ESX-ASW91

Prepared for : Guangzhou Panyu Juda Car Audio Equipment Co.,Ltd.  
Vtrek Dewei Industrial Garden, Shibeil Industrial Road, Dashi  
Town, Panyu Borough, Guangzhou, Guangdong, China

Prepared By : EST Technology Co., Ltd.  
San Tun Management Zone, Houjie Town, Dongguan,  
Guangdong, China

Tel: 86-769-83081888-808

Report Number: ESTE-R1705029  
Date of Test : April 11, 2017 ~ April 26, 2017  
Date of Report : May 05, 2017



## Maximum Permissible Exposure

### 1、Applicable Standard

Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure. In accordance with 47 CFR FCC Part 2 Subpart J, section 2.1091 this device has been defined as a mobile device whereby a distance of 0.2m normally can be maintained between the user and the device.

#### (a)、Limits for Occupational / Controlled Exposure

Frequency Range (MHz)	Electric Field Strength E (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842/f	4.89/f	(900/f)*	6
30-300	61.4	0.163	1.0	6
300-1500			F/300	6
1500-10000			5	6

#### (b)、Limits for General Population / Uncontrolled Exposure

Frequency Range (MHz)	Electric Field Strength E (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f)*	30
30-300	27.5	0.073	0.2	30
300-1500			F/1500	30
1500-10000			1.0	30

Note: f=frequency in MHz; \*Plane-wave equivalent power density

### 2、MPE Calculation Method

$$E \text{ (V/m)} = (30 \cdot P \cdot G)^{0.5} / d \quad \text{Power Density: } Pd \text{ (W/m}^2\text{)} = E^2 / 377$$

E = Electric Field (V/m)

P = Peak RF output Power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

The formula can be changed to

$$Pd = (30 \cdot P \cdot G) / (377 \cdot d^2)$$

From the peak EUT RF output power, the minimum mobile separation distance, d=0.2m, as well as the gain of the used antenna, the RF power density can be obtained

### 3、Calculated Result and Limit

Mode	Frequency (MHz)	Peak output power (dBm)	Peak output power (mW)	Target power (dBm)	Antenna gain		Power Density (S) (mW /cm <sup>2</sup> )	Limited of Power Density (S) (mW /cm <sup>2</sup> )	Test Result
					(dBi)	(Linear)			
GFSK	2402	0.459	1.111	0±1	0	1	<b>0.00025</b>	1	Compiles
	2441	-0.248	0.945	-1±1	0	1	<b>0.00020</b>	1	Compiles
	2480	-0.676	0.856	-1±1	0	1	<b>0.00020</b>	1	Compiles
8-DPSK	2402	0.419	1.101	0±1	0	1	<b>0.00025</b>	1	Compiles
	2441	-0.304	0.932	-1±1	0	1	<b>0.00020</b>	1	Compiles
	2480	-0.671	0.857	-1±1	0	1	<b>0.00020</b>	1	Compiles