

FIC

DESERTSTORM JUMPER SETTING V1.3

VGA

USB

GAME/AUDIO

KB/MS

COM

PRINT

BISER

J18 (DIMM1)

J19 (DIMM2)

CLK0
CLK1
CLK2

SIS5598

NB/SB/VGA

CLOCK

SOCKET 7

TAGRAM

SRAM
64*64

J29

7 8 1 2

J2 (FLOPPY)

J11 (IDE2)

J10 (IDE1)

J17

BATTERY

BIOS
PLCC

SIO
SIS6801

AUDIO
ES1869

J25 LEFT CHANNEL

J26 RIGHT CHANNEL

J17 1-2 NORMAL

2-3 CLEAR CMOS

J27 BOTTON/B CONNECTOR

J29

VDD2	1-2	3-4	5-6	7-8
2.0V	OFF	OFF	OFF	OFF
2.1V	OFF	OFF	OFF	ON
2.2V	OFF	OFF	ON	OFF
2.3V	OFF	OFF	ON	ON
2.4V	OFF	ON	OFF	OFF
2.5V	OFF	ON	OFF	ON
2.6V	OFF	ON	ON	OFF
2.7V	OFF	ON	ON	ON
2.8V	ON	OFF	OFF	OFF
2.9V	ON	OFF	OFF	ON
3.0V	ON	OFF	ON	OFF
3.1V	ON	OFF	ON	ON
3.2V	ON	ON	OFF	OFF
3.3V	ON	ON	OFF	ON
3.4V	ON	ON	ON	OFF
3.5V	ON	ON	ON	ON

FREQ0	FREQ1	FREQ2	105C/M2/K6	P54C/K6
1-2	1-2	1-2	3.5X	1.5X
2-3	1-2	1-2	2X	2X
2-3	2-3	1-2	2.5X	2.5X
1-2	2-3	1-2	3X	3X
2-3	1-2	2-3	4X	
2-3	1-3	2-3	4.5X	
1-2	1-3	2-3	5X	
1-2	1-2	3-3	5.5X	

CLOCK TABLE

Input Address			CPU, SDRAM	PCI Clock
CLK2	CLK1	CLK0	clock (MHz)	(MHz)
0	0	0	50.0	25.0
0	0	1	75.0	30.0
0	1	0	93.3	41.65
0	1	1	68.5	34.25
1	0	0	55.0	27.5
1	0	1	75.0	37.5
1	1	0	60.0	30.0
1	1	1	66.8	33.4

FIC DESERTSTORM

JUMPER SETTING

Document Number **16550**

Date Friday, July 17, 1998 Sheet 1 of 19

Rev 1.3