

### PARENT UNIT LIGHTS DIM MODE FOR VM3252-2 ONLY MOUNT THE BABY UNIT ON DRY WALL (OPTIONAL) Sound sensitivity and sound activation Adjust the sound sensitivity of the baby unit The dim mode is to help you save the parent unit power. Your parent unit display will dim automatically after 10 minutes of inactivity, in which there is neither key pressed nor alert received from the baby unit. Items to purchase Status check - Two baby units 0 You can choose to hear sounds from the baby unit all the time, or to hear sounds that exceed a certain level. You can use the · On when the parent unit is linked to the baby unit. LINK You will need to purchase the following items separately to mount your baby unit If you are viewing baby unit § 1, the **POWER** LED light of baby unit § 1 turns on. As baby unit § 2 is not being viewed, its **POWER** LED light flashes. · Flashes when the link to the baby unit being viewed is lost. or to hear sounds that exceed a certain level. You can use the parent unit to adjust the microphone sensitivity of your baby unit. The higher the sensitivity level, the more sensitive the baby unit is in detecting sounds for transmitting to the parent unit. The VOX sensitivity level is presert to the highest level. 00100000 2 screws 2 anchors On when the parent unit is connected to AC power, or the battery is 10 min inactivity **Ω** 1 0 ₽2 - $\bigcirc$ .....> . harging. Flashes when the parent unit battery is low and needs charging. NOTE Off when the parent unit is disconnected from AC power. The types of screws and anchors you need depend on the composition of the wall. ī Ē i On when the speaker volume of the parent unit is turned off; or when the parent unit speaker is talking to the baby unit. Highest ¥. High I Low Lowest Insert the screws into the holes and Medium 0 tighten the screws until only 1/4 inch Press any buttons **ENOTE** TALK · On when the parent unit is talking to the baby unit. The parent unit speaker is constantly on, and you will hear The parent unit speaker turns on for soft The parent unit speaker turns on for loud babbling and louder The parent unit speaker turns on for loud If you power on only one baby unit, your parent unit may or Press the to switch to the baby unit you have powered on. on only one baby unit, your parent unit may display 🍒 and the LINK LED light flashes. of the screws are exposed. NOTE 0 While the screen is dimmed, any keypress or alert message will trigger the screen to return to the preset brightness level. After 10 minutes of inactivity, it will resume to dim mode. crying or screeching sounds from babbling Change different views - Patrol all sounds (including background noises) from and loud and loude sounds from sounds from your baby. It remains sounds from your baby. It remains quiet when your baby sleeps Press MENU when the parent unit is idle. Press ◀ or ► to choose 🖳 then press SELECT or ▲. your baby. It remains quiet when your baby. It remains quiet when NIGHT VISION quiet when your baby makes soft Press ▼ or ▲ to choose 🛃, then press SELECT to confirm your selection. NOTE your baby's Check for reception strength and camera angle before drilling the holes. your baby makes soft your baby makes soft The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the baby unit being viewed detects low light levels, the infrared LEDs are switched on automatically. The images from the baby unit are in black and white, and **Q** sounds Use a pencil to mark two holes in parallel. Make sure they are the same distance apa as the wall mount holes on the baby unit. oundly sounds sounds ۲ (1) 10s Sound activated screen Align the wall mount holes on the baby unit with the screws on the wall. Slide the baby unit down until it locks When sound activation is on, the parent unit screen stays off to save power when the baby unit detects no sound. 0 OB10WAL into place. Once the baby unit detects sounds that are louder than the NOTES 1 chosen sound sensitivity level, the parent unit screen turns IN NOTES It is normal if you see a short white glare on your parent unit screen as the baby unit is adapting to the dark environment. When the infrared LEDs are on, the images are in black and white. This is normal. 6 on automatically. It will then turn off again after 50 seconds Change different views - Single-cam Press CAN to switch to another camera in SINGLE-CAM mode. Drill two holes in the wall (7/23 inch drill bit ) STIP. TIP Depending on the surroundings and other interfering factors, like lightings, objects, colors and backgrounds, the display resolution may vary. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display. If you drill the holes into a stud, go to step 3. -OR-(3) Press 🖨 If you drill the holes into an object other than a stud, insert the wall anchors into the holes. Tap gently on the ends with a hammer until the wall anchors are flush with the wall. Adjust the camera angle DISCLAIMER AND LIMITATION OF LIABILITY

## $^{\rm G_{s_{\Delta}}}$ Frequently asked questions

A		
lelow are the questions m	ost frequently asked about the baby monitor.	The RBRC s an industry
Why does the baby monitor not respond normally?	Try the following (in the order tiske) for common cure: Disconnet the power to the bady units and the parent unit. 2. Remove the batteries in the parent unit. Then, in that the batteries again. 3. Lemove the batteries in the parent unit. Allow the bady units and the parent unit. 4. Unit on the bady units and the parent unit. Allow the bady units and the parent unit. 5. While for the parent unit to synchronize with the bady units. Allow up to one minute for this to take place.	service with The RBRC V municipal v VTech's participation in RB program or at authorized / recycling and disposal ba protecting our environme The RBRC Seal and 1 (800
Why don't the power-on light of the baby unit and parent unit go on when I switch on the units?	Perhaps the parent unit is not connected to the power. Insert the appliance plug into the parent unit and put the adapter in a wall socket. Then, <u>press and hold</u> $O$ to switch on the parent unit and to establish connection with the baby unit.	FCC AND IC
	Perhaps the baby unit is not connected to the power. Insert the appliance plug into the baby unit and put the adapter in a wall socker. Then, slide the <b>ON/OFF</b> switch to <b>ON</b> to switch on the baby unit and to establish connection with the parent unit.	FCC Part 15 This equipment has been t Federal Communications C harmful interference in a r
Why doesn't my parent unit charge while connected to AC power?	Make sure the power is not controlled by a wall switch.	and, if not installed and use However, there is no guar harmful interference to rac user is encouraged to try to • Reorient or relocate the
	Make sure the battery is correctly installed in your parent unit.	
	You may have used the battery for a long time. Replace a new battery.	
Why is my screen in black and white?	The screen is in black and white during night-time or in a dark room when the night vision feature is activated. This is normal.	<ul> <li>Increase the separation</li> <li>Connect the equipment</li> <li>Consult the dealer or an</li> </ul>
Why do I get glare or blurry display on my screen when viewing my baby at night?	During night-time or in a dark room, the surroundings and other interfering factors, like lightings, objects, colors and backgrounds may affect the image quality on your parent unit screen. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display.	WARNING: Changes or mi could void the user's author This device complies with P not cause harmful interfere
Why does the baby monitor produce a high-pitched noise?	The parent unit and baby units may be too close to each other. • Move the parent unit away from the baby units until the noise stops; OR • Turn down the volume of your parent unit.	undesired operation. To ensure safety of users, th by a user or bystander acco the FCC criteria. The baby u approximately 8 in (20 cm) face. This Class 8 dioital apparat
Why does the parent unit beep?	The baby units may be out of range. Move the parent unit closer to the baby units (but not less than 3 feet).	
	The parent unit may not have enough charge for the parent unit to perform normally. Charge the battery in the parent unit until the battery icon becomes solid	CAN ICES-3 (B)/NMB-3(B) Industry Canada
	The temperature of your baby's room may be too high or too low.	This device contains licence Canada's licence-exempt R
Why does the parent unit react too quickly to other sounds?	The baby unit also picks up other sounds than those of your baby. Adjust the VOX sensitivity level to a lower level or lower the parent unit speaker volume.	interference. (2) This device device. The term "IC:" before the or met.
Why don't I hear a sound/Why can't I hear my baby cry?	The parent unit speaker volume may be too low. Press VOL+ to increase the volume.	This product meets the app
	You may have set a low VOX sensitivity level. See Adjust the sound sensitivity of the baby unit to set to a higher level.	RF radiation exposure stat The baby unit complies wit be installed and operated
Why can't I establish a connection? Why is the connection lost every now and then? Why are there sound interruptions?	The baby units may be out of range. Move the parent unit closer to the baby units (but not less than 3 feet).	be installed and operated v accessories may not ensure in conjunction with any oth to Canada's Health Code 6
	Other electronic products and wireless products may cause interference with your baby monitor. Try installing your baby monitor as far away from these devices as possible.	
	If you power on only one baby unit, your parent unit may display to and the LINK LED light flashes. Press CAN to switch to the baby unit you have powered on.	CHARGING
		This baby monitor meets t is set up to comply with th

The RBRC seal

C seal on the NI-MH battery indicates that VTech Communications, Inc. is voluntarily participating in try program to collect and recycle thate batteries at the end of their useful lives, when taken out of thin the United State and Canada. C program provides a convenient alternative to placing used NI-MH batteries into the trash or a usefu, which may be litigat in your area. RBC makes it easy for you to drop off the spent battery at local retailers participating in the RBRC d VTech product service centers. Please call 1 (800) 8 BATTERY' for information on Ni-MH battery 00) 8 BATTERY® are registered trademarks of Call2recycle, Inc.

# C REGULATIONS

Isotical and flound to compley with the insquirements for a Class B digital device under Part 15 of the instance of the second receiving antenna. between the equipment and receiver. I into an outlet on a dircuit different from that to which the receiver is connected.

ions to this equipment not expressly approved by the party responsible for compliance operate the equipment. e FCC rules. Operation is subject to the following two conditions: (1) this device may this device must accept any interference received, including interference that may cause he FCC has established criteria for the amount of radio frequency energy that can be safely ab

ording to the intended usage of the product. This product has been tested and found to comply u unit shall be installed and used such that parts of all persons' body are maintained at a distance of or more. The transmitter and antenna of the parent unit shall be held at least 1 in (2.5 cm) from you

ce-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Developmer RSS(s). Operation is subject to the following two conditions: (1) Thit device may not cause or must access taw interference, including interference that may cause undesired operation of the

certification/registration number only signifies that the Industry Canada technical specifications were pplicable Innovation, Science and Economic Development Canada technical specifications.

Latemati Win FCC RF radiation exposure limits set forth for an uncentrolled environment. The baby unit should dwith a minimum distance of B in [20 cm] between the baby unit and all persons' body. Use of other re compliance with ICC RF exposure guidelines. This transmitter must not be co-located or operating their advances of the equipment complies also with industry Canada RSS-102 with respect of for Exposure of Humans to RF Friedure.

## IA ENERGY COMMISSION BATTERY TESTING MODE

This baby monitor mosts the California benergy Commission (LEL) regulations for energy Consumption, you usuary minimum is set up to comply with the energy-conserving standards right out of the box. Follow the instructions to install and charging the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to baby units, the CEC battery charging testing mode is activated while the powered off and charging.

## FOR CETL COMPLIANCE ONLY

# Mesures de sécurité importantes La plaque signalétique appliquée est située au bas du socle de l'unité du bébé. Lorsque vous utilisez votre appareil, vous devriez toujours suivre certaines mesures de précaution de base afin de réduire les risques d'incendie, d'électrocution et de blessures corporelles, dont ceux qui suivent : Observez toutes les instructions et mises en garde inscrites sur l'appareil.

MISE EN GARDE: Packdar supplifies of 2 manufacture uniter cal BDB a lume capacital minimum calls and an antibiation adult to due insurinsion. La supplimitien du nourrission est la responsabilité du parent du cal la parentan qui d'accoss de la ferifant. Cal vous ne devrises pas présumer qu'il continuars a de fonctionner comer chement phantier una particula te tempos domine. De la devrise pas présumer qu'il continuars de fonctionner comer chement phantier una particula te disette de la devrise de la devrise pas présumer qu'il continuars de fonctionner. De la devrise pas présumer qu'il continuars de fonctionner de la devrise pas présumer qu'il continuars de fonctionner papervisor vorte bable.

remotings incorrer point part is suble présenter distringues Vous devinite traite l'arcégnisis chaques los dis que vous metter l'appartei en fonction. La verifitar si celles ci ne contra part des presentes de prese de confidentialité sur contra part des presentes de la verificación de la verificación produit na à presente de utilité averificación de la verificación produit na à presente de utilité averificación de la verificación produit na à presente de utilité averificación de la verificación parte en coust of utilitation. Les entant devrations des utilités produit na de verificación de la verificación de produit na la construcción de la verificación de la verificación de produit na la construcción de la verificación de la verificación de produit na la construcción de la verificación de la verificación de produit na la construcción de la verificación de la verificación de produit na la construcción de la verificación de la verificación de la verificación de produit na la construcción de la verificación de l superviser votre bible. N'utilises pas cet appareil près de l'eau ni de toute autre source d'humidité, par exèmple, près d'une baignoire, cuive à lessive, évier de cuisine, dans un sous-sol humide ou ni près d'une pécine, dans un soussel humide ou une qu'ils ne jouent pas avec l'appareil. Le produit n'est pas concu pour étre utilisé par des personnes (incluant des enfants) aux capacités physiques sensorieiles cu mentalais réduités ou qui manguent d'appérience et de connaissances, à moins qu'on leur ait donné suffisamment de supervisión ou d'instructions relativement à l'utilisation de l'appareil par une personne responsable de leur sécurité. 24

MISE EN GARDE Utilise a de batterie est utilisé pour l'unité Parents. N'incinére les piles. Celles-ci risquaraient d'explosar. Jatez les s usées selon les renseignements suivant **le sceau du** 

pils utdes stein is remaingreement subant le sceau de huitiers que la secte produit utilisar que la secte produit l'attributer que la secte produit l'attributer d'un adsplateur deri la potenté o la ternion sant inschagela filos de l'atternation adsplateur de l'unité du bioló. Sofin : 49 CC 500mA Adsplateur de l'unité du bioló. Sofin : 49 CC 500mA adsplateur de l'unité du bioló. Sofin : 49 CC 500mA adsplateur de l'unité du bioló. Sofin : 49 CC 500mA adsplateur de l'unité du bioló. Sofin : 49 CC 500mA adsplateurs socteur en té é conçus pour átres orientés concretement, con la servicia los qui partir site los destructures en la servicia do qui partir site los d'atternation et le mémbrerir et place s clubic et branche d'atternation et le mémbrerir et place s clubic et branche d'atternation et le mémbrerir et place s clubic et branche d'atternation et le mémbrerir et place s clubic et branche d'atternation et le mémbrerir et place s clubic et branche divalorités ou dans un

Table quode la lumitine du solalito ui da feu. Autoria da la lumitine du solalito ui da feu. Autoria da la lumitina da monte interna da la lumitina da la lumitina da monte interna da lumitina da la lumitina da lum

ocution. Ne renversez iamais de liquide dans ce

Affin de réduite les réques d'électricoution, ne démontez pas cet appareil, més leportez-le dans un contre de servi-tuories, l'exemption de balance ou le rentra de soutes pléce autories, l'exemption de la balance ou le rentra de soutes pléce autories, l'exemption de la balance ou le rentra de soutes pléce autories, l'exemption de la balance ou le rentra de soutes pléce des points de tension dangeres cou d'autres dangérs. Un remontage incorrect peut par la suite présenter dès risque d'électricoution.

able de leur sécurité. CONSERVEZ CES INSTRUCTIONS

0 ° C (32 ° F) et 40 ° C (304 ° F). Véceposes pas cet appareil a des froids ou des chaleurs extremes, ansi qu'à la lumière directe du soleit. Ne frintalite pas prés d'une source de churdhage. Le bloc-piles ne doit pas être exposé à la chaleur encessive telleguis la lumière du soleit ou au fou.

Mises en garde 1. Utilisez et entreposez le produit à une température entre 0° C (32° F) et 40° C (104° F).

chemise, lorsque celui-ci est en marche. L'étude effectuée par l'organisme WRS n'a pas identifié de risque pour les détenteurs de simulateurs cardispaces causés par les gens qui utilisent dispositifs sans fil à proximité de ceux-ci.

Letti calle previo de particita, sono dans unado con sinte con calma una poro las RPODUTES RESERVICER A LIVE RESE DE COURANT la prése de courant doit être instalée prés de goodant, entre constante en la constalté la constraine à la prése porocidar su antériques variantes de antéria de antéria Alébrandhera ce proceduir de la prése de courant avant de procedar su antériques Varializes para de antérias de antérias Débrandhera las conditos d'alimentation avant de semplacer la béloc pilia. Na coopar para las conditos d'alimentation pour remplacer la bélos para las las conditos d'alimentation pour templacer la bélos para las las conditos d'alimentation pour templacer la bélos para las las conditos d'alimentations para templacer la bélos para las las conditos d'alimentations para templacer la bélos para las las conditos d'alimentations para templacer las bélos para las las conditos d'alimentations para templacer las bélos para las las conditos d'alimentations para templacer las bélos para las las conditos d'alimentations para templacer las bélos para las las conditis de las para las para las conditis de las para las las conditis de las conditis de las para las las conditis de las conditis de las para las las conditis de las para las las conditis de las conditis de las para las las para las conditis de las conditis de las para las las conditis de las conditis d couverbure. D'autres équipements électroniques peuvent produire des interférences sur votre moniteur vidéo et audio. Tentez d'instalier votre moniteur vidéo ou audio à l'écart des appareits électroniques tels que des routeurs sans fil, adios, tidéphones cultularies, interphones, moniteurs, Mélphones, cordinateurs personnels, électroménagers et téléphones sains fil. 

Ne laissez aucun objet reposer ni appuyer sur le cordon d'alimentation. N'initallez pas cet apparel dans un endroit où l'on risque d'écraser le cordon d'alimentation ou de le s fonctionner cet appareil qu'avec le type nation indiqué sur l'étiquette. Si vous ne connaissez fil portatifs et les stimulateurs cardiaques implantés dans l'organisme. Appuyée par l'Administration des aliments et drogues (FDA) des Etats-Unis, la firme WTR recommande au médécins:

d'alimentation l'insertation que vous potsetaux e vous pas le type d'alimentation que vous potsetaux e vous domicile, consultez votre marchand bu votre compagnie locale d'électricaté. Ne surchargez pas les prises de courant murales ni les rallonges électriques. médicini: Avis aux dévnieurs de stimulateurs cardiaques Vous dévnieur maintenir les dispositifs sans fil à au moins six posocies du simulations cardinação. Is no dévour los places in tolégopon aux sens poste de chamisa, lorsque collui-d'est en marche. Divuis districtuones MBE da par les fils des fils. neversigen enversionen. Ne placez pas cet appareil sur un charlot, meuble, trépied, support de montage ni table chancelants.

No photo paper of approved for an orthorization, histoidal, the photo paper of approved for an orthorization of the photo-thermal of the photo paper of the photo photo

I IMITED WARRANTY

# What does this limited warranty cover?

what does this limited warranty cover? The manufacture or this VTech Houckur warrants to the holder of a valid proof of purchase ("Consume" or "you?) that the "Houckur all accessories provided in the tailet apackage ("Houckur") are free from defects in material and workmarthype purchars to the following sums and a diversimating purchase to the following sums and accordance with the Product operating instructions. This limited warranty evends only to the consume for Phoduct purchased and used in the United States of America and Canada. will VTech do if the Product is not free fr

That will Vick-that of the Products I read free trees detects period "National Products" (Constrained and Constrained States) period "National Products" (Constrained States) period "National Products" (Constrained States) without charge, a Manuality Detective Product. If we repar-tition the states of the states of the states of states and the states of the states of the states of states and the states of the states of the states of states and the states of the states of the states of states and the states of the states of the states of states and the states of the states of the states of states and the states of the states of the states of states and the states of the states of

How long is the limited warranty period?

# How long it he limited warranty period? The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase. If VTech repairs or the limited warranty, this limited warranty data specifics to the repaired or replacement Product for a period of relation (a) of days from the date the repaired or projectionent Produc-tion (a) and the limited warranty (which were it longer). What is not covered by the limited warranty? This limited warranty idea not cover:

 Product that has been subjected to misuse, accid, shipping or other physical damage, improper in abnormal operation or handling, neglect, inunda fire, water or other liquid intrusion; or oduct that has been damaged due to repair, alteration modification by anyone other than an authorized price representative of VTech: or

Product to the extent that the problem experienced is caused by signal conditions, network reliability, or cable or antenna systems; or

 Product to the extent that the problem is caused by use with non-VTech accession or with non-VTech accessories; or 5. Product whose warranty/quality stickers, product serial number plates or electronic serial numbers have been removed, altered or rendered illegible; or Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Product used for rental purposes); or

 genera que unissent dispositis nan fía proximitió de course d. Chemos dectomagnétiques (EMF) Caproduit de Visch et conforme à buteris les normes se rapportar aux chemps déactromagnétiques (EMF) standard. Su visit la manajueux concertement en a subart les instructions de ce direction de la concertement en a subart les instructions de ce direction, solon les mellibres évidences scientifica un directions disposition autoinnement. put not limited to Products used for rental purposes; or 7. Product returned without a valid proof of purchase (see litem 2 below); or 8. Charges for installation or set up, adjustment of customer controls, and installation or repair of systems outside the unit.

VTech Communications, Inc. and its suppliers assume no responsibility for any damage or loss resulting from the use of this user's manual. VTech Communications, Inc. and its suppliers assume no responsibility for any loss or claims by third parties that may arise through the use of this product. Company: VTech Communications, Inc. How do you get warranty service? To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1(800) 595-9511. In Canada, go to www.vtechcanada.com or call 1(800) 267-7377. Company: Vien Communications, inc. Address: 9020 SW Washington Square Road - Ste 555 Tigard, OR 97223, United States Phone: 1 (800) 595-9511 in the U.S. or 1 (800) 267-7377 in Canada NOTE: Before calling for service, please review the user's manual - a check of the Product's controls and features may save you a service call.

International 2 a Deck of any Except a provided any Except a provided by populative law, you assume the risk of loss of umage during transl and transportation and any population of the provided transmit with the will intern regarded or replaced Pocket under this immedi-ments. The product of the provided transport to the provided transmit with the product during the pro-ting the provided transmit with the product during the will requere that you authorise the cost of regard pro-ting the provided transmit with the product during the pro-ting the provided transmit with the product during the pro-ting the provided transmitted transmitted to the pro-ting the provided transmitted transmitted transmitted to the pro-ting the provided transmitted transmitted to the pro-ting the provided transmitted transmitted transmitted to the pro-ting the provided transmitted transmitted to the pro-ting the provided transmitted transmitted transmitted to the pro-ting the provided transmitted transmitted transmitted to the pro-ting the provided transmitted transmitted to the pro-ting the provided transmitted transmitted to the pro-ting the provided transmitted transmitted transmitted to the pro-ting the provided transmitted transmitted transmitted to the pro-ting the provided transmitted transmitted to the pro-ting the provided transmitted transmitte

# What must you return with the Proc service?

 Return the entire original package and contents includin the Product to the VTech service location along with a description of the mailfunction or difficulty; and Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product mode the date of purchase or receipt; and Provide your name, complete and correct mailing address, and telephone number.

## Other limitations

Other imitations This warranty is the complete and exclusive agreement between you and VTach. It supersides all other writter cal communications related to this Product. The warranty each describes all of VTach's responsibilities regarding the authorized to make modifications to this limited warran-w-rhowid net net on any such modifications. State Pri-

but not limited to lost p the Product or other as

onsequential damages, so the above lit nay not apply to you.

# Please retain your original sales receipt as proof of purchase.

you should not rely on any such modification. State/Pre Law Rights: This warranty gives you specific legal rights you may also have other rights, which vary from state to or province to province.

the Product is fit for ordinary use rom the date of purchase. Some s