

PARENT UNIT ICONS (CONT'D)

Status icons

Connection status

- Strong signal strength.
- Moderate signal strength.
- Low signal strength.
- Weak signal strength.

Split mode (For VM5463-2 only)

Patrol mode (For VM5463-2 only)

Current view status

- The baby unit number that is being viewed when in:
 - Single CAM mode.
 - Patrol mode (For VM5463-2 only).
 - Split mode (For VM5463-2 only).

Night vision - On

Zoom - On

Lullaby - On

Night light - On

Night light - Auto-on

- Color icon indicates the night light is set to auto-on, and is currently turned on by sound activation.
- Gray icon indicates the night light is currently off but is set to auto-on. Night light will turn on when sound is detected by the baby unit.

Status icons

Projection light - On

Projection light - Auto on

- Color icon indicates the projection light is set to auto-on, and is currently turned on by sound activation.
- Gray icon indicates the projection light is currently off but is set to auto-on. Projection light will turn on when sound is detected by the baby unit.

Real-time temperature

- Real-time temperature detected by the baby unit in Fahrenheit (°F) or Celsius (°C) (e.g. 57°F or 14°C).

Temperature alert tone - On

9-level sound indicator

- Indicates low sound level detected by the baby unit.
- Indicates moderate sound level detected by the baby unit.
- Indicates high sound level detected by the baby unit.

Mute alert

- Displays when the parent unit speaker volume is set to off.
- Displays when the parent unit is talking to the baby unit.

Battery status

- Animates when the battery is charging.
- Battery is fully charged.
- Battery is low and needs charging.

Speaker volume - displays the parent unit speaker volume level while adjusting.

Alert icons

- Displays when parent unit's battery is low and needs charging.
- Displays when connection between parent unit and baby unit is lost.
- Displays when sound is detected at a baby unit when in Split view. (For VM5463-2 only)
- Baby unit detects temperature reaches or exceeds the set maximum.
- Baby unit detects temperature is at or is lower than the set minimum.

PROJECTION LIGHT

TIP

- The projection light located on the top of the baby unit projects a starry soft night light scene onto the ceiling with a tilting angle. Adjust your baby unit's position with the projection light to get sooth your baby to sleep. For optimal performance, place the baby unit in upright position.

Optimal position

SOUND SENSITIVITY AND SOUND ACTIVATION

Adjust sound detection sensitivity

You can turn on **Sound activation** and adjust the **VOX sensitivity** to detect sounds and turn on the parent unit when its screen is switched off or dimmed.

When the baby unit detects sounds that exceed certain levels, the parent unit screen will turn on and the baby unit starts transmitting the sounds to the parent unit, and you can see and hear your baby. If you have turned on the **Night light Auto-on** and the **Projection light Auto-on** feature, they will turn on automatically to soothe your baby.

If you turn off **Sound activation**, you will hear sounds from the baby unit all the time, even when the parent unit screen is switched off.

If you have turned on sound alert, the parent unit beeps when the baby unit detects sounds while in **Split mode** (For VM5463-2 only).

VOX SENSITIVITY LEVEL

- Level 5 (Highest)**: The parent unit screen and speaker turn on for very small sounds, including background noises from your baby's room.
- Level 4 (High)**: The parent unit screen and speaker turn on for soft babbling and louder sounds from your baby.
- Level 3 (Medium)**: The parent unit screen and speaker turn on for loud crying or screaming sounds from your baby.
- Level 2 (Low)**: The parent unit screen and speaker turn on for crying or screaming sounds from your baby.
- Level 1 (Lowest)**: The parent unit remains quiet when your baby makes soft sounds.

DISCLAIMER (Default setting): The parent unit screen and speaker turn on for soft babbling and louder sounds from your baby. The parent unit remains quiet when your baby makes soft sounds.

Sound activated screen and audio

When **Sound activation** is on, the parent unit screen stays off to save power when the baby unit detects no sound. Once the baby unit detects sounds that are louder than the chosen sound sensitivity level, the parent unit screen will turn on for 30 seconds. The parent unit will then turn off again after 50 seconds of no sound detection.

NOTE

- If you have muted the parent unit speaker, only the parent unit screen will turn on when a sound is detected.

NIGHT VISION

The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the baby unit is in black and white, and appears on the screen.

NOTES

- If normal if you see a short white glare on your parent unit screen as the baby unit is adapting to the dark environment.
- When the infrared LEDs are on, the images are in black and white. This is normal.

TIP

- Depending on the surroundings and other interfering factors, like lightings, objects, colors and backgrounds, the video quality may vary. Adjust the baby unit's angle or place the baby unit at a higher level to prevent glare and blurry display.

DIM MODE

The parent unit display will dim to conserve energy after 10 minutes of inactivity, in which there is neither key pressed nor alert received from the baby unit.

10 min inactivity

Press any button

FOR VM5463-2 ONLY

Status check - Two baby units

If you are viewing baby unit 1, the **POWER LED** light of baby unit 2 turns on. As the baby unit 2 is not being viewed, its **POWER LED** light flashes.

NOTE

- If you power on only one baby unit, you may see the parent unit displaying and then the **LINK LED** light flashing.
- Press **VIEW** in **Single CAM** or **Patrol mode** to switch to the baby unit you have powered on.

Change different views - Single CAM

In **Single CAM** or **Patrol mode**, press **VIEW** to switch between the image of baby units 1 and 2.

Press VIEW

Change different views - Patrol

Select **Patrol** as your monitoring mode to alternately view the image from baby units 1 and 2 every 10 seconds.

Change different views - Split

Select **Split** as your monitoring mode to alternately view the images from both baby units at once.

MOUNT THE BABY UNIT ON DRY WALL (OPTIONAL)

NOTES

- Check for reception strength and camera angle before drilling the holes.
- The types of screws and anchors you need depend on the composition of the wall. You may need to purchase the screws and anchors separately to mount your camera units.

- Place the wall mount bracket on a wall and then use a pencil to mark two holes in parallel. Remove the wall mount bracket and drill two holes in the wall (7/32 inch drill bit).
- If you drill the holes into a stud, go to step 3.
 - If you drill the holes into an object other than a stud, insert the wall anchors into the holes. Tap gently on the ends with a hammer until the wall anchors are flush with the wall.
- Insert the screws into the holes and tighten the screws until 1/4 inch of the screws are exposed.
- Place the camera unit on the wall mount bracket, and then slide it forward until it locks into place. Align the holes on the wall mount bracket with the screws on the wall, and slide the wall mount bracket down until it locks into place.
- You can maximize your camera unit's viewing angles by tilting the wall mount bracket. Hold the camera unit, and then rotate the knob in anticlockwise direction. This will loosen the joint of the wall mount bracket. Tilt your camera unit up or down to adjust to your preferred angle. Then, rotate the knob in clockwise direction to tighten the joint and secure the angle.

THE RBRC SEAL

The RBRC seal on the Li-Ion battery indicates that Vtech Communications, Inc. is voluntarily participating in an industry program to collect and recycle these batteries at the end of their useful lives, when taken to a recycling service within the United States and Canada.

Vtech's participation makes it easy for you to drop off the spent battery at local retailers participating in the program or at authorized Vtech product service centers. Please call a **1-800-8-BATTERY** for information on local battery recycling and collection restrictions in your area. Vtech's participation in this program is part of its commitment to protecting our environment and conserving natural resources.

The RBRC seal and 1-800-8-BATTERY are registered trademarks of CalRecycle, Inc.

FCC AND IC REGULATIONS

FCC Part 15

This device has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This Class B digital apparatus complies with Canadian requirement: CAN ICES-3 (B) / NMB-3 (B).

This device contains license-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's license-exempt RSSI. Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

The term "IC" before the certification/registration number only signifies that the Industry Canada technical specifications were met. This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.

RF radiation exposure statement

The baby unit complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. The baby unit should be installed and operated with a minimum distance of 19 (20 cm) between the baby unit and all persons' body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. This transmitter must not be co-located or operating in close proximity with other transmitters or receivers that operate on the same frequency.

RF radiation exposure statement

The baby unit complies with the applicable Innovation, Science and Economic Development Canada technical specifications.

CALIFORNIA ENERGY COMMISSION BATTERY CHARGING TESTING MODE

This baby monitor meets the California Energy Commission (CEC) regulations for energy conservation. Your baby monitor is set up to comply with the energy conservation standards right out of the box. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to baby units, the CEC battery charging testing mode is activated while it is powered off and charging.

FOR CETL COMPLIANCE ONLY

Measures de sécurité importantes

Les renseignements applicables sont situés au bas du socle de l'unité de bébé.

Lorsque vous utilisez votre appareil, vous devriez toujours utiliser certaines mesures de précaution de base afin de réduire les risques d'incendie, d'électrocution ou de blessures corporelles, y compris :

- Observez toutes les instructions de mise en marche inscrites sur l'appareil.
- L'installation par un adulte est requise.
- MISE EN GARDE:** N'installez pas l'unité de bébé à une hauteur supérieure à 2 mètres.
- Ne touchez pas l'appareil à l'intérieur de l'enceinte de l'unité de bébé. La supervision du haut-parleur et du microphone de l'appareil doit être assurée à tout moment. Ne laissez pas l'appareil fonctionner sans surveillance pendant une période de temps prolongée. De plus, il ne doit pas être utilisé comme un dispositif médical et ne devrait pas être utilisé comme tel.
- N'utilisez pas cet appareil près de l'eau ni de toute autre source de chaleur, par exemple, près d'une bougie, d'une chaise à réchauffer, d'un sèche-cheveux, d'un sèche-linge ou d'un sèche-solinge.
- MISE EN GARDE:** Utilisez uniquement les piles fournies. Il ne faut pas utiliser d'autres piles que celles recommandées par le fabricant. Ne réinsérez pas de piles. Celles-ci peuvent être dangereuses si elles ne sont pas utilisées conformément aux instructions.
- N'utilisez que les adaptateurs inclus avec ce produit.
- L'utilisation d'un adaptateur différent de celui-ci peut causer une surchauffe ou une surtension de l'appareil et entraîner un incendie ou des dommages matériels.

MISE EN GARDE: Utilisez uniquement les piles fournies. Il ne faut pas utiliser d'autres piles que celles recommandées par le fabricant. Ne réinsérez pas de piles. Celles-ci peuvent être dangereuses si elles ne sont pas utilisées conformément aux instructions.

CONSERVEZ CES INSTRUCTIONS

Mises en garde

- Évitez d'exposer le produit à une température entre 10°C et 35°C.
- Ne placez pas le produit à l'extérieur.
- Ne placez pas le produit à l'intérieur d'un véhicule automobile, à moins qu'il n'y ait une ventilation adéquate.
- Le bloc-chargeur ne doit pas être exposé à la chaleur excessive ou à la lumière directe du soleil.
- Ne laissez pas le produit à l'intérieur d'un véhicule automobile pendant une longue période.

ATTENTION: Risque de strangulation des enfants. Ne laissez pas les enfants jouer avec les câbles, les cordons, les fils ou les fils de l'appareil.

ATTENTION: Ne laissez pas les enfants jouer avec les câbles, les cordons, les fils ou les fils de l'appareil.

LIMITED WARRANTY

What does this limited warranty cover?

The manufacturer of the Vtech Product warrants to the holder of a valid proof of purchase ("Consumer" or "you") that the Product and all accessories provided in the sales package ("Product") are free from defects in material and workmanship, pursuant to the following terms and conditions, when installed and used normally and in accordance with the Product operating instructions. This limited warranty extends only to the Consumer for Products purchased and used in the United States of America and Canada.

What will Vtech do if the Product is not free from defects in material and workmanship during the limited warranty period ("Materially Defective Product")?

During the limited warranty period, Vtech's authorized service representatives will replace a Vtech's product, without charge, a Materially Defective Product. If we choose to replace defective parts, modules, or equipment. Replacement of the Product, at Vtech's option, is your exclusive remedy. Vtech will return the replacement Products to you in working condition. You should expect the replacement to take approximately 30 days.

How long is the limited warranty period?

The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase (90 days on products purchased as Refurbished). This limited warranty also applies to the replacement Product for a period of either (a) 90 days from the date the replacement Product is shipped to you (b) the time remaining on the original one-year warranty (whichever is longer).

What is not covered by this limited warranty?

This limited warranty does not cover:

- Product that has been subjected to misuse, accident, shipping or other physical damage, improper installation, abnormal operation or handling, neglect, inundation, fire, water or other liquid immersion or;
- Product that has been damaged due to repair, alteration or modification by anyone other than an authorized service representative of Vtech; or
- Product to the extent that the problem experienced is caused by pre-existing conditions, network reliability, or cable or antenna system; or
- Product to the extent that the problem is caused by use of non-approved accessories.

Product purchased, used, serviced, or shipped for repair from outside the United States or America, or Canada, or for use in other countries, is not covered by this warranty, but not limited to Products used for commercial purposes.

Product returned without a valid proof of purchase item 2 below.

Charge for installation or set up, adjustment of customer controls, and installation or repair of systems under the unit.

Please retain your original sales receipt as proof of purchase.

How do you get warranty service?

To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1(800) 995-9311. In Canada, go to www.vtechcanada.com or call 1(800) 263-7377.

NOTE: Before calling for service, please review the user's manual - a check of the Product's controls and features may save you a service call.

Except as provided by applicable law, you assume the risk of loss or damage during transit and transportation and are responsible for delivery or handling charges incurred in the transport of the Product(s) to the service location. Vtech will return replaced Product(s) under this limited warranty. Transportation, delivery or handling charges are prepaid. Vtech assumes no risk of damage or loss of the Product in transit.

What must you return with the Product to get warranty service?

- Return the entire original package and contents including the Product to the Vtech service location along with a description of the malfunction or difficulty and your proof of purchase.
- Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or receipt; and
- Provide your name, complete and correct mailing address, and telephone number.

Other limitations

This warranty is the complete and exclusive agreement between you and Vtech. It supersedes all other written or oral communications related to this Product. Vtech provides no other warranties for this Product. The warranty exclusively describes all of Vtech's responsibilities regarding the Product. There are no other express warranties. No one is authorized to make modifications to this limited warranty and you should rely on any such modifications. State-Provincial Law Repeals: This warranty gives you specific legal rights, and you may also have other rights, which vary from state to state or province to province.

Limitations: Modifications, including those of fitness for a particular purpose and merchantability (an unwritten warranty that the Product is fit for ordinary use) are limited one year from the date of purchase. Some states' provisions do not allow limitations on how long an implied warranty may last, so the above limitation may not apply to you. In no event shall Vtech be liable for any indirect, special, incidental, consequential, or similar damages (including, but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of lost data or equipment, and claims by third parties) resulting from the use of this Product. Some states' provisions do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you.