

Level	VTN Part Number	Part Description	Extra Description	Qty	Reference
PARENT	80-4222-00-00	SONY CPX971,ADL-MKII-B,BLAC		1	
1	85-4222-02-00	PACK ASSY,SONY CPX971,BLK		1	
.2	30-5132-00-00	WALL-MNT,SONY971,BU,BLK,R,0		1	
.2	46-4016-10-00	PHONE CORD,BLK,6WX2CONT,7"L		1	
.2	46-4035-00-00	PHONE CORD BLK 6WX2CONT,9"L		1	
1	85-4222-00-00	PROD ASSY,SONY CPX971,HS,BL		1	
.2	50-4222-02-00	PCBA,CPX971,HS,AUDIO,MAIN		1	
..3	14-3400-60-24	STD,BLK,1571,#30,40L,2T2T		1	
..3	14-3400-62-24	STD,RED,1571,30#,40L,2T2T		1	
..3	14-3900-42-00	STD WIRE,RED,UL,#26,90L,3T3		1	
..3	22-7200-00-07	CAP,TRIM,20PF,100V,N450		1	C1
..3	25-	CRYSTAL,4MHZ,COMMUTEK		1	X1
..3	30-5127-00-00	SWITCH SONY971,HS,BLK,R,0,0		1	
..3	39-3404-00-00	FOAM TAPE		1	
..3	43-1052-00-33	LED,GREEN,SML010MT		0	D1,D2,D3,D9
..3	43-1065-00-00	LED,DIFFUSE,RED,D3X5.2		1	D5
..3	47-1003-60-00	ANTENNA		1	
..3	50-	PCBA,CPX971,HS,AUDIO SMD BD		1	
..4	20-0039-01-00	X'TR,CHIP,MMBT3906T,SOT23,RL	TRANSISTOR,CHIP,MMBT3906T	7	Q12,Q13,Q14,Q16,Q18,Q19,Q2
..4	20-0041-01-00	X'TR,MMBT3904LT1,SOT-23,REEL	MMBT3904LT1,SOT-23,L PROF.REE	4	Q1,Q15,Q17,Q20
..4	21-0001-01-00	DIODE,SW,SOT23,SMD BAS16		1	D6
..4	21-1035-04-00	DIODE,SW,SOT23		2	D7,D8
..4	21-1042-04-00	DIODE,TVS,SOT23,SM12,SMD		1	D14
..4	22-2105-30-33	CAP,TANT,1UF,16V,10%		1	C102
..4	22-2106-01-33	CAP,TANT,10UF,6V,20%		3	C100,C119,C99
..4	22-2225-21-33	CAP,TANT,2.2UF,10V,+20%		3	C113,C122,C126
..4	22-3101-25-G6	CAP,CER,100PF,50V,5%		4	C103,C137,C95,C97
..4	22-3102-26-G5	CAP,CER,1000PF,50V,+10%		3	C118,C127,C139
..4	22-3104-06-G5	CAP,CER,0.1UF,16V,10%		6	C107,C108,C109,C121,C3,C40
..4	22-3123-26-G5	CAP,CER,0.012UF,50V,10%		1	C111
..4	22-3182-26-G5	CAP,CER,RL,1800P,50V,10%		1	C101
..4	22-3220-25-G6	CAP,CER,22PF,50V,+5%		3	C140,C75,c91
..4	22-3221-25-G6	CAP,CER,RL,220PF,50V,5%		2	C104,C132
..4	22-3222-26-G5	CAP,CER,2200PF,50V,+10%		1	C128
..4	22-3223-16-G5	CAP,CER,RL,22NF,25V,10%		2	C116,C2
..4	22-3224-20-M3	CAP,CER,SMD,0.22UF,16V,10%		1	C129
..4	22-3330-25-G6	CAP,CER,33PF,50V,5%		2	C105,C131
..4	22-3470-25-G6	CAP,CER,RL,47PF,50V,5%		1	C134
..4	22-3472-26-G5	CAP,CER,4700PF,50V,10%,RL,X		1	C112
..4	22-3473-06-G5	CAP,CER,RL,47NF,16V,10%		5	C110,C114,C123,C125,C138
..4	22-3561-26-G5	CAP,CER,560PF,50V,10%		2	C106,C130
..4	22-3680-25-G6	CAP,CER,RL,68PF,50V,5%		1	C124
..4	22-3759-20-G6	CAP,CER,7.5PF,50V,+0.25PF		1	C93
..4	23-0101-86-21	RES,CR,SMD,REEL,100,1/16W,5		3	R10,R71,R78
..4	23-0102-86-21	RES,CR,SMD,REEL,1K,1/16W,5%		5	R100,R11,R114,R122,R138
..4	23-0103-86-21	RES,CR,SMD,REEL,10K,1/16W,5		6	R1,R106,R107,R115,R143,R98
..4	23-0104-86-21	RES,CR,SMD,REEL,100K,1/16W,		6	R134,R23,R36,R74,R75,R95
..4	23-0105-86-21	RES,CR,SMD,RL,1M OHM,1/16W,		2	R144,R146
..4	23-0106-86-21	RES,CF,SMD,RL,10M OHM,1/16W		2	R90,R96
..4	23-0123-86-21	RES,CER,SMD,RL,12K 1/16W,5%		1	R111
..4	23-0150-86-21	RES,SMD,RL,15R OHM,1/16W,5%		1	R139
..4	23-0152-86-21	RES,CR,SMD,REEL,1K5,1/16W,5		1	R42
..4	23-0153-86-21	RES,CR,SMD,REEL,15K,1/16W,5		1	R77
..4	23-0154-86-21	RES,SMD,RL,150K OHM,1/16W,5		3	R129,R130,R131
..4	23-0184-86-21	RES,CR,0603,RL,180K,1/16W,5		4	R108,R109,R110,R116
..4	23-0222-86-21	RES,CR,SMD,2.2K OHM,1/16W,5		2	R102,R121
..4	23-0224-86-21	RES,CR,SMD,REEL 220K,1/16W		5	R105,R140,R24,R65,R81
..4	23-0273-86-21	RES,CR,SMD,REEL,27K,1/16W,5		1	R4
..4	23-0333-86-21	RES,SMD,33K OHM,1/16W,5%		3	R124,R133,R94
..4	23-0394-86-21	RES,CF,SMD,RL,390K,1/16W,5%		1	R103
..4	23-0471-86-21	RES,CR,SMD,REEL,470,1/16W,5		1	R142
..4	23-0473-86-21	RES,CR,SMD,REEL,47K,1/16W,5		7	R141,R49,R63,R69,R70,R97,R99
..4	23-0474-86-21	RES,CF,SMD,RL,470K,1/16W,5%		4	R123,R125,R127,R82
..4	23-0513-86-21	RES,CR,SMD,REEL,51K,1/16W,5		1	R128
..4	23-0561-86-21	RES,CR,SMD,560 OHM,1/16W,5%		1	R76
..4	23-0564-86-21	RES,CR,SMD,RL,560K,1/16W,5%		2	R147,R91
..4	23-0624-86-21	RES,CR,SMD,REEL,620K,1/16W,		1	R145
..4	23-0682-86-21	RES,CR,SMD,REEL,6.8K,1/16W,		1	R80
..4	23-0823-86-21	RES,CR,0603,REEL,82K,1/16W,		2	R112,R3
..4	23-0824-86-21	RES,SMD,REEL,820K,1/16W,5%		2	R135,R89
..4	23-1003-G0-21	RES,CR,SMD,RL,100K,1/16W,+		3	R84,R86,R88
..4	23-1473-G0-21	RES,CR,SMD,RL,1/16W,147K,1%		1	R87
..4	23-1823-G0-21	RES,RL,182K,CR,SMD,1/16W,1%		1	R85
..4	23-1913-G0-21	RES,CR,SMD,RL,1/16W,191K,1%		1	R83
..4	24-2103-10-05	VR-TRIM TOP 10K +-25%		2	R113,R119
..4	27-5210-13-05	IC,COMPANDER,SSOP24		1	U7
..4	27-2026-03-01	IC,LOW DROPOUT REGULATOR		1	U11

...4	27-3280-00-00	IC MCU,OPT,MC68HSC705P6DW		1	U3
...4	27-5015-09-01	IC,QUAD OP AMP,CHIP,TAPE&RE		1	U5
...4	35-4393-00-00	PCB,CPX971,HS,AUDIO,R.0		1	
.2	50-4222-00-00	PCBA,CPX971,HS,RF,MAIN		1	
...3	10-3013-00-00	PTS DIA2X8,BH(+),ZN-CR PLT		10	
...3	22-7200-00-07	CAP,TRIM,20PF,100V,N450		1	C10
...3	23-0000-81-14	RES,CF,SMD,RL,0 OHM,1/8W,5%		1	R1
...3	25-2212-00-39	IFT,7MM,10.7MHZ,100PF,Q=60		1	L2
...3	25-3128-00-10	FILTER,CER,10.7MHZ,230KHZ		1	F5
...3	25-3321-00-10	FILTER,CER,10.7MHZ,BW(150KH		1	F4
...3	30-4808-00-00	RF-SHIELD,FR HS ADLMK2A R.0		1	
...3	30-4809-00-00	RF-SHIELD,REAR HS ADLMK2A R		1	
...3	46-1177-00-00	F-CABLE #28 3+40+3X10WAYS R		1	
...3	50-	PCBA,VT9111,HS,RF SMD BD		1	
...4	20-1142-03-00	X'TR,RF,NPN,SOT343,RL,BFP67		1	Q2
...4	20-3067-13-00	X'TR,RF,NPN,SOT323,RL,2SC4083	HFE 80-180,2SC4083T106P	3	Q1,Q3,Q8
...4	21-1047-04-00	DIODE,VRA,USC,SMD	2-16P,1SV214	3	D1,D2,D3
...4	22-3102-26-G5	CAP,CER,1000PF,50V,+10%	SM,RL,X7R,GRM39	4	C10,C21,C33,C38
...4	22-3103-26-G5	CAP,CER,0.01UF,50V,+10%	SM,RL,X7R,GRM39	4	C11,C24,C29,C39
...4	22-3104-06-G5	CAP,CER,0.1UF,16V,10%	SMD,0603,RL,X7R	2	C23,C28
...4	22-3109-29-G6	CAP,CER,1PF,50V,+0.1PF		1	C67
...4	22-3123-26-G5	CAP,CER,0.012UF,50V,10%	SMD,RL,X7R,0603	1	C84
...4	22-3129-29-G6	CAP,CER,1P2,50V,+0.1PF		1	C63
...4	22-3151-25-G6	CAP,CER,RL,150PF,50V,5%	0603	5	C26,C30,C65,C78,C79
...4	22-3159-29-G6	CAP,CER,1.5PF,50V,+0.1PF	SM,RL,COG,GRM39	4	C15,C51,C60,C7
...4	22-3189-29-G6	CAP,CER,1.8PF,50V,+0.1PF	SM,RL,COG,GRM39	1	C54
...4	22-3249-29-G6	CAP,CER,2P4,50V,+0.25P,COG		1	C1
...4	22-3272-26-G5	CAP,CER,2.7NF,50V,10%	0603	1	C89
...4	22-3273-16-G5	CAP,CER,SMD,27NF,25V,10%	0603	1	C76
...4	22-	CAP,CER,0.33UF,25V,10%	SMD,RL,X7R,0805	1	C83
...4	22-3470-25-G6	CAP,CER,RL,47PF,50V,5%	0603	14	C13,C14,C16,C19,C20,C31,C35,C36,C37,C57,C64,C8,C85,C9
...4	22-3471-26-G5	CAP,CER,470PF,50V,+10%	SM,RL,X7R,GRM39	1	C77
...4	22-3479-20-G6	CAP,CER,4.7PF,50V,+0.25PF		9	C12,C2,C58,C59,C6,C70,C71,C74,C82
...4	22-3560-25-G6	CAP,CER,56PF,50V,+5%	SM,RL,COG,GRM39	1	C22
...4	22-3569-20-G6	CAP,CER,5.6PF,50V,+0.25PF	SM,RL,COG,GRM39	2	C34,C5
...4	22-3629-25-G6	CAP,CER,6.2PF,50V,5%	SMD,0603	1	C3
...4	22-3689-20-G6	CAP,CER,6.8PF,50V,+0.25PF	SM,RL,COG,GRM39	5	C17,C55,C66,C72,C81
...4	22-3759-20-G6	CAP,CER,7.5PF,50V,+0.25PF	SM,RL,COG,GRM39	3	C32,C4,C86
...4	22-3919-20-G6	CAP,CER,9.1PF,50V,0.25PF		2	C52,C69
...4	23-0102-86-21	RES,CR,SMD,REEL,1K,1/16W,5%	MCR03EZHJW102	2	R132,R14
...4	23-0103-86-21	RES,CR,SMD,REEL,10K,1/16W,5%	MCR03EZHJW103	9	R120,R27,R45,R51,R53,R54,R57,R67,R68
...4	23-0106-86-21	RES,CF,SMD,RL,10M OHM,1/16W,5		2	R48,R61
...4	23-0120-86-21	RES,CR,SMD,REEL,12,1/16W,5%		1	R6
...4	23-0181-86-21	RES,CR,SMD,REEL,180,1/16W,5%	0603 CHIP RESISTOR	1	R4
...4	23-0153-86-21	RES,CR,SMD,REEL,15K,1/16W,5%	MCR03EZHJW153	1	R12
...4	23-0223-86-21	RES,CR,SMD,REEL,22K,1/16W,5%	MCR03EZHJW223	1	R3
...4	23-0240-86-21	RES,CR,SMD,REEL,24,1/16W,5%	MCR03EZHJW240	4	R29,R37,R50,R52
...4	23-0271-86-21	RES,SMD,RL,270 OHM,1/16W,5%	0603	2	R32,R41
...4	23-0273-86-21	RES,CR,SMD,REEL,27K,1/16W,5%	MCR03EZHJW273	1	R5
...4	23-0303-86-21	RES,SMD,RL,30K OHM,1/16W,5%	0603	1	R47
...4	23-0470-86-21	RES,CR,SMD,REEL,47,1/16W,5%		1	R2
...4	23-0472-86-21	RES,SMD,RL,4.7K OHM 1/16W,5%	0603	1	R66
...4	23-0512-86-21	RES,CR,SMD,REEL,5K1,1/16W,5%	MCR03EZHJW512	1	R58
...4	23-0561-86-21	RES,CR,SMD,560 OHM,1/16W,5%		2	R13,R16
...4	23-0621-86-21	RES,CR,SMD,620 OHM,1/16W,5%	MCR03EZHJW750	1	R15
...4	23-0680-86-01	RES,SMD,RL,68,1/16W,5%	CR,0603	2	R8,R9
...4	23-0750-86-21	RES,CR,SMD,REEL,75,1/16W,5%		2	R31,R40
...4	23-0820-86-21	RES,CF,SMD,RL 82 OHM,1/16W,5%		1	R34
...4	23-0910-86-21	RES,SMD,RL,91R,1/16W,5%		2	R33,R35
...4	23-1002-G0-21	RES,CR,SMD,RL,1/16W,10K0,1%	0603	1	R39
...4	23-1102-G0-21	RES,CR,SMD,RL,11K,1/16W,+1%	MCR03,0603	1	R30
...4	23-1302-G0-21	RES,CR,SMD,REEL,13K,1/16W,1%	MCR03,0603	1	R38
...4	23-1502-G0-21	RES,CR,SMD,RL,1/16W,15K0,1%	0603	1	R28
...4	25-3515-00-10	FILTER,BAND PASS,903MHZ		1	F1
...4	25-3516-00-10	FILTER,BAND PASS,926MHZ		1	F2
...4	25-3525-00-10	FILTER,SAW,903.65MHZ		1	F3
...4	25-7339-75-10	INDUCTOR 3.3UH,5%,SMD		1	L12
...4	27-6674-13-05	IC,PLL,SSOP-16		1	U3
...4	27-66F0-03-99	IC,FM DEMOD,SSQ28,U2765B		1	U1
...4	35-4331-00-00	PCB,ADL MK2B,HS,RF,BD,R.0		1	
.2	52-4222-00-00	CASING ASSY,CPX971,HS,BLACK		1	
...3	10-0245-00-01	PL-S,STL,D3X10 PH(+),ZN-CR		2	
...3	10-0246-00-01	PL-S,STL,D3X12 PH(+),ZN-CH		2	
...3	10-3034-00-00	PTS,STL,D2X5,BH(+),ZN-CR PL		5	
...3	11-1055-00-00	SPR WASHER #6		1	
...3	28-0054-10-21	MICROPHONE CONDENSER,CMT-60		1	U9
...3	28-0082-05-00	RECEIVER,DYNAMIC		1	U8
...3	28-1007-02-00	TRANSDUCER,BUZZER,2048HZ		1	U4
...3	29-1119-00-14	BATT-ASSY NI-CD AA-SIZE 3X1		1	

..3	30-4900-01-00	BATT-HOUSING		1	
..3	30-4901-01-10	BATT-HOUSING		1	
..3	30-4933-00-00	ANTENNA SUPPORT 910ADL BLK		1	
..3	30-5127-00-00	SWITCH SONY971,HS,BLK,R.0,0		1	
..3	30-5128-10-00	LENS-FR,HS,SONY971,TRS,R.1,		1	
..3	30-5129-00-00	DOOR-BATT,HS,SONY971,BLK,R0		1	
..3	30-5130-00-00	CASE-REAR,SONY971,HS,BLK,R.		1	
..3	30-5131-10-00	CASE-FR,HS,SONY971,BLACK,R.		1	
..3	30-5188-00-00	ANTENNA SLEEVE SONY ADL BLK		1	
..3	31-4277-00-00	ANTENNA HOLDER 910ADL R.0		1	
..3	31-4309-00-00	CONTACT-BKT,HS,SONY971,R.0,		3	
..3	31-4330-00-00	CONTACT-BATT,HS,SONY-971,R.		2	
..3	32-5116-00-00	CONDUCTIVE TAPE,HS,SONY971,		1	
..3	34-4009-00-00	ANTENNA COIL-WIRE 910ADL R.		1	
..3	39-4105-00-00	RECEIVER RING HS SONY R.0		1	
..3	39-4260-00-00	BUZ-FELT HS BLK ADLMK2A R0		2	
..3	39-4264-01-00	MIC HOLDER HS ADLMK2A R1		1	
..3	39-4303-10-00	RUBBER PAD,BU,SONY971,BLK,R		1	
1	85-4222-01-00	PROD ASSY,SONY CPX971,BS,BL		1	
.2	52-4222-01-00	CASING ASSY,CPX971,BS,BLACK		1	
..3	10-0245-00-01	PL-S,STL,D3X10 PH(+),ZN-CR		3	
..3	10-1064-00-00	PTS STS D3X16 PH(+) ZN-CR P		9	
..3	10-3001-00-00	PTS,STL,D2.6X8,PH(+),ZN-CR,		3	
..3	30-4455-41-10	SWITCH CAP BU		1	S1
..3	30-5121-00-00	HOOK,SONY971,BU,BLK,R.0,0		1	
..3	30-5122-00-00	LI-GUIDE,SONY971,BU,TRS,R.0		1	
..3	30-5123-00-00	KNOB-PG,BU,SONY971,BLK,R.0,		1	
..3	30-5125-00-00	BASE BTM,SONY971,BLK,R.0,0		1	
..3	30-5126-10-00	BASE TOP,SONY971,BLK,R.1,0		1	
..3	31-4161-00-00	ANT-BRACKET BU ADL-MK2 R.0		1	
..3	31-4308-00-00	CONTACT-BKT,BU,SONY971,R.0,		3	J2,J3,J4
..3	39-4060-00-00	RUBBER FT,AT&T9100,BLK,R.0		2	
.2	50-4222-06-00	PCBA,CPX971,BS,AUDIO,MAIN		1	
..3	14-1000-30-00	JMP WIRE,NI,0.6D		0	
..3	20-1122-00-00	OPTO-COUPLER,PS2532-1,DIP,BUL	CTR>1500%	1	U1
..3	20-8004-13-18	OPTO-COUPLER,LTV817		1	U2
..3	21-0001-00-00	DIODE,1N4148,TAPE AND REEL		1	D6
..3	21-0012-00-05	DIODE,RE,1N4004 400V 1A		4	D1,D2,D3,D4
..3	21-0199-00-00	DIODE,VAI,MTL OX,D7MM(V300L		1	D7
..3	21-3004-02-00	DIODE,ZENER,AXL,REEL		2	D8,D9
..3	22-1100-61-U4	CAP,ELEC,10U,50V,20%		4	C10,C28,C29,C6
..3	22-1101-21-U4	CAP,ELEC,100U,16V,20%	RAD,SMR	1	C12
..3	22-1229-61-U4	CAP,ELEC,2.2UF,50V,20%		2	C30,C47
..3	22-3102-26-W9	CAP,CER,1NF,50V,10%	COG,CHIP,REEL	2	C13,C14
..3	22-6474-66-74	CAP,METAL,0.47UF,250V,10%		1	C1
..3	22-7200-00-07	CAP,TRIM,20PF,100V,N450		1	C56
..3	23-0012-15-01	RES,CF,AXL,RL,100 OHM,1W,5%	RES,CF,AXL,REEL	1	R25
..3	23-0014-11-01	RES,CF,AXL,RL,10K OHM,1/8W,		1	R1
..3	23-0680-15-00	RES,CF,AXL,BULK,68 OHM,1W,5		2	R78
..3	24-0074-00-00	VR,5K (RVF6P01A-502N)	SEMI FIXED RESISTOR	2	R39,R40
..3	25-1114-00-67	COIL-INDTR,RL,10UH 10% Q>80		2	L3,L4
..3	25-3539-00-66	CRYSTAL,4MHZ,10PPM,HC-49/U		1	X1
..3	25-5223-00-A4	X'FR,AUDIO,EI-19		1	T1
..3	27-2109-00-00	IC,REGULATOR,5V		1	U9
..3	40-5062-00-67	TEL JACK,PCB,6PX2C(3,4),AU-		1	J1
..3	40-6097-00-00	DC PWR SOCKET		1	J2
..3	44-0065-00-01	FUSE,SLO-BLO,W/PIG,,25A,250		1	W1
..3	46-1182-01-00	FLAT CABLE #28 4+70+4X6WAY		1	J3
..3	50-4222-07-00	SMDA,CPX971,BS,AUDIO,MAIN		1	
..4	20-0039-01-00	X'TR,CHIP,MMBT3906T,SOT23,R		3	Q11,Q5,Q6
..4	20-0041-01-00	X'TR,MMBT3904LT1,SOT-23,REE		4	Q10,Q7,Q8,Q9
..4	22-3103-26-G5	CAP,CER,0.01UF,50V,+/-10%		4	C24,C42,C5,C50
..4	22-3104-06-G5	CAP,CER,0.1UF,16V,10%		6	C2,C37,C38,C39,C51,C7
..4	22-3120-25-G6	CAP,CER,12PF,50V,5%		1	C31
..4	22-3182-26-G5	CAP,CER,RL,1800P,50V,10%		1	C34
..4	22-3220-25-G6	CAP,CER,22PF,50V,+/-5%		1	C52
..4	22-3221-25-G6	CAP,CER,RL,220PF,50V,5%		2	C25,C33
..4	22-3223-16-G5	CAP,CER,RL,22NF,25V,10%		2	C45,C46
..4	22-3224-20-M3	CAP,CER,SMD,0.22UF,16V,10%		2	C21,C23
..4	22-3270-25-G6	CAP,CER,RL,27PF,50V,5%		1	C53
..4	22-3330-25-G6	CAP,CER,33PF,50V,5%		2	C26,C35
..4	22-3332-26-G5	CAP,CER,RL,3.3NF,50V,10%		1	C20
..4	22-3392-25-G6	CAP,CER,RL,3900PF,50V,10%		1	C48
..4	22-3470-25-G6	CAP,CER,RL,47PF,50V,5%		1	C22
..4	22-3472-26-G5	CAP,CER,4700PF,50V,10%,RL,X		4	C17,C19,C41,C43
..4	22-3473-06-G5	CAP,CER,RL,47NF,16V,10%		2	C32,C4
..4	22-3561-26-G5	CAP,CER,560PF,50V,10%		2	C27,C36
..4	22-3681-26-G5	CAP,CER,680PF,50V,10%		1	C49
..4	22-3759-20-G6	CAP,CER,7.5PF,50V,+/-0.25PF		1	C54

...4	22-3822-26-G5	CAP,CER,8200PF,50V,10%,RL,X7R		1	C40
...4	23-0102-86-21	RES,CR,SMD,REEL,1K,1/16W,5%		3	R34,R55,R89
...4	23-0103-86-21	RES,CR,SMD,REEL,10K,1/16W,5		4	R23,R26,R47,R48
...4	23-0104-86-21	RES,CR,SMD,REEL,100K,1/16W,		6	R33,R38,R62,R81,R83,R85
...4	23-0105-86-21	RES,CR,SMD,RL,1M OHM,1/16W,		4	R32,R44,R45,R46
...4	23-0106-86-21	RES,CF,SMD,RL,10M OHM,1/16W		1	R84
...4	23-0113-86-21	RES,CR,SMD,RL,11K,1/16W,5%		1	R28
...4	23-0123-86-21	RES,CER,SMD,RL,12K 1/16W,5%		2	R78,R79
...4	23-0124-86-21	RES,CR,SMD,REEL,120K,1/16W,5%		1	R54
...4	23-0153-86-21	RES,CR,SMD,REEL,15K,1/16W,5		1	R76
...4	23-0154-86-21	RES,SMD,RL,150K OHM,1/16W,5		3	R41,R42,R43
...4	23-0181-86-21	RES,CR,SMD,REEL,180,1/16W,5%	0603 CHIP RESISTOR	2	R5,R6
...4	23-0183-86-21	RES,CR,SMD,REEL,18K,1/16W,5%		1	R53
...4	23-0184-86-21	RES,CR,0603,RL,180K,1/16W,5		3	R50,R51,R52
...4	23-0201-86-21	RES,CR,SMD,REEL,200,1/16W,5%	MCR03EHJW201	1	R20
...4	23-0223-86-21	RES,CR,SMD,REEL,22K,1/16W,5		4	R27,R29,R30,R88
...4	23-0273-86-21	RES,CR,SMD,REEL,27K,1/16W,5%		1	R82
...4	23-0334-86-21	RES,CF,SMD,RL,330K,1/16W,5%		2	R57,R58
...4	23-0364-86-21	RES,SMD,360K OHM,1/16W,5%		1	R37
...4	23-0392-86-21	RES,CR,SMD,REEL,3.9K 1/16W 5%		1	R4
...4	23-0393-86-21	RES,CR,SMD,REEL,39K,1/16W,5		1	R56
...4	23-0472-86-21	RES,SMD,RL,4.7K OHM 1/16W,5		3	R17,R18,R19
...4	23-0473-86-21	RES,CR,SMD,REEL,47K,1/16W,5		6	R21,R24,R35,R61,R75,R80
...4	23-0474-86-21	RES,CF,SMD,RL,470K,1/16W,5%		2	R31,R36
...4	23-0561-86-21	RES,CR,SMD,560 OHM,1/16W,5%		2	R2,R86
...4	23-0564-86-21	RES,CR,SMD,RL,560K,1/16W,5%		1	R49
...4	23-0682-86-21	RES,CR,SMD,REEL,6.8K,1/16W,		2	R22,R3
...4	23-1002-G0-21	RES,CR,SMD,RL,1/16W,10K,1%		6	R60,R64,R66,R68,R70,R72
...4	23-2002-G0-21	RES,CR,SMD,RL,1/16W,20K0,1%		7	R63,R65,R67,R69,R71,R73,R74
...4	23-6192-G0-21	RES,SMD,RL,61K9,1/16W,1%(06		1	R59
...4	27-3099-03-N7	IC EEPROM 6MS 93C46M8		1	U7
...4	27-3280-00-00	IC MCU,OPT,MC68HSC705P6DW		1	U6
...4	27-5015-09-01	IC,QUAD OP AMP,CHIP,TAPE&RE		1	U5
...4	27-5210-03-05	COMPANDER,IC,24-PIN		1	U4
...4	35-4378-00-00	PCB,CPX971,BS,AUDIO,R0		1	
.2	50-4222-04-00	PCBA,CPX971,BS,RF,MAIN		1	
...3	10-3013-00-00	PTS DIA2X8,BH(+),ZN-CR PLT		11	
...3	22-7200-00-24	CAP,TRIM,20P,100V,N450		1	C99
...3	23-0000-81-14	RES,CF,SMD,RL,0 OHM,1/8W,5%		1	R1
...3	25-2212-00-39	IFT,7MM,10.7MHZ,100PF,Q=60		1	L12
...3	25-3128-10-10	FILTER,CER,10.7MHZ,230KHZ		1	F5
...3	25-3321-01-10	FILTER,CER,10.7M,150KBW,L L		1	F4
...3	30-4988-00-00	RF SHIELD-FR,BU,ADL-MK2B		1	
...3	30-4989-00-00	RF SHIELD-BACK,BU,ADL-MK2B		1	
...3	46-1177-00-00	F-CABLE #28 3+40+3X10WAYS R		1	J1
...3	50-4222-05-00	SMDA,CPX971,BS,RF,MAIN		1	
...4	20-0041-01-00	X'TR,MMBT3904LT1,SOT-23,REE		2	Q3,Q4
...4	20-1142-03-00	X'TR,RF,NPN,SOT343,RL,BFP67		1	Q2
...4	20-3067-13-00	X'TR,RF/NPN,SOT323,RL,2SC40		3	Q1,Q8,Q9
...4	21-1047-04-00	DIODE,VRA,USC,SMD		3	D1,D2,D3
...4	21-3116-04-00	DIODE,ZEN,3.0V,200MW,UDZ,RE		1	D5
...4	22-3100-20-G6	CAP,CER,10PF,50V,+0.25PF		2	C52,C69
...4	22-3102-26-G5	CAP,CER,1000PF,50V,+10%		6	C22,C27,C35,C37,C39,C40
...4	22-3103-26-G5	CAP,CER,0.01UF,50V,+10%		3	C24,C29,C38
...4	22-3104-06-G5	CAP,CER,0.1UF,16V,10%		3	C23,C28,C36
...4	22-3151-25-G6	CAP,CER,RL,150PF,50V,5%		6	C26,C30,C57,C65,C78,C79
...4	22-3154-16-M3	CAP,CER,0.15UF,25V,10%	SMD,RL,X7R,0805	1	C83
...4	22-3159-29-G6	CAP,CER,1.5PF,50V,+0.1PF		3	C51,C60,C63
...4	22-3189-29-G6	CAP,CER,1.8PF,50V,+0.1PF		1	C7
...4	22-3209-29-G6	CAP,CER,2P,50V,+/-0.25P,COG		1	C54
...4	22-3221-25-G6	CAP,CER,RL,220PF,50V,5%		1	C95
...4	22-3249-29-G6	CAP,CER,2P4,50V,+/-0.25P,COG		1	C15
...4	22-3272-26-G5	CAP,CER,2.7NF,50V,10%		1	C89
...4	22-3273-16-G5	CAP,CER,SMD,27NF,25V,10%		1	C76
...4	22-3279-20-G6	CAP,CER,2.7PF,50V,+0.25PF		1	C2
...4	22-3309-29-G6	CAP,CER,3PF,50V,+0.1PF		3	C12,C17,C67
...4	22-3369-20-G6	CAP,CER,3.6PF,50V,+0.25PF		1	C1
...4	22-3399-20-G6	CAP,CER,3.9PF,50V,0.25PF		1	C11
...4	22-3439-20-G6	CAP,CER,4.3PF,50V,+0.25PF		1	C6
...4	22-3470-25-G6	CAP,CER,RL,47PF,50V,5%		13	C13,C14,C16,C18,C19,C31,C33,C34,C56,C64,C8,C85,C9
...4	22-3471-26-G5	CAP,CER,470PF,50V,+10%		3	C146,C147,C77
...4	22-3479-20-G6	CAP,CER,4.7PF,50V,+0.25PF		8	C58,C59,C70,C71,C72,C74,C81,C82
...4	22-3560-25-G6	CAP,CER,56PF,50V,+5%		1	C25
...4	22-3562-26-G5	CAP,CER,5600PF,50V,10%	SMD,0603	1	C84
...4	22-3569-20-G6	CAP,CER,5.6PF,50V,+0.25PF		3	C21,C4,C5
...4	22-3689-20-G6	CAP,CER,6.8PF,50V,+0.25PF		2	C55,C66
...4	22-3759-20-G6	CAP,CER,7.5PF,50V,+0.25PF		3	C3,C32,C86
...4	23-0000-86-21	RES,CR,SMD,REEL,0,1/16W,5%		1	R15
...4	23-0000-86-21	RES,CR,SMD,REEL,0,1/16W,5%	MCR03EZHW000	3	R10,R14,R15

...4	23-0101-86-21	RES,CR,SMD,REEL,100,1/16W,5		3	R2,R33,R35
...4	23-0102-86-21	RES,CR,SMD,REEL,1K,1/16W,5%		2	R179,R9
...4	23-0103-86-21	RES,CR,SMD,REEL,10K,1/16W,5		12	R150,R16,R17,R27,R45,R51,R53,R54,R57,R58,R67,R68
...4	23-0106-86-21	RES,CF,SMD,RL,10M OHM,1/16W		2	R48,R61
...4	23-0111-86-21	RES,CR,SMD,RL,110R,1/16W,5%		1	R25
...4	23-0153-86-21	RES,CR,SMD,REEL,15K,1/16W,5		1	R12
...4	23-0240-86-21	RES,CR,SMD,REEL,24,1/16W,5%		4	R37,R50,R52,R6
...4	23-0273-86-21	RES,CR,SMD,REEL,27K,1/16W,5%		2	R21,R5
...4	23-0303-86-21	RES,SMD,RL,30K OHM,1/16W,5%		1	R47
...4	23-0393-86-21	RES,CR,SMD,REEL,39K,1/16W,5		1	R3
...4	23-0470-86-21	RES,CR,SMD,REEL,47,1/16W,5%		1	R29
...4	23-0471-86-21	RES,CR,SMD,REEL,470,1/16W,5		1	R32
...4	23-0472-86-21	RES,SMD,RL,4.7K OHM 1/16W,5		1	R66
...4	23-0561-86-21	RES,CR,SMD,560 OHM,1/16W,5%		1	R7
...4	23-0681-86-21	RES,SMD,RL,680 OHM,1/16W,5%		1	R41
...4	23-0750-86-21	RES,CR,SMD,REEL,75,1/16W,5%		1	R34
...4	23-0820-86-21	RES,CF,SMD,RL 82 OHM,1/16W,5%		2	R4,R8
...4	23-1000-G0-21	RES,CR,SMD,RL,100 OHM,1/16W		1	R39
...4	23-1002-G0-21	RES,CR,SMD,RL,1/16W,10K,1%		2	R30,R40
...4	23-1102-G0-21	RES,CR,SMD,RL,1/16W,11K,1%		1	R38
...4	23-1502-G0-21	RES,CR,SMD,RL,1/16W,15K0,1%		1	R28
...4	23-2210-G0-21	RES CR,SMD,RL,1/16W,221R,1%		1	R31
...4	23-4709-84-A3	RES,0805,SMD,RL,47R,1/10W,1		1	R13
...4	25-3515-00-10	FILTER,BAND PASS,903MHZ		1	F1
...4	25-3516-00-10	FILTER,BAND PASS,926MHZ		1	F2
...4	25-3526-00-10	FILTER,SAW,926.4MHZ		1	F3
...4	25-7339-75-10	INDUCTOR 3.3UH,5%,SMD		1	L13
...4	27-6674-13-05	IC,PLL,SSOP-16		1	U10
...4	27-66F0-03-99	IC,FM DEMOD,SSO28,U2765B		1	U1
...4	35-4396-00-00	PCB,SONY971,RF,BD,BS,R,0		1	
.2	50-4222-08-00	PCBA,CPX971,BS,LED		1	
...3	23-0201-11-01	RES,CF,AXL,RL,200R,1/8W,5%		1	R1
...3	35-4380-00-00	PCB,SONY971,LED,BS,R,0		1	
...3	42-1013-00-00	TACT SW,MOM,6MMX6MM		1	S1
...3	43-1065-00-00	LED,DIFFUSE,RED,D3X5.2		2	D1,D2
.2	52-4137-02-00	CASING ASSY,ANT,SPP-935		1	
...3	30-4557-01-00	ANT PLUG BS 910ADL-MK2 BLK,		1	
...3	30-5032-20-00	ANT BODY,BU,SPP-935,GREY,R,		1	
...3	30-4568-12-00	ANT-CAP,BU,SPP-935,GRY,R,1,		1	
...3	41-2002-04-00	RING TERMINAL,W/1BARREL,0.4		1	
...3	14-3614-00-00	STD,BLK,UL1007,AWG#18,2000F		0.741	