



ENGINEERING PROCESS INSTRUCTIONS:

1. Use automatic insertion machine for small axial and/or radial leaded components.
2. Manually insert capacitors and varistors.
3. For electrolytic capacitors and diodes, take note of polarity.
4. For all sub-assembly insertion, check for pin designations, color codes and assembly orientations.
5. Check for proper color codes and length of lead wires.
6. When all components and assemblies are inserted, run assembly thru soldering conveyor, flux and dip soldering.
7. Trim excess leads after wave soldering.
8. Visually inspect component and trace sides.
Do touch-up and repair if necessary.
9. Perform electrical tests according to test specification sheet.
For Test parameter, refer to 87-201-242.
10. For Circuit schematic, refer to 89-201-260.
11. Component C2 is bent inward approximately 80°. (see detail B)
12. Components R5 & R6 are located underneath C10 component.
Components R3, D5, D6, D17, D18 & D19 are located underneath T4 component.
Components D1, D2, D3, & D4 are located underneath C1 component.
Component D22 is located underneath C3 component.
Component D103 is located underneath C4 component.
Components R7, R8, R104, R108, R110, R111, D104, D105, D106, D108, & U101 are underneath C2 component.
13. Component C11 is not used.
14. Yellow lead wires are placed in positions 1Y2 & 2Y2.
Red lead wires are placed in positions 1R & 2R.
Blue wires are placed in positions 1B & 2B.
15. Transistors assembly should be bent inwards at an angle of not more than 25°. (see Detail A). See drawing 86-001-006 figure 1D for preforming.
16. Insert Q103 with connected pins facing R103/D107.

ATC

OCT 28 1997

DOCUMENT CONTROL CENTER



Autoinstert D109 Zener into R111 position and manually insert R111.



Use grounding strap when handling this device.

SEE SEPARATE BOM 98-025-077-00
ASSEMBLY DRAWING

REV.	ZONE	DESCRIPTION OF CHANGE (ECN NO.)	BY	DATE
E		97N2202D ADD AUTOINSERTION NOTE FOR D109 AND R111	JW	10.07.97
D		97N2202A REVISED AND UPDATED BOM	JW	10.03.97
C		97N2060 IMPROVEMENT IN EOL DETECTOR CIRCUIT	MG	04.08.97

UNLESS OTHERWISE SPECIFIED UNITS ARE IN MILLIMETERS(mm) TOLERANCES ARE:	FRACTIONS: DECIMALS: ANGLES:	DRAWN BY: [Signature] CHECKED BY: [Signature] APPROVED BY: [Signature] DATE: 10/1/97	DRAWN BY: [Signature] CHECKED BY: [Signature] APPROVED BY: [Signature] DATE: 10/3/97
---	------------------------------------	---	---

ADVANCE TRANSFORMER CO.		O'HARE INTERNATIONAL CENTER 10275 WEST HIGGINS ROAD ROSEMONT, ILLINOIS 60018-3603	
TITLE: PCB ASSEMBLY (HFL-120-2/39 RS)			
SIZE	PART NO.	DWG NO.	REV.
LTR	98-025-077-00	98-025-077	D
SCALE	NTS	DATE	SHEET
		10-03-97	1 OF 1

THIS DOCUMENT AND DATA DESCRIBED HEREIN OR HEREWITH IS NOT TO BE REPRODUCED, USED OR DISCLOSED IN WHOLE OR IN PART TO ANYONE WITHOUT THE PERMISSION OF ATC, INC.