



A Tyco International Company

Digital Security Controls
3301 Langstaff Road
Concord, Ontario Canada L4K 4L2

Tele: 905 760 3000
Toll Free: 888 888 7838
www.dsc.com

TUV SUD BAPT TCB
Octagon House,
Segensworth Road,
Fareham,
Hampshire,
PO15 5RL

Date: **August 28, 2014**

RF exposure analysis for the equipment 3G4010, 3G4010CF (FCC ID: F53143G4010; IC: 160A-3G4010)

The devices 3G4010 and 3G4010CF (FCC ID: F53143G4010; IC: 160A-3G4010) are cellular alarm communicator device integrating a module 2G/3G (Telit UE920-NAR). This device is to be used only for fixed and mobile applications.

The antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all the persons and must not be co-located or operating in conjunction with any other antenna or transmitter except as under the conditions described KDB 447498 D01 General RF Exposure Guidance.

MPE exposure limits

The table below is excerpted from Table 1B of 47 CFR 1.1310 titled Limits for Maximum Permissible Exposure (MPE), Limits for General Population/Uncontrolled Exposure:

Frequency Range (MHz)	Power density (mW/cm ²)	Averaging time (minutes)
300 – 1500	f (MHz) /1500	30
1500 – 100.000	1,0	30

The table below is excerpted from RSS-102, Issue 4, 4.2, titled “RF Limits for Devices used by the General Public”:

Frequency Range (MHz)	Power density (W/m ²)	Averaging time (minutes)
300 – 1500	f (MHz) /150	6
1500 – 100.000	10	6

EIRP/ERP limits

For 850 MHz frequency band and according to FCC §22.913 the maximum ERP of the device is 7 W (equivalent to 11,48 W EIRP) while IC SRSP-503 defines an EIRP limit of 11,5 W.

For 1900 MHz frequency band and according to FCC §24.232 and IC SRSP-510, the maximum EIRP of the device should be lower than 2 W.

Using the equation $S = \frac{PG}{4\pi R^2}$ to calculate the exposure to electromagnetic fields

- where: S = power density (in appropriate units, e.g. mW/cm²)
- P = power input to the antenna (in appropriate units, e.g., mW)
- G = power gain of the antenna in the direction of interest relative to an isotropic radiator
- R = distance to the center of radiation of the antenna (appropriate units, e.g., cm)

compliance with FCC/IC MPE and EIRP limits is demonstrated following the calculations shown in the following page.



A Tyco International Company

Digital Security Controls
3301 Langstaff Road
Concord, Ontario Canada L4K 4L2

Tele: 905 760 3000

Toll Free: 888 888 7838

www.dsc.com

Band	Modulation	Test Mode	Frequency (MHz)	Avg burst Conducted power (dBm)	Duty cycle (%)	FCC/IC MPE limit (mW/cm ²)	FCC EIRP limit per §22.913 and §24.232 (W)	IC EIRP limit per SRSP-503 and SRSP-510 (W)	Evaluation distance for compliance with MPE limits (cm)	Antenna gain to meet FCC/IC MPE limit (dBi)	Antenna gain to meet FCC EIRP limit (dBi)	Antenna gain to meet IC EIRP limit (dBi)	Maximun antenna gain to meet all the limits (dBi)	Maximun antenna gain to meet all the limits per frequency band (dBi)
GPRS 850	GMSK	2 of 8 transmission slots Duty factor 1/4	824,2	31,46	25,0%	0,55	11,48	11,50	20	8,97	9,13	9,14	8,97	Maximun antenna gain for 850 MHz frequency band:
EGPRS 850	8PSK	2 of 8 transmission slots Duty factor 1/4	848,8	26,30	25,0%	0,57	11,48	11,50	20	14,26	14,29	14,30	14,26	
FDD V	QPSK	Duty factor 100%	826,4	23,21	100,0%	0,55	11,48	11,50	20	11,21	17,38	17,39	11,21	8,97
GPRS 1900	GMSK	2 of 8 transmission slots Duty factor 1/4	1909,8	29,05	25,0%	1,00	2,00	2,00	20	13,98	3,96	3,96	3,96	Maximun antenna gain for 1900 MHz frequency band:
EGPRS 1900	8PSK	2 of 8 transmission slots Duty factor 1/4	1909,8	25,33	25,0%	1,00	2,00	2,00	20	17,70	7,68	7,68	7,68	
FDD II	QPSK	Duty factor 100%	1852,4	21,24	100,0%	1,00	2,00	2,00	20	15,77	11,77	11,77	11,77	3,96

Yours sincerely,

By: Dan Nita

Title: Approvals Manager

Company: Digital Security Controls Ltd.

Telephone / Fax: 905-760-3000/905-760-3020

e-mail: dnita@tycoint.com