

# STATEMENT ON EXPOSURE TO ELECTROMAGNETIC FIELDS

## EQUIPMENT

Type of equipment:	LED lamp with Zigbee radio
Type / Model:	LED1624G9
Manufacturer:	IKEA of Sweden AB
By request of:	IKEA of Sweden AB

## STANDARD

EN 62479  
47 CFR §1.1310  
RSS-102 Issue 5  
Radiation Protection Standard for Maximum Exposure Levels to Radiofrequency fields – 3  
kHz to 300 GHz  
AS/NZS 2772.1

*This Statement of Compliance is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Statement. Only the Client is authorized to permit copying or distribution of this Statement of Compliance. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.*

**CONDITIONS**

Operating frequency range is 2405-2480 MHz.

Highest output power to antenna is +14.0 dBm.

Antenna gain is -3.6 dBi.

A test separation distance of 20 cm is used.

Maximum duty cycle is 22.7%

**CALCULATIONS****EIRP:**

$$+14.0 \text{ dBm} + (-3.6) \text{ dBm} = +10.4 \text{ dBm}$$

**Conversion dBm to W:**

$$\text{Conducted:} \quad 1 \text{ mW} * 10^{(14.0 \text{ dBm}/10)} = 25.1 \text{ mW}$$

$$\text{EIRP:} \quad 1 \text{ mW} * 10^{(10.4 \text{ dBm}/10)} = 11.0 \text{ mW}$$

**Time averaged maximum power:**

$$\text{Conducted:} \quad 25.1 \text{ mW} * 0.227 = 5.70 \text{ mW}$$

$$\text{EIRP:} \quad 11.0 \text{ mW} * 0.227 = 2.50 \text{ mW}$$

**Power density S:**

$$S \left[ \frac{\text{W}}{\text{m}^2} \right] = \frac{\text{DC} \times \text{EIRP}}{4 \times \pi \times R^2} = \frac{0.227 \times 0.011}{4 \times \pi \times 0.2^2} = 0.005$$

*This Statement of Compliance is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Statement. Only the Client is authorized to permit copying or distribution of this Statement of Compliance. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.*

**LIMITS & EVALUATIONS:**

Standard	Reference for limit	Limit	Unit	Values	Result
EN 62479	EN 62479 <sup>1</sup>	40	mW	2.5	PASS
CFR 47 §1.1310	CFR 47 §1.1310 <sup>2</sup>	10	W/m <sup>2</sup>	0.005	PASS
RSS-102 issue 5 (2015)	RSS-102 issue 5 (2015) <sup>3</sup>	2.72	W	0.0025	PASS
Radiation Protection Standard for Maximum Exposure Levels to Radiofrequency fields – 3 kHz to 300 GHz	Radiation Protection Standard for Maximum Exposure Levels to Radiofrequency fields – 3 kHz to 300 GHz <sup>4</sup>	10	W/m <sup>2</sup>	0.005	PASS
AS/NZS 2772.1	AS/NZS 2772.2 <sup>5</sup>	20	mW	2.5	PASS

1. Table A.1: For general public and limbs exposure.
2. Section (e), Table 1 - Limits for Maximum Permissible Exposure (MPE)
3. Section 2.5.2 at or above 300 MHz and below 6 GHz and the source-based, time-averaged maximum e.i.r.p. of the device is equal to or less than  $1.31 \times 10^{-2} f^{0.6834}$  W (adjusted for tune-up tolerance), where  $f$  is in MHz
4. Table 7: For general public and 2 GHz- 300 GHz the equivalent plane wave power flux density is: 10
5. Section 3.7.3: In some circumstances an RF exposure evaluation may not be required. This is the case with low-power devices whose nominal average RF radiated power does not exceed 20 mW and which do not produce exceptionally high instantaneous fields.

Intertek Semko AB, Radio&amp; EMC

Date of issue: 2017-10-25



Issued by: Daniel Nilsson

*This Statement of Compliance is for the exclusive use of Intertek's client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this Statement. Only the Client is authorized to permit copying or distribution of this Statement of Compliance. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek.*