

TK2703 RF Keyboard Specification

1. Electronic Specification

TK2703 Wireless is located in the wireless multimedia keyboard.

RF Link	
Carrier mode	Channel : 27.145MHz Shared channel for keyboard
Distance	Keyboard: 2 Meters ; It is based on wooden table and open site. The receiver should be out of your computer and monitor for more than 20 cm.
Bandwidth	10KHz±1kHz
Broadcast mode	Single way
Modulation	FSK
Channel Separation	50KHz
ID code	256 sets ID code
Transmitter	
● Keyboard	Features
keypad	The 99-keytop of keyboard with 16 hot keys
Power	3.0V , AA*2
Voltage range	2.4V~3.2V
Current Consumption	Run mode: 7mA ; Sleep mode: 13uA
Channel	One Channel
Suspend Timeout	Keystroke wakeup
Peak power level	<80dBuV
Low Battery	2.4±0.5V approximate
ID Button	Tack switch

Keyboard Hardware Installation

1. Always turn off your computer you connected or disconnect your keyboard.
2. Plug the keyboard connector firmly into the AT/PS2 port on the computer.
3. Turn on your PC.

Software Installation

1. Make sure the keyboard is connected to the computer.
2. Put the Setup disk (or CD) into the disk drive.
3. From Windows95/98,click on **Start/Run** .
4. Specify the disk drive and type **setup**. For example, type **e:\setup** if you are using drive E.
5. Follow the instructions on the screen to finish the software installation.

Internet & Multimedia hot keys

1. Track rewind: Previous track of audio or video CD' s
2. Play & Pause: Play and Pause of audio or video CD' s
3. Stop: Stop play of audio or video CD' s
4. Track forward: Next track of audio or video CD' s
5. Power : Turn system off into power mode
6. Vol.-&+: decrease or increase volume
7. Mute: Mute volume
8. Favorite : open my favorite mode
9. E-mail: Open mail folder
10. Back: See last page when viewing the Internet
11. www: Open browser in Netscape or IE
12. Forward: Go to next page when viewing the Internet
13. Sleep: Turn system into sleep mode