



Spectrum Research & Testing Lab., Inc.

No.167, Ln. 780, Shan-Tong Rd. Ling 8, Shan-Tong Li, Chung-Li City, Taoyuan County 320, Taiwan (R.O.C.)

## RF exposure evaluation

Subject: FCC Application for FCC ID: FSUGMZL6

According to 447498 D01 General RF Exposure Guidance v05

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances  $\leq 50$  mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$  for 1-g SAR and  $\leq 7.5$  for 10-g extremity SAR, where

$f(\text{GHz})$  is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

$$\text{eirp} = \text{pt} \times \text{gt} = (\text{EXd})^2 / 30$$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, ---  $10^{((\text{dBuV/m})/20)} / 10^6$

d = measurement distance in meters (m)---3m

$$\text{So pt} = (\text{EXd})^2 / 30 \times \text{gt}$$

Field strength = 85.50 dBuV/m @3m


Ant gain = 5 dBi ;so Ant numeric gain=  $10^{(5/10)} = 3.16$

$$\text{So pt} = \{ [10^{(85.50/20)} / 10^6 \times 3]^2 / 30 \times 3.16 \} \times 1000 \text{ mW} = 0.337 \text{ mW}$$

$$\text{So } (0.337 \text{ mW} / 5\text{mm}) \times \sqrt{2.409} = 0.104 < 3$$

Then SAR evaluation is not required

Sincerely yours,

  
\_\_\_\_\_  
(Johnson Ho, Director)

  
\_\_\_\_\_  
(Date)