

APPLICANT: Thomson Consumer Electronics

FCC ID: G9H2-9950

## TABLE OF CONTENTS

### **TEST REPORT:**

PAGE 1.....15.214(d) - SECURITY CODING INFORMATION  
PAGE 2-3.....TEST EQUIPMENT LIST AND TEST PROCEDURE  
PAGE 4-5.....CIRCUIT DESCRIPTIONS  
PAGE 6.....RADIATION INTERFERENCE TEST DATA - BASE  
PAGE 7.....RADIATION INTERFERENCE TEST DATA - HANDSET  
PAGE 8.....OCCUPIED BANDWIDTH TEST DATA  
PAGE 9.....POWERLINE CONDUCTED TEST DATA

### **EXHIBITS:**

EXHIBIT 1.....POWER OF ATTORNEY  
EXHIBIT 2A.....BASE MAIN BLOCK DIAGRAM  
EXHIBIT 2B.....BASE RF BLOCK DIAGRAM  
EXHIBIT 3A.....HANDSET MAIN BLOCK DIAGRAM  
EXHIBIT 3B.....HANDSET RF BLOCK DIAGRAM  
EXHIBIT 4A.....BASE RF SCHEMATIC  
EXHIBIT 4B.....BASE VCO SCHEMATIC  
EXHIBIT 4C.....BASE MAIN CIRCUIT SCHEMATIC  
EXHIBIT 4D.....TAD & POWER SCHEMATIC  
EXHIBIT 5A.....HANDSET RF SCHEMATIC  
EXHIBIT 5B.....HANDSET VCO SCHEMATIC  
EXHIBIT 5C.....HANDSET MAIN CIRCUIT SCHEMATIC  
EXHIBIT 6.....FCC ID LABEL SAMPLES  
EXHIBIT 7.....FCC ID LABEL LOCATION  
EXHIBIT 8.....EXTERNAL PHOTOGRAPH - FRONT SIDE  
EXHIBIT 9.....EXTERNAL PHOTOGRAPH - REAR SIDE  
EXHIBIT 10.....INTERNAL PHOTOGRAPH - COMPONENT SIDE  
EXHIBIT 11.....INTERNAL PHOTOGRAPH - COPPER SIDE  
EXHIBIT 12A-JJ..USERS MANUAL  
EXHIBIT 13.....OCCUPIED BANDWIDTH PLOT - NO MOD - BASE  
EXHIBIT 14.....OCCUPIED BANDWIDTH PLOT - 2500 Hz TONE - BASE  
EXHIBIT 15.....OCCUPIED BANDWIDTH PLOT - NO MODULATION - HANDSET  
EXHIBIT 16.....OCCUPIED BANDWIDTH PLOT - LOUD VOICE - HANDSET  
EXHIBIT 17.....LINE 1 POWERLINE CONDUCTED PLOT - BASE  
EXHIBIT 18.....LINE 2 POWERLINE CONDUCTED PLOT - BASE

APPLICANT: Thomson Consumer Electronics

FCC ID: G9H2-9950

REPORT #: F:\CUS\T\TCE\TCE217A8.RPT

PAGE #: TABLE OF CONTENTS

SECURITY CODING INFORMATION

APPLICANT: Thomson Consumer Electronics

FCC ID: G9H2-9950

15.214(d) - THIS DEVICE COMPLIES WITH THE SECURITY CODE REQUIREMENTS OF 15.214(d)(1)(2) AND (3) BY MEANS OF THE FOLLOWING:

THIS PHONE IS EQUIPPED WITH A DIGITAL SECURITY SYSTEM WITH OVER 1 MILLION CODE COMBINATIONS.

WHEN MAKING A CALL, THE TELEPHONE SEARCHES THROUGH ITS 32 AVAILABLE CHANNELS AUTO CHANNEL SCAN TO FIND THE CLEAREST ONE.

THE RECEIVER PORTION OF THIS TELEPHONE, FCC ID: G9H2-9950, WAS TESTED WITH PASSING RESULTS. A VERIFICATION REPORT HAS BEEN ISSUED PER FCC RULES PART 15.109.

APPLICANT: Thomson Consumer Electronics

FCC ID: G9H2-9950

REPORT #: F:\CUS\T\TCE\TCE217A8.RPT

PAGE #: 1

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950

#### TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B, with preselector HP 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B OPT H02  
Cal. 9/30/97
2. Eaton Biconnical Antenna Model 94455-1  
20-200 MHz Serial No. 0997 Cal. 9/17/97
3. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA 25 cal. 5/15/97
4. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 9/24/97
5. Electro-Metric Antennas Model TDS-25-1, TDS-25-2, 9/3/97
6. Electro-Metric Line Impedance Stabilization Network Model  
No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. 9/30/97
7. Electro-Metric Line Impedance Stabilization Network Model  
No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. 9/30/97

#### TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution bandwidth was 100KHz and the video bandwidth was 300KHz. The ambient temperature of the UUT was 89oF with a humidity of 86%.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz)	METER READING + ACF = FS
33	20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

POWER LINE CONDUCTED INTERFERENCE: The procedure used was ANSI STANDARD C63.4-1992 using a 50uH LISN. Both lines were observed. The bandwidth of the spectrum analyzer was 10kHz with an appropriate sweep speed. The ambient temperature of the UUT was 89oF with a humidity of 86%.

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
PAGE #:

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950

TEST PROCEDURES CONTINUED

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The UUT was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The UUT was placed flush with the back of the table (1.5m side). The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
PAGE #: 3

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950

CIRCUIT\_DESCRIPTION:

BASE UNIT

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q500 and then to a SAW bandpass filter, FL501. The frequency range of the base receiver is 926-928MHz. From the bandpass filter the signal is fed to the mixer, Q501 which converts the signal down to 26.05MHz. From Q501 the signal is fed to the IF filter FL502 and then to the integrated circuit U500. In the U500 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector the audio is fed to a low pass filter and to the Channel Detector Indicator. From the low pass filter the audio is fed into another low pass filter and shaper and then to the CPU, U311. From the CPU, U311, the audio is fed to a speaker amplifier and the telephone line depending which is selected. From the CPU the line audio is fed to U305A and then to U305B then to the telephone coupling transformer, T301. The CPU also compares the SECURITY CODES and provides the outgoing SECURITY CODE.

On the transmitting side, when a ring signal is detected the transmitter is turned on by photo coupler integrated circuit U301 and the ring detect signal is fed into the CPU, U306, which in turn triggers the transmitter and send a ring signal to the handset. The base transmit frequency range is 902-904MHz. When the handset answers the base unit connects to the phone line and telephone line audio is fed into the speech network and then to an audio amplifier, Q304. The audio is then fed into the compressor U311. From U311 the audio is fed into the VCO, VT which modulated the outgoing carrier. From the VCO the signal is fed through a series of amplifiers, Q508 & Q509. From Q508 the signal is fed to the antenna.

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
PAGE #: 4

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950

#### CIRCUIT\_DESCRIPTIONS CONTD.

##### HANDSET

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q100 and then to a SAW 903MHz bandpass filter. The frequency range of the handset receiver is 902-904MHz. From the bandpass filter the signal is fed to the mixer, Q101 which converts the signal down to 26.05MHz. From Q101 the signal is fed to the IF filter FL102 and then to the integrated circuit U100. In the U100 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector, p/o U100 the audio is fed to a low pass filter and to the RING Detector Indicator. From the low pass filter the audio is fed simultaneously to the earphone element and to the CPU, U101. The earphone audio is fed into U2 and then to U4 then to the receiver element, RC1. The CPU uses the data to continuously monitor the security code.

The transmitter frequency range is 926-928MHz. The outgoing audio is picked up by the microphone and fed to the audio integrated circuit U2. This audio integrated circuit feeds a low pass filter then feeds the signal to the VCO, VT. From the VCO the signal is fed in to the amplifier Q107 and Q108 to the duplexer and then to the antenna.

##### ANTENNA\_AND\_GROUND\_CIRCUITRY

This unit makes use of a short, antenna. The antenna is inductively coupled. The antenna is self contained, no provision is made for an external antenna.

No ground connection is provided. The unit relies on the ground track of the printed circuit board.

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
PAGE #: 5

APPLICANT: Thomson Consumer Electronics  
 FCC ID: G9H2-9950 (BASE)  
 NAME OF TEST: RADIATION INTERFERENCE  
 RULES PART NO.: 15.249  
 REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

FREQUENCY	LEVEL
____MHz____	____dBuV/M____
902- 928 MHz:	54.0 dBuV/M
ABOVE 960 MHz:	54.0 dBuV/M

TEST DATA:

EMISSION FREQ. MHz	METER READING @ 3m dBuV	COAX LOSS dB	ACF dB	FIELD STRNGTH dBuV/m	MARGIN dB	ANT.
TUNED FREQUENCY 902.75						
902.75	48.10	2.90	24.19	75.19	14.49	H
1805.50	3.40	1.00	27.22	31.62	38.06	H
2708.25R	1.10	1.14	29.77	32.01	37.68	H
3611.00R	2.10	1.27	32.03	35.40	34.28	V
4513.75R	1.10	1.41	33.58	36.09	33.60	V
5416.50R	1.10	1.54	34.59	37.24	32.45	V
TUNED FREQUENCY 903.17						
903.17	50.80	2.90	24.19	77.89	16.11	V
1806.34	4.70	1.00	27.23	32.93	36.76	H
2709.51R	1.30	1.14	29.77	32.21	37.47	H
3612.68R	0.60	1.27	32.03	33.90	35.78	V
4515.85R	1.90	1.41	33.58	36.89	32.79	V
5419.02R	0.60	1.54	34.60	36.74	32.94	V

SAMPLE CALCULATION:

$FSdBuV/m = MR(dBuV) + ACFdB.$

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: S. S. SANDERS                      DATE: 30 JULY 1998

APPLICANT: Thomson Consumer Electronics  
 FCC ID: G9H2-9950  
 REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
 PAGE #: 6

APPLICANT: Thomson Consumer Electronics  
 FCC ID: G9H2-9950 (HANDSET)  
 NAME OF TEST: RADIATION INTERFERENCE  
 RULES PART NO.: 15.249  
 REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

FREQUENCY		LEVEL
____MHz____		____dBuV/M____
902- 928	MHz:	54.0 dBuV/M
ABOVE 960	MHz:	54.0 dBuV/M

TEST DATA:

EMISSION FREQ. MHz	METER READING @ 3m dBuV	COAX LOSS dB	ACF dB	FIELD STRNGTH dBuV/m	MARGIN dB	ANT.
TUNED FREQUENCY 926.19						
926.75	47.60	2.90	24.11	74.61	19.39	V
1853.50	5.60	1.01	27.41	34.02	35.66	V
2780.25R	1.50	1.15	29.95	32.60	37.08	H
3707.00R	0.90	1.29	32.27	34.45	35.23	H
4633.75R	1.50	1.43	33.71	36.64	33.04	H
TUNED FREQUENCY 927.19						
927.19	54.30	2.90	24.12	81.32	12.68	V
1854.38	6.20	1.01	27.42	34.63	35.06	V
2781.57R	1.50	1.15	29.95	32.60	37.08	H
3708.76R	0.80	1.29	32.27	34.36	35.32	H
4635.95R	2.10	1.43	33.72	37.24	32.44	H

SAMPLE CALCULATION:

$FSdBuV/m = MR(dBuV) + ACFdB.$

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD C63.4-1992 with the following exception: the unit was operated into its own antenna with the antenna at a height of four feet. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: S. S. SANDERS DATE: 30 JULY 1998

APPLICANT: Thomson Consumer Electronics  
 FCC ID: G9H2-9950  
 REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
 PAGE #: 7



APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
NAME OF TEST: Occupied Bandwidth  
RULES PART NO.: 15.233  
REQUIREMENTS: The field strength of any emissions appearing between the band edges and up to 10 kHz above and below the band edges shall be attenuated at least 26 dB below the level of the unmodulated carrier or to the general limits of 15.209, whichever permits the higher emission levels.

THE GRAPHS IN EXHIBITS 13-16 REPRESENT THE EMISSIONS TAKEN FOR THIS DEVICE.

METHOD OF MEASUREMENT: A small sample of the transmitter output was fed into the spectrum analyzer and the above photo was taken. The vertical scale is set to -10 dBm per division. The horizontal scale is set to 5 kHz per division.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: S. S. SANDERS 30 JULY 1998

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
PAGE #: 8

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
NAME OF TEST: POWER LINE CONDUCTED INTERFERENCE  
RULES PART NUMBER: 15.207  
MINIMUM REQUIREMENTS:      FREQUENCY                      LEVEL  
                                    \_\_\_MHz\_\_\_                      \_uV\_  
                                    0.450-30                      250  
TEST PROCEDURE: ANSI STANDARD C63.4-1992

THE HIGHEST EMISSION READ FOR LINE 1 WAS 25.97 uV @1.16 MHz.

THE HIGHEST EMISSION READ FOR LINE 2 WAS 25.673 uV @ 1.22 MHz.

THE GRAPHS IN EXHIBITS 17-18 REPRESENT THE EMISSIONS READ FOR  
POWERLINE CONDUCTED FOR THIS DEVICE.

TEST RESULTS: Both lines were observed. The measurements indicate that the unit DOES appear to meet the FCC requirements for this class of equipment.

PERFORMED BY: S. S. SANDERS

DATE: 30 JULY 1998

APPLICANT: Thomson Consumer Electronics  
FCC ID: G9H2-9950  
REPORT #: F:\CUS\T\TCE\TCE217A8.RPT  
PAGE #: 9