

**CLIMAX TECHNOLOGY CO., LTD.**  
No. 258, Sinhu 2nd Rd., Neihu District, Taipei City 114, Taiwan ( R.O.C.)

Federal Communications Commission  
Authorization and Evaluation Division  
Equipment Authorization Branch  
7435 Oakland Mills Road  
Columbia, MD 21046

**Applicant's declaration concerning RF Radiation Exposure**

We hereby indicate that the product  
Product description: Telecare Alarm System  
Model No: CTC-1052xxx-xxxxxx Series (x=0~9, A~Z or blank)

The equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. The integral antennas used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter within the host device.

A safety statement concerning minimum separation distances from enclosure of the  
Product : Telecare Alarm System  
will be integrated in the user's manual to provide end-users with transmitter operating conditions for satisfying RF exposure compliance.

The appropriate information can be drawn from the test report no: W6M22006-20020-P-247 and the accompanying calculations.

Company: CLIMAX TECHNOLOGY CO., LTD.  
Address: No. 258, Sinhu 2nd Rd., Neihu District, Taipei City 114, Taiwan ( R.O.C.)

Date: 2020.07.01

Signature

George Lin



Report Number: W6M22006-20020-P-247

FCC ID: GX9CTC1052QT

**10 Maximum Permissible Exposure**

**10.1 Exemption Limits for Routine Evaluation according to 47 CFR FCC Part 2 Subpart J, section 2.1091**

FCC OET Bulletin 65 Edition 97.01 determines the equations for predicting RF fields and applicable limits.

The prediction for power density in the far-field but will over-predict power density in the near field, where it could be used for walking a “worst case” or conservative prediction.

Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess limit for maximum permissible exposure. In accordance with 47 CFR FCC Part 2 Subpart J, section 2.1091 this device has been defined as a mobile device whereby a distance of 20 cm normally can be maintained between the user and the device.

**MPE Calculation Method**

**(A) Limits for Occupational/Controlled Exposure**

Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Time  E  <sup>2</sup> ,  H  <sup>2</sup> or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842/f	4.89/f	(900/f <sup>2</sup> )*	6
30-300	61.4	0.163	1.0	6
300-1500	--	--	f/300	6
1500-100,000	--	--	5	6

**(B) Limits for General Population/Uncontrolled Exposure**

Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Time  E  <sup>2</sup> ,  H  <sup>2</sup> or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f <sup>2</sup> )*	30
30-300	27.5	0.073	0.2	30
300-1500	--	--	f/1500	30
1500-100,000	--	--	1.0	30

f = frequency in MHz


\*Plane-wave equivalent power density

E = Electric field (V/m) P = output power (W) G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

$$Pd = \frac{30 \times P \times G}{377 \times d^2}$$

The formula can be changed to mW/cm<sup>2</sup>.



# Worldwide Testing Services(Taiwan) Co., Ltd.

Report Number: W6M22006-20020-P-247

FCC ID: GX9CTC1052QT

Frequency	Max output power		Antenna Gain	Power Density(S) (mW/cm <sup>2</sup> )	Limit of Power Density (S) (mW/cm <sup>2</sup> )	Test Result
	(dBm)	(W)				
WCDMA Band II	22.57	0.18	3.21	0.0753	1	Complies
WCDMA Band IV	22.74	0.19	2.67	0.0691	1	Complies
WCDMA Band V	23.64	0.23	-0.13	0.0446	0.5644	Complies
LTE Band II	23.35	0.22	3.21	0.0901	1	Complies
LTE Band IV	23.15	0.21	2.67	0.0760	1	Complies
LTE Band V	23.81	0.24	-0.13	0.0464	0.5577	Complies
LTE Band XII	23.46	0.22	1.58	0.0635	0.4740	Complies
LTE Band XIII	23.66	0.23	0.85	0.0562	0.5213	Complies

From the peak EUT RF output power, the minimum mobile separation distance,  $d=0.2$  m, as well as the gain of the used antenna, the RF power density can be obtained.